



hp M32f FHD Monitor User Guide

[Home](#) » [HP](#) » hp M32f FHD Monitor User Guide 



FHD Monitor
Maintenance and Service Guide
M32f model
M31389
User Guide

Contents

- [1 M32f FHD Monitor](#)
- [2 Getting started](#)
- [3 Monitor features](#)
- [4 Illustrated parts catalog](#)
- [5 How to order parts](#)
- [6 Removal and replacement procedures](#)
- [7 Connector repair](#)
- [8 Function test](#)
- [9 Support and troubleshooting](#)
- [10 Documents / Resources](#)
 - [10.1 References](#)
- [11 Related Posts](#)

M32f FHD Monitor

SUMMARY

This guide provides information about spare parts, removal and replacement of parts, diagnostic tests, problem troubleshooting, and more.

© Copyright 2021 HP Development Company, L.P.

AMD is a trademark of Advanced Micro Devices, Inc. Bluetooth is a trademark owned by its proprietor and used by HP Inc. under license. NVIDIA is a trademark and/or registered trademark of NVIDIA Corporation in the U.S. and other countries. USB Type-C and USB-C are registered trademarks of USB Implementers Forum. DisplayPort and the DisplayPort logo are trademarks owned by the Video Electronics Standards Association (VESA) in the United States and other countries.

The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

First Edition: Mar 2022

Document Part Number: M31389-M32f-MSGV1

Assembly part number: M31389-001

Product notice

Only trained service personnel familiar with this product should service it. Before performing any maintenance or service, be sure to read “Important Safety Information”.

Getting started

Read this chapter to learn about safety information and where to find additional HP resources.

Important safety information

Carefully read the cautions and notes within this document to minimize the risk of personal injury to service personnel. The cautions and notes are not exhaustive. Proper service methods are important to the safe, reliable operation of equipment. Improper service methods can damage equipment.

The service procedures recommended and described in this service manual provide effective methods of performing service operations. Service engineers should have prior repair knowledge and experience as well as appropriate training for the product before performing service procedures.

- Be sure your working environment is dry and clean and meets all government safety requirements.
- Be sure that other persons are safe while you are servicing the product.
- Do not perform any action that can cause a hazard to the customer or make the product unsafe.
- Use proper safety devices to ensure your personal safety.
- Always use approved tools and test equipment for servicing.
- Never assume the product's power is disconnected from the main power supply. Check that it is disconnected before opening the product's cabinet.
- Modules containing electrical components are sensitive to electrostatic discharge (ESD). Follow ESD safety procedures while handling these parts.
- Some products contain more than one battery. Do not disassemble or expose a battery to high temperatures, such as throwing into fire, or the battery may explode.
- Refer to government requirements for battery recycling or disposal.

This information provides general service information for the monitor. Adherence to the procedures and precautions is essential for proper service.

IMPORTANT: Only trained service personnel who are familiar with this HP product should perform service or maintenance for it. Before performing any service or maintenance, personnel must read the important safety information.

IMPORTANT: You must disconnect the power cord from the power source before opening the monitor to prevent component damage.

Important service information and precautions

- Repair must be performed by professional service technicians in a repair center. End users should not perform these procedures.
- Please note during servicing that the primary side is the high voltage area.
- This monitor meets ROHS requirements. Be sure to use lead-free solder wire when soldering.
- If you must change a capacitor, be sure to match the polarity as printed on the PCB.
- If you must replace a capacitor, make sure the specification and part number match the BOM and location.
- If you must replace a capacitor, insert new parts carefully to avoid a short circuit caused by the near pin.
- Do not get the board wet. Water and moisture can cause a short circuit that causes malfunctions.
- To avoid damage, be sure to use lead-free solder.
- When soldering, work quickly to avoid overheating the circuit board.
- Keep the soldering iron tip clean and well tinned when replacing parts.
- After repair, perform a close inspection of the circuit board to confirm it is in good condition.
- After repair, perform a function test to confirm the power supply is working properly.

ERP Lot5 requirement

1. A professional repairer must have the technical competence to repair electronic displays and comply with the applicable regulations for repairers of electrical equipment in the Member States where the repairer operates. Reference to an official registration system as professional repairer, where such a system exists in the Member States, shall be accepted as proof of compliance.
2. A professional repairer must have insurance that covers liabilities resulting from repairs, regardless of whether required by the Member State.

RoHS (2002/95/EC) requirements

Applied to all countries that require RoHS.

The RoHS (Restriction of Hazardous Substance in Electrical and Electronic Equipment Directive) is a legal requirement by the EU (European Union) for the global electronics industry sold in the EU and other countries. Any electrical and electronics products launched in the market after June 2006 should meet this RoHS requirement. Products launched in the market before June 2006 are not required to be compliant with RoHS parts. If the original parts are not RoHS complaint, the replacement parts can be non-ROHS complaint. If the original parts are RoHS compliant, the replacement parts **MUST** be RoHS complaint. If product service or maintenance requires replacing parts, confirm the RoHS requirement before replacement.

General descriptions

This manual contains general information. There are two levels of service:

Level 1: Cosmetic/appearance/alignment service

Level 2: Circuit board or standard parts replacement

Firmware updates

Firmware updates for the monitor are available at support.hp.com. If no firmware is posted, the monitor does not need a firmware update.

Before returning the repaired product to the customer

Perform an AC leakage current check on exposed metallic parts to be sure the product is safe to operate without the potential of electrical shock. Do not use a line isolation transformer during this check.

Measurements that are not within specified limits present a possible shock hazard. You must check and repair the product before returning it to the customer.

Monitor features

This chapter provides an overview of the monitor's features.

Features

Depending on the model, your monitor might include the following features:

- 80 cm (31.5 in) diagonal viewable area with 1920 × 1080 resolution, plus full-screen support for lower resolutions; includes custom scaling for maximum image size while preserving original aspect ratio
- Liquid crystal display (LCD) with active matrix.
- Wide color gamut to provide coverage of sRGB color spaces
- Nonglare panel with an LED backlight
- Wide viewing angle to allow viewing from a sitting or standing position, or moving from side to side
- Tilt adjustment capabilities
- Two High-Definition Multimedia Interface (HDMI) video inputs and VGA input.
- Four OSD buttons, three that can be reconfigured to quickly allow selection of the most commonly used operations
- Plug and Play capability if supported by your operating system
- Security cable slot on the rear of the monitor for an optional security cable
- On-screen display (OSD) adjustments in several languages for easy setup and screen optimization
- HP Display Assistant software for adjusting monitor settings and enabling theft deterrence features
- Energy saver feature to meet requirements for reduced power consumption

NOTE: For safety and regulatory information, refer to the Product Notices provided in your documentation kit. To access the latest user guide, go to <http://www.hp.com/support>, and follow the instructions to find your product. Then select User Guides.

Rear components

To identify the components on the rear of the monitor, use this illustration and table.




Table 1-1: Rear components and their descriptions

	Component	Function
1	Security cable slot	Connects an optional security cable.
2	Power connector	Connects a DC adapter.
3	Power light	On: The monitor is on. Off: Depending on your monitor model, the monitor have no voltage from adapter
4	VGA connector	Connects the VGA cable to a source device.
5	HDMI ports (2)	Connect the HDMI cable to a source device such as a computer or game console.

Locating the serial number and product number



Depending on the product, the serial number and product number are located on a label on the rear of the monitor or on a label under the front bezel of the monitor head. You might need these numbers when contacting HP for support.



For worldwide models (except India):

Barcode label

Manufactured: Oct, 2020
Product No.: 2H5M7AA#ABA
Spare No.: M34201-001
Assembly Part No.: M31389-001
Rev.: R1M080



Spec label



For India:

Bar code label

Manufactured: Oct, 2020
Product No.: 2H5M7AA#ABA
Spare No.: M34201-001
Assembly Part No.: M31389-001
Rev.: R1M080




Spec label



Illustrated parts catalog

To identify the monitor major components, use this illustration and table.



Item	Description	Qty
1	FRONT DECO(VIRG/N ABS+5% PET/JACK BLACK (6009- 0337)XENCORE 3-M32F)ASSy	1
2	LENS(PC122/TRANSPARENT/ENCORE 3)	1
3	FRONT DECONI RGI N ABS+5% PET/NATUR S/LVER{ENCORE J-MJ2F}	1
4	FOAM TAPE (L70814/3'0.61EXP060-D33-S)	1
5	M31 5HVR01.1-HSAK1 Encore III M32f LCM P/N(Black)	1
6	WH FFC JOP(1.0mm)340mm(1+PRO)60V G/F W/CONN(A15+BC)+AL HF	1
7	WH FFC 8P(0.5mm)500mm(JFOLD)60V G/F (A8+A6) HF	1
8	WH A1007H00-6P-2L/AI251-H06 /28 75mm+AC I r -A TE W/8 HF	1
9	MAIN BO ASS'Y HP Encore III M32f (M315HVR01.1-HSAK1) 2L	1

10	SHIELDING (SECC 0.57)(1A2H-AUD10)(ENCORE3)	1
11	MAC. SCR EW-MH 44-4005.0L, ni	2
12	MAC. SCREW-MI NU.0•4.0L, BLK-Ni	16
13	REAR SU PPORT-R(PC R-85% ABS+5% PET/JACK BLACK (6009-0337))(ENCORE 3-M32F)	1
14	REAR SU PPORT-L(PC R-85% ABS+5% PET/JACK BLACK (6009-0337)XENCORE 3-M32F)	1
15	MAC. SCREW-MI NU.0•4.0L, BLK-Ni	1
16	REAR COVER(VIRGIN ABS+5% PU/JACK BLACK (6009-0337}XENCORE J-MJ2F}ASS'Y	1
17	REAR COVER(VIRGIN ABS+5% PET/JACK BLACK (6009-0337)XENCORE 3-M32F)	16
18	DISPLAYKEY(VIRGIN ABS+5% PET/JACK BLACK (6009-0337)XENCORE 3)	1
19	DISPLAY BO ASS'Y HP Encore III	1
20	POWER LENS(PC/TFIANSSPARENT)(2213xi)	1
21	MAC. SCREW-MI M3.0*6.0L, BLK-ZNNI(HEAD DIAMETER 7.0)	2
22	HINGE(ENCOREJ-M321)(Sliver) CX	1
23	MAC. SCREW-MB M4.0-5.0L.BLK_Ni,NYLOK	4
24	NECK(ENCOREJ-M324(Sliver) ASS'Y CX	1
25	NECK(ENCOREJ-M321)(Sliver) CX	1
26	CABLE MANAGER(ENCOREJ-M32f)(Sliver}CX	1
27	BASE(ENCOREJ-M32f)(Sliver) CX	1
28	SPONGE PU(24.0•12.0*16.01)(ENCORE2_23F)(BLK)	1

How to order parts

Capacitors by distributor

HDMI: [0476591100 Molex](#) | [Connectors, Interconnects](#) | [DigiKey](#)

VGA: [K86X-ED-15S-BR Kycon, Inc.](#) | [Connectors, Interconnects](#) | [DigiKey](#)

TYPE	LHD P/N	Main Source SPEC.	Distributor P/N	Source
HDMI	R030410000210	19P 180' H=13mm SMD	900-0476591100TR-ND 900-0476591100CT-ND 900-0476591100DKR-ND	H=8.5mm
VGA	R030012105155	180' 15P H=10.5mm	2092-K86X-ED-15S-BR-ND	H=6mm

NOTE: The connector may need to be modified to meet functionality, regulatory and safety requirements if it is not an exact match.

You can purchase cables from the HP part store at <https://partsurfer.hp.com/Search.aspx>.

NOTE: HP continually improves and changes product parts. For complete and current information about supported parts for your computer, go to

<http://partsurfer.com>, select your country or region, and then follow the on-screen instructions.

Internal and External Power Supplies are available for purchase from the following EU distributor: EET

<https://www.eetgroup.com/en-eu/>


Removal and replacement procedures

Adherence to these procedures and precautions is essential for proper service.

Preparation for disassembly

Use this information to properly prepare to disassemble and reassemble the monitor.

1. Read the "Important safety information" and "Important service information and precautions" sections in the "Getting started" chapter of this guide.
2. Clean the room for disassembly.
3. Identify the disassembly area.
4. Check the position that the monitors are to be placed along with the number of monitors. Prepare the area for material flow according to the disassembly layout.
5. Be sure to have the following equipment and materials:
 - Press fixture
 - Working table
 - Screwdriver
 - Knife
 - Gloves
 - Cleaning cloth
 - ESD protection
 - Scraper bar in the following dimensions:



Rear Cover

Before removing the RC, follow these steps:


- ▲ Prepare the monitor for disassembly. See Preparation for disassembly on page 9.

Step 1 Quick release Base stand

(1) Lay the display on soft desk and push the button of stand to unlock the stand, then pull out the stand from the monitor head.




(2) Twist out the screw and separate base and stand.



Step 2: Strip two screws from the rear cover, then move rear cover follow the below way.






Remove 8PINFFC from the MB



Step 3: Remove two acetate cloth tape and pull out the LED/30pin ffc cable.



Step 4: Remove the rear support thirteen screws, hinge four screws, MB three screws.





Remove deco from the monitor.




Connector repair

This procedure includes HDMI and VGA connectors.

The connectors are on the main board (board part number R353200920150)

The connectors identifiers are as follows:

Connector	Location
VGA	P100
HDMI	P200/P300



Before repairing connectors, follow these steps:

▲ Prepare the monitor for disassembly. See Preparation for disassembly on page 12.

VGA P100

Repair the VGA connector:

1. Use a hot air gun to melt the solder on the pins. Pin solder with soldering iron and absorber. You can gently push down with the soldering iron once everything is molten to move the P100 out of the through holes.



2. Lift the P100 connector from the PCB..
3. Place the new component on the PCB. Be sure that it matches the PCB footprint.
4. Solder the new component.


HDMI connector P200/P300

Repair the HDMI connector:

5. Use a soldering iron and a desoldering pump to remove as much solder as possible from the pin.



6. Use a soldering iron or hot air gun to melt the solder on the pins.



7. Lift the P200/P300 connector from the PCB.
8. Place the new component on the PCB. Be sure that it matches the PCB footprint.
9. Solder the new component.

Function test

After repair, be sure to confirm that all functions are working.

Table 4-1: Function test

Test item	Operating description	Tool used
HDMI test	Confirm whether image displays correctly on the monitor.	Computer or DVD player
VGA test	Confirm whether image displays correctly on the monitor.	Computer or DVD player


Support and troubleshooting

The following table lists possible problems, the possible cause of each problem, and the recommended solutions.

Table 4-2: Solving common problems

Problem	Possible cause	Solution
Screen is blank or video is flashing.	Power cord is disconnected.	Connect the power cord.
	Monitor is off.	Power the power button. NOTE: If pressing the Power button has no effect, press and hold the power button for 10 seconds to disable the Power button lockout feature.
	Video cable is improperly connected.	Connect the video cable properly.
	System is in Sleep mode.	Press any key on the keyboard or move the mouse to exit Sleep mode.
	Video card is incompatible.	Open the OSD menu and select the Input Control menu. Set Auto-Switch Input to Off and manually select the input
Image appears blurred, Indistinct, or too dark.	Brightness is too low.	Open the OSD menu and select Brightness to adjust the brightness scale as needed.
Check Video Cable is displayed on screen.	Monitor video cable is disconnected.	Connect the appropriate video signal cable between the computer and monitor. Be sure that the computer power is off while you connect the video cable.
Input Signal Out of Range is displayed on screen.	Video resolution and/or refresh rate are set higher than what the monitor supports.	Change the settings to a supported setting.
The monitor is off, but it did not seem to enter into Sleep mode.	The monitor's power saving control is disabled.	Open the OSD menu and select Power Control > Auto-Sleep Mode and set auto-sleep to On.
On-Screen Menus are Locked is displayed.	The monitor's OSD lock function is enabled.	Press and hold the Menu button on the front bezel to 10 seconds to disable the OSD lockout function.
Power Button is Locked is Displayed	The monitor's power button is locked.	Press and hold the power button for 10 seconds to disable the power button lock function.
No low-power sleep mode	The monitor's power button is locked.	Press and hold the power button for 10 seconds to disable the power button lock function.



 <small>Maintenance and Service Guide M32f M31389 M32f M31389</small> <small>Copyright © 2014 Hewlett-Packard Development Company, L.P. All rights reserved. HP, the HP logo, and M32f are trademarks of Hewlett-Packard Development Company, L.P. in the United States and other countries. M31389 is a trademark of Hewlett-Packard Development Company, L.P. in the United States and other countries. FHD is a trademark of Intel Corporation in the United States and other countries. Monitor is a trademark of Intel Corporation in the United States and other countries.</small>	<p>hp M32f FHD Monitor [pdf] User Guide M32f FHD Monitor, M32f, M31389, FHD Monitor, Monitor</p>
--	--

References

-  partsurfer.com
-  support.hp.com
-  hp.com/support
-  [HP PartSurfer](#)
-  [EET International](#)

Manuals+.