



KeyPad Plus Wireless Touch Keypad for Managing The Ajax Security System User Manual

Contents

- 1 KeyPad Plus Wireless Touch Keypad for Managing The Ajax Security System
- 2 Functional elements
- 3 Operating principle
- 4 Function button
 - 4.1 Duress code
 - 4.2 Two-stage arming
 - 4.3 Connection
 - 4.4 Before starting connection
 - 4.5 To connect KeyPad Plus
 - 4.6 Icons
- 5 States
- 6 Settings
- 7 Adding a personal password
 - 7.1 Adding passes and tags
- 8 Security management by passwords
- 9 Security management of the facility using a common password
 - 9.1 Security management of the facility using a personal password
 - 9.2 Group security management with a personal password
 - 9.3 Using a duress code
 - 9.4 To use a common duress code
- 10 Security management using Tag or Pass
 - 10.1 Mute Fire Alarm function
- 11 Indication
- 12 Functionality testing
- 13 Choosing a location
- 14 Installing the keypad
- 15 Maintenance
- 16 Complete set
- 17 Technical Specifications
- 18 Warranty
- 19 Documents / Resources
 - 19.1 References
- 20 Related Posts

KeyPad Plus


KeyPad Plus Wireless Touch Keypad for Managing The Ajax Security System




KeyPad Plus is a wireless touch keypad for managing the Ajax security system with encrypted contactless cards and key fobs. Designed for indoor installation. Supports “silent alarm” when entering the duress code. Manages security modes using passwords and cards or key fobs . Indicates the current security mode with a LED light. The keypad operates as part of the Ajax security system by connecting via the Jeweller secure radio communication protocol to the hub. The communication range without obstacles is up to 1700 meters. The pre-installed battery life is up to 4.5 years.

Buy KeyPad Plus keypad

Functional elements






1. Armed indicator
2. Disarmed indicator
3. Night mode indicator
4. Malfunction indicator
5. Pass/Tag Reader
6. Numeric touch button box
7. Function button
8. Reset button
9. Arm button
10. Disarm button
11. Night mode button
12. SmartBracket mounting plate (to remove the plate, slide it down)

Do not tear off the perforated part of the mount. It is required for actuating the tamper in case of any attempt to dismantle the keypad.

13. Tamper button
14. Power button
15. Keypad QR Code

Operating principle



KeyPad Plus arms and disarms the security of the entire facility or separate groups as well as allows activating the Night mode. You can control the security modes with KeyPad Plus using:

1. Passwords. The keypad supports common and personal passwords, as well as arming without entering a password.
2. Cards or key fobs. You can connect Tag key fobs and Pass cards to the system. To quickly and securely identify users, KeyPad Plus uses the DESFire® technology. DESFire® is based on the ISO 14443 international standard and combines 128-bit encryption and copy protection.

Before entering a password or using Tag/Pass, you should activate (“wake up”) the KeyPad Plus by sliding your hand over the touch panel from top to bottom. When it is activated, the button backlight is enabled, and the keypad beeps.

The KeyPad Plus is equipped with LED indicators that show the current security mode and keypad malfunctions (if any). The security status is displayed only when the keypad is active (the device backlight is on).



You can use the KeyPad Plus without ambient lighting as the keypad has a backlight. The pressing of the buttons is accompanied by a sound signal. The backlight brightness and keypad volume are adjustable in the settings. If you do not touch the keypad for 4 seconds, KeyPad Plus reduces the backlight brightness, and 8 seconds later goes into power-saving mode and turns off the display. If the batteries are discharged, the backlight turns on at the minimum level regardless of the settings.

Function button

KeyPad Plus has a Function button that operates in 3 modes:

- Off — the button is disabled and nothing happens after it is pressed.
- Alarm — after the Function button is pressed, the system sends an alarm to the security company monitoring station and all users.
- Mute interconnected fire alarm — after the Function button is pressed, the system mutes the fire alarm of the FireProtect/FireProtect Plus detectors. Available only if an Interconnected FireProtect Alarm is enabled (Hub → Settings → Service → Fire detectors settings)

Duress code

KeyPad Plus supports duress code. It allows you to simulate alarm deactivation.

but the security company and other users of the security system will be warned about the incident.

Learn more

Two-stage arming

KeyPad Plus can participate in two-stage arming, but cannot be used as a second-stage device. The two-stage arming process using Tag or Pass is similar to arming using personal or common password on the keypad.

Learn more

Event transmission to the monitoring station

The Ajax security system can connect to the CMS and transmit events and alarms to the monitoring station of the security company in Sur-Gard (ContactID), SIA DC-09, and other proprietary protocol formats. A complete list of supported protocols is available [here](#). The device ID and the number of the loop (zone) can be found in its states.

Connection

KeyPad Plus is incompatible with Hub, third-party security central units, and ocBridge Plus and uartBridge integration modules.

Before starting connection

1. Install the Ajax app and an account . Add a hub and create at least one room
2. Ensure that the hub is on and has Internet access (via Ethernet cable, Wi-Fi, and/or mobile network). This can be done by opening the Ajax app or by looking at the hub logo on the faceplate — it lights white or green if the hub is connected to the network.
3. Make sure that the hub is not in armed mode and does not start updates by checking its status in the app.

Only a user or PRO with full administrator rights can add a device to the hub.

To connect KeyPad Plus

1. Open the Ajax app. If your account has access to multiple hubs, select the one to which you want to connect KeyPad Plus.
2. Go to the Devices menu and click Add Device.
3. Name the keypad, scan or enter the QR code (located on the package and under the SmartBracket mount), and select a room.
4. Click Add; the countdown will begin.
5. Turn on the keypad by holding the power button for 3 seconds. Once connected, KeyPad Plus will appear in the hub device list in the app. To connect, locate the keypad at the same protected facility as the system (within the coverage area of the hub radio network range). If the connection fails, try again in 10 seconds.

The keypad only works with one hub. When connected to a new hub, the device stops sending commands to the old hub. Once added to a new hub, KeyPad Plus is not removed from the device list of the old hub. This must be done manually through the Ajax app. KeyPad Plus turns off automatically 6 seconds after being turned on if the keypad fails to connect to the hub. Therefore, you do not need to turn off the device to retry the connection. Updating the statuses of devices in the list depends on the Jeweller settings; the default value is 36 seconds.

Icons


The icons represent some of KeyPad Plus states. You can see them in the Devices tab in the Ajax app.

Icon	Value
	Jeweller signal strength — Displays the signal strength between the hub or range extender and KeyPad Plus
	Battery charge level of KeyPad Plus
	KeyPad Plus works via a ReX radio signal range extender
	KeyPad Plus body status notifications are temporarily disabled Learn more
	KeyPad Plus is temporarily deactivated Learn more
	Pass/Tag reading is enabled in KeyPad Plus settings
	Pass/Tag reading is disabled in KeyPad Plus settings

States

The states include information about the device and its operating parameters. The states of KeyPad Plus can be found in the Ajax app:

1. Go to the Devices tab.
2. Select KeyPad Plus from the list.

Parameter	Value
Malfunction	Pressing  opens the KeyPad Plus malfunctions list. The field is displayed only if a malfunction is detected
Temperature	Keypad temperature. It is measured on the processor and changes gradually. Acceptable error between the value in the app and the room temperature: 2–4°C
Jeweller signal strength	Jeweller signal strength between the hub (or ReX range extender) and the keypad. Recommended values — 2-3 bars
Connection	Connection status between the hub or range extender and the keypad: Online — the keypad is online Offline — no connection to the keypad

Battery charge	<p>The battery charge level of the device. Two states are available:</p> <p>OK</p> <p>Battery low</p> <p>When the batteries are discharged, the Ajax apps and the security company will receive appropriate notifications.</p> <p>After sending a low battery notification, the keypad can work for up to 2 months</p> <p>How battery charge is displayed in Ajax apps</p>
Lid	<p>The status of the device tamper, which reacts to the detachment of or damage to the body:</p> <p>Opened Closed</p> <p>What is a tamper</p>
Works via *range extender name*	<p>Displays the status of the ReX range extender use. The field is not displayed if the keypad works directly with the hub</p>
Pass/Tag Reading	<p>Displays if card and keyfob reader is enabled</p>
Easy armed mode change/Assigned group easy management	<p>Displays whether or not the security mode can be switched with Pass or Tag and without confirmation by the control buttons , ,</p>

Temporary Deactivation	<p>Shows the status of the device:</p> <p>No — the device operates normally and transmits all events</p> <p>Lid only — the hub administrator has disabled notifications about the body opening</p> <p>Entirely — the hub administrator has entirely excluded the keypad from the system. The device does not execute system commands and does not report alarms or other events</p> <p>Learn more</p>
Firmware	KeyPad Plus firmware version
ID	Device identifier
Device No.	Number of the device loop (zone)

Settings

KeyPad Plus is configured in the Ajax app:

1. Go to the Devices tab.
2. Select KeyPad Plus from the list.
3. Go to Settings by clicking on the gear icon .

To apply the settings after the change, click the Back button

Parameter	Value
First field	Device name. Displayed in the list of hub devices, SMS text, and notifications in the event feed. To change the device name, click on the pencil icon . The name can contain up to 12 Cyrillic characters or up to 24 Latin characters
Room	Selecting the virtual room to which KeyPad Plus is assigned. The name of the room is displayed in the text of SMS and notifications in the event feed
Group Management	Selecting the security group controlled by the device. You can select all groups or just one. The field is displayed when the Group mode is enabled
Access Settings	Selecting the method of arming/disarming: Keypad code only User passcode only Keypad and user passcode
Keypad code	Selection of a common password for security control. Contains 4 to 6 digits
Duress code	Selecting a common duress code for silent alarm. Contains 4 to 6 digits
	Learn more
Pass/Tag Reset	Allows deleting all hubs associated with Tag or Pass from device memory Learn more
Temporary Deactivation	Allows the user to disable the device without removing it from the system. Two options are available: Entirely — the device will not execute system commands or participate in automation scenarios, and the system will ignore device alarms and other notifications Lid only — the system will only ignore notifications about the triggering of the device tamper button Learn more about temporary deactivation of devices
User Manual	Opens the KeyPad Plus User Manual in the Ajax app
Unpair Device	Disconnects KeyPad Plus from the hub and deletes its settings

Entry and exit delays are set in the corresponding detector settings, not in the keypad settings.
Learn more about entry and exit delays

Adding a personal password

Both common and personal user passwords can be set for the keypad. A personal password applies to all Ajax keypads installed at the facility. A common password is set for each keypad individually and can be different or the same as the passwords of other keypads.

To set a personal password in the Ajax app:

1. Go to the user profile settings (Hub → Settings → Users → Your profile settings).
2. Select Passcode Settings (User ID is also visible in this menu).
3. Set User Code and Duress Code.

Each user sets a personal password individually. The administrator cannot set a password for all users.

Adding passes and tags

KeyPad Plus can work with Tag key fobs, Pass cards , and third-party cards and key fobs that use DESFire® technology.

Before adding third-party devices that support DESFire®, make sure they have enough free memory to handle the new keypad. Preferably, the third-party device should be pre-formatted.

The maximum number of connected passes/tags depends on the hub model. At the same time, the bound passes and tags do not affect the total limit of devices on the hub.

Hub model	Number of Tag or Pass devices
Hub Plus	99
Hub 2	50
Hub 2 Plus	200

The procedure for connecting Tag, Pass, and third-party devices is the same. See the connecting instructions [here](#).

Security management by passwords

You can manage the Night mode, security of the entire facility or separate groups using common or personal passwords. The keypad allows you to use 4 to 6 digit passwords. Incorrectly entered numbers can be cleared with the [button](#).


If a personal password is used, the name of the user who armed or disarmed the system is displayed in the hub event feed and in the notifications list. If a common password is used, the name of the user who changed the security mode is not displayed.

Arming with a personal password

The username is displayed in the notifications and events feed


Arming with a personal password

The username is displayed in the notifications and events feed



Arming with a common password

The device name is displayed in the notifications and events feed



Keypad Plus is locked for the time specified in the settings if an incorrect password is entered three times in a row within 1 minute. The corresponding notifications are sent to users and to the monitoring station of the security company. A user or PRO with administrator rights can unlock the keypad in the Ajax app.

Security management of the facility using a common password

1. Activate the keypad by swiping your hand over it.
2. Enter the common password.
3. Press the arming /disarming /Night mode key.

For example: 1234 →

1. Activate the keypad by swiping your hand over it.
2. Enter the common password.
3. Press the * (Function button).
4. Enter the Group ID.
5. Press the arming /disarming /Night mode key.

For example: 1234 → * → 2 →

What is Group ID

If a security group is assigned to KeyPad Plus (in the Group Management field in the keypad settings), you do not need to enter the group ID. To manage the security mode of this group, entering a common or personal password is sufficient.

If a group is assigned to KeyPad Plus, you will not be able to manage Night mode using a common password. In this case, Night mode can only be managed using a personal password if the user has the appropriate rights. Rights in the Ajax security system

Security management of the facility using a personal password

1. Activate the keypad by swiping your hand over it.
2. Enter the User ID.
3. Press the * (Function button).
4. Enter your personal password.
5. Press the arming /disarming /Night mode key.

For example: 2 → * → 1234 →

What is User ID

Group security management with a personal password

1. Activate the keypad by swiping your hand over it.
2. Enter the User ID.
3. Press the * (Function button).
4. Enter your personal password.
5. Press the * (Function button).
6. Enter the Group ID.
7. Press the arming /disarming /Night mode key.

For example: 2 → * → 1234 → * → 5 →

If a group is assigned to KeyPad Plus (in the Group Management field in the keypad settings), you do not need to enter the group ID. To manage the security mode of this group, entering a personal password is sufficient.

What is Group ID

Using a duress code

A duress code allows you to simulate alarm deactivation. The Ajax app and sirens installed at the facility will not give the user away in this case, but the security company and other users will be warned about the incident. You can use both a personal and a common duress code.

Scenarios and sirens react to disarming under duress in the same way as to normal disarming.

To use a common duress code

1. Activate the keypad by swiping your hand over it.
2. Enter the common duress code.
3. Press the disarming key .

For example: 4321 →

To use a personal duress code

1. Activate the keypad by swiping your hand over it.
2. Enter the User ID.
3. Press the * (Function button).
4. Enter the personal duress code.
5. Press the disarming key .

For example: 2 → * → 4422 →

Security management using Tag or Pass

1. Activate the keypad by swiping your hand over it. KeyPad Plus will beep (if enabled in the settings) and turn on the backlight.
2. Bring Tag or Pass to the keypad pass/tag reader. It is marked with wave icons.
3. Press the Arm, Disarm, or Night mode button on the keypad.

Mute Fire Alarm function

KeyPad Plus can mute an interconnected fire alarm by pressing the Function button (if the required setting is enabled). The reaction of the system to pressing a button depends on the settings and the state of the system:


- Interconnected FireProtect Alarms have already propagated — by the first press of the Button, all sirens of the fire detectors are muted, except for those that registered the alarm. Pressing the button again mutes the remaining detectors.
- Interconnected alarms delay time lasts — by pressing the Function button, the siren of the triggered FireProtect/FireProtect Plus detector is muted.

Keep in mind that the option is available only if Interconnected FireProtect Alarm is enabled.

[Learn more](#)

Indication

KeyPad Plus can report the current security mode, keystrokes, malfunctions, and its status by LED indication and sound. The current security mode is displayed by the backlight after the keypad is activated. The information about the current security mode is relevant even if the arming mode is changed by another device: a key fob, another keypad, or an app.



You can activate the keypad by swiping your hand over the touch panel from top to bottom. When activated, the backlight on the keypad will turn on and a beep will sound (if enabled).

Event	Indication
There is no connection to the hub or ReX range extender	LED X blinks
KeyPad Plus body is open (SmartBracket mount is removed)	LED X blinks briefly once
Touch button pressed	Short beep, the current system security status LED blinks once. The volume depends on the keypad settings
The system is armed	Short beep, Armed or Night mode LED lights up
The system is disarmed	Two short beeps, the Disarmed LED lights up
An incorrect password was entered or there was an attempt to change security mode by an unconnected or deactivated pass/tag	Long beep, digital unit LED backlight blinks 3 times
The security mode cannot be activated (for example, a window is open and the System integrity check is enabled)	Long beep, the current security status LED blinks 3 times
The hub does not respond to the command — there is no connection	Long beep, X (Malfunction) LED lights up
The keypad is locked due to a wrong password	Long beep, during which the security status LEDs

Functionality testing

The Ajax security system provides several types of tests that help you make sure that installation points of devices are selected correctly.

KeyPad Plus functionality tests do not start straight away but after no more than one hub-detector ping period (36 seconds when using the standard hub settings). You can change the ping period of devices in the Jeweller menu of the hub settings.

Tests are available in the device settings menu (Ajax App → Devices → KeyPad Plus → Settings)

- Jeweller Signal Strength Test
- Attenuation Test

Choosing a location



When holding KeyPad Plus in your hands or using it on a table, we cannot guarantee that the touch buttons will work properly.\

It is a good practice to install the keypad 1.3 to 1.5 meters above the floor for convenience. Install the keypad on a flat, vertical surface. This allows KeyPad Plus to be firmly attached to the surface and to avoid false tamper triggering.

Besides, the placement of the keypad is determined by the distance from the hub or the ReX range extender, and the presence of obstacles between them that prevent the passage of the radio signal: walls, floors, and other objects. Be sure to check the Jeweller signal strength at the installation site. If the signal strength is low (a single bar), we cannot guarantee a stable operation of the security system! At the very least, relocate the device as repositioning even by 20 cm can significantly improve the signal reception.

If poor or unstable signal strength is still reported after the relocation of the device, use the ReX radio signal range extender

Do not install the keypad:

- In places where parts of clothing (for example, next to the hanger), power cables, or Ethernet wire may obstruct the keypad. This can lead to false triggering of the keypad.
- Inside premises with temperature and humidity outside the permissible limits. This could damage the device.
- In places where KeyPad Plus has an unstable or poor signal strength with the hub or ReX range extender.
- Within 1 meter of a hub or ReX range extender. This could result in the loss of connection with the keypad.
- Close to electrical wiring. This may cause communication interferences.
- Outdoors. This could damage the device.


Installing the keypad

Prior to installing KeyPad Plus, be sure to select the optimal location following the requirements of this manual!

1. Attach the keypad to the surface with double-sided adhesive tape and carry out signal strength and attenuation tests. If the signal strength is unstable or if one bar is displayed, move the keypad or use the ReX range extender.

Double-sided adhesive tape may only be used for temporary attachment of the keypad. The device attached with adhesive tape can at any time be detached from the surface and fall, which may lead to failure. Please note that if the device is attached with adhesive tape, the tamper will not trigger when trying to detach it.

2. Check the convenience for password entry using Tag or Pass to manage security modes. If it is inconvenient to manage the security at the selected location, relocate the keypad.
3. Remove the keypad from the SmartBracket mounting plate.
4. Attach the SmartBracket mounting plate to the surface using the bundled screws. When attaching, use at least two fixing points. Be sure to fix the perforated corner on the SmartBracket plate so that the tamper responds to a detachment attempt.



5. Slide KeyPad Plus onto the mounting plate and tighten the mounting screw at the bottom of the body. The screw is needed for more reliable fastening and protection of the keypad from quick dismantling.
6. As soon as the keypad is fixed on the SmartBracket, it shall blink once with LED X — this is a signal that the tamper has been triggered. If the LED does not blink after installation on SmartBracket, check the tamper status in the Ajax app, and then make sure the plate is firmly attached.

Maintenance



Check the functioning of your keypad on a regular basis. This can be done once or twice a week. Clean the body from dust, cobwebs, and other contaminants as they emerge. Use a soft dry cloth that is suitable for equipment care.

Do not use substances that contain alcohol, acetone, gasoline or other active solvents to clean the detector. Wipe the touch keypad gently: scratches can reduce the sensitivity of the keypad.

The batteries installed in the keypad provide up to 4.5 years of autonomous operation at default settings. If the battery is low, the system sends appropriate notifications, and the X (Malfunction) indicator smoothly lights up and goes out after each successful password entry.

KeyPad Plus can work up to 2 months after the low battery signal. However, we recommend you replace the batteries immediately upon notification. It is advisable to use lithium batteries. They have a large capacity and are less affected by temperatures.

- How long Ajax devices operate on batteries, and what affects this

- How to replace batteries in KeyPad Plus

Complete set

1. KeyPad Plus
2. SmartBracket mounting plate
3. 4 pre-installed lithium batteries AA (FR6)
4. Installation kit
5. Quick Start Guide

Technical Specifications

Compatibility	Hub Plus, Hub 2, Hub 2 Plus, ReX
Color	Black, White
Installation	Indoor only
Keypad type	Touch-sensitive
Sensor type	Capacitive
Contactless access	DESFire EV1, EV2 ISO14443-A (13.56 MHz)
Tamper protection	Yes
Password guessing protection	Yes. The keypad is locked for the time set in the settings if an incorrect password is entered three times
Protection against attempts to use not bound to the system pass/tag	Yes. The keypad is locked for the time defined in the settings
Frequency band	868.0 – 868.6 MHz or 868.7 – 869.2 MHz, depending on the sales region
Radio signal modulation	GFSK
Maximum radio signal strength	6.06 mW (limit up to 20 mW)
Radio signal range	Up to 1,700 m (without obstacles) Learn more
Power supply	4 lithium batteries AA (FR6). Voltage 1.5V
Battery life	Up to 3.5 years (if pass/tag reading is enabled)

Compliance with standards



Warranty

The warranty for the AJAX SYSTEMS MANUFACTURING Limited Liability Company products is valid for 2 years after purchase and does not extend to the bundled batteries.

If the device does not function properly, we recommend that you first contact the support service as half of the technical issues can be resolved remotely!











Warranty obligations

Documents / Resources

 <p>KeyPad Plus User Manual</p>	<p>AJAX KeyPad Plus Wireless Touch Keypad for Managing The Ajax Security System [pdf] User Manual KeyPad Plus, Wireless Touch Keypad for Managing The Ajax Security System, Wireless Touch Keypad, Touch Keypad, KeyPad Plus, Keypad</p>
 <p>KeyPad User Manual</p>	<p>AJAX KeyPad [pdf] User Manual KeyPad</p>

References

- 🔗 [OS Malevich 2.12: Full control over the hub communication and even more features for Ajax sirens | Ajax Systems Blog](#)
- 🔗 [End user agreement - Ajax Systems](#)
- 🔗 [Jeweller radio technology | Ajax Systems](#)
- 🔗 [Current product lines of the Ajax security system](#)
- 🔗 [Current product lines of the Ajax security system](#)
- 🔗 [Hub — Intelligent security control panel | Ajax Systems](#)
- 🔗 [KeyPad Plus — Security keypad with support for contactless chips](#)
- 🔗 [KeyPad - Wireless touch keyboard | Ajax Systems](#)
- 🔗 [ocBridge Plus — Module for Ajax devices integration with wired systems](#)
- 🔗 [ReX — Intelligent radio signal range extender | Ajax Systems](#)
- 🔗 [uartBridge — Module for Ajax devices integration with third-party wireless alarms systems](#)
- 🔗 [Jeweller and Wings radio protocols in the Ajax security system](#)
- 🔗 [Software | Ajax Systems](#)
- 🔗 [Ajax devices standards compliance list](#)
- 🔗 [Warranty - Ajax Systems](#)
- 🔒 [User account types and rights | Ajax Systems Support](#)
- 🔒 [How to enable and configure group mode in the Ajax security system | Ajax Systems Support](#)
- 🔒 [How to enable and configure group mode in the Ajax security system | Ajax Systems Support](#)
- 🔒 [How battery charge is displayed in Ajax apps | Ajax Systems Support](#)
- 🔒 [What is Easy armed mode change | Ajax Systems Support](#)
- 🔒 [What is the identificator \(ID\) of the group? | Ajax Systems Support](#)
- 🔒 [How to create the Ajax account? | Ajax Systems Support](#)
- 🔒 [What is a tamper | Ajax Systems Support](#)
- 🔒 [What is duress code, and how to use it | Ajax Systems Support](#)
- 🔒 [What is the user identifier? | Ajax Systems Support](#)

-  [How long Ajax devices operate on batteries, and what affects this | Ajax Systems Support](#)
-  [How to temporarily deactivate a device without removing it from the system | Ajax Systems Support](#)
-  [How to change batteries in the KeyPad | Ajax Systems Support](#)
-  [Which CMSs can Ajax hubs be connected to | Ajax Systems Support](#)
-  [Jeweller radio protocol: technology and capabilities | Ajax Systems Support](#)
-  [Tag and Pass User manual | Ajax Systems Support](#)
-  [Tag and Pass User manual | Ajax Systems Support](#)
-  [Tag and Pass User manual | Ajax Systems Support](#)
-  [Hub 2 Plus User manual | Ajax Systems Support](#)
-  [Hub 2 \(2G\) / \(4G\) User manual | Ajax Systems Support](#)

Manuals+.