



Aladdin Pixel Controller With Lumenradio User Manual

[Home](#) » [ALADDiN](#) » Aladdin Pixel Controller With Lumenradio User Manual 



Aladdin PIXEL CONTROLLER
with Lumenradio, DMX & ArtNet



USER MANUAL

Contents

- 1 Pixel Controller With Lumenradio
- 2 TECHNICAL SPECIFICATIONS
- 3 WARRANTY
- 4 WARRANTY EXCLUSIONS
- 5 SELECTED OPTIONAL ACCESSORIES
- 6 START-UP GUIDE
- 7 STATES
- 8 DMX / ArtNet OPERATION
- 9 IMPORTANT CAUTIONS AND WARNINGS
- 10 Documents / Resources
 - 10.1 References

Pixel Controller With Lumenradio



THANK YOU FOR YOUR PURCHASE

User Manual

Version: 14. February 2024, 5:58 PM

Aladdin Lights

info@aladdin-lights.com

TECHNICAL SPECIFICATIONS

Article Code	–
Compatibility	MOSAIC Series
Cooling	Passive cooling
Power Input	4-pin Chogori Socket
Power Consumption	–
Dimensions	–
Weight	–
User Interface	Graphic OLED (128×64)
Temperature Range	–
DMX512 support	In (5-pin) and out (5-pin) / Lumenradio / ArtNet
Processor	ARM Cortex-M3
Ethernet	2 x Ethernet Sockets (10 Mbps)
DMX512	5 CH – RGBWW
Dimming Range	0.5% – 100%
Temperature Range	2'200 K – 12'000 K
IP-Rating	–

WARRANTY

We provide a one year warranty period after the purchase. This warranty covers repairs or a replacement for faulty products within this period. After this warranty has been expired, you can still get repairs for your product which will be charged extra.




Aladdin Lights reserves the right to refuse warranty service on products under disputable conditions.

WARRANTY EXCLUSIONS

In case of any of the below listed causes, the warranty does not apply, even if it is within the free warranty period.

- Product failure due to consumer negligence.
- Product failure due to usage of not compatible power sources.
- Product failure due to disassembly by not official resellers/distributors.

SELECTED OPTIONAL ACCESSORIES

		
FB2035ANT	FL12BIBASIC2M	FL12BIEXCA5M
Antenna for wireless Lumenradio t ransmission.	2 meters of extension cable for inbet ween dimmer unit and panel.	5 meters of extension cable for inbet ween dimmer unit and panel.

START-UP GUIDE



1	Lock / Black-Out Switch
2	Menu Page Buttons
3	OLED Display
4	Rotary Function Buttons – F1, F2, F3
5	LED Panel Connector Socket
6	RP-SMA Socket (Lumenradio Antenna)
7	Ethernet Ports (RJ45)
8	DMX-512A Input Socket (5-Pin XLR-M)
9	DMX-512A Output Socket (5-Pin XLR-F)
10	Micro SD Card Slot
11	V-Lock Plate

STATES

The OLED display shows you different pages for primary light control.

OLED	STATE
	WHITE page has been selected. Control with the rotary button.
	RGB page has been selected. Control with the rotary button.
	HSI page has been selected. Control with the rotary button.
	FILTER page has been selected. Choose filters or save & load values into memory.
	EFFECT page has been selected. Choose effects and control speed & intensity
	DMX page has been selected. Choose effects and control speed & intensity
	DMX/ARTNET page has been selected. Choose input: LumenRadio, DMX cable or ArtNet.

DMX / ArtNet OPERATION

In DMX or LumenRadio mode, you always need to choose a start address and the profile for the device. However, as this is self-explanatory we will go more into the ArtNet mode which seems a bit more complicated.

OLED	OPERATION
	Select ArtNet as Input type for ArtNet control. Then press F2 for the next step.
	You get to the IP address submenu. press F2.
	after you have pressed F2, the device retrieves the internal addresses (IP & MAC), which you need later for your controller software.

IMPORTANT CAUTIONS AND WARNINGS

- You must set the sheet type (see OPERATION) before connecting to a panel.
- Do not use near flammables and heaters.
- Do not expose the unit to direct sunlight for a long period (applies also for storing in a car).
- Do not damage the product with improper force or cause any impact with heavy objects.
- Keep out of reach of children.
- Use the product only within temperature range of -10°C – +40°C.
- When you have technical problems while using the product, stop using it immediately and contact your dealer / reseller.



Documents / Resources



[Aladdin Pixel Controller With Lumenradio](#) [pdf] User Manual
Pixel Controller With Lumenradio, Controller With Lumenradio, Lumenradio

References

- ✨ [Lights.com](#)
- [User Manual](#)

[Manuals+](#), [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.