


ANALOG DEVICES LT8608S 42V 1.5A Synchronous Step Down Regulator User Manual

[Home](#) » [Analog Devices](#) » ANALOG DEVICES LT8608S 42V 1.5A Synchronous Step Down Regulator User Manual 

ANALOG DEVICES LT8608S 42V 1.5A Synchronous Step Down Regulator User Manual



Contents

- [1 DESCRIPTION](#)
- [2 QUICK START PROCEDURE](#)
- [3 QUICK START PROCEDURE](#)
- [4 PARTS LIST](#)
- [5 Documents / Resources](#)
 - [5.1 References](#)

DESCRIPTION

Demonstration circuit 2711A is a 42V, 1.5A synchronous step-down regulator featuring the LT8608S. The demo board is designed for 5V output from a 5.5V to 42V input. The wide input range allows a variety of input sources, such as automotive batteries and industrial supplies. The LT8608S is a compact, high efficiency, high speed

synchronous monolithic step-down switching regulator with the second-generation Silent Switcher® structure that minimizes EMI and reduces PCB layout sensitivity. LT8608S consumes only 3µA of quiescent current when output is regulated at 5V. Top and bottom power switches, compensation components and other necessary circuits are inside of the LT8608S to minimize external components and simplify design.

The SYNC pin on the demo board is grounded by default for low ripple Burst Mode® operation. Move JP1 to PULSE SKIPPING position can change the operation mode to pulse-skipping operation. Once JP1 is on SPREAD SPECTRUM position, VCC is applied to the SYNC pin of low EMI spread spectrum operation. To synchronous to an external clock, move JP1 to SYNC and apply the external clock to the SYNC turret. Figure 1 shows the efficiency of the circuit.

The demo board has an EMI filter installed. The radiated EMI performances of the board (with EMI filter) are shown in Figure 2 and Figure 3. The red lines in Figure 2 and Figure 3 are CISPR25 Class 5 peak limit. To use the EMI filter, the input should be tied to VEMI, not VIN. An inductor L2, which is shorted on the board by default now, can be added in the EMI filter to further reduce the conducted emission.

The LT8608S data sheet gives a complete description of the part, operation and application information. The data sheet must be read in conjunction with this demo manual for DC2711A.

PERFORMANCE SUMMARY

SYMBOL	PARAMETER	CONDITIONS	MIN	TYP	MAX	UNITS
VIN	Input Voltage Range		5.5		42	V
VOU T	Output Voltage		4.8	5	5.2	V
IOUT	Maximum Output Current		1.5			A
fawn	Switching Frequency		1.85	2	2.15	MHz
EFE	Efficiency at DC	VIN = 12V, IOUT = 0.75A	90.3			%

QUICK START PROCEDURE

DC2711A is easy to set up to evaluate the performance of the LT8608S. Refer to Figure 4 for measurement equipment setup and follow the procedure below

NOTE: When measuring the input or output voltage ripple, care must be taken to avoid a long ground lead on the oscilloscope probe. See Figure 5 for the proper scope technique

1. Set an input power supply that is capable of 42V at 1.5A. Then turn off the supply.
2. With power off, connect the supply to the input terminals VIN and GND.
3. Turn on the power at the input.


NOTE: Make sure that the input voltage never exceeds 42V.

4. Check for the proper output voltage of 5V. Turn off the power at the input.
5. Once the proper output voltage is established, connect a variable load capable of sinking 1.5A at 5V to the output terminals VOUT and GND. Set the current for 0A.
 - a. If efficiency measurements are desired, an ammeter can be put in series with the output load in order to measure the DC2711A's output current.


- b. A voltmeter can be placed across the output terminals in order to get an accurate output voltage measurement.
6. Turn on the power at the input.
- NOTE:** If there is no output, temporarily disconnect the load to make sure that the load is not set too high.
7. Once the proper output voltage is established again, adjust the load and/or input within the operating range and observe the output voltage regulation, ripple voltage, efficiency and other desired parameters.
8. An external clock can be added to the SYNC terminal when SYNC function is used (JP1 on the SYNC position). Please ensure that the chosen RT sets the LT8608S switching frequency to equal or below the lowest SYNC frequency. See the data sheet section, Synchronization.

QUICK START PROCEDURE

Figure 1. Efficiency vs Load Current at 2MHz Switching Frequency




Radiated EMI Performance (CISPR25 Radiated Emission Test with Class 5 Peak Limits)



DC2711A DEMO BOARD
(WITH EMI FILTER INSTALLED)
14V INPUT TO 5V OUTPUT AT 1.5A, $f_{sw} = 2\text{MHz}$

Figure 2. LT8608S Demo Circuit EMI Performance in CISPR25 Radiated Emission Test, Antenna Polarization: Vertical ($V_{IN} = 14V$, $V_{OUT} = 5V$, $I_{OUT} = 1.5A$, 2MHz Switching Frequency)

Radiated EMI Performance (CISPR25 Radiated Emission Test with Class 5 Average Limits)



DC2711A DEMO BOARD
(WITH EMI FILTER INSTALLED)
14V INPUT TO 5V OUTPUT AT 1.5A, fawn = 2MHz

Figure 3. LT8608S Demo Circuit EMI Performance in CISPR25 Radiated Emission Test, Antenna Polarization: Horizontal (VIN = 14V, VOUT = 5V, IOUT = 1.5A, 2MHz Switching Frequency)




Figure 4. Proper Measurement Equipment Setup




Figure 5. Measuring Output Ripple

PARTS LIST

ITEM	QTY	REFERENCE	PART DESCRIPTION	MANUFACTURER/PART NUMBER
------	-----	-----------	------------------	--------------------------

Required Circuit Components

1	1	C2	CAP., X7R, 4.7μF, 50V, 10% 1206	MURATA, GRM31CR71H475KA12L
2	1	C5	CAP., C0G, 10pF, 25V, 5%, 0603	AVX, 06033A100JAT2A
3	1	C6	CAP., X7R, 47μF, 10V, 10%, 1210	MURATA, GRM32ER71A476KE15 L
4	1	C8	CAP., X7R, 0.01μF, 16V, 10%, 0603	AVX, 0603YC103KAT2A
5	1	C13	CAP., X7R, 1μF, 16V, 10%, 0603	AVX, 0603YC105KAT2A
6	1	L1	IND., 2.2μH	COILCRAFT, XFL4020-222ME
7	1	R2	RES., CHIP, 18.2k, 1/10W, 1%, 0603	VISHAY, CRCW060318K2FKEA
8	1	R3	RES., CHIP, 49.9k, 1/10W, 1%, 0603	VISHAY, CRCW060349K9FKEA
9	2	R1, R4	RES., CHIP, 1M, 1/10W, 1%, 0603	VISHAY, CRCW06031M00FKEA
10	1	R5	RES., CHIP, 187k, 1/10W, 1%, 0603	VISHAY, CRCW0603187KFKEA
11	1	U1	IC, REGULATOR, LQFN-12	ANALOG DEVICES, LT8608SEV# TRMPBF


Additional Demo Board Circuit Components

1	1	C1	CAP., ALUM 22μF 63V	SUN ELECT, 63CE22BS
2	2	C3, C10	CAP., X7R, 4.7μF, 50V, 10% 1206	MURATA, GRM31CR71H475KA12L
3	1	C9	CAP., X7R, 4.7μF, 16V, 10%, 0805	MURATA, GRM21BR71C475K73L
4	1	C11	CAP., X7R, 1μF, 50V, 10%, 0805	MURATA, GRM21BR71H105KA12 L
5	1	C12	CAP., X7R, 0.1μF, 50V, 10%, 0603	MURATA, GRM188R71H104KA93 D
6	1	FB1	FERRITE BEAD 0805	TDK, MPZ2012S331AT000
7	0	L2 (OPT.)	IND., 2010	
8	0	R6 (OPT.)	RES., 0603	

Hardware: For Demo Board Only

1	9	E1-E9	TESTPOINT, TURRET, 0.094"	MILL-MAX, 2501-2-00-80-00-00-07-0
2	1	E10 (OPT.)	TESTPOINT, TURRET, 0.094"	
3	1	JP1	DOUBLE ROW HEADER 2 × 4 0.079"	SULLINS, NRPN042PAEN-RC
4	1	XJP1	SHUNT, 0.079" CENTER	SAMTEC, 2SN-BK-G
5	4	MH1-MH4	STAND-OFF, NYLON 0.50" TALL	KEYSTONE, 8833(SNAP ON)

SCHEMATIC DIAGRAM



Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Device



ESD (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on

devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.


Legal Terms and Conditions

By using the evaluation board discussed herein (together with any tools, component documentation or support materials, the "Evaluation Board"), you are agreeing to be bound by the terms and conditions set forth below ("Agreement") unless you have purchased the Evaluation Board, in which case the Analog Devices Standard Terms and Conditions of Sale shall govern. Do not use the Evaluation Board until you have read and agreed to the Agreement. Your use of the valuation Board shall signify your acceptance of the Agreement. This Agreement is made by and between you ("Customer") and Analog Devices, Inc. ("ADI"), with its principal place of business at One Technology Way, Norwood, MA 02062, USA. Subject to the terms and conditions of agreement, ADI hereby grants to Customer a free, limited, personal, temporary, non-exclusive, licensable, non transferable license to use the Evaluation Board FOR EVALUATION PURPOSES ONLY. Customer understands and agrees that the Evaluation Board is provided for the sole unexclusive purpose referenced above, and agrees not to use the Evaluation Board for any other purpose. Furthermore, the license granted is expressly made subject to the following additional limitations: Customer shall not (i) rent, lease, display, sell, transfer, assign, sublicense, or distribute the Evaluation Board; and (ii) permit any Third Party to access the Evaluation Board. As used herein, the term "Third Party" includes any entity other than ADI, Customer, their employees, affiliates and in-house consultants. The Evaluation Board is NOT sold to Customer; all rights not expressly granted herein, including ownership of the Evaluation Board, are reserved by ADI. This Agreement and the Evaluation Board shall all be considered the confidential proprietary information of ADI. Customer may not disclose or transfer any portion of the Evaluation Board to any other party for any reason. Upon discontinuation of use of the Evaluation Board termination of this Agreement, Customer agrees to promptly return the Evaluation Board to ADI.

ADDITIONAL RESTRICTIONS. Customer may not disassemble, decompile or reverse engineer chips on the Evaluation Board. Customer shall inform ADI of any occurred damages or any modifications or alterations it makes to the Evaluation Board, including but not limited to soldering or any other activity that affects the material content of the Evaluation Board. Modifications to the Evaluation Board must comply with applicable law, including but not limited to the RoHS Directive. **TERMINATION.** ADI may terminate this Agreement at any time upon giving written notice to Customer. Customer agrees to return to ADI the Evaluation Board at that time. **LIMITATION OF LIABILITY.** THE EVALUATION BOARD PROVIDED HEREUNDER IS PROVIDED "AS IS" AND ADI MAKES NO WARRANTIES OR REPRESENTATIONS OF ANY KIND WITH RESPECT TO IT. ADI SPECIFICALLY DISCLAIMS ALL REPRESENTATIONS, ENDORSEMENTS, GUARANTEES, OR WARRANTIES, EXPRESS OR IMPLIED, RELATED TO THE EVALUATION BOARD INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTY OF MERCHANTABILITY, TITLE, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF INTELLECTUAL PROPERTY RIGHTS. IN NO EVENT WILL ADI AND ITS LICENSORS BE LIABLE FOR ANY INCIDENTAL, SPECIAL, INDIRECT, OR CONSEQUENTIAL DAMAGES RESULTING FROM CUSTOMER'S POSSESSION OR USE OF THE EVALUATION BOARD, INCLUDING BUT NOT LIMITED TO LOST PROFITS, DELAY COSTS, LABOR COSTS OR LOSS OF GOODWILL. ADI'S TOTAL LIABILITY FROM ANY AND ALL CAUSES SHALL BE LIMITED TO THE AMOUNT OF ONE HUNDRED US DOLLARS (\$100.00). **EXPORT.**

Customer agrees that it will not directly or indirectly export the Evaluation Board to another country, and that it will comply with all applicable United States federal laws and regulations relating to exports. **GOVERNING LAW.** This Agreement shall be governed by and construed in accordance with the substantive laws of the Commonwealth of Massachusetts (excluding conflict of law rules). Any legal action regarding this Agreement will be heard in the state or federal courts having jurisdiction in Suffolk County, Massachusetts, and Customer hereby submits to the personal jurisdiction and venue of such courts. The United Nations Convention on Contracts for the International Sale of Goods shall not apply to this Agreement and is expressly disclaimed.



	<p>ANALOG DEVICES LT8608S 42V 1.5A Synchronous Step Down Regulator [pdf] User Manual</p> <p>DC2711A, LT8608S, LT8608S 42V 1.5A Synchronous Step Down Regulator, LT8608S, 42V 1.5A Synchronous Step Down Regulator, Synchronous Step Down Regulator, Step Down Regulator, Regulator</p>
--	--

References

- [User Manual](#)