

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [MIDAS](#) /

› [Midas M32C Digital Rack Mixer User Manual](#)

MIDAS M32C

Midas M32C Digital Rack Mixer User Manual

Model: M32C

1. INTRODUCTION

The Midas M32C is a 40-input channel, 25-bus, 1U rackmountable digital mixing core designed for professional live and installed sound applications. It integrates advanced digital signal processing with Midas's renowned audio quality, offering extensive connectivity and control options for complex audio environments.

This manual provides essential information for the proper setup, operation, and maintenance of your M32C Digital Rack Mixer. Please read it thoroughly before using the device.



Figure 1.1: Midas M32C Digital Rack Mixer. This image shows the front perspective of the M32C unit, highlighting its compact 1U rackmount design, front panel display, USB port, and control knob.

2. IMPORTANT SAFETY INSTRUCTIONS

To reduce the risk of electric shock, fire, or damage to the unit, observe the following safety precautions:

- **Power Source:** Connect the unit only to an AC power supply of the specified voltage. Ensure the power cord is securely plugged into both the unit and the wall outlet.
- **Grounding:** The unit must be properly grounded. Do not defeat the safety purpose of the polarized or grounding-type plug.
- **Ventilation:** Ensure adequate ventilation. Do not block any ventilation openings. Install in accordance with the manufacturer's instructions.
- **Water and Moisture:** Do not expose this apparatus to rain or moisture. Do not use this apparatus near water.

- **Heat:** Do not install near any heat sources such as radiators, heat registers, stoves, or other apparatus (including amplifiers) that produce heat.
- **Servicing:** Refer all servicing to qualified service personnel. Servicing is required when the apparatus has been damaged in any way, such as power-supply cord or plug is damaged, liquid has been spilled or objects have fallen into the apparatus, the apparatus has been exposed to rain or moisture, does not operate normally, or has been dropped.

3. SETUP

3.1 Unpacking and Inspection

Carefully unpack the M32C and inspect it for any signs of damage that may have occurred during transit. Retain the original packaging for future shipping or storage.

3.2 Physical Installation

The M32C is designed for standard 19-inch rack mounting and occupies 1U of rack space. Secure the unit using appropriate rack screws. Ensure sufficient airflow around the unit for proper cooling.

3.3 Connections

Refer to the rear panel diagram below for connection points.



Figure 3.1: Midas M32C Rear Panel. This image displays the rear panel of the M32C, showing all input and output ports including AC input, expansion slot, USB, Ethernet, MIDI, ULTRANET, AES50, and monitor/talkback connections.

- **AC INPUT:** Connect the supplied AC power cable here.
- **EXPANSION SLOT:** For optional expansion cards (e.g., DN32-USB for USB audio interface).
- **USB 2.0:** For firmware updates and data transfer.
- **REMOTE ETHERNET:** Connect to a network router or computer for remote control via M32-EDIT software or M32-MIX app.
- **MIDI IN/OUT:** For connecting external MIDI devices.
- **ULTRANET PERSONAL MONITORING:** Connect to Behringer P16-M personal mixers for distributed monitoring.
- **AES50 PORT A/B:** Connect to Midas digital stage boxes (e.g., DL16, DL32) for expanded input/output capabilities. These ports support up to 96 inputs and 96 outputs.
- **MONITOR OUTPUT (BAL/UNBAL):** Analog outputs for local monitoring.
- **TALKBACK INPUT (MIC/TRIM):** Analog input for a talkback microphone.

3.4 Initial Power-Up

After all connections are made, press the power button on the front panel. The unit will initiate its startup sequence. Observe the front panel display for status indicators.

4. OPERATING THE M32C

4.1 Front Panel Controls



Figure 4.1: Midas M32C Front Panel. This image shows a direct front view of the M32C, detailing the USB/DATA port, the central display, AES50 port indicators, the main rotary encoder, and the power button.

- **USB/DATA Port:** Used for connecting USB storage devices for firmware updates or scene/preset management.
- **Display:** Provides essential status information, including AES50 connection status and basic system parameters.
- **AES50 PORT A/B Indicators:** LEDs indicate active AES50 connections.
- **Rotary Encoder:** Used for navigating menus and adjusting parameters displayed on the front panel.
- **Power Button:** Turns the unit on or off.

4.2 Remote Control

The M32C is primarily controlled via external software. Connect the unit to a network using the REMOTE ETHERNET port. You can then use:

- **M32-EDIT Software:** A comprehensive application for Windows, macOS, and Linux, offering full control over all mixer functions.
- **M32-MIX App:** Mobile applications for iOS and Android devices, providing remote control capabilities for mixing on the go.

4.3 AES50 Networking

The AES50 ports are crucial for expanding the M32C's capabilities. They allow connection to digital stage boxes, providing remote microphone preamplifiers and analog outputs, effectively extending the mixer's I/O count to up to 96 inputs and 96 outputs.

4.4 Mix Buses and DSP

The M32C features 25 time-aligned and phase-coherent mix buses, providing flexible routing and processing options for monitors, effects sends, and matrix mixes. The 40-bit floating point digital signal processing ensures high-fidelity audio and extensive dynamic range.

5. MAINTENANCE

5.1 Cleaning

To maintain the appearance and functionality of your M32C, regularly clean the exterior with a soft, dry cloth. Avoid using abrasive cleaners or solvents. Ensure ventilation openings are free from dust and debris.

5.2 Firmware Updates

Periodically check the Midas website for firmware updates. Keeping your M32C's firmware current ensures optimal performance, access to new features, and bug fixes. Firmware updates are typically performed via the front panel USB port using a USB flash drive.

6. TROUBLESHOOTING

If you encounter issues with your M32C, consult the following common troubleshooting steps:

- **No Power:**
 - Verify the AC power cable is securely connected to both the unit and a working power outlet.
 - Check the power switch position.
- **No Audio Input/Output:**
 - Ensure AES50 connections to stage boxes are secure and active (check AES50 indicators).
 - Verify input and output routing within the M32-EDIT software or M32-MIX app.
 - Check gain staging for all channels and buses.
- **Remote Control Connection Issues:**
 - Confirm the Ethernet cable is properly connected to the REMOTE ETHERNET port and your network.
 - Check network settings (IP address, subnet mask) on both the M32C and your control device.
 - Ensure firewall settings on your computer or mobile device are not blocking the M32-EDIT/M32-MIX application.
- **Unit Freezes or Behaves Erratically:**
 - Perform a power cycle (turn off, wait 10 seconds, then turn on).
 - Consider performing a factory reset (refer to the Midas website or full software manual for instructions).
 - Ensure firmware is up to date.

7. SPECIFICATIONS

Feature	Detail
Input Channels	40
Mix Buses	25 (time-aligned, phase-coherent)
Digital Signal Processing	40-bit floating point
Networking	AES50 (up to 96 inputs / 96 outputs)
Construction Material	High-performance aluminium and high-impact steel structure
Rack Size	1U
Dimensions (H x W x D)	7.49 x 4.65 x 0.78 inches (approximate, unit specific)
Item Weight	7.7 pounds (3.5 kg)
Power Source	Wired AC
Connectivity Technology	Wired (Ethernet, USB, MIDI, AES50)

8. WARRANTY INFORMATION

Midas products are covered by a limited warranty. For detailed information regarding the terms and conditions of your warranty, including registration and claims procedures, please refer to the official Midas website or the warranty card included with your product. Keep your proof of purchase for warranty validation.

9. SUPPORT AND CONTACT

For technical support, service, or further information regarding your Midas M32C Digital Rack Mixer, please visit the official Midas website:

www.midasconsoles.com


You may also find additional resources, FAQs, and software downloads on the support section of the website.



© 2025 Midas. All rights reserved.

Related Documents - M32C

	Midas M32R Digital Rack Mixer Quick Start Guide Get started quickly with the Midas M32R Digital Rack Mixer. This guide covers setup, safety, and core functions of the digital console, featuring 40 input channels, 16 Midas PRO microphone preamplifiers, and 25 mix buses for live and studio use.
	MIDAS M32R LIVE Quick Start Guide: Digital Mixer Console This Quick Start Guide provides essential information for operating the MIDAS M32R LIVE digital mixer console. It covers safety instructions, control surface layout, rear panel connections, main display functions, firmware updates, USB recording, block diagram, technical specifications, and FCC compliance for live sound and studio applications.

	MIDAS M32C Digital Rack Mixer: Professional Audio Console User Manual Comprehensive user manual for the MIDAS M32C Digital Rack Mixer, detailing its features, operation, safety guidelines, and technical specifications for professional installed and live sound applications.
	Midas M32R Digital Rack Mixer User Manual Comprehensive user manual for the Midas M32R Digital Rack Mixer, detailing its features, operation, safety instructions, and specifications for live and studio use.
	MIDAS M32 Digital Mixing Console User Manual Comprehensive user manual for the MIDAS M32 Digital Console, detailing its features for live and studio sound, including 40 input channels, 32 MIDAS microphone preamplifiers, and 25 mix buses.
	Midas M32R LIVE Quick Start Guide A comprehensive quick start guide for the Midas M32R LIVE digital console, detailing its features, controls, and basic operations for live and studio use.

Documents - MIDAS – M32C

	[pdf] Quick Start Guide Instructions Guide M32C Quick Start Guide MediaValetTurbosound iQ15 and iQ18S speakers with Ultranet connectivity TRS Talkback mic EN Step 1 Hook Up ES Paso Conexión FR Etape Connexions DE QSG MI 0604 AAC QSG WWcdn mediavalet aunsw musictribe UM889TC0GEyETU4BksuT3g AesmsdINGkyGWwQ3zh9Jdg Original WW Quick Start Guide M32C Digital Rack Mixer for Installed and Live Sound Applications with 40 Input Channels and 25 Mix Buses V 2.0 2 M32C Important Safety Instructions Terminals marked with this symbol carry electrical current of sufficient magnitude to constitute risk of electric shock. Use only ... lang:en score:28 filesize: 3.93 M page_count: 23 document date: 2024-07-25
---	---



[pdf] Datasheet Warranty Recall

میکسر Midas M32C Proavl Data Sheet proavl net 2020 10 |||

Product Information Document Digital Mixers . Digital Rack Mixer for Installed and Live Sound Appl ... mode power supply 3-Year Warranty Program* Designed and engineered in England The 40-input, 25-bus **M32C** takes the brain of the flagship M32 Digital Mixing Console and packs it all into a high-performance aluminum and steel hi form factor. Controls the M32C with our DL16 or DL32 Stage Boxes to effortlessly run sound with high ISO counts in multiple remote locations. Dual AES50 networking QoS connectors allow for up to 96 remote inputs and 48 output channels to be controlled from and processed by the M32C. All of this can be managed concurrently from various locations and instances via our free remote control software applications, M32 EDT, M32 MUI, and M32 Q.

lang:en score:25 filesize: 9.25 M page_count: 20 document date: 2020-10-13



[pdf] User Manual Quick Start Guide Instructions Guide

FEEL Prod Grap PH Artwork P0BM8 QSG EN A4 2017 03 13 Rev 2 indd mac adizas M32C DIGITAL RACK MIXER media63 music group 4 Quick Start Guide 5 Les points repérés par ce symbole portent une tension électrique suffi sante pour constituer un risque d électrocution Utilisez uniquement des câbles enceintes professionnels de haute qualité avec fi ches Jack mono 6 35 mm ou à verrouillages déjà installées media PLM data docs m32c digital rack mixer IIS Windows Server Digital Rack Mixer for Installed and Live Sound Applications with 40 Input Channels 25 Mix Buses 385545 d1aeri3ty3izns cloudfront net 38 accompanying literature Please read the manual Caution To reduce risk of electric shock do not remove top cover or rear section No user serviceable parts inside Refer servicing to qualifi ed personnel re expose this appliance rain moisture 8847617884190 mediadl musictribe sys master hcc h0d

M32C DIGITAL RACK MIXER Digital Rack Mixer for Installed and Live Sound Applications with 40 Input Channels and 25 Mix Buses Quick Start Guide 2 **M32C** DIGITAL RACK MIXER Important Safety Instructions Terminals marked with this symbol carry electrical current of sufficient magnitude to constitute r...

lang:en score:25 filesize: 5.14 M page_count: 12 document date: 2017-03-13



[pdf] Quick Start Guide Instructions Guide

میکسر Midas M32C Proavl QSG proavl net 2020 10 |||

M32C DIGITAL RACK MIXER Digital Rack Mixer for Installed and Live Sound Applications with 40 Input Channels and 25 Mix Buses Quick Start Guide 2 **M32C** DIGITAL RACK MIXER Important Safety Instructions Terminals marked with this symbol carry electrical current of sufficient magnitude to constitute r...

lang:en score:24 filesize: 4.77 M page_count: 12 document date: 2020-10-13



lang:en score:23 filesize: 2.28 M page count: 20 document date: 2015-06-30



[\[pdf\]](#) User Manual

Yan Table of Contents This Control Program shall be used with Behringer Mixers models X32 compact producer rack and core Midas M32 M32R M32C control program allows The the Volume Sources Mute each zone Defining up to six presets Up 16 Mono Zones can created controlled MBC 16Z user manual en techtop co il

1 Table of Contents Introduction er Mixers models X32, X32 compact, X32 producer, X32 rack and X32 core Midas Mixers M32, M32R and **M32C**. This control program allows: The Control of the Volume, Sources and Mute of each zone Defini...

lang:en **score:23** filesize: 1.15 M page_count: 27 document date: 2015-10-14



[\[pdf\]](#) Warranty Borchure Catalog Recall

EXPE Mult Prin PH Approval P0BM8 M32C PID 2015 01 14 Rev 1 indd mike pajo 23234 MidasM32CBrochure MIDAS Product Information Document Midas brochure en fullcompass common files midasconsoles Catalog starin info Info eviaudio fr 80 category 91 consoles 532

Product Information Document Digital Mixers . Digital Rack Mixer for Installed and Live Sound Appl ... ode power supply 3-Year Warranty Program** Designed and engineered in England The 40-input, 25-bus **M32C** takes the brain of the flagship M32 Digital Mixing Console and packs it all into a high-perform...

lang:en **score:23** filesize: 3.79 M page_count: 10 document date: 2015-01-15



[\[pdf\]](#) Warranty Borchure Recall

FEEL Prod Grap PH Approval P0BM8 M32C PID 2016 02 15 Rev 1 indd mike pajo click hereMidas MIDAS Digital Rack Mixer Cannon Sound And LightMidas Product Information Documentcdn shopify s files 1639 9445 Midas Document v 1620084230 Brochureclick MixerMidas DocumentMidas 2422 2859 1677683092cdn ||| Product Information Document Digital Mixers . Digital Rack Mixer for Installed and Live Sound Appl ... mode power supply 3-Year Warranty Program* Designed and engineered in England The 40-input, 25-bus **M32C** takes the brain of the flagship M32 Digital Mixing Console and packs it all into a high-perform...

lang:en **score:23** filesize: 9.62 M page_count: 20 document date: 2016-02-15



[\[pdf\]](#) Warranty Recall

FEEL Prod Grap PH Approval P0BM8 M32C PID 2016 02 15 Rev 1 indd mike pajo Digital Rack Mixer for Installed and Live Sound Applications with 40 Input Channels 25 Mix Buses Mixers Product Information Document Midas MIDAS mediadl musictribe media PLM data docs media63 music group Product Information Document Digital Mixers . Digital Rack Mixer for Installed and Live Sound Appl ... mode power supply 3-Year Warranty Program* Designed and engineered in England The 40-input, 25-bus **M32C** takes the brain of the flagship M32 Digital Mixing Console and packs it all into a high-perform...

lang:en **score:22** filesize: 9.62 M page_count: 20 document date: 2016-02-15



lang:fr score:19 filesize: 43.7 K page_count: 2 document date: 2020-07-08

[\[pdf\]](#) Warranty Borchure Recall

EXPE Mult Prin PH Approval P0BM8 M32C PID 2015 01 14 Rev 1 indd mike pajo Full Compass SystemsThe included 32 x KLARK TEKNIK DN32 USB audio interface 8 stereo effects engines zero latency monitoring independent from DAW and 100 23234 MidasM32CBrochurefullcompass common files 23234

MidasM32CBrochure srsltid AfmBOOqdlrwul W2Bx5tiEAzALwJ2UF4kEDkF42cv5M2gYlasVhMoUsh

SystemsM32C 100 M32 CUE is the perfect tool for setting up your personal mix with MIDAS Digital Mixing Console Compatible iPhone fullcompass W2Bx5tiEAzALwJ2UF4kEDkF42cv5M2gYlasVhMoUshfullcompass

AfmBOopb0SnPVYZT3yrRXyMZYTqjPc5ULvBcaJ6HeBt60oJf gxTXWrH iPhone M32 gxTXWrHfullcompass

AfmBOorgxneMbho8QyAEoM DZ261qRqBZk1LrDeKnFrtnPurSvswg45sk

DZ261qRqBZk1LrDeKnFrtnPurSvswg45skfullcompass AfmBOopTl uQBInKnlau6AGAC Ef XdtSxfY

nJ9zelce39XAXwVE22l nJ9zelce39XAXwVE22lfullcompass AfmBOopmt3ljv0Ev70NHAHzl4dto hVUmB

1Hyo61a2 64w3N9gRfg9D 64w3N9gRfg9Dfullcompass AfmBOoo

OvP0Jsl8gNGhmcZgBaQkwiC5WqufJWs30MSPnaRp8lpJCPG3 iPhone The s ULTRANET bus allows

streaming to 16 channels of pristine digital an array TURBOSOUND iQ speakers all on a single fullcompass

OvP0Jsl8gNGhmcZgBaQkwiC5WqufJWs30MSPnaRp8lpJCPG3fullcompass

AfmBOoofcNW9v8TaQ42oiuSucG fG29RBkys1Xw9HOGusrkWkufoj5bk AfmBOorFVRfyoYDyl

LvQL4BgQ44QpLkLlAopQBhQc8Gitykks3An1iGfullcompass AfmBOooDUS2V8gmLo1vPbi3MYej

99ERb8Td80NLSQezB06j94QzRKvhfullcompass AfmBOop0rpsxR4sAbXnPm2AK8lwKIX0goGHOZ0

jhOnbYeOK7q9OvWMYfullcompass AfmBOor95i2QzkfgvUvZbZeW23Vp0eZ RJoqFegPOKSLjirBompcO

Mmfullcompass AfmBOopM3BNHuLylexqNusiF7rJY7ivTT0iXlu8KlVokuHn8pZ9cL7Z3gfullcompass

AfmBOopFVt84fhW29ahEJu94eeiXTbCuy9PA6DO5s7OAR GLIh158HeMfullcompass AfmBOopPVuQ66

Uzmx0Z7EQ sFCOIXR7RGzSNRmFauYnNs36pPftZ6eQfullcompass

AfmBOopyUfWhB5ZSrJRismqrc2TS0S1igYDGC7GBYOO j5kNP337q65yfullcompass single M32 also

available Android devices allowing you set Consolefullcompass

fG29RBkys1Xw9HOGusrkWkufoj5bkfullcompass AfmBOor8LQu

RQWV7q9ZRE0aITDizgwxJWOafrLf2KQl6tRHUZ PfDkO AfmBOopVidA0I9DGJcTF38C

sTiAqv7bMPdL3alXapqxRtryrWCYv tlfullcompass

AfmBOoqw4OXcGV6to5aLDsSmLlye513mAjQu2HNYEmzUQdG 37cDbF1zfullcompass

Consolev1fullcompass AfmBOorQBX2lysGPtARWqXxN unYBJT9i3FdC19gwps3KXVabVivRjESfullcompass

AfmBOooiH36i1o1sBI7Y9l3YttjhLzIINZ 6eRGlc3PpZYAUPcjjDjgfullcompass Consolev1v1fullcompass

AfmBOoo5JLUy9Divz18Uig3LYgTMHW1ZcF5oDISTxmbxKJYTt8 5Xwtfullcompass

Consolev1v1v1fullcompass


AfmBOoomsBCKglQfpVnj5TPvxgd0KsNGjVVYAK0LrZLfNiV2VowObv2Xfullcompass |||

Product Information Document Digital Mixers . Digital Rack Mixer for Installed and Live Sound Appl ... ode power supply 3-Year Warranty Program** Designed and engineered in England The 40-input, 25-bus **M32C** takes the brain of the flagship M32 Digital Mixing Console and packs it all into a high-perform...

lang:en score:18 filesize: 3.79 M page_count: 10 document date: 2015-01-15




MIDAS



Pro Audio Equipment Catalog - Microphones, Interfaces, Speakers & More

Explore a comprehensive catalog of professional audio equipment from B&H Photo Video, featuring a wide range of microphones, audio interfaces, studio monitors, headphones, PA systems, and more. Find the perfect gear for your studio or live sound needs.

lang:en score:17 filesize: 10.27 M page_count: 50 document date: 2017-10-19



[pdf]

REGISTRATION XL3 XL200 XL250 Heritage3000 Heritage2000 Heritage1000 Legend3000 MIDAS
 RENTAL AGENT INFORMATION MIDAS Company Name Midas 202109 bestecaudio wp |||
 REGISTRATION If you wish your company to be listed in the MIDAS Rental Network Directory, please f ... PRO2 Surface PRO2C Surface PRO1 Surface DL441 DL442 DL443 DL444 M32-Live M32 M32R-Live M32R **M32C** Console DL251 DL252 DL231 DL15x DL16 DL32 DN32-DANTE DN32-MADI DN32-LIVE DN32-ADAT DN32-...


lang:en score:17 filesize: 986.48 K page_count: 1 document date: 2021-08-23



[pdf]

FEEL Prod Grap PH Approval P0BMD DL32 PID 2016 01 28 Rev 1 indd mac adizaz MIDAS Product Information Document mediadl musictribe media PLM data docs
 Product Information Document I/O Interfaces - 32 Input, 16 Output Stage Box with 32 MIDAS Micropho ... ng capability can still tap directly into the DL32 s powerful feature set. For instance, a DL32 and **M32C** could be jointly utilised to create a remote controlled digital mixing system in only 4U. Anoth...

lang:en score:17 filesize: 7.49 M page_count: 7 document date: 2016-02-02



herunterladenStagebox Midas MDL32mm audiotechnik de media f2 68 1723722136 ts |||

Product Information Document I/O Interfaces - 32 Input, 16 Output Stage Box with 32 MIDAS Micropho ... ng capability can still tap directly into the DL32 s powerful feature set.

For instance, a DL32 and **M32C** could be jointly utilised to create a remote controlled digital mixing system in only 4U. Anoth...

lang:en score:17 filesize: 7.49 M page count: 7 document date: 2016-02-02

[\[pdf\]](#) Specifications Dimension Guide Recall

MIDAS M32C

SPEC sounddd shop Specification |||

18 M32C DIGITAL RACK MIXER Specifications Processing Number of processing channels Internal effects engines, true stereo / mono Internal total recall scenes incl. preamp and fader Signal processing Network I/O latency stagebox in console processing* stagebox out Connectors Talkback mic inpu...

lang:en score:17 filesize: 63.35 K page count: 1 document date: 2021-02-18

[\[pdf\]](#)

Your Mind to Sound Interface DL32 3U CAT5 STP FOH MIDAS

M32Live Bro2312 v2 bestecaudio wp |||

Your Mind-to-Sound Interface Digital Console for Live and 32 Midas PRO Microphone and Live Mu ive M32R Live . - 91MVH*O M32 Live M32R Live **M32C** 91MVH*O. 91MVH*O 6SFJ5FMFUSPOJY- BJSDIJME 1VMUFD 21B 2 ...

lang:en score:17 filesize: 10.15 M page count: 8 document date: 2023-11-30

[\[pdf\]](#)

Digital mixing has revolutionized virtually everything in the live entertainment production workflow. The DL32 is perfect for Midas Product information Heliart media63 music group your Front of House FOH console and rest of the world. I/O packed, highly affordable digital stage box provides 32 MIDAS PRO solution for connecting onstage talent with 48 bidirectional audio channels over Cat 5e cable. kHz Single duplex interconnection sample clocks Ethernet physical layer data transmission High channel count P0BMD Information Document heliart ee static custom File Tooteinfo media PLM docs

Product Information Document I/O Interfaces DL32 32 Input, 16 Output Stage Box with 32 MIDAS Microp ... ng capability can still tap directly into the DL32 s powerful feature set. For instance, a DL32 and **M32C** could be jointly utilised to create a remote controlled digital mixing system in only 4U. Anoth...

lang:en score:17 filesize: 6.83 M page count: 7 document date: 2018-03-01



[pdf] Quick Start Guide Warranty

M32C il y a 1 jour —

1/4 TS

QSG MI 0604 AAC CN mediadl

musictribe media PLM data docs P0BM8 |||

M32C Digital Rack Mixer for Installed and Live Sound Applications with 40 Input Channels and 25 Mix Buses V 2.0 2 **M32C** , TS , , , , , , , 1. 2. 3. 4. 5. 6. 7. 8. , , 9. , 10. , , 11. 12. , , , , 13. , 14. , , ...

lang:en score:17 filesize: 3.33 M page_count: 7 document date: 2023-08-10



[pdf] User Manual Quick Start Guide

M32C MIDAS User Manual 26388 1 herunterladenDigitalmischpult Midas MM32Cmm audiotechnik de media

53 a9 68 1723719867 ts MM32CM32C QSG WWmm 1723719867cdn mediavalet aunsz musictribe

4TRsFxYFc0 v7SVnjr509w WnyB F7WMkCVIKHfxykt4Q Original WW |||

...

lang:en score:16 filesize: 8.84 M page_count: 21 document date: 2015-09-11



[pdf]

EXPE Mult Prin PH Approval P0BMD DL32 PID 2015 01 13 Rev 1 indd mike pajo Evi Audio Le offre 32

préamplis micro MIDAS PRO Series contrôlables à distance plus 16 sorties analogiques symétriques sur XLR

pour la scène et tout cela dans fr eviaudio 2020 11 |||

Botier de scène - Botier de scène 32 entrées, 16 sorties avec 32 préamplis micro MIDAS, et interfaces ... au AES50 peut profiter directement de la puissance offerte par le DL32. Par

exemple, un DL32 et une **M32C** peuvent être raccords ensemble pour créer un système de

mixage numérique avec contrôle distance dans...

lang:fr score:16 filesize: 5.89 M page_count: 7 document date: 2020-09-04

[pdf] Specifications

DL32 MarkertekThe provides 32 MIDAS PRO · Series remote controllable mic preamps plus 16 balanced

analog XLR returns at the stage end and all it takes is a DL32 Specificationsmarkertek Attachments

Specifications Midas srsltid AfmBOorVSN6pa3GPBGToT2llh Qa0mhOt5uBez a3TD8zPNy1FOQHrhh

MarkertekDL32 a The SpecificationsDL32 a3TD8zPNy1FOQHrhhmarkertek AfmBOoq4oxqWelC2Ag

nt8aWxUCTBivT2gFdHg7bP3giFvYwabSfiqNK a direct connection to TURBOSOND iQ loudspeakers

BEHRINGER LAB GRUPPEN LAKE TANNOY TURBOSOUND TC ELECTRONIC HELICON
BEHRINGER DL32 nt8aWxUCTBivT2gFdHg7bP3giFvYwabSfiqNKmarkertek AfmBOooEkbt93
rdyjWTGlyT1uXa 1Azhvk3WzulYD2hb2h0aw3DeSi BEHRINGER The
1Azhvk3WzulYD2hb2h0aw3DeSimarkertek AfmBOopVls87sBNPGAjZhQ2MegWGxrH jEn6iQwX4bcXL4Mucc
fmivl fmivlmarkertek AfmBOorr4IF0IUzFUBsGM1uTDox9k9mDfs OgeH2iHoD4 x4KLy4TRdl Digital mixing has
revolutionizedDL32 AfmBOoqsY3Txc0K YSRKHadHfD892I7vdcW5gFcaSONjub3LHH PZrMmarkertek
revolutionizedDigital AfmBOoqG2b8UHilqu34JRYSOsgPGfXAfEXmaAlaFqf32FVFccbsmM3cZmarkertek
AfmBOopRTJBse8BM4r1MgXg0K 3OePbjz0w5l ylnkdhrW7BtwslyG6zmarkertek
AfmBOoo5cRE60jAvyomTQQoqT yNjKjAD9Zjb txWJPpu57yDXXo8lo6markertek
AfmBOopwhNYqZtXih6WvyTxM0dcXWMvO0tfrDtJV4koCdx3F6lltJqmarkertek AfmBOooFxeAHG0Vx
1MK4WpcyqRY9gq2IXCPxkq DZp0 fx40ARCFIk9markertek
AfmBOoogSZhWks5ZIZgsk2rQhFdM7mqZE2wZHYM7NCHgXjs9bcQReHTKmarkertek AfmBOorhMVMZoWO
K0OQHvz5LkhdH 54SqQqVwkQEaaGbajPrihhCrZ2markertek AfmBOoqGOqsA
RCFKguuAnEfEyq3gemVLWX9xccN3A5GOX7VNTlm5R7Wmarkertek
AfmBOoreNsea8L4dhtMarijLS2KuepqlSsoykQ0qaemeOzABNj0Xy6bemarkertek
AfmBOopF9NwtQVqxkL92uz3Eult1fnqJyJBis2ZlrrOBT2GvK6OFkljBmarkertek
AfmBOoql7jMTbUYsuyEu9PdmokvmaJRnUQb4Hs42osmyDGjAwlBIXDlmarkertek
AfmBOor97Gs9kWofl4CS5ae1q6l6ZrYfI35v7YV66xulKguPCEZmUe Nmarkertek
AfmBOoqukMo3IRiPpDwUgHdyG3FMKJT34gahGL4yzEO6HtkhP1wtzsy8markertek
AfmBOooKMTrkwgj2CUxSohj mhVTxpLceSH ZfkPSP0 AWBBFIL7xCLmarkertek
AfmBOopZdp1Sljhd91gKEog3QKjpryZnvAWb6Xpztiti428AD7EYCqA7Rmarkertek AfmBOooZrcitiLQm
0SQqPc2QpXuUuLIXXpcnjALoJeH9npUv43Vv8Y 4markertek
AfmBOopgwBmoZRpQ2X1GsCHSI05lu72sdU04QcWkX8qpKHWRldg3JxUrmarkertek AfmBOooEF txam
AMsDReai2aqiDPJyZXiIHZ r49hyWINsoH3yQgzbdmarkertek
AfmBOopfgZNTTuq18oBum2pKxk1c7MTNGNfb9g4ITv ReKglw0fj5aCtmarkertek
AfmBOopUtQnFBVpzrMoYJZiKJ1SAS3laOY49lGeiO5VdeXPAQdSpzjGxmarkertek AfmBOorMt2qfQQ
TLdx9MmiEjtXO G26uohuBFEU9tMOIZ8UIT3 Y19markertek
AfmBOooWqluoXnEc7GQf8RK2Rp8LCMDlffQaAsGud3TIKUrpGTHZ LIYmarkertek AfmBOorpnTdz
OSC7UZCHPS8AZKDS7Wwvjy 1nXtEzAVjMrLafCai7r3markertek
AfmBOoozVAbORmO8ba87pcdpNdLlsoOdDgxhRGfQOHylWbP XopRyjmNmarkertek
AfmBOoqh6wz9l9DWsqDYxsHPqPLQe1UkK6Bju5WCt56rr6zphityN9t3ymarkertek
AfmBOoqdZeQhbVyMQprCu9ZuKvzkHA Op89LZYNJWSrZ8slWupixS MUmarkertek
AfmBOooBkwg7uTzKlSiNd3S4zOpk2UutiGpoVI3D1Q23kJZ3VZggVjDDmarkertek
AfmBOop2KPCvFhHwNXQjt8hk4L YKqgYOhFHak9kZNTeGJlBrJB6aLcMmarkertek AfmBOorf
VF24y6b19ohmrpBBupLIyj3yfSxMHZiSkbnwy0273Ux1W69markertek AfmBOoreoMz k4rjnhoh9vKMK1i
MCH8AqC9OHLd0Mm1JkX L6tuB3yXmarkertek
AfmBOoqnTEnd8TWNKgZKpVjQ3nx54BXMmVHP7TUrcBmsmffWDyK6P7Unmarkertek
AfmBOoqPT9gstb39dZnfjglwOiGz iVz4T7JN3ytp LELF5P0gy r6 Gmarkertek
AfmBOoqFuMVBHyM7Nih5PrmGjdszOIO651MRQxma5QPqKE7PK8jmRvhwmarkertek
AfmBOoqhDVTGLfRDSdvwhCxEGJc rdpfJfee4jFVCva7CcrP2FUEgCcLmarkertek AfmBOor8DyG
vTARYS827Ri7alsMZNbyNChAICQYVeK8i0BCSKQrC z0markertek
AfmBOooRP4JINJ1Uy64oZMaqklDQgwDerKLKdDR9b81s3FkyMcOGbcwlmarkertek AfmBOorCAx 4qg7
svZLXqueb jUKugxTO0qZJNVL9dMPW8w3yn3rGHhmarkertek AfmBOoo97nqS5QTXSoGWNOCB
pN4JtIZKPCHiXKLNlyu59lNwJg 8E9markertek AfmBOopdhNgOAqO2afpiOU9
Ny3BTKGd8Fjm3nozR5uoCfzVwH3fsIL9markertek AfmBOopsRc9 oJBWe MwGA0ew
Ej9lra9u2KEvylbXxzWpIIQAp8QqWymarkertek
AfmBOopz8TEPaJksGEkfwNQ86TyfkmSijjNkO1bsMdpTEbiWGze61Aumarkertek AfmBOop9OKHHXvrC
t1pyaXKdYfKUXLgabDp WETzGfRpNUInqBocYIEmarkertek AfmBOorW1HhJlNvgMXpYtn4tx6uglKTIGH3Rb2
yJ9Gbf5AV5R2SxYhdmarkertek AfmBOoqCz1gSyrxEwM8gWzsy 0l4PtV
9BtHVDUHSAI2YiOGRdpLZfVemarkertek AfmBOoqRMCadQ7HCnbzmAX7hLcXuiKtVMKVpB
KcYehNkGyVD9edkQJAmarkertek
AfmBOorJJyCYTAg66dp0s2RGV05Pu665VHRxreOEIb0fv0jQFv3lryamarkertek
AfmBOopw30ttD6uOxgm0xoABokymo mZRfneZ 6k oB Pc7GXi6GiE2Umarkertek



AfmBOoqOSTXkiDCeriPR6Ddm6qxZ9Yd3vscZcE6U0hwKlusvJ9ttJH02markertek AfmBOOpj1YD Piu
PLoe0YP59fQtHQsT5PpTa5wg0Rz38AqGgNz2rxNWmarkertek
AfmBOOpz8TEPaJksGEkfwNQ86TyfkmSijjNkO1bsMdptebiWGze61Au
AfmBOoql8qKjYuMfCpALy0wYFGXTAuaD0QLgLfID3CTcvvvEOeRg 5tmarkertek
PLoe0YP59fQtHQsT5PpTa5wg0Rz38AqGgNz2rxNW |||

Product Information Document I/O Interfaces DL32 32 Input, 16 Output Stage Box with 32
MIDAS Microp ... ng capability can still tap directly into the DL32 s powerful feature set.
For instance, a DL32 and **M32C** could be jointly utilised to create a remote controlled
digital mixing system in only 4U. Anoth...

lang:en score:16 filesize: 6.83 M page_count: 7 document date: 2018-03-01



[pdf]

bestecaudio M32Live Bro wp |||

32 LIVE Your Mind-to-Sound Interface 32r LIVE 32C 32 LIVE Digital Console for Live and
32 Midas ... Live M32 3 36 / LED 16 FXPlug-In M32 Live M32R Live **M32C** 16 FXPlug-
InM32 50 FXPlug-In Urei 1176Teletronix LA-2A Fairchild 670 Pultec ...

lang:de score:15 filesize: 4.05 M page_count: 8 document date: 2019-12-03



[pdf] Warranty Recall

385546 d1aeri3ty3izns cloudfront net media 38 |||

Product Information Document Digital **M32C** Digital Rack Mixer for Installed and Live
Sound Applications with 40 Input Channels and 25 Mix Buses ## 40-input channel, 25-
bus, 1U rackmountable digital mixing core for live and installed sound application ## 25
time-aligned and phase-coherent mix buses ...

lang:en score:15 filesize: 6.47 M page_count: 20 document date: 2018-01-26



[\[pdf\]](#)

Midas Bro 1811 bestecaudio wp |||

DI DIL L 5 5 .JEBT 7 101VMBUJPO 2 6-53 / 5 .JEBT130 NN 2 ... M32R LIVE .34VSGBDF
/-*7 VEJPJOUFSGBDF UIFS PO 3 */065 64# 5 3/ 5 8 8FJHIULH **M32C** . 6OJU /64#
VEJP*OUFSGBDF 8 8FJHIULH 9-3 5343 5# 9-3 5343 5# 5345# 9-3 5343 ...

lang:af score:14 filesize: 3.35 M page_count: 12 document date: 2022-11-25



[\[pdf\]](#)

Untitled Midas Catarog2410 bestecaudio wp |||

DI DIL L 5 5 .JEBT 7 101VMBUJPO 2 6-53 / 5 .JEBT130 NN J1B ... M32R LIVE
 .34VSGBDF /-*7 VEJPJOUFSGBDF UIFS PO 3 */065 64# 5 3/ 5 8 8FJHIULH **M32C** .
 60JU /64# VEJP*OUFSGBDF 8 8FJHIULH 9-3 5343 5# 9-3 5343 5# 5345# 9-3 5343 ...

lang:i-klingon score:14 filesize: 3.87 M page_count: 16 document date: 2024-10-24



[Pro Audio Gear Guide: Optimize Your Studio Setup](#)

Explore B&H's comprehensive guide to upgrading your pro audio setup, featuring microphones, monitors, mixers, and more. Learn how to identify weak links and enhance your sound quality.

lang:en score:13 filesize: 12.16 M page_count: 49 document date: 2018-10-11

MIDAS Gesamtpreisliste 04/2015		Stand: 04/05/2015	
Art.Nr.		Datei: 1	
MIDAS M32 - kompaktes Digitalmischpult			
25427	MIDAS M32 - Digitalmischpult	5.390,00 €	6.144,10 €
25428	MIDAS M32 - Digitalmischpult	3.240,00 €	3.888,10 €
25429	MIDAS M32 - Digitalmischpult	1.390,00 €	1.528,10 €
25430	MIDAS M32 - Digitalmischpult	1.270,00 €	1.517,10 €
25431	MIDAS M32 - Digitalmischpult	2.190,00 €	2.638,10 €
25432	MIDAS M32 - Digitalmischpult	300,00 €	450,10 €
25433	MIDAS M32 - Digitalmischpult	600,00 €	750,10 €
25434	MIDAS M32 - Digitalmischpult	270,00 €	327,10 €
25435	MIDAS M32 - Digitalmischpult	300,00 €	450,10 €

[pdf]

4D Druckauftrag Ohne Titel12 M Siebert MKT megaaudio de files |||


MIDAS Gesamtpreisliste 04/2015 Art.Nr. 25427 25992 26063 25835 26062 25833 25834

25836 25837 Bezei ... USB 2.0 Expansion Karte mit bis zu 32-Kanlen bidirektional inkl.

Rackohren 19 Rackversion MIDAS **M32C** - Digitalmischpult 19 /1HE DSP-Power fr 40

Input Kanle und 25 Busse inkl. USB 2.0 Expansion Kar...

lang:de score:13 filesize: 48.54 K page_count: 5 document date: 2015-05-04



[pdf]

M32

M32

bestecaudio wp |||

M32 : M32/M32 LIVE/M32R/M32R LIVE/**M32C** : FAT32USB M32

https://www.midasconsoles.com/Categories/Midas/Mixers/Digital/M32/p/P0B3I/Downloads

STEP 1 USB : dcp_corefs_release-4.02.update STEP USB RECORDER VIEW 2 **M32C**

STEP 3 STEP1USB STEP V4.02 4 STEP M32/M32 LIVE/M32R/M32R

LIVESETUPUPD...

lang:de score:13 filesize: 229.25 K page_count: 3 document date: 2020-05-19

MIDAS Retail Products		Date: 04/05/2015	
Art.Nr.		Date: 1	
25427	MIDAS M32 - Digitalmischpult	5.390,00 €	6.144,10 €
25428	MIDAS M32 - Digitalmischpult	3.240,00 €	3.888,10 €
25429	MIDAS M32 - Digitalmischpult	1.390,00 €	1.528,10 €
25430	MIDAS M32 - Digitalmischpult	1.270,00 €	1.517,10 €
25431	MIDAS M32 - Digitalmischpult	2.190,00 €	2.638,10 €
25432	MIDAS M32 - Digitalmischpult	300,00 €	450,10 €
25433	MIDAS M32 - Digitalmischpult	600,00 €	750,10 €
25434	MIDAS M32 - Digitalmischpult	270,00 €	327,10 €
25435	MIDAS M32 - Digitalmischpult	300,00 €	450,10 €

[pdf]

BA MT Retail 20220401 bestecaudio wp |||

Direct injection box 000-AHB00-00010 DN100 000-AS600-00010 DN200 Network module

000-B4F00-0 ... RICE OPEN PRICE 410,000 275,000 Digital Rack Mixer for Installed and

Live Sound 000-BM803-00010 **M32C** 40ch25/ OPEN PRICE 88,000 M32 Series Case

M32-Case M32R-Case M32FRP 9mm M32RFRP 6mm OPE...

lang:en score:12 filesize: 241.28 K page_count: 1 document date: 2022-04-19

[illegible]

Retail Products BA 20241021 bestecaudio wp |||

Products 202 ... RICE OPEN PRICE 510,000 360,000 Digital Rack Mixer for Installed and
Live Sound 000-BM803-00010 **M32C** 40ch25/ OPEN PRICE 156,000 M32 Series Case
M32-Case M32R-Case M32FRP 9mm M32RFRP 6mm OP...

lang:en score:12 filesize: 203.93 K page count: 1 document date: 2024-10-21

[illegible]

BA Retail 20220901 bestecaudio wp ||

Products 202 ... RICE OPEN PRICE 490,000 345,000 Digital Rack Mixer for Installed and
Live Sound 000-BM803-00010 **M32C** 40ch25/ OPEN PRICE 150,000 M32 Series Case
M32-Case M32R-Case M32FRP 9mm M32RFRP 6mm OP...

lang:en score:12 filesize: 197.82 K page_count: 1 document date: 2022-07-26

The screenshot shows the MIBAS software interface. The title bar indicates 'MIBAS' and 'CONNECTION'. The main window displays a table with the following data:

NAME	ADDRESS	PORT	PROTOCOL	MODE	STATUS
192	168	10	119		
255	255	255	0		
192	168	10	254		

Below the table, there is a 'CONNECTION' section with a 'CONNECT' button. At the bottom, there is a 'Status' section with a 'Refresh' button and a 'Close' button. The background of the interface shows a 3D rendering of a power substation.

M32 PC Mac Wi Fi Mac WiFi bestecaudio wp |||

M32PC/Mac Wi-Fi : M32/M32 LIVE/M32R/M32R LIVE/**M32C** : DHCPWi-FiLAN STEP

SETUP/NETWORKDHCPON 1 STEP EthernetWi-FiLANLAN 2 Wi-FiWANINTERNET

STEP SETUP/NETWORKIP 3 PC/Mac M32-Edit

<https://www.midasconsoles.com/Categories/Midas/Mixers/Digital/M32/p/P0B3I/Downloads>

STEP PC/MacWi-FiLAN 1 STEP M32-...

lang:en score:12 filesize: 208.62 K page count: 3 document date: 2020-05-19

Professional Audio
www.bhprofessionalaudio.com

SMH-1010CH/1020CH
Single- & Dual-Sided Professional Communication Headsets

SMH-1010CH single-sided and 1020CH dual-sided communication headsets are ideal for use with wired and wireless communication systems in TV or radio broadcast, communications systems, and sports applications.

Features:

- CLEAR VOICE
- REDUCED NOISE
- PRECISE POSITIONING
- NOISE REDUCTION
- COMFORT
- COMPATIBILITY
- OPTIONAL TURTLE
- LOCKING CABLE DESIGN
- COLLAPSIBLE

SENAL UTM-86 Premium Lavalier Microphone

The UTM-86 features an professional condenser capsule and a frequency response optimized for speech and singing. It can be used in broadcast, studio, and live sound applications.

Features:

- Optimized for Speech
- Miniature Size
- Low Noise
- Interchangeable Capsule

Specifications:

Model	Price
SMH-1010CH Single-Sided Professional Communication Headset	\$199.00
SMH-1020CH Dual-Sided Professional Communication Headset	\$249.00
SENAL UTM-86 Premium Lavalier Microphone	\$149.00

[B&H Professional Audio Equipment Catalog - Microphones, Studio Gear, Instruments & More](#)

Explore the extensive B&H Professional Audio catalog featuring a wide range of microphones, studio monitors, mixers, instruments, and accessories for broadcast, studio, and live sound applications. Includes detailed product overviews and expert tips for optimal audio production.

lang:en score:12 filesize: 6.33 M page_count: 48 document date: 2019-05-01

M32C DIGITAL RACK MIXER

Digital Rack Mixer for installed and Live Sound Applications with 40 Input Channels and 25 Mix Buses

User Manual

MIDAS

[MIDAS M32C Digital Rack Mixer: Professional Audio Console User Manual](#)

Comprehensive user manual for the MIDAS M32C Digital Rack Mixer, detailing its features, operation, safety guidelines, and technical specifications for professional installed and live sound applications.

lang:en score:12 filesize: 8.84 M page_count: 21 document date: 2015-09-11

Chapel Bar
AT FOTOGRAFISKA
PRIVATE EVENTS

AT FOTOGRAFISKA PRIVATE EVENTS TABLE OF CONTENTS

03 OUR MUSEUM
0405 CHAPEL BAR 06 SERVICES AMEN ... ustable 1 D.A.S. Audio VENTEC 15a - Powered 15 Full-Range 2-Way Loudspeaker Adjustable 1 Midas **M32C** Rackmount Mixer with iPad Mix Console 2 Midas DL16 16i08o AES Configured Stage Boxes 6 EVEN...

[pdf]

Chapel Private Events 2024 cdn sanity io files 2xi539qp production

e10ae82c24da7569317285729cc1303441f6a061 filename |||

AT FOTOGRAFISKA PRIVATE EVENTS TABLE OF CONTENTS 03 OUR MUSEUM 0405 CHAPEL BAR 06 SERVICES AMEN ... ustable 1 D.A.S. Audio VENTEC 15a - Powered 15 Full-Range 2-Way Loudspeaker Adjustable 1 Midas **M32C** Rackmount Mixer with iPad Mix Console 2 Midas DL16 16i08o AES Configured Stage Boxes 6 EVEN...

lang:en score:12 filesize: 4.63 M page_count: 10 document date: 2024-07-12

CE EC Declaration of Conformity

We, the undersigned:

MUSIC Group Services PH Corp
50th Floor Ayala Life@City Center, 6811 Ayala Avenue, 1208 Makati City, PHILIPPINES

MUSIC Group Services UK Limited
Mark Industrial Park, Walker Heath Road, Kidderminster, Worcestershire DY11 1TH, UK

certify and declare under our sole responsibility that the following apparatus:

Digital Rack Mixer for installed and Live Sound Applications with 40 Input Channels and 25 Mix Buses

conforms with essential requirements of the EMC Directive 2014/53/EU and/or the LVD Directive 2014/35/EU and/or the RoHS Directive 2011/65/EU, based on the following specifications applied:

Standard	Year
EN 60950	2002 + A1: 2006 + A2: 2010 + A3: 2011
EN 55150-1	2009
EN 55150-2	2009
ENEC 61000-3-2	2006 + A1: 2009 + A2: 2013 Class A
ENEC 61000-3-3	2013
ENEC 61000-4-2	2013
ENEC 61000-4-3	2013
ENEC 61000-4-4	2013
ENEC 61000-4-11	2013

This declaration is based on Safety test report no. 211-558907-490

issued from the test laboratory: **EMC Certification and Testing (China) Co., Ltd.** Shenzhen Branch

This declaration is based on EMC test report no. **2015-EMC-10040229**

issued from the test laboratory: **ETS, INC.**


2015-07-06 **ETS, INC.** Kurt LANG, Manager, MUSIC GROUP

[\[pdf\] Specifications Declaration of Conformity Test Report](#)

Declaration of Conformity Electromagnetic Compatibility and or Low Voltage DoC EMC EMV Safety LVD CE EC IMPL Tech GLOB RnD Comp Document P0BM8 2015 07 06 Rev 0 mediadl musictribe media PLM data docs media63 music group

EC Declaration of Conformity We, the undersigned, MUSIC Group Services PH Corp Name of the manufact ... 0 Input Channels and 25 Mix Buses Description MUSIC Group Services PH Corp Manufacturer MIDAS Brand **M32C** Identification conforms with essential requirements of the EMC Directive 2014/30/EU and/or the...

lang:en score:11 filesize: 36.63 K page_count: 1 document date: 2015-06-06



Professional Audio Equipment Catalog: Microphones, Interfaces, and Studio Gear | B&H Photo

Explore a comprehensive catalog of professional audio equipment from B&H Photo, featuring a wide selection of microphones (large diaphragm, small diaphragm, USB, dynamic, ribbon, tube), audio interfaces, mixers, studio monitors, keyboards, synthesizers, PA systems, amplifiers, and essential audio accessories from leading brands.

lang:en **score:10** filesize: 10.61 M page_count: 49 document date: 2016-10-13



Catálogo de Equipos de Audio Profesional Senal y B&H

Explore a comprehensive catalog of professional audio equipment from Senal and B&H, featuring communication headsets, lavalier microphones, studio microphones (condenser, dynamic, ribbon, tube, USB), mixers, preamplifiers, compressors, equalizers, digital recorders, DJ gear, keyboard controllers, synthesizers, digital pianos, guitar amplifiers, drum equipment, effect pedals, wireless systems, PA speakers, and DJ lighting. Includes expert tips for achieving great vocal sound in a home studio.

lang:es **score:10** filesize: 5.84 M page_count: 48 document date: 2019-06-04