Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

MIBOTE Mibote-04-ZF

MIBOTE 6-Outlet Power Strip with 4 USB Ports, Surge Protector User Manual

Model: Mibote-04-ZF

1. Introduction

Thank you for choosing the MIBOTE 6-Outlet Power Strip with 4 USB Ports and Surge Protector. This device is designed to provide convenient power distribution and surge protection for your electronic devices at home, in the office, or while traveling. Please read this manual carefully before use to ensure safe and optimal operation.

2. Product Features

- **Multifunctional Design:** Combines 6 standard AC outlets and 4 USB charging ports, allowing simultaneous charging of multiple devices such as cellphones, tablets, laptops, and digital cameras.
- **Smart USB Output:** Each USB port detects and delivers an ideal output current consistently, up to 2.4A for compatible devices, with a total USB output of 5V 4A.
- **All-around Surge Protection:** Features a 1700 Joules surge protection rating to safeguard computers, electronics, and home theater equipment from power surges, over-current, over-voltage, and short-circuit events.
- **Superior Quality Construction:** Made with a fire-resistance PC shell and 100% copper wire for better conductivity and thermal performance. Includes an On/Off switch and a visible, non-intrusive LED light.
- **Compact and Portable:** Designed for convenience in various settings, including home, office, and travel.
- **Certifications:** FCC, RoHS certified.



Image: Overview of the power strip's safety features, including overload, short-circuit, high temperature, lightning surge, and over-current protection, along with a reset switch, anti-slip rubber footpad, and 5ft heavy-duty copper cord.

3. Package Contents

The following items are included in your MIBOTE Power Strip package:

- 1x MIBOTE 6-Outlet Power Strip with 4 USB Ports
- 1x Lighting USB Cable
- 1x Micro USB Cable
- 1x User Manual (this document)

Your browser does not support the video tag.

Video: An official MIBOTE video demonstrating the smart power strip and its features, including the unboxing of the product and its included accessories.

4. Setup Instructions

1. **Unpack the Device:** Carefully remove the power strip and all accessories from the packaging.
2. **Placement:** Position the power strip on a stable, flat surface, away from water or excessive heat sources. Ensure adequate ventilation around the unit. The anti-slip rubber footpads on the bottom help secure its position.
3. **Connect to Power:** Plug the power strip's main cord into a grounded wall outlet. The power strip supports AC 100-240V, 50/60Hz input.
4. **Power On:** Locate the ON/OFF switch, typically on the side or back of the unit, and switch it to the 'ON' position. A visible LED indicator will illuminate to confirm power is supplied.



Image: The MIBOTE power strip showing its 6 AC outlets on the top surface and 4 USB ports on one side, ready for device connection.

5. Operating Instructions

5.1 Using AC Outlets

- Plug your electronic devices into any of the 6 available AC outlets.
- Ensure that the total power consumption of all connected devices does not exceed 1875W (10A).
- The outlets are designed to accommodate various plug sizes, including block power adapters, due to good spacing.

5.2 Using USB Ports

- Connect your USB-powered devices (e.g., smartphones, tablets, smartwatches) to any of the 4 USB ports using appropriate USB cables.
- The smart USB ports will automatically detect your device and deliver the optimal charging current up to 2.4A per port, with a total output of 5V 4A.



Image: The MIBOTE power strip with multiple devices plugged into both AC outlets and USB ports, illustrating its multi-device charging capability.

6. Safety Information

WARNING: To reduce the risk of electric shock, fire, or injury, please follow these safety guidelines:

- Do not exceed the maximum power rating of 1875W (10A).
- Do not use in wet environments or near water.
- Do not disassemble or modify the power strip.
- Keep out of reach of children and pets.
- Ensure the power cord is not pinched or walked on.
- If the power strip experiences an overload, the built-in protection will automatically shut off power. Press the reset button to restore power after removing the overloaded device.
- This device is a surge protector, not a voltage converter. When traveling internationally, ensure your devices are compatible with the local voltage and use appropriate plug adapters if necessary.

7. Product Specifications

Feature	Specification
Model Number	Mibote-04-ZF
AC Outlets	6
USB Ports	4
Max Input Voltage	100-240V AC, 50/60Hz
Rated Power	1875W
Max Current	10A
USB Total Output	5V 4A
USB Output (per port)	5V 2.4A / 1A (Smart Distribution)
Surge Energy Rating	1700 Joules

Feature	Specification
Peak Current	15000A
Response Time	< 1 ns
Power Cord Length	5 ft
Material	Fireproof ABS shell, Copper wire
Certifications	FCC, RoHS, CE
Dimensions	Approximately 6"x3.5"x1.5" (from customer review)
Weight	12 ounces

8. Maintenance

- **Cleaning:** Disconnect the power strip from the wall outlet before cleaning. Use a dry, soft cloth to wipe the surface. Do not use liquid cleaners or aerosols.
- **Storage:** When not in use for extended periods, unplug the power strip and store it in a cool, dry place.
- **Inspection:** Periodically inspect the power cord and the unit for any signs of damage. If damage is found, discontinue use and contact customer support.

9. Troubleshooting

9.1 No Power to Outlets/USB Ports

- **Check Power Switch:** Ensure the ON/OFF switch on the power strip is in the 'ON' position.
- **Check Wall Outlet:** Verify that the wall outlet is functioning by plugging in another device.
- **Reset Surge Protector:** If the power strip has experienced an overload, the surge protection may have tripped. Press the reset button (usually a red button near the power cord entry) to restore power.
- **Inspect Cord:** Check the power cord for any visible damage or kinks.

9.2 Slow Charging via USB Ports

- **Cable Quality:** Ensure you are using a high-quality USB cable. Low-quality or damaged cables can significantly reduce charging speed.
- **Device Compatibility:** While the smart ports adjust output, some devices may have specific charging requirements.
- **Total USB Load:** If many devices are connected, the total 4A output is shared. Disconnect some devices to see if charging speed improves for others.

10. Warranty and Customer Support

MIBOTE products are designed for reliability and performance. For warranty information, technical support, or any questions regarding your product, please refer to the contact information provided on the product packaging or visit the official MIBOTE website.
Please retain your purchase receipt for warranty claims.

© 2026 MIBOTE. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B01JRXRTC2

More documents and user manuals: **https://manuals.plus/**