Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

Zendure ZDPX6PD-w

Zendure X6 USB-C Hub Portable Charger User Manual

Model: ZDPX6PD-w

Introduction

Thank you for choosing the Zendure X6 USB-C Hub Portable Charger. This versatile device combines a high-capacity power bank with a USB-C data hub, offering efficient charging and data management for a wide range of electronic devices. Please read this manual carefully to ensure proper use and to maximize the performance of your Zendure X6.

The Zendure X6 features 45W Power Delivery (PD) for fast charging of compatible devices like MacBooks, iPhones, and Nintendo Switch, along with Quick Charge (QC 3.0) for Android devices. Its unique X-Charge mode supports low-power devices, and the integrated LED display provides precise battery status. With 5 output ports and pass-through charging, it's designed for convenience and reliability.

Product Overview



Front view of the Zendure X6 Portable Charger, showcasing its compact design and ribbed texture.



Top view of the Zendure X6, highlighting the various USB ports and the digital LED display showing '100' for full charge.

Key Features

- **45W Power Delivery (PD) USB-C:** Supports fast charging for laptops, tablets, and smartphones, and allows for rapid recharging of the power bank itself.
- **Quick Charge (QC 3.0) Compatible:** Provides accelerated charging for compatible Android devices.
- **USB Type-C Hub Mode:** Functions as a data hub, allowing you to sync and manage files between a USB-C host device and two USB-A peripherals.
- **X-Charge Mode:** Specifically designed to charge low-power devices such as smartwatches, wireless earbuds, and fitness trackers, which often require minimal current.
- **Accurate LED Display:** Shows the exact remaining battery capacity as a percentage and indicates the current operating mode.
- **20,000 mAh High-Capacity:** Provides multiple charges for smartphones and tablets, and significant power for laptops.
- **5-Port Output:** Includes one PD USB Type-C port, one ZEN+ 2.0 QC port, and three ZEN+ ports for simultaneous charging of up to five devices.
- **Pass-Through Charging:** Allows the Zendure X6 to charge connected devices while it is being recharged itself.
- **TSA Approved:** Meets regulations for transport in carry-on bags on airplanes.

Your browser does not support the video tag.

Official product video demonstrating the key features and versatility of the Zendure X6 USB-C Hub Portable Charger, including its charging capabilities and hub functionality.

Setup

Initial Charge

Before first use, fully charge your Zendure X6. This ensures optimal battery performance and accuracy of the LED display.

1. Connect the included 2-in-1 USB-C cable to the PD/Hub port on the Zendure X6.
2. Connect the other end of the cable to a compatible USB-C power adapter (not included). For fastest charging, use a

45W or higher Power Delivery charger.

3. The LED display will show the charging progress as a percentage. The device is fully charged when the display shows '100'.

What's in the Box

- Zendure X6 20,000mAh Portable Charger
- 2-in-1 USB-C Cable (USB-C to USB-C with USB-A adapter)
- User Manual (this document)
- Travel Pouch
- Zendure Fan Stickers

Operating Instructions

Charging Devices

The Zendure X6 can charge up to five devices simultaneously.

1. Connect your device's charging cable to the appropriate output port on the Zendure X6.
2. The Zendure X6 will automatically detect your device and begin charging. The LED display will show the remaining battery percentage.
3. For optimal charging, use the PD/Hub port for USB-C Power Delivery compatible devices and the ZEN+ 2.0 (QC 3.0) port for Quick Charge compatible devices. The ZEN+ ports provide standard high-speed charging.



The Zendure X6 actively charging a laptop via its USB-C PD port and a smartphone via a USB-A port.



The Zendure X6 simultaneously charging a Nintendo Switch, a smartphone, and another device, demonstrating its multi-port capability.

USB Hub Mode

To use the Zendure X6 as a USB-C data hub:

1. Connect the Zendure X6's PD/Hub port to your USB-C host device (e.g., laptop, tablet) using a USB-C to USB-C cable.
2. Connect your USB-A peripherals (e.g., flash drive, mouse, keyboard) to the ZEN+/Hub ports on the Zendure X6.
3. Your host device should now recognize the connected peripherals. The LED display will show 'H' to indicate Hub Mode.

X-Charge Mode for Low-Power Devices

For devices that require very low charging current (e.g., smartwatches, Bluetooth headphones), activate X-Charge mode:

1. Press and hold the power button for approximately 3 seconds until the LED display shows 'X'.
2. Connect your low-power device to any of the USB-A output ports.

3. The Zendure X6 will now provide a stable low-current output suitable for these devices.
4. To exit X-Charge mode, press the power button once. The display will return to showing the battery percentage.



Illustration of the Zendure X6's LED display showing different modes: percentage for charge level, 'H' for Hub mode, and 'X' for X-Charge mode.

Maintenance

- Keep the Zendure X6 away from extreme temperatures, direct sunlight, and humid environments.
- Avoid dropping or subjecting the device to strong impacts.
- Clean the exterior with a soft, dry cloth. Do not use harsh chemicals or abrasive materials.
- Store the power bank with approximately 50-75% charge if not used for extended periods to prolong battery life. Recharge every 3-6 months.

Troubleshooting

Problem	Possible Cause	Solution
Device not charging from Zendure X6.	Cable issue, device not compatible, X6 battery depleted.	Check cable connection. Ensure cable is functional. Recharge Zendure X6. Try X-Charge mode for low-power devices.
Zendure X6 not recharging.	Charging cable or adapter issue, port damage.	Try a different USB-C cable and power adapter. Ensure the adapter supports Power Delivery.
USB Hub mode not working.	Incorrect connection, host device incompatibility.	Ensure the Zendure X6 is connected to a USB-C host device. Verify peripherals are properly connected to the ZEN+/Hub ports.
LED display is off or unresponsive.	Battery depleted, internal error.	Recharge the Zendure X6. If the issue persists, contact customer support.

Specifications

Feature	Detail
Product Dimensions	2.76 x 4.8 x 1.85 inches
Item Weight	13.6 ounces
Model Number	ZDPX6PD-w
Battery Type	Lithium Ion (6 cells included)
Battery Capacity	20000 Milliamp Hours (74.37 Wh)
Input (USB-C PD)	Up to 45W
Output (USB-C PD)	Up to 45W
Output (ZEN+ 2.0 QC)	Quick Charge 3.0 compatible
Output (ZEN+ Ports)	3 x ZEN+ ports (2.4A max per port)
Total Outputs	5 (1x USB-C PD, 1x QC 3.0, 3x ZEN+)
Color	White and Grey
Special Features	Portable Charger, Wireless (as per manufacturer listing)

Warranty & Support

Zendure offers a 24-month worry-free warranty for the X6 Portable Charger. This warranty covers manufacturing defects and ensures your product performs as expected.

For technical support, warranty claims, or any inquiries regarding your Zendure X6, please visit the official Zendure support website or contact their customer service directly. Zendure is committed to providing lifetime friendly customer service.

You can find more information and contact details on theZendure Store on Amazon.

© 2023 Zendure. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B075Q5YTFJ

More documents and user manuals: **https://manuals.plus/**