

[manuals.plus](#) /› [Varaluz](#) /› [Varaluz Sawyers Bar Linear Pendant 287N06HG Instruction Manual](#)

## Varaluz 287N06HG

# Varaluz Sawyers Bar Linear Pendant (Model 287N06HG) Instruction Manual

Havana Gold Finish

## 1. INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Varaluz Sawyers Bar Linear Pendant, Model 287N06HG. Please read all instructions carefully before beginning installation and retain this manual for future reference.

### 1.1 Safety Information

- **WARNING:** Risk of electric shock. Disconnect power at the main circuit breaker or fuse box before installation or servicing.
- All wiring connections must be in accordance with local and national electrical codes (NEC). Consult a qualified electrician if you are unsure about wiring.
- This fixture is intended for indoor use only.
- Do not exceed the maximum wattage specified for the bulbs.
- Ensure the mounting surface can support the weight of the fixture.
- Wear safety glasses and gloves during installation.

## 2. PACKAGE CONTENTS

Carefully unpack your fixture and identify all parts. Ensure all components are present and undamaged before discarding packaging materials. If any parts are missing or damaged, do not attempt to install the fixture.

- Linear Pendant Fixture (1)
- Mounting Canopy (1)
- Suspension Chains (2)
- Stems (2)
- Mounting Hardware Kit (screws, wire nuts, etc.)
- Instruction Manual (this document)



Figure 1: Overview of the Varaluz Sawyers Bar Linear Pendant in Havana Gold finish. The fixture features a linear design with alternating solid and perforated steel panels, creating a unique visual effect.

### 3. SPECIFICATIONS

<b>Model Number</b>	287N06HG
<b>Brand</b>	Varaluz
<b>Finish</b>	Havana Gold
<b>Material</b>	Alloy Steel, Glass (Shade)
<b>Dimensions (L x W x H)</b>	30 x 22 x 20 inches (Fixture only)
<b>Item Weight</b>	20 Pounds
<b>Number of Light Sources</b>	6
<b>Bulb Type</b>	E26 Medium Base Incandescent (Bulbs not included)
<b>Max Wattage per Bulb</b>	100 Watts
<b>Voltage</b>	110/220 Volts
<b>Power Source</b>	Corded Electric
<b>Mounting Type</b>	Protruding (Ceiling Mount)

<b>Included Components</b>	Fixture, Canopy, Chains, Stems
<b>Certifications</b>	CSA Listed
<b>Usage</b>	Indoor Use Only
<b>Assembly Required</b>	Yes



**Figure 2:** Dimensional diagram of the pendant fixture, showing a length of 30 inches, width of 22 inches, and fixture height of 20 inches. It also indicates 10 feet of chain and 6 inches of stem are included for suspension.

#### 4. SETUP AND INSTALLATION

Before installation, ensure power is turned off at the circuit breaker. It is recommended to have two people for installation due to the size and weight of the fixture.

#### **4.1 Tools Required (Not Included)**

- Phillips Head Screwdriver
- Flathead Screwdriver
- Wire Strippers
- Pliers
- Electrical Tape
- Ladder

#### **4.2 Mounting the Canopy and Chains**

1. Turn off power at the main circuit breaker.
2. Attach the mounting bracket (if separate) to the junction box using the provided screws.
3. Connect the fixture's ground wire to the ground wire from the junction box (usually bare copper or green) using a wire nut.
4. Connect the fixture's white wire to the white (neutral) wire from the junction box using a wire nut.
5. Connect the fixture's black wire to the black (hot) wire from the junction box using a wire nut.
6. Carefully tuck all wires into the junction box.
7. Secure the canopy to the mounting bracket using the provided screws. The canopy measures 4.5" L x 8" W x 0.6" Thick.
8. Attach the suspension chains to the canopy and the fixture stems. The fixture includes 10 feet of chain and 6 inches of stem, allowing for adjustable hanging height.



**Figure 3:** Close-up view of the mounting canopy and suspension chain components. This image illustrates how the chain connects to the ceiling mount and the fixture's stems.

#### 4.3 Installing Bulbs

1. Once the fixture is securely mounted and wired, screw six (6) E26 medium base incandescent bulbs (not included) into the sockets.
2. Do not exceed 100 watts per bulb.



**Figure 4:** Detailed view of a bulb socket within the fixture, showing the perforated steel panel and the interior finish. This illustrates where the E26 medium base bulbs are to be installed.

## 5. OPERATING INSTRUCTIONS

---

After successful installation and bulb insertion, restore power at the circuit breaker. The fixture can then be operated using a standard wall switch connected to the circuit.

## 6. MAINTENANCE

---

### 6.1 Cleaning

- Always disconnect power before cleaning.
- Wipe the fixture with a soft, dry cloth.
- Do not use abrasive cleaners, solvents, or polishes as they may damage the finish.

### 6.2 Bulb Replacement

- Turn off power at the circuit breaker and allow bulbs to cool completely before replacing.
- Unscrew the old bulb and replace it with a new E26 medium base incandescent bulb, not exceeding 100 watts.

## 7. TROUBLESHOOTING

Problem	Possible Cause	Solution
Fixture does not light	<ul style="list-style-type: none"><li>Power is off at the circuit breaker.</li><li>Loose or incorrect wiring.</li><li>Bulbs are faulty or not screwed in properly.</li></ul>	<ul style="list-style-type: none"><li>Check the circuit breaker and ensure power is on.</li><li>Verify all wiring connections are secure and correct. Consult a qualified electrician if needed.</li><li>Ensure bulbs are screwed in tightly and test with new bulbs.</li></ul>
Flickering lights	<ul style="list-style-type: none"><li>Loose bulb connection.</li><li>Incorrect bulb type or wattage.</li><li>Loose wiring connection.</li></ul>	<ul style="list-style-type: none"><li>Tighten bulbs.</li><li>Ensure bulbs meet specifications (E26, max 100W).</li><li>Check wiring connections.</li></ul>

## 8. WARRANTY AND SUPPORT

### 8.1 Warranty Information

This Varaluz fixture is covered by a **Lifetime Limited Warranty**. Please refer to the manufacturer's official website or contact customer support for full details regarding warranty terms and conditions.

### 8.2 Customer Support

For technical assistance, missing parts, or warranty claims, please contact Varaluz customer support. Visit the official Varaluz website for contact information.

[Visit the Varaluz Store on Amazon](#)

© 2023 Varaluz. All rights reserved. Specifications are subject to change without notice.