

[manuals.plus](#) /

› [DLYFULL](#) /

› [DLYFULL UT4 USB Multi-Charger Instruction Manual](#)

DLYFULL UT4

DLYFULL UT4 USB Multi-Charger Instruction Manual

Model: UT4

1. INTRODUCTION

This manual provides detailed instructions for the safe and efficient operation of your DLYFULL UT4 USB Multi-Charger. Please read this manual thoroughly before use and retain it for future reference.



Figure 1: Front view of the DLYFULL UT4 USB Multi-Charger, displaying battery status and charging modes.

2. SAFETY INFORMATION

To prevent injury or damage to the charger and batteries, always observe the following safety precautions:

- Use only compatible batteries as listed in the specifications.
- Do not attempt to charge non-rechargeable batteries.
- Do not expose the charger to water, high humidity, or extreme temperatures.
- Keep out of reach of children.
- Do not disassemble or modify the charger.
- Ensure proper ventilation during charging.

3. PACKAGE CONTENTS

Verify that all items are present in the package:

- DLYFULL UT4 USB Multi-Charger
- USB Type-C Cable (may vary by region)
- User Manual (this document)

4. SETUP

4.1 Connecting the Power Supply

1. Connect the provided USB Type-C cable to the input port on the back of the DLYFULL UT4 charger.
2. Connect the other end of the USB Type-C cable to a compatible USB power adapter (DC 5V / 2A recommended, not included).
3. The charger display will illuminate, indicating it is ready for use.



Figure 2: Rear view of the DLYFULL UT4 charger, highlighting the USB Type-C input and USB-A output ports.

5. OPERATING INSTRUCTIONS

5.1 Inserting Batteries

The DLYFULL UT4 features four independent charging slots. Insert compatible rechargeable batteries into the slots, ensuring correct polarity (+ and -). The charger will automatically detect the battery type and display its current voltage.

5.2 Selecting Operating Modes

The charger supports various operating modes. Use the "MODE" button to cycle through available options for the selected slot. Use the "SLOT" button to select which battery slot to configure.

- **CHARGE:** Standard charging mode.
- **DISCHARGE:** Discharges the battery to a safe level before recharging (useful for Ni-MH batteries to reduce memory effect).
- **REFRESH:** Charges, discharges, and then recharges the battery to optimize capacity and extend

battery life.

- **TEST:** Measures the actual capacity of the battery.

5.3 USB Output Function

The charger can also function as a power bank to charge external devices. To use this feature:

1. Ensure a charged battery is inserted into **Slot 1**.
2. Connect your external device (e.g., smartphone) to the USB-A output port on the back of the charger.
3. The charger will provide up to 5V / 2A output.



Figure 3: The DLYFULL UT4 charger in use, demonstrating battery insertion and showing included battery sleeves.

6. MAINTENANCE

- Clean the charger with a dry, soft cloth. Do not use abrasive cleaners or solvents.
- Keep the charging slots free from dust and debris.
- Store the charger in a cool, dry place when not in use.

7. TROUBLESHOOTING

- **Charger not powering on:**

Ensure the USB Type-C cable is securely connected to both the charger and a working power source. Verify the power source provides DC 5V / 2A.

- **Battery not charging:**

Check that the battery is inserted with correct polarity. Ensure the battery is compatible with the

charger. Try cleaning the battery contacts and charger terminals.

- **"Low Input" message on display:**

This indicates the input power supply is insufficient. Use a power adapter that provides at least DC 5V / 2A.

8. SPECIFICATIONS

入力	DC 5V / 2A (USB Type-C)	
出力	USB 5V	2A Max
放電電流	350mAh	
動作温度域	0~40°C	
Li-ion 最高保護電圧	4.20V ±0.05V	
Ni-MH 最高保護電圧	1.53V ±0.05V	
対応電池	Li-ion 3.6V /3.7V	10340/14500/16340(RCR123A)17500/ 17650/17670/18490/18500/18650/ 20700/21700/22650/26500/26650
	LiFePo4 3.2V	
	Ni-MH 1.2V	単2形/単3形/単4形/C/SC
注意	単2形Ni-MH電池は同時に2本までセット可能	

Figure 4: Original specifications table for the DLYFULL UT4 charger.

Feature	Detail
Model	UT4 (Multi-Charger)
Input	DC 5V / 2A (USB Type-C)
USB Output	5V / 2A Max (from Slot 1)
Ni-MH Charging Current	1A (for 1.48V batteries)
Ni-MH Discharge Current	350mAh
Operating Temperature	0°C to 40°C
Li-ion Max Protection Voltage	4.20V ± 0.05V
Ni-MH Max Protection Voltage	1.53V ± 0.05V

Feature	Detail
Compatible Batteries	Li-ion: 3.6V / 3.7V (10340, 14500, 16340 (RCR123A), 17500, 17650, 17670, 18490, 18500, 18650, 20700, 21700, 22650, 26500, 26650) LiFePO4: 3.2V Ni-MH: 1.2V (AA, AAA, C, SC)
Certifications	CE, RoHS
Color	Black

Note: Up to two Ni-MH batteries of size AA can be set simultaneously.

9. WARRANTY INFORMATION

Specific warranty details for the DLYFULL UT4 USB Multi-Charger are not provided in this document. Please refer to the product packaging, the official DLYFULL website, or contact your retailer for warranty terms and conditions.

10. CUSTOMER SUPPORT

For technical assistance, troubleshooting, or general inquiries regarding your DLYFULL UT4 USB Multi-Charger, please visit the official DLYFULL website or contact their customer support channels. Contact information may also be available on the product packaging.