

Manuals.plus /

› Baseus /

› Baseus Spacemate 11-in-1 USB-C Docking Station User Manual

Baseus Spacemate

Baseus Spacemate 11-in-1 USB-C Docking Station User Manual

INTRODUCTION

This manual provides detailed instructions for the proper setup, operation, and maintenance of your Baseus Spacemate 11-in-1 USB-C Docking Station. Please read this manual thoroughly before using the product to ensure optimal performance and safety. Keep this manual for future reference.

PRODUCT OVERVIEW

The Baseus Spacemate 11-in-1 USB-C Docking Station is designed to expand the connectivity of your USB-C enabled laptop or tablet, particularly those running Linux. It offers a comprehensive range of ports for various peripherals and display outputs.

Key Features:

- **4K HDMI and DisplayPort (DP):** Connect to external monitors for high-resolution video output.
- **Gigabit Ethernet:** Provides a stable and fast wired network connection.
- **100W Power Delivery (PD):** Allows for pass-through charging of your host device.
- **Audio 3.5mm Jack:** For connecting headphones or speakers.
- **10Gbps USB A/C Ports:** High-speed data transfer for external devices.
- **SD/MicroSD Card Readers:** For convenient access to memory cards.

Product Diagram:

Below is an image illustrating the various ports and components of the docking station.



Laptop interface shortage? Having it can resolve your troubles

Image: Overview of the Baseus Spacemate 11-in-1 USB-C Docking Station ports.

The docking station features a compact design with a flexible USB-C cable for connection to your host device. It includes a bend angle design for secure attachment to certain tablets, and a heat dissipation base for optimal performance.

**Bend angle design
customized
for iP tablet Pro**



Image: Docking station showcasing its bend angle design for tablet integration.

Considerate open type heat dissipation base



Image: The docking station's heat dissipation base.

SETUP INSTRUCTIONS

Follow these steps to connect and begin using your Baseus Spacemate 11-in-1 USB-C Docking Station.

1. **Unpack the Device:** Carefully remove the docking station from its packaging. Ensure all components, including any included spacers, are present.
2. **Connect to Host Device:** Plug the integrated USB-C cable from the docking station into the USB-C port of your laptop or tablet. For tablets, the bend angle design allows for a secure fit on the corner. If using with a case, you may need to remove the spacer from the docking station for a proper fit.
3. **Power Connection (Optional but Recommended):** For stable operation and to charge your host device, connect a USB-C power adapter (not included) to the Power Delivery (PD) USB-C port on the docking station.
4. **Connect Peripherals:** Connect your desired peripherals such as external monitors (via HDMI or DisplayPort), USB devices (keyboard, mouse, external drives), Ethernet cable, and audio devices to the corresponding ports on the docking station.
5. **Driver Installation (if necessary):** For most modern operating systems, the docking station should be plug-

and-play. If your system (especially Linux distributions) does not automatically recognize all functions, consult your operating system's documentation for USB-C hub compatibility and potential driver requirements.

Visual Setup Guide:

The following video demonstrates the physical connection of the docking station to a tablet and highlights its features.

Your browser does not support the video tag.

Video: Demonstration of connecting the Baseus USB-C Hub to an iPad Pro, showing the fit and port overview.

OPERATING INSTRUCTIONS

Once connected, the docking station extends your device's capabilities. Here's how to utilize its various functions:

- **Video Output (HDMI/DP):** Connect an HDMI or DisplayPort cable from the docking station to your external monitor. Your operating system should automatically detect the display. You can configure display settings (mirror, extend) through your device's display preferences. The docking station supports 4K resolution.
- **USB Data Transfer (USB A/C):** Use the USB-A and USB-C data ports to connect external hard drives, flash drives, keyboards, mice, and other USB peripherals. The 10Gbps ports ensure fast data transfer speeds.
- **Ethernet Connection:** Plug an Ethernet cable into the Gigabit Ethernet port for a stable and high-speed internet connection, bypassing Wi-Fi.
- **Audio Output (3.5mm Jack):** Connect headphones or speakers to the 3.5mm audio jack for sound output. Ensure your device's audio settings are configured to use the docking station's audio output.
- **Card Reader (SD/MicroSD):** Insert your SD or MicroSD cards into the respective slots to access files. The card reader functions as a standard external drive.
- **Power Delivery (PD):** The USB-C PD port allows you to charge your host device while using the docking station. Connect your device's original power adapter to this port. The docking station supports up to 100W power delivery.

High-Speed Data Transfer:

The docking station supports high-efficiency data transmission, significantly reducing file transfer times.

Fast 5Gbps high efficiency transmission



Image: Illustration of 5Gbps high-efficiency transmission via USB 3.0.



Image: Highlighting 10Gbps data transfer capability.

Extended Display Functionality:

Transform your small screen into a large display for enhanced productivity or entertainment.

Wonderful from small screen to large screen



Image: Demonstrating screen extension from a tablet to a large monitor.



Image: Multi-monitor setup with the docking station.

MAINTENANCE

To ensure the longevity and proper functioning of your docking station, follow these maintenance guidelines:

- **Cleaning:** Use a soft, dry cloth to clean the exterior of the docking station. Avoid using liquid cleaners, aerosols, or harsh chemicals, as these can damage the device.
- **Storage:** When not in use, store the docking station in a cool, dry place away from direct sunlight and extreme temperatures.
- **Handling:** Avoid dropping the device or subjecting it to strong impacts. Do not bend the integrated USB-C cable excessively.
- **Port Care:** Keep all ports free from dust and debris. If necessary, use compressed air to gently clear any obstructions.

TROUBLESHOOTING

If you encounter issues with your Baseus Spacemate 11-in-1 USB-C Docking Station, refer to the following common problems and solutions:

- **No Display Output:**
 - Ensure the HDMI/DP cable is securely connected to both the docking station and the monitor.
 - Verify the monitor input source is correctly selected.
 - Check your host device's display settings to ensure the external monitor is detected and configured.
 - Try a different HDMI/DP cable or monitor if possible.
- **USB Devices Not Recognized:**
 - Ensure the USB device is properly inserted into the docking station port.
 - Try connecting the USB device to a different port on the docking station or directly to your host device to

rule out device issues.

- Restart your host device.

- **No Network Connection (Ethernet):**

- Verify the Ethernet cable is securely connected to both the docking station and your router/modem.
- Check your host device's network settings.
- Ensure your router/modem is functioning correctly.

- **Host Device Not Charging (PD):**

- Ensure your power adapter is connected to the PD USB-C port on the docking station.
- Verify your power adapter is functional and provides sufficient wattage (up to 100W supported).
- Check the connection between the docking station and your host device.

- **Audio Not Working:**

- Ensure headphones/speakers are fully plugged into the 3.5mm audio jack.
- Check your host device's audio output settings to select the docking station as the output device.

SPECIFICATIONS

Brand	Baseus
Model	Spacemate (B07VX46FPK)
Number of Ports	11
Connector Type	USB Type C (Host Connection), 3.5mm Jack, HDMI, DisplayPort, USB Type C (PD), USB Type A, SD/MicroSD
Video Output	4K HDMI, DisplayPort
Ethernet	Gigabit Ethernet
Power Delivery	Up to 100W
USB Data Speed	10Gbps (for compatible USB A/C ports)
Compatible Devices	USB-C enabled laptops and tablets (optimized for Linux)
Color	Gray
Item Weight	4.8 Ounces

Note: Specifications are subject to change without prior notice.

WARRANTY AND SUPPORT

Baseus products are designed and manufactured to the highest quality standards. For information regarding warranty coverage, terms, and conditions, please refer to the warranty card included with your product or visit the official Baseus website.

If you require technical assistance or have questions about your Baseus Spacemate 11-in-1 USB-C Docking Station, please contact Baseus customer support through the channels provided on the official website or product packaging.

When contacting support, please have your product model number and purchase information ready.

Online Resources:

- Visit the Baseus Store on Amazon for product information and updates.