

E-Projects B-0001-B08f

E-Projects L7805CV Positive Voltage Regulator User Manual

Model: B-0001-B08f

1. INTRODUCTION

The E-Projects L7805CV is a highly reliable positive voltage regulator designed to provide a stable 5-volt output from a higher, unregulated DC input voltage. This component is widely used in various electronic circuits to ensure a consistent power supply for sensitive components. It comes in a standard TO-220 package, making it suitable for through-hole mounting and efficient heat dissipation.

This manual provides essential information regarding the setup, operation, and specifications of the L7805CV voltage regulator.

2. KEY FEATURES

- **Fixed 5V Output:** Provides a stable and regulated 5V DC output.
- **Wide Input Voltage Range:** Operates with an input voltage from 7 VDC to 35 VDC.
- **Thermal Overload Protection:** Built-in circuitry to prevent damage from excessive temperature.
- **Short Circuit Protection:** Protects the device from damage due to output short circuits.
- **Output Transition SOA Protection:** Ensures safe operation under varying load conditions.
- **TO-220 Package:** Standard package for easy mounting and heat sinking.
- **High Reliability:** Designed for robust and consistent performance.

3. SPECIFICATIONS

Parameter	Value
Model Number	L7805CV
Output Voltage (V _{OUT})	5 VDC
Input Voltage Range (V _{IN})	7 VDC to 35 VDC
Maximum Output Current (I _{OUT})	1.0 A (typical, with adequate heatsink)

Parameter	Value
Package Type	TO-220
Operating Junction Temperature Range	0°C to +125°C
Manufacturer	Various

4. SETUP AND INSTALLATION

Proper installation is crucial for the optimal performance and longevity of the L7805CV voltage regulator. Refer to the pinout diagram below for correct connections.



Figure 1: L7805CV TO-220 Package. This image shows the black plastic body of the L7805CV voltage regulator with a metal tab for heat dissipation and three silver pins extending from the bottom. From left to right, the pins are typically Input, Ground, and Output.

Pinout Configuration (Front View, Pins Facing You):

- Pin 1 (Left):** Input Voltage (V_{IN}) - Connect your unregulated DC input voltage here (7V to 35V).
- Pin 2 (Middle):** Ground (GND) - Connect to the common ground of your circuit. This pin is typically connected to the metal tab for heat sinking.
- Pin 3 (Right):** Output Voltage (V_{OUT}) - This pin provides the regulated 5V DC output.

Basic Application Circuit:

For stable operation, it is recommended to use bypass capacitors at both the input and output of the regulator. A typical setup includes:

- A 0.33 μ F (or larger) capacitor connected between the input pin and ground, placed close to the regulator. This helps to filter out input ripples.
- A 0.1 μ F (or larger) capacitor connected between the output pin and ground, also placed close to the regulator. This improves transient response and output stability.

Heat Sinking:

The L7805CV dissipates power as heat, especially when the input voltage is significantly higher than the output voltage or when supplying higher currents. The metal tab of the TO-220 package is connected to the ground pin (Pin 2) and is designed to be attached to a heatsink. Ensure adequate heatsinking is provided to keep the junction temperature within the specified operating range, particularly for applications drawing more than a few hundred milliamperes.

5. OPERATING PRINCIPLES

The L7805CV is a linear voltage regulator. It operates by continuously adjusting an internal series pass transistor to maintain a constant output voltage, regardless of variations in the input voltage or load current (within its specified limits). The difference between the input and output voltage, multiplied by the output current, is dissipated as heat. This makes linear regulators simple to use and provides a very clean, low-noise output, but they are less efficient than switching regulators, especially with large input-output voltage differentials.

6. MAINTENANCE

The L7805CV is a solid-state electronic component and requires no routine maintenance. It contains no user-serviceable parts. To ensure continued reliable operation, it is important to:

- Ensure the operating environment is within the specified temperature range.
- Verify that adequate heat sinking is maintained, especially if the device is operating at higher currents or with significant input-output voltage differences.
- Keep the surrounding area free from excessive dust or moisture.

7. TROUBLESHOOTING

If you encounter issues with your L7805CV voltage regulator, consider the following common troubleshooting steps:

- **No Output Voltage (0V):**
 - Check the input voltage (V_{IN}) to ensure it is within the 7V to 35V range.
 - Verify that the ground (GND) connection is solid.
 - Check for a short circuit on the output (V_{OUT}) line. The regulator has short-circuit protection, which may shut down the output.
 - Ensure the regulator is not overheating. Thermal shutdown will occur if the junction temperature exceeds its limit.
- **Output Voltage Too Low (but not 0V):**
 - The load current might exceed the regulator's maximum output current (1A). Reduce the load or use multiple regulators in parallel (with current sharing resistors) or a higher current regulator.
 - Inadequate heat sinking leading to thermal throttling. Improve heat dissipation.
 - Input voltage is too close to the output voltage (dropout voltage). Ensure V_{IN} is at least 2V-3V higher than V_{OUT} .
- **Regulator Overheating:**
 - The power dissipated ($P_D = (V_{IN} - V_{OUT}) * I_{OUT}$) is too high for the current heat sink. Increase the size of the heatsink or use forced air cooling.
 - Check for excessive load current.

8. WARRANTY AND SUPPORT

E-Projects stands behind the quality of its products. While specific warranty details may vary, general support for this product is available through the point of purchase or by contacting E-Projects directly. For technical assistance or inquiries regarding product performance, please refer to the contact information provided by your retailer or on the official E-Projects website.

Please retain your proof of purchase for any warranty claims.

© 2024 E-Projects. All rights reserved.

This manual is for informational purposes only. Specifications are subject to change without notice.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B07Y3DY89Y>

More documents and user manuals: <https://manuals.plus/>