

## Ezlo PSE02

# Ezlo PSE02 Philio Multi Sound Z-Wave Siren User Manual

Model: PSE02 | Brand: Ezlo

## 1. INTRODUCTION

This manual provides detailed instructions for the installation, operation, and maintenance of your Ezlo PSE02 Philio Multi Sound Z-Wave Siren. Please read this manual thoroughly before using the device to ensure proper functionality and safety. The PSE02 is a Z-Wave enabled multi-sound siren designed to enhance your home security system by providing audible alerts.

## 2. SAFETY INFORMATION

- Do not expose the device to moisture or extreme temperatures.
- Do not attempt to disassemble or repair the device yourself. Refer all servicing to qualified personnel.
- Ensure proper battery installation to prevent damage or injury.
- Keep the device out of reach of children.
- The siren can produce sounds up to 110 dB. Avoid prolonged exposure to loud sounds to prevent hearing damage.

## 3. PRODUCT OVERVIEW

The Ezlo PSE02 is a compact, wireless Z-Wave siren. It integrates into your Z-Wave network to provide audible alerts for various events, such as security breaches or system notifications. Its design allows for discreet wall mounting.



This image displays the Ezlo PSE02 Philio Multi Sound Z-Wave Siren. It features a compact, white, rectangular design with rounded corners. A small, curved indicator light is visible near the top edge, which illuminates to show device status.

## 4. SETUP

---

### 4.1 What's in the Box

- Ezlo PSE02 Philio Multi Sound Z-Wave Siren
- Mounting hardware (screws and anchors)
- User Manual (this document)

### 4.2 Powering the Device

1. Open the battery compartment cover on the back of the siren.
2. Insert the required batteries, ensuring correct polarity (+/-). The device requires 5 Volts, typically supplied by standard batteries.
3. Close the battery compartment cover securely.

### 4.3 Z-Wave Inclusion (Pairing)

To add the siren to your Z-Wave network:

1. Place your Z-Wave controller (hub/gateway) into inclusion mode. Refer to your controller's manual for specific instructions.
2. Within 1.5 seconds, press the Z-Wave button on the PSE02 three times. The indicator light will flash to confirm inclusion mode.
3. The siren will automatically connect to your Z-Wave network. The indicator light will stop flashing once successfully included.
4. Verify the device appears in your Z-Wave controller's device list.

## 4.4 Z-Wave Exclusion (Unpairing)

To remove the siren from your Z-Wave network:

1. Place your Z-Wave controller into exclusion mode.
2. Within 1.5 seconds, press the Z-Wave button on the PSE02 three times. The indicator light will flash to confirm exclusion mode.
3. The siren will be removed from your Z-Wave network. The indicator light will stop flashing.

## 4.5 Mounting the Device

The PSE02 is designed for wall mounting.

1. Choose a suitable location for the siren, ensuring it is within range of your Z-Wave network.
2. Use the provided mounting bracket and hardware to secure the siren to the wall.
3. Ensure the siren is securely attached and stable.

# 5. OPERATING THE SIREN

---

Once successfully included in your Z-Wave network, the Ezlo PSE02 siren can be controlled via your Z-Wave controller or associated mobile application.

- **Activating the Siren:** Use your Z-Wave controller's interface to send commands to the siren. This typically involves selecting the siren device and choosing an 'on' or 'alarm' function.
- **Multi-Sound Functionality:** The PSE02 supports multiple sound types. Your Z-Wave controller's interface may allow you to select specific siren tones or sound effects. Refer to your controller's documentation for details on how to access these options.
- **Sound Level:** The siren can produce sounds up to 110 dB.
- **Deactivating the Siren:** Use your Z-Wave controller's interface to send an 'off' or 'disarm' command to the siren.

# 6. MAINTENANCE

---

## 6.1 Battery Replacement

When the batteries are low, the siren may indicate this through its indicator light or a notification via your Z-Wave controller. Replace batteries as follows:

1. Open the battery compartment cover.
2. Remove the old batteries and dispose of them according to local regulations.

- 3. Insert new batteries, ensuring correct polarity.
- 4. Close the battery compartment cover.

## 6.2 Cleaning

Wipe the device with a soft, dry cloth. Do not use abrasive cleaners or solvents, as these can damage the casing.

## 7. TROUBLESHOOTING

- **Siren not pairing with Z-Wave controller:**  
Ensure the siren is within range of your Z-Wave controller. Try performing an exclusion first, then attempt inclusion again. Check battery levels.
- **Siren not sounding:**  
Verify the siren is powered on and has sufficient battery life. Check your Z-Wave controller's settings to ensure the siren is properly configured and receiving commands.
- **Short battery life:**  
Ensure you are using fresh, high-quality batteries. Frequent activation of the siren will consume battery power more quickly.
- **Indicator light not working:**  
Check battery levels. If the device is powered and still no light, contact customer support.

## 8. SPECIFICATIONS

Feature	Specification
Model Number	PSE02
Brand	Ezlo
Noise Level	110 dB
Mounting Type	Wall Mount
Power Source	Battery Powered
Voltage	5 Volts
Control Method	App (via Z-Wave controller)
Batteries Required	Yes
Color	White

## 9. WARRANTY INFORMATION






Ezlo products are designed for reliability and performance. For specific warranty terms and conditions, please refer to the warranty card included with your product or visit the official Ezlo website. Keep your purchase receipt as proof of purchase for any warranty claims.

## 10. CUSTOMER SUPPORT

If you encounter any issues or have questions regarding your Ezlo PSE02 Philio Multi Sound Z-Wave Siren that are not covered in this manual, please contact Ezlo customer support. Contact information can typically be found on the Ezlo website or on the product packaging.

© 2023 Ezlo. All rights reserved.

### Related Documents - PSE02

	<p><a href="#">Ezlo Gateways and Qubino Devices Compatibility Guide</a></p> <p>A comprehensive guide detailing the compatibility between Ezlo gateways (Atom, PlugHub, Plus, Secure) and various Qubino Z-Wave devices, including supported functions.</p>
	<p><a href="#">Ezlo PlugHub Energy Product Manual - Setup and Operation Guide</a></p> <p>This manual provides instructions for setting up, pairing, and managing the Ezlo PlugHub Energy device, including interoperability, inclusion, exclusion, and factory reset procedures.</p>
	<p><a href="#">Ezlo Atom Advanced Information and User Guide</a></p> <p>Comprehensive guide to Ezlo Atom smart home hub features, including interoperability, device pairing (inclusion), exclusion, learn mode, and factory reset procedures. Learn how to integrate Z-Wave devices with your smart home system.</p>
	<p><a href="#">Ezlo Secure Smart Home Controller: Setup and User Manual</a></p> <p>This manual provides comprehensive instructions for setting up and using the Ezlo Secure Smart Home Controller, including device pairing, Z-Wave integration, and smart home automation features.</p>
	<p><a href="#">Ezlo 100 User Guide: Smart Home Automation Hub</a></p> <p>Comprehensive user guide for the Ezlo 100, a USB-powered Z-Wave home automation hub. Learn how to set up, connect, manage devices, and utilize its features for smart home control.</p>

ezlo plus

Smart Home Controller

Quick Start Guide

vera

## Ezlo Plus Quick Start Guide: Smart Home Controller Setup

Get started with your Ezlo Plus Smart Home Controller. This guide provides step-by-step instructions for setup, app installation, network connection, and adding devices for a smarter, safer home.

Documents - Ezlo – PSE02

[pdf] User Manual Catalog

Multiple Sound Siren PSE02 Catalog of Certified Z Wave Home Controls Philio Manual Battery Shutdown

When the DC power is dropped The system will auto switch to use battery If you want really shutdown

COMMAND CLASS SWITCH BINARY BASIC Manufacturer EZPHLPSE02US User 2014 10 29

homecontrols products s EZ Ezlo rus z wave me drive file 88ad3f5a88af0ed72593aa6a496e4f42348c

wavealliance org ProductManual File folder filename MarketCertificationFiles 1166 80 Manuals

Multiple Sound Siren **PSE02** Concurrent multi-channel support reduces external interference. Better RF range, improve about 10 meters in indoor. Support 100 Kbps transmit speed, speed up communication. Product Overview Circle Button The multiple sound siren **PSE02** is a wireless siren, based on Z...

lang:en score:26 filesize: 116.99 K page\_count: 5 document date: 2014-10-13

[pdf] User Manual Installation Guide Guide Warranty

vesternet dl file id 798 product 1890 zipabox indoor siren manualVeraEdge and Zipato Indoor Siren with 6

different sounds General Discussions Ezlo Communityzipabox manualvesternet manual |||

INDOOR SIREN QUICK INSTALLATION GUIDE v1.2 TRADEMARKS Zipato and the Zipato logo are registered Trad ... - EU UNITED STATES - US RUSSIA - RU ISRAEL - IS AUSTRALIA - AU INDIA - IN JAPAN/TAIWAN - JP/TW ph-**pse02**.eu ph-**pse02**.us ph-**pse02**.ru ph-**pse02**.is ph-**pse02**.au ph-**pse02**.in 868.42, 869.85 MHz 908.42, 916....

lang:en score:26 filesize: 122.93 K page\_count: 2 document date: 2015-09-14

[pdf] User Manual Instructions Catalog

Multiple Sound Siren PSE02 Home ControlsIf you want to really shutdown the system please follow instructions as below 1 Press and hold circle button 2 Click tamper 3 times in 5 secondsEZPHLPSE02US User Manualhomecontrols homecontrols products s EZ Ezlo EZPHLPSE02US Manual srsItid AfmBOoqPVmf4dJvvNIAW7Uv DzIw9DAKdA2f2MhRzcHdUwkcHuD9Tdpm ControlsMultiple secondsThe multiple sound siren is a wireless based on Z Wave™ technology It plus product it support securityEZPHLPSE02US ManualEZPHLPSE02US

DzIw9DAKdA2f2MhRzcHdUwkcHuD9Tdpmhomecontrols AfmBOoqQLCrRO8nwBsO2TEqCPfALAIkaO77rIG8OOB9JLdgQVMWOZhtM ControlsPSE02 2014 10 29lf securityMulti Wave Alliance Product CatalogEZPHLPSE02US ManualIPSE02 29homecontrols AfmBOoqQLCrRO8nwBsO2TEqCPfALAIkaO77rIG8OOB9JLdgQVMWOZhtMproducts z wavealliance org 16752 29 29EZPHLPSE02US AfmBOorYBPfCC 0qd7DO9KN0CQuWupp8lpp2dmiVPzPMWzAXQk oiKay securityThe AfmBOoqQLCrRO8nwBsO2TEqCPfALAIkaO77rIG8OOB9JLdgQVMWOZhtMhomecontrols AfmBOooEdTbY5bdAlzwC9UlfpxSqo280gmWOEBpNckIbj2y4D um98lproducts AfmBOorg8kBiC4NAXu9po9v1Y6lb z5Jm91gQdhGZf4Dn6fxQSDJi1okhomecontrols AfmBOoqLErx07kT8nT6ImGnOCeCMY7x4 kD7nehq9R ITb3X2bGrPRUxhomecontrols AfmBOoqeWaZv8alyed GiWrNrEnXEuGN953klulbIT5rCUB2bBm5lXgWhomecontrols AfmBOoogPBmk1WO3ilanFiDch45yyLN2ednxPxBRY5GOQPUnuqLSLbbKhomecontrols um98lhomecontrols AfmBOoqzAyr1aITHh8Eo n3BkP94R 64zOIRi4YICZUEr58 3m6JzZproducts oiKayhomecontrols AfmBOopVab nhPkrGiROwXPgRcahz1Gg cAdNSQHwN6V1yWuHMPejetT 3m6JzZhomecontrols

AfmBOoo113QQTeLQ0pTydezIH2biDEWOZw5aIMJXup2p9FHeFvXY0sCfproducts ||| Multiple Sound Siren **PSE02** Concurrent multi-channel support reduces external interference. Better RF range, improve about 10 meters in indoor. Support 100 Kbps transmit speed, speed up communication. Product Overview Circle Button The multiple sound siren **PSE02** is a wireless siren, based on Z... lang:en score:25 filesize: 117 K page\_count: 5 document date: 2014-10-13

