Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

BAOFENG UV-S9 Plus

BAOFENG UV-S9 Plus Two-Way Radio User Manual

Comprehensive instructions for setup, operation, and maintenance of your BAOFENG UV-S9 Plus 8W VHF UHF Dual Band Handheld Radio.

1. Introduction

Thank you for choosing the BAOFENG UV-S9 Plus 8W VHF UHF Dual Band Handheld Two-Way Radio. This manual provides detailed instructions to help you understand and operate your radio effectively. Please read this manual thoroughly before using the device to ensure proper function and safety.

The BAOFENG UV-S9 Plus is a high-power, dual-band radio designed for reliable long-range communication, featuring a large 2200mAh battery and versatile charging options.

2. Product Overview and Components

Familiarize yourself with the radio's components and the items included in the package.



Figure 2.1: Included Components. This image displays all items typically found in the BAOFENG UV-S9 Plus package, including the radio unit, antenna, rechargeable battery, belt clip, desktop charging cradle, AC power adapter, USB charging cable, and an earpiece.



Figure 2.2: Radio Parts Diagram. This diagram labels the various parts of the radio, such as the antenna, power/volume knob, frequency/channel mode switch, LED indicator, frequency display switch, speaker/microphone, flashlight LED, FM/Alarm button, PTT (Push-to-Talk) button, flashlight/monitor button, band key, and keypad.

3. Setup

3.1 Battery Installation

1. Ensure the radio is powered off.
2. Align the battery pack with the grooves on the back of the radio.
3. Slide the battery pack upwards until it clicks securely into place.
4. To remove, press the battery release latch (if present, typically at the bottom of the battery) and slide the battery downwards.



Figure 3.1: Battery Compartment. This image shows the rear of the radio with the battery attached, highlighting the secure fit and the product information label.

3.2 Antenna Attachment

Screw the antenna clockwise into the connector on the top of the radio until it is finger-tight. Do not overtighten.

3.3 Charging the Battery

The BAOFENG UV-S9 Plus offers two convenient charging methods:

- **Desktop Charging Cradle:** Place the radio (with battery installed) into the charging cradle. Connect the AC power adapter to the cradle and plug it into a wall outlet. The indicator light on the cradle will show charging status.
- **USB Direct Charging:** Connect the provided USB charging cable to the radio's charging port (typically on the side, under a protective cover) and to a USB power source (e.g., computer USB port, USB wall adapter, car charger).



Figure 3.2: Charging Methods. This image illustrates both the desktop charging cradle and the USB direct charging cable in use with the radio.



Figure 3.3: USB Charging Connection. A detailed view of the USB charging cable plugged into the radio's charging port.

4. Operating Instructions

4.1 Power On/Off and Volume Control

Rotate the top knob clockwise to power on the radio and adjust the volume. Rotate counter-clockwise until a click is heard to power off.

4.2 Frequency/Channel Mode Switch (VFO/MR)

Press the **VFO/MR** button to switch between Frequency Mode (VFO) and Channel Mode (MR). In VFO mode, you can manually input frequencies. In MR mode, you can select pre-programmed channels.

4.3 Push-to-Talk (PTT) Button

Press and hold the large **PTT** button on the side of the radio to transmit. Release it to receive.

4.4 Power Output Adjustment

The UV-S9 Plus allows you to select between different power output levels (1W, 4W, 8W) to optimize battery life or maximize range. This setting can typically be adjusted through the radio's menu system.



Figure 4.1: Adjustable Power Levels. The radio's display indicates the current transmit power setting, which can be toggled between High (8W), Mid (4W), and Low (1W).

Video 4.1: Power Output Demonstration. This video demonstrates the actual power output of the BAOFENG UV-S9 Plus radio when connected to an SWR meter, showing it can achieve over 8 Watts.

4.5 Flashlight Function

The radio includes a built-in LED flashlight. Refer to the radio's specific button layout (Figure 2.2) for the dedicated flashlight button, or consult the menu for activation.

4.6 FM Radio

The UV-S9 Plus can also function as an FM radio receiver. Press the**FM/ALARM** button to enter FM radio mode. Use the keypad to tune to desired frequencies.

5. Maintenance

5.1 Cleaning

Wipe the radio's surface with a soft, damp cloth. Do not use harsh chemicals or abrasive cleaners. Ensure all port covers are securely closed to maintain water resistance.

5.2 Battery Care

- Charge the battery fully before first use.
- Avoid overcharging or completely draining the battery.
- If storing the radio for extended periods, charge the battery to approximately 50% capacity.

5.3 Storage

Store the radio in a cool, dry place away from direct sunlight, extreme temperatures, and corrosive materials. Remove the battery if storing for a long duration.

6. Troubleshooting

Problem	Possible Cause	Solution
Radio does not power on.	Battery is low or not installed correctly.	Charge the battery. Ensure the battery is securely attached.
Cannot transmit or receive.	Incorrect frequency/channel, antenna not connected, or out of range.	Verify frequency/channel settings. Ensure antenna is securely attached. Move closer to the other radio or repeater.
Poor audio quality.	Low battery, weak signal, or microphone/speaker obstruction.	Charge battery. Check signal strength. Ensure microphone and speaker are clear.
Battery not charging.	Charger or cable faulty, or improper connection.	Check charger and cable for damage. Ensure connections are secure. Try a different power source.

7. Specifications

Feature	Detail
Model Number	UV-S9 Plus
Brand	BAOFENG
Frequency Range	VHF: 136-174 MHz, UHF: 400-520 MHz, FM Radio: 65-108 MHz
Number of Channels	128
Power Output	8W / 4W / 1W (selectable)
Battery Capacity	2200mAh (Lithium-Ion)

Feature	Detail
Voltage	7.4 Volts
Dimensions (H x W x D)	5.91 x 2.28 x 1.26 inches (150 x 58 x 32 mm approx, excluding antenna)
Weight	1.04 pounds (approx. 470g with battery and antenna)
Water Resistance Level	Waterproof (specific IP rating not provided)
Compatible Devices	BAOFENG two-way radios, other devices using the same frequency bands




Figure 7.1: Measured Power Output. This image shows the radio's actual power output measured by an SWR meter, confirming its capability to transmit at 8 Watts or higher when fully charged.



Figure 7.2: Product Dimensions. A visual representation of the radio's physical dimensions.

8. Warranty and Support

For warranty information, technical support, or service inquiries, please refer to the contact information provided by your retailer or visit the official BAOFENG website. Keep your purchase receipt as proof of purchase for warranty claims.

Additional resources, including software for programming and advanced guides, may be available online from the

manufacturer or community forums.

© 2024 BAOFENG. All rights reserved. This manual is for informational purposes only.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B08J49W4YC

More documents and user manuals: **https://manuals.plus/**