Sercomm DM1000

Sercomm DM1000 DOCSIS 3.1 Cable Modem User Manual

Model: DM1000

Introduction

The Sercomm DM1000 is a high-performance DOCSIS 3.1 cable modem designed to deliver high-speed broadband internet access. It features an integrated 2.5Gbps Ethernet port, enabling speeds exceeding 1Gbps for home or office use. This modem is built to provide low latency and high bandwidth, essential for modern internet activities such as work, online learning, and entertainment. Its compact design allows for seamless integration into various environments. The DM1000 supports standard provisioning and upgrades via SNMP and is compatible with DOCSIS 3.1 and DOCSIS 3.0 standards, including 32x8 SCQAM channels.

Product Overview



Figure 1: Sercomm DM1000 DOCSIS 3.1 Cable Modem. This image shows the compact black modem with ventilation grilles on its top surface and side, indicating its design for efficient heat dissipation.

Key Features:

- **DOCSIS 3.1 and DOCSIS 3.0 Compliant:**Ensures compatibility with current and next-generation cable internet services.
- **DOCSIS/EuroDOCSIS 3.0 32x8 SCQAM Channels Support:** Provides robust channel bonding for high-speed data transfer.
- **Ethernet 2.5Gbps NBASE-T Port:** Supports ultra-fast wired connections, allowing for speeds over 1 Gbps.
- **For Third Party ISP Only:** Designed for use with independent internet service providers.

Setup Guide

1. Before You Begin:

- Ensure you have an active cable internet service subscription with a compatible Third Party ISP.
- Locate a coaxial cable outlet (cable TV wall jack) in your home.
- Have an Ethernet cable ready to connect the modem to your computer or router.
- Ensure the power adapter is available.

2. Connecting Your Modem:

1. **Connect Coaxial Cable:** Screw one end of the coaxial cable into the cable outlet and the other end into the "Cable In" port on the back of your DM1000 modem. Ensure connections are finger-tight.
2. **Connect Ethernet Cable:** Connect one end of the Ethernet cable to the 2.5Gbps Ethernet port on the back of the DM1000 modem and the other end to the WAN (Internet) port on your router, or directly to your computer's Ethernet port.
3. **Connect Power Adapter:** Plug the power adapter into the "Power" port on the modem and then into an electrical outlet.

3. Power On and Activation:

1. Once powered on, the modem will begin its startup sequence. This may take several minutes.
2. Observe the LED indicators on the front panel. Refer to the "Operating" section for LED status meanings. The "Online" LED should eventually turn solid green, indicating a successful connection to your ISP's network.
3. **Contact Your ISP:** If the "Online" LED does not turn solid green after several minutes, or if you cannot access the internet, you may need to contact your Internet Service Provider (ISP) to activate the modem. Provide them with the modem's MAC address, usually found on a sticker on the bottom or back of the device.

Operating

LED Indicators:

The front panel of the DM1000 modem features several LED indicators that provide information about its operational status:

- **Power (Green):**
  - *Solid:* Modem is powered on.
  - *Off:* Modem is off or not receiving power.
- **DS (Downstream) (Green/Blue):**
  - *Solid Green:* Downstream channel is locked (DOCSIS 3.0).
  - *Solid Blue:* Downstream channel is locked (DOCSIS 3.1).
  - *Flashing:* Scanning for downstream channel.
- **US (Upstream) (Green/Blue):**
  - *Solid Green:* Upstream channel is locked (DOCSIS 3.0).
  - *Solid Blue:* Upstream channel is locked (DOCSIS 3.1).
  - *Flashing:* Scanning for upstream channel.

- **Online (Green):**
  - *Solid:* Modem is successfully connected to the internet.
  - *Flashing:* Modem is registering with the ISP network.
  - *Off:* Modem is not connected to the internet.
- **LAN (Green/Orange):**
  - *Solid Green:* Ethernet link is established at 1Gbps.
  - *Solid Orange:* Ethernet link is established at 2.5Gbps.
  - *Flashing:* Data activity on the Ethernet port.
  - *Off:* No Ethernet link detected.

Maintenance

To ensure optimal performance and longevity of your Sercomm DM1000 modem, follow these maintenance guidelines:

- **Placement:** Place the modem in a well-ventilated area, away from direct sunlight, heat sources, and moisture. Ensure adequate airflow around the device.
- **Cleaning:** Gently wipe the exterior of the modem with a soft, dry cloth. Do not use liquid cleaners or aerosols.
- **Cable Connections:** Periodically check all cable connections (coaxial, Ethernet, power) to ensure they are secure and not damaged.
- **Firmware Updates:** Firmware updates for the modem are typically managed and pushed by your Internet Service Provider (ISP). Do not attempt to manually update the firmware unless instructed by your ISP.
- **Restarting:** If you experience connectivity issues, a simple restart of the modem (unplugging the power for 30 seconds and plugging it back in) can often resolve minor problems.

Troubleshooting

If you encounter issues with your Sercomm DM1000 modem, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
No Power (Power LED Off)	Power adapter not connected or faulty outlet.	Ensure power adapter is securely connected to the modem and a working electrical outlet. Try a different outlet.
Online LED Flashing or Off	Modem not registered with ISP, coaxial cable issue, or ISP outage.	Check coaxial cable connection. Restart the modem. Contact your ISP to verify service status and modem activation.
Slow Internet Speed	Network congestion, old router, or ISP issue.	Restart modem and router. Ensure your router supports the speeds provided by the modem. Test speed directly connected to the modem (bypassing router). Contact your ISP if issues persist.

Problem	Possible Cause	Solution
LAN LED Off	Ethernet cable disconnected or faulty, or device connected to modem is off.	Ensure Ethernet cable is securely connected to both modem and connected device (router/PC). Try a different Ethernet cable. Verify the connected device is powered on.

For persistent issues not resolved by these steps, please contact your Internet Service Provider for further assistance. They can perform remote diagnostics and provide specific support for your service.

Specifications

Feature	Detail
Brand	Sercomm
Model	DM1000
Modem Type	Cable Modem
DOCSIS Compliance	DOCSIS 3.1, DOCSIS 3.0
Ethernet Port	1 x 2.5Gbps NBASE-T
Data Transfer Rate	Up to 1 Gigabits Per Second (theoretical, depends on ISP plan)
Compatible Devices	Router
Dimensions (Approx.)	21.7 x 18.9 x 7.7 cm
Weight (Approx.)	680 g
Power Source	AC Adapter (included)
Connectivity Technology	Wi-Fi (via connected router), Ethernet
UPC	765756029896

Warranty and Support

For information regarding the warranty of your Sercomm DM1000 cable modem, please refer to the documentation provided at the time of purchase or contact your retailer. Warranty terms and conditions may vary depending on the region and point of sale.
For technical support, troubleshooting, or service-related inquiries, it is recommended to contact your Internet Service Provider (ISP). As the DM1000 is designed for Third Party ISPs, your ISP is the primary point of contact for network connectivity and modem performance issues.

© 2024 Sercomm. All rights reserved.
This manual is for informational purposes only. Specifications are subject to change without notice.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question