Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

Spider Farmer G8600

Spider Farmer G8600 LED Grow Light User Manual

Model: G8600

1. Introduction

Thank you for choosing the Spider Farmer G8600 LED Grow Light. This manual provides essential information for the safe and efficient operation of your new grow light. The G8600 is an 800W full-spectrum LED fixture designed for optimal plant growth in indoor environments, offering high efficiency, dimmable control, and smart app integration.



The Spider Farmer G8600 LED Grow Light, a bar-style fixture designed for indoor plant cultivation.

2. Safety Information

- Always disconnect power before installation, cleaning, or maintenance.
- Do not operate the light in wet or damp conditions. Ensure the environment is dry.

- Avoid direct eye exposure to the light when it is operating.
- Ensure proper ventilation around the fixture to prevent overheating.
- Keep out of reach of children and pets.
- Use only the provided power cord and accessories.

3. Package Contents


Verify that all components are present in your package:

- Spider Farmer G8600 LED Grow Light Fixture
- Power Cord
- Hanging Kit (Rope hangers, carabiners)
- User Manual

4. Setup and Installation

4.1 Unfolding the Fixture

The G8600 features a foldable design for easy setup. Simply unfold the light bars until they are fully extended and locked into position. No complex assembly is required.



The G8600 LED grow light in its unfolded state, ready for immediate use.

4.2 Mounting

Use the provided hanging kit to suspend the grow light from a sturdy ceiling or grow tent frame. Ensure the light is securely fastened and level. The recommended coverage area for the G8600 is 4x4ft for commercial racks or 5x5ft for grow tents.



The G8600 LED grow light installed within a 5x5ft grow tent, showing its coverage over multiple plants and ETL certification.

4.3 Daisy-Chain Connection

For larger setups, multiple G8600 units can be daisy-chained together. Connect the output port of one light's controller to the input port of the next. Up to 50 units can be controlled from a single master light, allowing for synchronized dimming.



Multiple G8600 LED grow lights connected in a daisy-chain configuration, demonstrating the ability to control up to 50 units from a single master controller.

5. Operating Instructions

5.1 Power On/Off and Dimming

Connect the power cord to the fixture and a suitable power outlet. The integrated controller features a digital display and a rotary knob for brightness adjustment. Turn the knob to set the desired light intensity from 0% to 100%.




A close-up of the G8600's integrated controller, featuring a digital display showing brightness percentage and a rotary knob for precise dimming adjustments.

5.2 Light Spectrum

The G8600 provides a full spectrum of light, balanced with pure (4800-5000K) and warm (2800-3000K) white light, suitable for all stages of plant growth from seed to harvest. Specific wavelengths contribute to different aspects of plant development:


- **Blue (400-500nm):** Promotes leaf growth, inhibits excessive stretching, keeps plants compact.
- **Green (500-600nm):** Penetrates canopy, enhances overall photosynthesis efficiency.
- **Red (600-700nm):** Increases yield, promotes more flowers and larger fruits.
- **Far-Red (700-750nm):** Contributes to taller, stronger plants.



A graph illustrating the full light spectrum provided by the G8600, including blue, green, red, and far-red wavelengths, and their effects on plant growth.

5.3 Recommended Growing Tips


The following table provides general guidelines for light duration, distance from canopy, and dimming levels for different plant growth stages. Adjustments may be necessary based on specific plant needs and environmental conditions.



A table outlining recommended light settings (time, distance, dimming) for seedling, vegetative, and flowering stages, with and without CO2 supplementation.

5.4 PPFD Map

The G8600 delivers even light distribution and deep canopy penetration. Refer to the PPFD map for detailed light intensity measurements at various points within a 4x4ft grow tent at different hanging heights.



A PPFD (Photosynthetic Photon Flux Density) map illustrating the light distribution and intensity of the G8600 in a 4x4ft grow tent at 8-inch and 12-inch heights.

6. Smart App Control

Enhance your control over the G8600 with the Spider Farmer App. Download the app from the Apple App Store or Google Play Store to access advanced features:

- Custom light schedules
- Sunrise and sunset simulation
- Remote brightness adjustments
- Manage your grow light from anywhere, even when away.



A smartphone displaying the Spider Farmer application interface, demonstrating remote brightness adjustment for the grow light.

7. Maintenance

Regular maintenance ensures optimal performance and longevity of your G8600 LED Grow Light:

- **Cleaning:** Periodically wipe the light bars and housing with a soft, dry cloth to remove dust and debris. Do not use abrasive cleaners or solvents.
- **Inspection:** Regularly check the power cord and hanging components for any signs of wear or damage. Replace any damaged parts immediately.
- **Ventilation:** Ensure that the grow area has adequate airflow to prevent heat buildup around the fixture.

8. Troubleshooting

If you encounter issues with your G8600, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on	No power, loose connection, faulty power cord	Check power outlet, ensure all connections are secure, try a different power cord if available.
Light flickers or dims unexpectedly	Unstable power supply, controller issue, loose wiring	Verify stable power, check controller connections, contact support if issue persists.
App control not working	Bluetooth/Wi-Fi issue, app not updated, light not paired	Ensure Bluetooth/Wi-Fi is enabled on your device, update the app, re-pair the light with the app.
Overheating	Poor ventilation, dust accumulation	Improve airflow in the grow area, clean the fixture regularly.

9. Specifications

Feature	Detail
Model Number	G8600
Brand	Spider Farmer
Power Draw	800W (Light Source Wattage: 860 Watts)
PPE	2.85 µmol/J
PPF	2283 µmol/s
Coverage Area	4x4ft (commercial) / 5x5ft (grow tent)
Light Source Type	LED (Bridgelux Diodes)
Number of Light Sources	8 bars
Spectrum	Full Spectrum (4800-5000K pure white, 2800-3000K warm white)
Brightness	151368 lumen
Voltage	120 Volts
Bulb Features	Dimmable (0-100%)
Mounting Type	Ceiling Mount
Material	Aluminum
Color	Silver
Product Dimensions	44.17"L x 45.38"W x 3.28"H
Item Weight	27.6 pounds
Certification	CE, ETL



A close-up view highlighting the Bridgelux diodes used in the G8600, known for their reliability and efficiency.

10. Warranty and Support

The Spider Farmer G8600 LED Grow Light comes with a 5-year coverage, ensuring long-lasting performance and reliability. For any questions, technical assistance, or warranty claims, please contact our U.S.-based service center. You can find more information and contact details on the official Spider Farmer website or through their Amazon store:

Visit the Spider Farmer Store on Amazon

© 2025 Spider Farmer. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B09TKS5V87

More documents and user manuals: **https://manuals.plus/**