MSI PRO X670-P WIFI

MSI PRO X670-P WiFi ProSeries Motherboard User Manual

Model: PRO X670-P WIFI

1. Introduction

This manual provides detailed instructions for the installation, operation, and maintenance of your MSI PRO X670-P WiFi ProSeries Motherboard. Please read this manual thoroughly before proceeding with installation to ensure correct setup and optimal performance. The MSI PRO X670-P WiFi motherboard is designed to support AMD Ryzen 7000 Series Desktop Processors, offering stable functionality and high-quality assembly for efficient and productive computing experiences.



Image 1.1: MSI PRO X670-P WiFi Motherboard and its retail packaging.

2. Safety Information

Always observe the following safety precautions during installation and operation:

- Disconnect the power cord from the electrical outlet before touching any component.
- Wear an anti-static wrist strap to prevent electrostatic discharge (ESD) damage to components.
- Handle components by their edges to avoid touching sensitive parts.
- Ensure proper ventilation within your computer case to prevent overheating.
- Keep the motherboard away from moisture and extreme temperatures.

3. Package Contents

Verify that all items listed below are present in your motherboard package. If any item is missing or damaged, contact your retailer.

- MSI PRO X670-P WiFi Motherboard
- I/O Shield
- 2 x SATA Cables
- M.2 Plate Screw
- Wi-Fi Antenna
- M.2 Clips

- User Manual (this document)



Image 3.1: Motherboard and included accessories.

4. Motherboard Layout

Familiarize yourself with the various components and connectors on the motherboard before installation.




Image 4.1: Overview of the MSI PRO X670-P WiFi Motherboard.

4.1. CPU Socket (AMD AM5)

The motherboard features an AMD AM5 socket, compatible with AMD Ryzen 7000 Series processors. Ensure the CPU is correctly oriented before installation.




Image 4.2: AMD AM5 CPU Socket.

4.2. DDR5 DIMM Slots

Four DDR5 DIMM slots support dual-channel memory configurations. Refer to the motherboard's QVL (Qualified Vendor List) for compatible memory modules and optimal performance.

4.3. PCIe Slots

The motherboard includes multiple PCIe slots, supporting PCIe 4.0 and Lightning Gen 5 for high-speed expansion cards such as graphics cards and NVMe SSDs.




Image 4.3: PCIe and M.2 Slots.

4.4. M.2 Slots

Multiple M.2 slots are available for high-speed NVMe storage devices, supporting PCIe 4.0 and Gen 5 standards for maximum transfer speeds.

4.5. SATA Ports

The motherboard provides SATA 6Gb/s ports for connecting traditional hard drives and SSDs.

4.6. Rear I/O Panel

The rear I/O panel offers various connectivity options, including USB 3.2 Gen 2, Wi-Fi 6E, HDMI, DisplayPort, and audio jacks.






Image 4.4: Rear I/O Panel Connectors.

5. Setup

Follow these steps for proper installation of your motherboard and components.

5.1. Installing the CPU

1. Open the CPU socket lever.
2. Align the CPU with the socket, ensuring the golden triangle on the CPU matches the triangle on the socket.
3. Gently place the CPU into the socket. Do not force it.
4. Close the socket lever to secure the CPU.

5.2. Installing the CPU Cooler

Install your chosen CPU cooler according to its manufacturer's instructions. Ensure proper thermal paste application for effective heat dissipation.

5.3. Installing Memory (RAM)

1. Open the clips on both ends of the DIMM slots.
2. Align the memory module with the slot, matching the notch on the module with the key in the slot.
3. Press down firmly on both ends of the memory module until the clips snap into place.
4. For dual-channel operation, install memory modules into the recommended slots (e.g., A2 and B2).

5.4. Installing M.2 SSDs

1. Locate an available M.2 slot and remove the M.2 Shield Frozr heatsink if present.
2. Insert the M.2 SSD into the slot at a 30-degree angle.
3. Gently push down the SSD and secure it with the provided M.2 screw or clip.
4. Reinstall the M.2 Shield Frozr heatsink for optimal cooling.

5.5. Installing the Graphics Card

1. Open the latch on the primary PCIe x16 slot.
2. Align the graphics card with the slot and press down firmly until it clicks into place.
3. Secure the card to the case with screws.
4. Connect PCIe power cables from the power supply to the graphics card if required.

5.6. Connecting Power Supply

Connect the 24-pin ATX power connector and the 8-pin (and additional 8-pin if applicable) CPU power connectors from

your power supply to the motherboard.

5.7. Connecting Front Panel Headers

Connect the power button, reset button, HDD LED, and USB/audio headers from your computer case to the corresponding pins on the motherboard. Refer to the motherboard manual for exact pin layouts.

6. Operating

After hardware installation, proceed with initial boot and software setup.

6.1. Initial Boot and BIOS Setup

1. Connect a monitor, keyboard, and mouse.
2. Power on your system.
3. Press the **DEL** key during startup to enter the BIOS/UEFI setup utility.
4. Configure boot order, enable XMP/EXPO for memory, and set other desired system parameters.
5. Save changes and exit the BIOS.

6.2. Driver Installation

After installing your operating system, install the necessary drivers for the motherboard components (chipset, LAN, Wi-Fi, audio, etc.). These can be found on the MSI support website for your specific motherboard model.

6.3. MSI Center Software

MSI Center is a utility that allows you to monitor system status, optimize performance, and customize various settings for your MSI motherboard. Download and install it from the MSI website for additional control over your system.

7. Maintenance

Regular maintenance helps ensure the longevity and stable operation of your motherboard.

7.1. Cleaning

Periodically clean dust from inside your computer case and off motherboard components using compressed air. Ensure the system is powered off and unplugged before cleaning.

7.2. BIOS Updates

BIOS updates can provide improved compatibility, stability, and new features. Visit the MSI support website for the latest BIOS versions and instructions on how to update using the M-Flash utility.

8. Troubleshooting

This section addresses common issues you might encounter.

8.1. No Power / No POST

- Check all power connections (24-pin ATX, 8-pin CPU).
- Ensure the power supply is switched on.

- Verify that the CPU and RAM are correctly seated.
- Remove all non-essential components (e.g., extra drives, expansion cards) and attempt to boot with only the CPU, one RAM stick, and the graphics card (if no integrated graphics).

8.2. No Display Output

- Ensure the monitor is connected to the graphics card (or motherboard if using integrated graphics) and powered on.
- Try a different display cable or monitor.
- Reseat the graphics card.

8.3. Memory Issues (e.g., system not booting, incorrect capacity detected)

- Ensure RAM modules are installed in the correct slots for dual-channel operation.
- Try booting with only one RAM stick.
- Check the motherboard's QVL for memory compatibility.
- Update the BIOS to the latest version.

8.4. Debug LEDs

The motherboard features debug LEDs (CPU, DRAM, VGA, BOOT) that illuminate to indicate the component causing a boot failure. Consult the motherboard manual for specific LED indications.

9. Specifications

Key technical specifications for the MSI PRO X670-P WiFi Motherboard.

Feature	Specification
Brand	MSI
Series	PRO X670-P WIFI
Item Model Number	7D67-008R
CPU Socket	Socket AM5
Compatible Processors	AMD Ryzen 7000 Series
Chipset Type	AMD X670
RAM Memory Technology	DDR5
Memory Speed	DDR5-5600+ (OC)
PCIe Solution	Lightning Gen 4 / Gen 5
M.2 Solution	Lightning Gen 4 / Gen 5
SATA Ports	SATA 6Gb/s
USB Connectivity	USB 3.2 Gen 2, USB 3.2 Gen 1, USB 2.0

Feature	Specification
Wireless Type	Wi-Fi 6E, Bluetooth
Video Output	HDMI, DisplayPort
Form Factor	ATX
Dimensions (LxWxH)	12 x 9.6 x 2.5 inches
Item Weight	3.41 pounds

10. Warranty and Support

For warranty information, technical support, and driver downloads, please visit the official MSI website. You can find detailed support resources by navigating to the support section and searching for your specific motherboard model (PRO X670-P WIFI).
Official MSI Support Website: https://www.msi.com/support

© 2024 MSI. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question