

[Manuals.plus](#) /

› [PowerSmart](#) /

› PowerSmart PS5150 Portable Power Station User Manual

PowerSmart PS5150

PowerSmart PS5150 Portable Power Station User Manual

Model: PS5150

1. INTRODUCTION

Thank you for choosing the PowerSmart PS5150 Portable Power Station. This device is designed to provide reliable power for various applications, including outdoor activities, home backup, and emergency situations. With a 288Wh capacity and 500W output (1000W surge), it can power a wide range of electronic devices and small appliances. Please read this manual thoroughly before using the product to ensure safe and optimal operation.



Image 1.1: The PowerSmart PS5150 Portable Power Station, showcasing its compact design and integrated handle.

2. IMPORTANT SAFETY INSTRUCTIONS

Always follow basic safety precautions when using this product to reduce the risk of injury, electric shock, or fire. Keep this manual for future reference.

- Do not disassemble, repair, or modify the unit. Incorrect reassembly may cause fire or electric shock.
- Do not expose the unit to fire or extreme temperatures (above 60°C/140°F).
- Do not use or store the unit in a bathroom or in areas exposed to rain or moisture.
- Do not use the unit if it is damaged or has been modified.
- Keep the unit away from children and pets.
- Ensure proper ventilation during use and charging. Do not block ventilation openings.

- Use only recommended accessories and charging cables.
- In case of fire, use a dry powder fire extinguisher.



7 safety protections



Image 2.1: Overview of the seven safety protections integrated into the PowerSmart PS5150, including overcharging, voltage control, overcurrent, temperature control, low battery alarm, short circuit, and overload protection.

3. PRODUCT OVERVIEW AND COMPONENTS

The PowerSmart PS5150 features multiple output ports and a clear display for easy monitoring.

3.1. Output Ports

- 1 x AC Port (120V, 500W continuous, 1000W surge)
- 1 x 60W USB-C PD Port
- 3 x 54W USB-A Ports (Quick Charge 3.0 compatible)
- 1 x 12V DC Port
- 1 x 10W Wireless Charger



Image 3.1: Diagram illustrating the various output ports available on the PowerSmart PS5150, including AC, DC, USB-A, USB-C, and wireless charging pad.

3.2. LCD Display

The integrated LCD display shows real-time information such as input wattage, output wattage, and remaining battery percentage.

4. CHARGING THE POWER STATION

The PowerSmart PS5150 can be recharged using three methods:

- **AC Wall Outlet:** Connect the included 110V AC wall plug power adapter to the input port. Full charge takes approximately 4.8-5 hours.
- **Solar Panel (not included):** Connect a compatible 100W solar panel (via MC4 connector cable, included) to the DC input port. A full charge can be achieved in approximately 3 hours under optimal sunlight conditions.
- **Car Outlet:** Use the included car charger cable to charge the unit from your vehicle's 12V outlet. Full charge takes approximately 4.8-5 hours.

3 WAYS FOR CHARGING



3 hours
100W solar charger (Not Included)



4.8-5 hours
Wall Outlet



4.8-5 hours
Car outlet

Image 4.1: Visual representation of the three charging methods: solar panel, AC wall outlet, and car outlet, along with their approximate charging times.

FAST SOLAR RECHARGING

3 Hours
PowerSmart Portable Power

8 Hours
Data based on internal test
With original solar panels(100w) in full sun.



Image 4.2: Comparison of solar charging speed, showing the PowerSmart unit charging in 3 hours with a 100W solar panel.

5. OPERATING INSTRUCTIONS

5.1. Powering On/Off

Press and hold the main power button for a few seconds to turn the unit on or off. The LCD display will illuminate.

5.2. Using Output Ports

To use a specific output type (AC, DC, USB), press the corresponding button next to the port section. The indicator light for that section will turn on, signifying it is active. Connect your device to the appropriate port.

5.3. Wireless Charging

Place your Qi-compatible device on the wireless charging pad located on top of the power station. Ensure the device is

centered for optimal charging.

5.4. LED Light Function

The power station includes an integrated LED light. Press the light button to cycle through different brightness levels or activate the SOS flashing mode for emergencies.



Image 5.1: The PowerSmart PS5150 demonstrating its high-brightness LED light, suitable for various lighting needs.

5.5. Usage Examples

The 288Wh capacity and 500W output can support devices such as laptops, tablets, cell phones, lamps, fans, CPAP medical devices, projectors, TVs, and mini-fridges.

- **Outdoor & Camping:** Power mini-fridges (7 hours), fans (9 hours), drones (12 hours), LED lights (9 hours).
- **Home Backup:** Power phones (39 hours), laptops (3 hours), WiFi routers (23 hours), CPAP machines (12 hours).



Image 5.2: The PowerSmart PS5150 providing power for outdoor and camping scenarios, such as charging a laptop on a wooden deck.



Image 5.3: The PowerSmart PS5150 serving as a home backup power source, illuminating a living room and charging devices during an outage.

6. MAINTENANCE AND STORAGE

- **Cleaning:** Use a dry, soft cloth to clean the exterior of the unit. Do not use abrasive cleaners or solvents.
- **Storage:** Store the power station in a cool, dry place, away from direct sunlight and extreme temperatures.
- **Long-Term Storage:** For optimal battery life, fully charge the unit every 3-6 months if not in regular use.
- **Battery Care:** The unit contains a Lithium-Ion battery. Do not expose it to water or puncture it.

7. TROUBLESHOOTING

Problem	Possible Cause	Solution
Unit does not turn on	Battery is depleted; Power button not pressed correctly.	Charge the unit; Press and hold the power button for a few seconds.
No output from ports	Output port not activated; Device draws too much power (overload); Battery is low.	Activate the specific output port; Check device wattage; Recharge the power station.
Slow charging	Using a low-power charger; Solar panel not in direct sunlight.	Use the original AC adapter or a 100W solar panel; Ensure solar panel is in full sun.
Unit overheats	Poor ventilation; Excessive load.	Ensure ventilation openings are clear; Reduce the number of connected devices.

8. SPECIFICATIONS

Feature	Detail
Brand	PowerSmart
Model Name	Power Station (PS5150)
Capacity	288Wh

Feature	Detail
AC Output	500W (Continuous), 1000W (Peak)
USB-C PD Output	1 x 60W
USB-A Output	3 x 54W (QC3.0)
DC Output	1 x 12V Port
Wireless Charging	1 x 10W
Charging Methods	AC Wall Outlet, Solar Panel, Car Outlet
Dimensions (L x W x H)	10" x 10.3" x 14.6"
Item Weight	11.4 lbs (Product), 13.4 lbs (Shipping)
Battery Type	Lithium Ion
Included Components	Portable Power Station, MC4 Connector Cable, 110V AC Wall Plug Power Adapter, Car Charger Cable, User Manual



Image 8.1: Diagram showing the physical dimensions of the PowerSmart PS5150 Portable Power Station.

9. WARRANTY AND SUPPORT

The PowerSmart PS5150 Portable Power Station comes with a **2-YEAR WORRY-FREE WARRANTY**. For any questions, technical support, or warranty claims, please contact PowerSmart customer service. Refer to the contact information provided in the packaging or on the official PowerSmart website.

10. PRODUCT VIDEOS

No specific video URLs with creator type 'Seller' were provided in the product data for embedding. Please refer to the official PowerSmart website or product page for any available instructional videos.

© 2023 PowerSmart. All rights reserved.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B0BGLVL92V>

More documents and user manuals: <https://manuals.plus/>