

[Manuals.plus](#) /

> [Superer](#) /

> Superer 26V/24V AC Charger Instruction Manual

## Superer RSF-DY115B-2601000US

# Superer 26V/24V AC Charger Instruction Manual

Model: RSF-DY115B-2601000US

## PRODUCT OVERVIEW

---

This manual provides essential information for the safe and effective use of your Superer 26V/24V AC Charger. This power adapter is designed to provide a consistent and stable power supply for compatible devices.



Image: The Superer 26V/24V AC Charger, featuring the power brick, cable, and round tip connector.

## Package Contents

- 1 x Superer 26V/24V AC Power Adapter

## COMPATIBILITY AND SETUP

---

Before connecting the charger, ensure your device is compatible with the specifications of this power adapter. This charger is specifically designed for devices requiring 26V or 24V and a maximum of 1A. It is compatible with models such as TaoTronics TT-PCA003SPF, Renpho RF-GM168, RENPHO C3 JYH37-2400650-CA, and Chirogun Massage Guns.

**Important:** Do not use this charger if your device requires more than 1A or a different voltage (e.g., 9V or 12V models).

# Charging Port

Check the shape of your charging port before purchase



Round Tip



USB-C

Image: A visual comparison showing the compatible round tip charging port and an incompatible USB-C port. This charger uses a round tip connector.

# Compatibility

VOLTS	AMPS	WATTS	COMPATIBILITY
26V	1A	26W	✓
26V	0.5A	13W	✓
25.2V	1A	25.2W	✓
25V	1A	25W	✓
24V	1A	24W	✓
16.8V	1A	16.8W	✗



Image: A table illustrating various voltage, amperage, and wattage combinations and their compatibility with the charger, emphasizing the 26V 1A and 24V 1A compatibility.

## Connection Steps:

1. Verify that your device's power input specifications match the charger's output (26V/24V, max 1A).
2. Ensure the charging port on your device is a round tip connector, compatible with the charger's plug.
3. Plug the round tip connector of the charger into your device's charging port.
4. Insert the charger's wall plug into a standard 100-240V AC electrical outlet.

## OPERATING INSTRUCTIONS

Once properly connected, the charger will begin supplying power to your device. The charger is designed

to provide a consistent and stable power flow for efficient charging or operation.

# Consistent Power Supply

Provide consistent & stable power for your device.



Image: The Superer charger plugged into a wall outlet, connected to a massage gun, demonstrating typical usage.

## Key Features:

- **Robust Casing:** Designed for durability and protection.
- **Fastener Tape:** Included for convenient cable management.
- **Standard Connector:** Features a reliable round tip connector for compatible devices.

# Adapter Details



01

Robust Casing

02

Fastener Tape



03

Connector



Image: A detailed view highlighting the robust casing of the adapter, the included fastener tape for cable organization, and the specific round tip connector.

## MAINTENANCE

To ensure the longevity and optimal performance of your Superer AC Charger, follow these maintenance guidelines:

- Keep the charger in a dry environment and avoid exposure to moisture or extreme temperatures.
- Do not bend or crimp the cable excessively, especially near the connectors, to prevent internal wire damage.
- Clean the charger and cable periodically with a soft, dry cloth. Do not use liquid cleaners.
- Always unplug the charger from the wall outlet when not in use for extended periods.

- Store the cable neatly using the provided fastener tape to prevent tangles and damage.

## SAFETY AND TROUBLESHOOTING

The Superer AC Charger is built with multiple safety protections to ensure reliable operation and protect your devices.



Image: An illustration detailing the various safety features integrated into the charger, including Overheating Protection, Overvoltage Protection, Electrostatic Protection, Short Circuit Protection, Overcurrent Protection, and Overcharge Protection.

### Common Issues and Solutions:

Issue	Possible Cause	Solution
-------	----------------	----------

Issue	Possible Cause	Solution
Device not charging/powering on.	Incompatible voltage/amperage, loose connection, faulty outlet, damaged charger.	Ensure device requirements match charger output (26V/24V, max 1A). Check all connections are secure. Try a different electrical outlet. Inspect charger for visible damage. If damaged, discontinue use.
Charger feels warm during use.	Normal operation, excessive load, poor ventilation.	Slight warmth is normal. Ensure charger is not covered or in an enclosed space. If excessively hot, unplug immediately and contact support.

If issues persist after following these steps, please contact Superer customer support.

## SPECIFICATIONS

Feature	Detail
Model Number	RSF-DY115B-2601000US
Input Voltage	100-240V AC
Output	26V 1A 26W
Amperage	1 Amps
Connector Type	Round Connector
Compatible Devices	Massage Gun Charger (TaoTronics TT-PCA003SPF, Renpho RF-GM168, RENPHO C3 JYH37-2400650-CA, Chirogun Massage Gun)
Included Components	Power Adapter
Special Feature	Overcharge Protection
Color	Black
Item Weight	4.2 ounces
Package Dimensions	4.49 x 2.68 x 1.85 inches
Manufacturer	Superer

## WARRANTY AND SUPPORT

Superer stands behind the quality of its products. Your Superer AC Charger comes with comprehensive after-sales support.

# Positive Customer Support

Refund Within 30 Days of Purchase  
and Replace Service Within 12 Months



# 12

Replace Service Within 12 Months

Worry-free after sales



Replace Service  
Within 12 Months



Refund Within  
30 Days of Purchase



Quick feedback  
to any problems

Image: An infographic highlighting the customer support policies, including 30-day refund eligibility and a 12-month replacement guarantee.

- **30-Day Return Policy:** This product is eligible for replacement or returns within 30 days of purchase.
- **12-Month Guarantee:** The manufacturer provides an additional 12-month guarantee for replacement services.
- For any inquiries, technical assistance, or warranty claims, please contact Superer customer support through your purchase platform or the official Superer website.

