

Manuals.plus /

› LEKATO /

› LEKATO Portable Guitar Amplifier JA-05G User Manual

LEKATO JA-05G

LEKATO Portable Guitar Amplifier JA-05G User Manual

1. INTRODUCTION

Thank you for choosing the LEKATO Portable Guitar Amplifier JA-05G. This compact and versatile amplifier is designed for guitarists seeking a convenient solution for practice and performance. It features built-in effects, Bluetooth connectivity, and a rechargeable battery, making it ideal for use anywhere. Please read this manual thoroughly to understand its functions and ensure optimal performance.

What's in the Box:

- LEKATO Mini Electric Guitar Amplifier (JA-05G) x 1
- USB Charging Cable (Type-C) x 1
- User Manual x 1

- Mini Electric Guitar Amp ×1
- USB charging cable ×1
- User Manual ×1

LEKATO



IN THE BOX

Image: The LEKATO JA-05G amplifier, a USB-C charging cable, and the user manual, laid out to show the package contents.

2. PRODUCT OVERVIEW

The LEKATO JA-05G is a mini portable guitar amplifier equipped with essential features for guitar practice and casual playing.

Key Features:

- **4 Classic Built-in Effects:** Clean, Overdrive, Distortion, and Reverb.
- **Wireless Bluetooth Connectivity:** Connect your device to play backing tracks or use as a portable Bluetooth speaker.
- **Long Battery Life:** Integrated 1500mAh rechargeable battery offering up to 6 hours of working time.
- **Adjustable 230° Plug:** Accommodates various guitar jack positions.
- **Compact and Portable Design:** Lightweight at 141g, easily fits into a bag.

Controls and Indicators:

- **TONE Knob:** Adjusts the tonal characteristics of your guitar sound.

- **EFFECT Button:** Cycles through the four built-in effects.
- **VOL Knob:** Controls the overall output volume.
- **Power Button:** Turns the amplifier on or off.
- **Power Indicator (Blue LED):** Indicates power status and charging.
- **Effect Indicator (Green/Yellow/Red LED):** Shows the currently selected effect.



Image: The LEKATO JA-05G amplifier connected to an electric guitar, highlighting its compact design and control knobs.

3. SETUP

Follow these steps to set up your LEKATO JA-05G amplifier:

1. **Charge the Amplifier:** Before first use, fully charge the amplifier using the provided USB Type-C cable. Connect the cable to the Type-C port on the amplifier and a standard USB power adapter (not included). The blue LED will indicate charging status.
2. **Connect to Guitar:** Insert the 6.35mm jack of the amplifier directly into your guitar's output jack. The plug is adjustable up to 230 degrees to fit various guitar body shapes and jack orientations.
3. **Power On:** Press and hold the Power button until the blue LED illuminates.



PLUG AND PLAY

Easy to use, start your show
anytime, anywhere

LEKATO

Image: A user connecting the LEKATO JA-05G amplifier to an electric guitar, demonstrating its ease of use.



Image: A visual representation of the amplifier's 230-degree adjustable plug, allowing for flexible connection to various guitar types.

4. OPERATING INSTRUCTIONS

4.1 Power On/Off

- **To Power On:** Press and hold the Power button for approximately 2 seconds until the blue LED lights up.
- **To Power Off:** Press and hold the Power button for approximately 2 seconds until the blue LED turns off.

4.2 Using Built-in Effects

The amplifier includes four classic effects: Clean, Overdrive, Distortion, and Reverb. Press the **EFFECT** button to cycle through them.

- **Clean:** Provides a clear, unaltered guitar tone. (Effect LED: Green)
- **Overdrive:** Adds a warm, slightly distorted tone. (Effect LED: Yellow)
- **Distortion:** Produces a heavier, more aggressive distorted sound. (Effect LED: Red)
- **Reverb:** Adds spatial depth and echo to the sound. (Effect LED: Flashing)



Image: An illustration detailing the four distinct sound effects (Clean, Overdrive, Distortion, Reverb) that can be selected on the amplifier.

4.3 Adjusting Tone and Volume

- **TONE Knob:** Rotate the TONE knob to adjust the brightness or warmth of your guitar sound.
- **VOL Knob:** Rotate the VOL knob to increase or decrease the overall output volume of the amplifier.

4.4 Bluetooth Connectivity

The amplifier can connect wirelessly to your smartphone or other Bluetooth-enabled devices to play backing tracks or function as a portable Bluetooth speaker.

1. **Enable Bluetooth:** Ensure the amplifier is powered on. The blue LED will flash, indicating it's in pairing mode.
2. **Pair Device:** On your device, search for Bluetooth devices and select "LEKATO JA-05G" to pair.
3. **Connection Confirmation:** Once successfully paired, the blue LED on the amplifier will stop flashing and remain solid.
4. **Play Audio:** You can now play audio from your device through the amplifier.



WITH BT WIRELESS FUNCTION

Use as a mini portable speaker,
playing music with instrumental ensemble.

Image: The LEKATO JA-05G amplifier wirelessly connected to a smartphone via Bluetooth, demonstrating its capability to play music alongside guitar performance.

4.5 Charging the Battery

The amplifier features a built-in 1500mAh rechargeable battery.

- **Charging Port:** Use the Type-C port for charging.
- **Charging Indicator:** The blue LED will indicate the charging status.
- **Battery Life:** Provides up to 6 hours of continuous use, with a standby time of up to 20 hours.



Image: A detailed view of the amplifier's Type-C charging port, illustrating the charging process and highlighting its 1500mAh battery capacity and approximately 6 hours of operational time.

5. MAINTENANCE

- **Cleaning:** Use a soft, dry cloth to clean the amplifier's surface. Avoid using abrasive cleaners or solvents.
- **Storage:** Store the amplifier in a cool, dry place away from direct sunlight and extreme temperatures.
- **Battery Care:** To prolong battery life, avoid fully discharging the battery frequently. Charge it regularly, even if not in use for extended periods.
- **Avoid Moisture:** Do not expose the amplifier to water or excessive humidity.

6. TROUBLESHOOTING

Problem	Possible Cause	Solution
No sound from amplifier	Amplifier not powered on; Volume too low; Guitar not connected properly; Guitar volume off; Battery low.	Ensure amplifier is on; Increase VOL knob; Re-insert guitar jack firmly; Check guitar's volume; Charge the amplifier.
Bluetooth not connecting	Amplifier not in pairing mode; Device Bluetooth off; Amplifier already connected to another device; Out of range.	Ensure blue LED is flashing (pairing mode); Turn on Bluetooth on your device; Disconnect from other devices; Move device closer to amplifier.
Amplifier not charging	Charging cable faulty; Power adapter faulty; Charging port damaged.	Try a different USB Type-C cable; Use a different USB power adapter; Contact customer support if port is damaged.
Unwanted noise/feedback	High gain settings; Proximity to other electronics; Loose guitar connection.	Reduce gain/distortion effect; Move away from interference sources; Ensure guitar jack is secure.

7. SPECIFICATIONS

Feature	Specification
Brand	LEKATO
Model Name	Guitar Amp Portable (JA-05G)
Color	Black
Compatible Devices	Guitar, Bass, Ukulele, Mandolin, Banjo
Material	Plastic and Metal
Output Power	5 Watts
Product Dimensions	4.2D x 6W x 10.5H cm
Speaker Size	6 cm
Power Source	Rechargeable Battery
Battery Type	Lithium-ion (1500mAh)
Number of Output Channels	1

8. WARRANTY AND SUPPORT

- **Manufacturer Warranty:** This product comes with a 1-year manufacturer's warranty. Please retain your proof of purchase for warranty claims.
- **Return Policy:** Standard return policy allows for refund or replacement within 30 days of purchase. Refer to your retailer's specific return policy for details.

- **Customer Support:** For any issues or questions not covered in this manual, please contact LEKATO customer support through their official channels or your point of purchase.