CHUNYE 3010PM

CHUNYE 3010PM DC Power Supply User Manual

Model: 3010PM

1. Product Overview

The CHUNYE 3010PM is a versatile and adjustable DC power supply designed for various applications including laboratories, industrial use, and mobile device repair. It provides stable output voltage and current, along with essential protection features to ensure safe and reliable operation.



Figure 1.1: CHUNYE 3010PM DC Power Supply

This image shows the overall view of the CHUNYE 3010PM DC Power Supply, highlighting its compact design and front panel layout.

Key Features:

- **Output Stability:** Provides stable output voltage and current for consistent performance.
- **Protection Features:** Includes overload protection (OCP), overvoltage protection (OVP), and short circuit protection (SCP) to safeguard the device and connected equipment.
- **Efficiency:** Designed for efficient conversion of electrical energy, reducing waste and operating costs.
- **Power Output:** Delivers adequate power (up to 300W) to meet the demands of various connected devices.
- **Wide Application:** Suitable for use in laboratories, educational institutions, industrial settings, and for electronic repair tasks.

2. Safety Instructions

To ensure safe operation and prevent damage to the device or injury, please read and follow these safety instructions carefully before using the power supply.

- **Power Source:** Connect the power supply only to a grounded AC outlet with the correct voltage (220V). Ensure the power cord is in good condition.
- **Ventilation:** Ensure adequate ventilation around the unit. Do not block ventilation openings on the sides or rear of the device. Maintain at least 10 cm (4 inches) of clear space.
- **Environment:** Operate the device in a dry, indoor environment. Avoid exposure to moisture, rain, excessive humidity, or corrosive gases.
- **Overload:** Do not exceed the rated output voltage (30V) or current (10A) of the power supply. Overloading can cause damage to the unit and connected devices.
- **Maintenance:** Do not attempt to open or repair the unit yourself. There are no user-serviceable parts inside. Refer all servicing to qualified personnel.
- **Handling:** Avoid dropping or subjecting the unit to strong impacts. Handle with care.
- **Emergency:** In case of smoke, unusual odors, or abnormal operation, immediately disconnect the power supply from the AC outlet and cease use.
- **Output Terminals:** Ensure proper polarity when connecting loads to the output terminals. Incorrect connections can damage the power supply or the load.

3. Product Components and Controls

Familiarize yourself with the various parts and controls of your DC power supply to ensure correct and efficient operation.




Figure 3.1: Front Panel Layout with Labeled Components

This image displays the front panel of the CHUNYE 3010PM DC Power Supply, highlighting key components such as the voltage, current, and power displays, regulation knobs, output terminals, and USB ports. Each element is clearly labeled for easy identification.

- **Voltage Display:** Digital readout showing the current output voltage in Volts (V).
- **Current Display:** Digital readout showing the current output current in Amperes (A).
- **Power Display:** Digital readout showing the current output power in Watts (W).
- **Status Indicators:** LEDs indicating various operational states such as Constant Voltage (CV), Constant Current (CC), Over Current Protection (OCP), and Lock status.
- **Voltage Regulation Knob:** Rotary encoder for precise adjustment of the output voltage.
- **Current Adjustment Knob:** Rotary encoder for setting the maximum output current limit.
- **8.4V-30V Limited Transfer Switches:** Buttons or switches to quickly select or limit the output voltage range.
- **Output Switch Button:** Toggles the main power output to the terminals ON or OFF.
- **4 Sets of Storage Channels (M1-M4):** Buttons to save and recall frequently used voltage and current settings.
- **6 Sets of Smart USB Outputs:** Adjustable USB output ports (labeled 1-6) for charging or powering USB devices.
- **Power Switch:** Main ON/OFF switch for the entire unit, typically located on the front or rear panel.
- **Power Supply Positive and Negative Output Ports:**Main binding post terminals for connecting loads (Red for positive, Black for negative).
- **Fixed 5V USB Output:** Dedicated USB output port providing a stable 5V/2A supply.

4. Setup Instructions

Follow these steps to set up your CHUNYE 3010PM DC Power Supply for initial use.

1. **Unpacking:** Carefully remove the power supply from its packaging. Inspect the unit for any visible signs of damage that may have occurred during shipping.
2. **Placement:** Place the unit on a stable, level, and non-conductive surface. Ensure there is adequate ventilation space (at least 10 cm) around all sides of the unit to prevent overheating. Avoid placing it near direct sunlight, heat sources, or areas with high moisture.
3. **Power Connection:** Connect the provided AC power cord to the AC input socket located on the rear panel of the power supply. Then, plug the other end of the power cord into a grounded 220V AC power outlet.
4. **Initial Power On:** Flip the main Power Switch (usually located on the front or rear) to the 'ON' position. The digital displays should illuminate, indicating the unit is receiving power.
5. **Self-Test:** The unit may perform a brief self-test upon startup. Observe the displays for any error messages.

5. Operating Instructions

This section details how to operate your DC power supply for various tasks.

5.1. Adjusting Voltage and Current

1. Ensure the **Output Switch Button** is in the OFF position (output terminals are not active). This prevents accidental power delivery during setup.
2. Rotate the **Voltage Regulation Knob** to set the desired output voltage. Observe the **Voltage Display** to confirm the setting.
3. Rotate the **Current Adjustment Knob** to set the desired current limit. Observe the **Current Display**. This sets the maximum current the power supply will deliver to the load.
4. Once the voltage and current limit settings are configured, connect your load to the main **Power Supply Positive and Negative Output Ports**, ensuring correct polarity.
5. Press the **Output Switch Button** to enable the main output. The output terminals will now supply power according to your set voltage and current limit.
6. To disable output, press the **Output Switch Button** again.

5.2. Using Storage Channels (M1-M4)

The storage channels allow you to save and quickly recall up to four sets of frequently used voltage and current settings.

1. **Saving Settings:** Set the desired voltage and current using the respective knobs. Then, press and hold one of the **M1-M4 buttons** for approximately 3 seconds until a confirmation (e.g., a beep or display flash) indicates the settings are saved to that channel.
2. **Recalling Settings:** Briefly press one of the **M1-M4 buttons**. The saved voltage and current settings for that channel will be loaded onto the display and become the active settings.

5.3. Using USB Outputs

The power supply features multiple USB outputs for convenience.

- **Smart USB Outputs (1-6):** These ports provide adjustable voltage output, which can be controlled by the main voltage settings or specific internal adjustments (refer to advanced features if applicable). Connect your USB-powered device to one of these ports.
- **Fixed 5V USB Output:** This dedicated port provides a stable 5V/2A output. It is suitable for charging standard USB devices like smartphones or tablets.

5.4. Understanding Status Indicators

The front panel includes various indicators to inform you of the power supply's operational status.

- **CV (Constant Voltage):** This indicator illuminates when the power supply is operating in constant voltage mode, meaning it is maintaining the set output voltage.
- **CC (Constant Current):** This indicator illuminates when the power supply is operating in constant current mode, meaning it is maintaining the set current limit due to the load drawing more current than the limit.
- **OCP (Over Current Protection):** This indicator illuminates when an overcurrent condition has occurred, and the output has been limited or shut down to protect the connected load and the power supply.
- **LOCK:** This indicator illuminates when the front panel controls are locked to prevent accidental changes to the settings.

6. Maintenance

Proper maintenance ensures the longevity and reliable operation of your power supply.

- **Cleaning:** Always disconnect the power supply from the AC outlet before cleaning. Use a soft, dry cloth to wipe the exterior surfaces. Do not use abrasive cleaners, solvents, or chemical agents, as these can damage the casing and internal components.
- **Ventilation:** Periodically check that the ventilation openings on the unit are clear of dust and debris. Accumulated dust can hinder cooling and lead to overheating. Use a soft brush or compressed air to gently clear any blockages.
- **Storage:** When the unit is not in use for extended periods, store it in a cool, dry place, away from direct sunlight, extreme temperatures, and high humidity. It is recommended to keep it in its original packaging if available.
- **Inspection:** Periodically inspect the power cord and output cables for any signs of damage, fraying, or exposed wires. Replace damaged cables immediately.

7. Troubleshooting

This section provides solutions to common issues you might encounter. If the problem persists, contact customer support.

Problem	Possible Cause	Solution
No power/Display off	Power cord not connected securely; Main power switch off; AC outlet fault; Internal fuse blown.	Check power cord connection at both ends; Ensure main power switch is ON; Test AC outlet with another device; If fuse is accessible and replaceable, check it (only by qualified personnel).

Problem	Possible Cause	Solution
No output voltage/current	Output switch OFF; Current limit set too low; Overload protection (OCP) active; Short circuit in load.	Press Output Switch Button to ON; Increase current limit using the knob; Check load for short circuit or excessive current draw; Disconnect load and re-enable output.
Voltage/Current unstable or fluctuating	Poor connection to load; Faulty load; Loose output terminals; Internal fault.	Check all connections and ensure they are tight; Test with a different, known-good load; If problem persists, contact support.
Unit gets excessively hot	Insufficient ventilation; Prolonged operation at high load; Blocked cooling fan.	Ensure ventilation openings are clear and unit has ample space; Reduce load or operating time if possible; Check if cooling fan is operating (if applicable).
Controls are unresponsive (LOCK indicator on)	Front panel controls are locked.	Refer to the specific instructions for your model on how to unlock the controls (often by pressing and holding the LOCK button).

8. Specifications

The following are the technical specifications for the CHUNYE 3010PM DC Power Supply.

Feature	Value
Model Number	3010PM
Input Voltage	220V AC
Output Voltage Range	0-30V DC
Output Current Range	0-10A DC
Output Power	300W
Output Type	Single Channel
Fixed USB Output	5V/2A
Dimensions (L×W×H)	Approx. 320mm × 190mm × 270mm
Item Weight	2.2 pounds (Approx. 1 kg)
Protection Features	Overload Protection (OCP), Overvoltage Protection (OVP), Short Circuit Protection (SCP)

Note: Specifications are subject to change without prior notice. All values are typical and may vary slightly.

9. Warranty and Support

For warranty information, technical assistance, or service inquiries, please refer to the documentation provided with your purchase or contact the manufacturer directly. It is recommended to keep your purchase receipt as proof of purchase for warranty claims.

Manufacturer: CHUNYE

Please visit the official CHUNYE website or contact your retailer for the most up-to-date support information.