Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

XYGStudy ESP32-S3-LCD-7B

XYGStudy ESP32-S3-LCD-7B 7-inch LCD Development Board User Manual

Model: ESP32-S3-LCD-7B

1. Introduction

This document provides comprehensive instructions for the XYGStudy ESP32-S3-LCD-7B 7-inch LCD Development Board. This board is a versatile microcontroller development platform designed for Human-Machine Interface (HMI) applications. It integrates an ESP32-S3 chip, featuring a 32-bit LX7 dual-core processor, a 7-inch LCD display with 1024x600 resolution, and robust wireless connectivity including Wi-Fi and Bluetooth.
The ESP32-S3-LCD-7B is ideal for rapid prototyping and development of graphical user interfaces (GUIs) using frameworks like LVGL, offering a powerful and integrated solution for various embedded projects.

2. Package Contents

Verify that all items listed below are included in your package. If any items are missing or damaged, please contact XYGStudy support.

- ESP32-S3-LCD-7B Development Board × 1
- HY2.0 2P to 2PIN male cable × 3
- HY2.0 3P to 3PIN male cable × 1
- HY2.0 4P to 4PIN male cable × 2
- Screws pack × 1



Image 2.1: Contents of the ESP32-S3-LCD-7B package, showing the development board, various cables, and a screw pack.

3. Key Features

The ESP32-S3-LCD-7B development board offers a robust set of features for embedded system development:

- **Processor:** High-performance Xtensa 32-bit LX7 dual-core processor, operating at up to 240MHz main frequency.
- **Wireless Connectivity:** Supports 2.4GHz Wi-Fi (802.11 b/g/n) and Bluetooth 5 (LE) with an onboard antenna.
- **Memory:** Built-in 512KB SRAM and 384KB ROM, with onboard 16MB Flash and 8MB PSRAM for ample storage and execution.
- **Display:** Integrated 7-inch LCD display with 1024 × 600 resolution and 65K color depth.
- **Peripherals:** Onboard CAN, RS485, I2C interfaces, TF card slot, and an integrated full-speed USB port.
- **Power Management:** LED indicators for power status and battery charging status, supports backlight adjustment and real-time battery voltage monitoring.
- **Power Modes:** Supports flexible clock and multiple power modes to achieve low power consumption in various scenarios.



Image 3.1: Overview of the ESP32-S3 7-inch LCD Development Board highlighting its core features including processor, display, and connectivity.



Image 3.2: Detailed list of features for the ESP32-S3-LCD-7B, including processor, wireless, memory, and peripheral specifications.

4. Technical Specifications

Specification	Detail
Brand	XYGStudy
Model Number	ESP32-S3-LCD-7B
Processor	Xtensa 32-bit LX7 Dual-core, up to 240MHz
Display	7-inch LCD, 1024 × 600 resolution, 65K color
Wireless Connectivity	2.4GHz Wi-Fi (802.11 b/g/n), Bluetooth 5 (LE)
Onboard Memory	512KB SRAM, 384KB ROM, 16MB Flash, 8MB PSRAM
Interfaces	CAN, RS485, I2C, TF card slot, USB
UPC	795602426609

5. Board Layout and Components

Understanding the layout of the ESP32-S3-LCD-7B board is crucial for proper setup and operation. Refer to the image below for a detailed view of the onboard components and their functions.



Image 5.1: Detailed diagram of the ESP32-S3-LCD-7B development board, indicating the location of key components and interfaces.

5.1. Key Onboard Components:

1. ESP32-WROOM-1 N16R8 module
2. Display panel connector
3. TF card slot
4. USB Type-C port
5. UART1/USB to UART Type-C port
6. UART2 header
7. I2C header
8. RS485 header
9. CAN header
10. GPIO header
11. 5V output
12. 3.7V Lithium battery PH2.0 header
13. CAN terminal resistor selection
14. RS485 terminal resistor selection
15. UART selection
16. BOOT button
17. RESET button
18. DONE LED (indicates program burning completion)
19. CHARGE LED (indicates battery charging)
20. POWER LED (power indicator)

Note: The specific functions and pinouts for each header can be found in the detailed product documentation or schematic diagrams provided by XYGStudy.

6. Application Scenarios

The ESP32-S3-LCD-7B development board is suitable for a variety of applications, particularly those requiring a graphical interface and wireless connectivity.

Human-Machine Interface (HMI)

The board serves as an excellent platform for developing HMIs, which are the medium of interaction and information exchange between a user and a machine. It facilitates the transformation of internal system information into a user-friendly format.

LVGL GUI Development

With its powerful ESP32-S3 processor and high-resolution display, the board is optimized for LVGL GUI development. LVGL is a free, open-source graphics library that provides tools to create embedded GUIs with visual effects and low memory requirements.

Image 6.1: Visual representation of potential application scenarios, including HMI and LVGL GUI development.

7. Initial Setup

Follow these general steps to set up your ESP32-S3-LCD-7B development board:

1. **Power Connection:** Connect a 5V power supply to the USB Type-C port (5) or the 3.7V Lithium battery PH2.0 header (12) if using battery power. Observe the POWER LED (21) to ensure the board is receiving power.
2. **Computer Connection:** Connect the board to your computer using a USB Type-C cable via the USB Type-C port (5). This port is used for both power and data communication (programming/debugging).
3. **Driver Installation:** Your operating system may require specific USB-to-UART drivers (e.g., CP210x or CH340) to recognize the board. Refer to the ESP-IDF documentation or common ESP32 development guides for driver installation instructions if needed.
4. **Development Environment Setup:** Install your preferred development environment, such as the Arduino IDE with ESP32 board support or the Espressif IoT Development Framework (ESP-IDF). Follow the official documentation for your chosen environment to configure it for ESP32-S3.
5. **First Program Upload:** Test your setup by uploading a simple example program (e.g., a 'Hello World' to the serial monitor or a basic graphics demo to the LCD). Ensure the correct board and COM port are selected in your IDE.

For detailed software setup and programming guides, refer to the official Espressif documentation and community resources for ESP32-S3 development.

8. Operation

Operating the ESP32-S3-LCD-7B involves programming the ESP32-S3 chip and utilizing its various peripherals. Here are general guidelines:

- **Programming:** Use the USB Type-C port (5) to upload firmware. Ensure the board is in programming mode (often achieved by holding the BOOT button (17) while pressing and releasing RESET (18), then releasing BOOT).
- **Display Usage:** The 7-inch LCD can be driven using graphics libraries like LVGL. Integrate the display driver into your firmware to render text, images, and complex GUIs.
- **Wi-Fi & Bluetooth:** Utilize the ESP-IDF or Arduino libraries to connect to Wi-Fi networks, establish Bluetooth Low Energy (BLE) connections, and implement network communication protocols.
- **Peripheral Interfacing:** Connect external sensors, actuators, or other modules to the GPIO header (10), I2C header (7), RS485 header (8), or CAN header (9) as required by your application. Ensure correct voltage levels and pin configurations.
- **TF Card:** Insert a micro SD card into the TF card slot (3) for data logging, storing display assets, or expanding storage for your application.



Image 8.1: Illustration of the various peripheral interfaces supported by the ESP32-S3-LCD-7B, including RS485, CAN, I2C, and GPIO.

9. Maintenance

To ensure the longevity and optimal performance of your ESP32-S3-LCD-7B development board, follow these maintenance guidelines:

- **Handling:** Always handle the board by its edges to avoid touching sensitive components, especially the display surface and exposed circuitry.

- **Storage:** Store the board in a dry, anti-static environment, away from direct sunlight, extreme temperatures, and high humidity.
- **Cleaning:** Use a soft, dry, lint-free cloth to gently clean the display and board surfaces. Avoid using liquids or abrasive cleaners.
- **Power Supply:** Always use a stable 5V power supply. Over-voltage or unstable power can damage the board.
- **Static Discharge:** Take precautions against electrostatic discharge (ESD) when handling the board. Use an anti-static wrist strap or work on an ESD-safe mat.

10. Troubleshooting

If you encounter issues with your ESP32-S3-LCD-7B, consider the following troubleshooting steps:

- **Board Not Powering On:**
  - Check the power supply connection and ensure it provides stable 5V.
  - Verify the USB cable is functional and properly connected.
  - Ensure the POWER LED (21) is illuminated.
- **Computer Not Recognizing Board:**
  - Install the necessary USB-to-UART drivers (e.g., CP210x, CH340).
  - Try a different USB port or cable.
  - Restart your computer.
- **Firmware Upload Failure:**
  - Ensure the correct board and COM port are selected in your IDE.
  - Verify the board is in programming mode (hold BOOT, press/release RESET, then release BOOT).
  - Check for compilation errors in your code.
- **Display Not Working:**
  - Ensure the display panel connector (2) is securely seated.
  - Verify that your firmware includes the correct display initialization and driver code.
  - Check power supply stability, as displays can be sensitive to voltage fluctuations.
- **Wi-Fi/Bluetooth Connectivity Issues:**
  - Check your code for correct Wi-Fi credentials or Bluetooth pairing procedures.
  - Ensure the onboard antenna is not obstructed.
  - Test in an environment with minimal wireless interference.

For more advanced troubleshooting or specific technical issues, refer to the official Espressif documentation or seek assistance from the ESP32 developer community.

11. Dimensions

The physical dimensions of the ESP32-S3-LCD-7B development board and its display are provided below for integration into your projects.

Image 11.1: Detailed measurements of the ESP32-S3-LCD-7B development board in millimeters.

Image 11.2: Outline dimensions of the 7-inch LCD panel and the overall board assembly in millimeters.

12. Warranty and Support

12.1. Warranty Information

The XYGStudy ESP32-S3-LCD-7B development board comes with a **1-Year Warranty** from the date of purchase. This warranty covers manufacturing defects and malfunctions under normal use. It does not cover damage caused by misuse, accidents, unauthorized modifications, or improper handling.
Please retain your proof of purchase for warranty claims.

12.2. Technical Support

For technical assistance, troubleshooting, or inquiries regarding your ESP32-S3-LCD-7B board, please contact XYGStudy customer support through the platform where the product was purchased (e.g., Amazon message system). Provide your order details and a clear description of the issue to receive prompt support.
Additional resources, including documentation, code examples, and community forums, may be available on the official Espressif website or relevant developer communities.

© 2024 XYGStudy. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0FGP1JX5W

More documents and user manuals: **https://manuals.plus/**