

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- › [Strong](#) /
- › [Strong 4G LTE N300 WiFi Router \(Model 4GROUTER360M\) User Manual](#)

Strong 4GROUTER360M

Strong 4G LTE N300 WiFi Router (Model 4GROUTER360M) User Manual

Your guide to seamless 4G LTE and Wi-Fi connectivity.

1. INTRODUCTION

The Strong 4G LTE N300 WiFi Router provides high-speed internet access using a 4G SIM card, offering reliable Cat4 LTE speeds up to 150 Mbps and stable N300 Mbps Wi-Fi coverage. This device is designed for easy setup and use, supporting up to 32 devices simultaneously, making it suitable for both home and small office environments where wired broadband may not be available.



Image 1: The Strong 4G LTE N300 WiFi Router, a compact device with two external antennas for enhanced signal reception.

2. WHAT'S IN THE BOX

Please check the package contents carefully. If any items are missing or damaged, contact customer support.

- Strong 4G LTE N300 WiFi Router
- External Antennas (2 units)
- RJ45 Ethernet Cable
- External Power Supply
- Nano to Micro SIM Card Adapter
- Quick Installation Guide
- Safety and Warranty Card

3. SETUP GUIDE

Follow these steps for a quick and easy setup of your Strong 4G LTE N300 WiFi Router.

3.1. Prepare Your SIM Card

Before inserting your SIM card, ensure that any PIN protection is disabled. You can do this by inserting the SIM card into a smartphone and disabling the PIN request through the phone's settings.

3.2. Insert the SIM Card

1. Locate the SIM card slot on the router.
2. If you have a Nano SIM, use the provided Nano to Micro SIM adapter to fit it into the standard SIM slot.
3. Gently insert the prepared SIM card into the slot until it clicks into place.

3.3. Attach External Antennas

Screw the two external 4G antennas onto the designated connectors at the back of the router. Adjust their orientation for optimal signal reception.

3.4. Power On the Router

Connect the external power supply to the router's DC-in port and then plug it into a power outlet. The router will automatically power on and begin the startup sequence.

3.5. Connect to the Network (Plug & Play)

The router is designed for Plug & Play operation. Once powered on and with a valid SIM card, it will automatically connect to the 4G LTE network. You can then connect your devices via Wi-Fi or Ethernet.



Image 2: Visual guide for SIM card insertion and powering on the router for instant connection. The image also shows the SIM card slot supporting standard, micro, and nano SIMs with an adapter.

3.6. Accessing the Web Interface

For advanced settings and network management, access the router's web interface by typing **192.168.188.1** into your web browser's address bar. Refer to the Quick Installation Guide for default login credentials.

4. OPERATING INSTRUCTIONS

This section details how to use your Strong 4G LTE N300 WiFi Router for optimal performance.

4.1. Connecting Devices

The router supports connections for up to 32 devices simultaneously.

- **Wi-Fi Connection:** Locate the Wi-Fi network name (SSID) and password printed on the label at the bottom of the router. Select this network on your device and enter the password to connect.
- **Ethernet Connection:** Use an RJ45 Ethernet cable to connect devices such as PCs, game consoles, or Smart TVs to the router's 100 Mbps LAN port for a stable wired connection.



Image 3: The router connecting various devices including laptops, tablets, smartphones, and gaming consoles, demonstrating its capacity for up to 32 simultaneous connections.

4.2. Network Management and Security

The router offers robust security features to protect your network:

- **WPA/WPA2 Encryption:** Ensures secure wireless communication.
- **PIN Control:** Manage SIM card PIN settings.
- **MAC Filtering:** Control which devices can connect to your network based on their MAC addresses.

- **Advanced Firewall Settings:** Customize firewall rules for enhanced protection.

All these settings can be managed through the easy-to-use web interface (192.168.188.1).

Benefíciese de una seguridad de red integral

Disfrute de una protección robusta mediante cifrado WPA/WPA2, control por código PIN, filtrado de direcciones MAC y funciones avanzadas de firewall como filtrado de puertos y funcionalidad DMZ.



Image 4: A user managing network settings on a laptop, illustrating the router's WPA/WPA2 encryption and PIN control features for secure network management.

5. MAINTENANCE

Proper maintenance ensures the longevity and optimal performance of your router.

- **Cleaning:** Use a soft, dry cloth to clean the router's exterior. Do not use liquid cleaners or aerosols.
- **Placement:** Place the router in a well-ventilated area, away from direct sunlight, heat sources, and strong electromagnetic fields.
- **Firmware Updates:** The router features a USB port specifically for firmware updates. Regularly check the Strong official website for the latest firmware versions to ensure improved performance and security. Follow the instructions provided with the firmware update package carefully.

6. TROUBLESHOOTING

If you encounter issues with your router, refer to the following common troubleshooting steps:

- **No Internet Connection:**

- Ensure the SIM card is correctly inserted and has an active data plan.
- Verify that the SIM card's PIN protection is disabled.
- Check the signal strength indicators on the router. If the signal is weak, try adjusting the external antennas or relocating the router.
- Restart the router by unplugging and replugging the power adapter.

- **Wi-Fi Not Visible or Connecting:**

- Ensure the Wi-Fi function is enabled (check the router's LED indicators).
- Verify you are entering the correct Wi-Fi password (SSID and password are on the router's label).
- Try connecting a device via Ethernet to confirm the router has internet access.

- **Slow Speeds:**

- Check the 4G signal strength. Weak signal can lead to slower speeds.
- Ensure no other applications or devices are consuming excessive bandwidth.
- Consider the number of connected devices; the router supports up to 32, but performance may vary with heavy usage.

- **Cannot Access Web Interface:**

- Ensure your device is connected to the router's network (Wi-Fi or Ethernet).
- Confirm you are typing the correct IP address: **192.168.188.1**.
- Try a different web browser.

If these steps do not resolve the issue, please contact Strong customer support.

7. SPECIFICATIONS

Detailed technical specifications for the Strong 4G LTE N300 WiFi Router (Model 4GROUTER360M).

Feature	Specification
Brand	Strong
Model Name	4GROUTER360M
Connectivity Technology	4G, Ethernet, LTE, Wi-Fi
Wireless Standard	802.11n (N300 Mbps)
4G LTE Speed	Up to 150 Mbps (Cat4)
Ethernet Ports	1 x 100 Mbps LAN Port
SIM Card Slot	Standard (2FF), includes Nano to Micro adapter
Antenna Type	2 x External, Detachable 4G Antennas; 2 x Internal Wi-Fi Antennas

Max Connected Devices	Up to 32
Security Features	WPA/WPA2 Encryption, PIN Control, MAC Filtering, Firewall
Operating System	StrongOS
Dimensions (Package)	18.1 x 15.6 x 7.3 cm
Product Weight	204 g
Power Supply	External Power Adapter
Special Features	Secure Network Management, Plug & Play, Connect up to 32 devices, USB port for firmware updates

8. WARRANTY AND SUPPORT

Strong is committed to providing reliable products and excellent customer service.

8.1. Warranty Information

Your Strong 4G LTE N300 WiFi Router comes with a 4-year protection plan, ensuring long-term peace of mind. Please refer to the included Safety and Warranty Card for detailed terms and conditions.

8.2. Customer Support

For any technical assistance, troubleshooting, or warranty inquiries, please contact our expert support team:

- **Email:** support_at@strong-eu.com

Our support team offers solid service and extended coverage to assist you.

Soporte Fiable – Protección de 4 Años

Disfruta de 4 años de cobertura con tu compra y gana tranquilidad a largo plazo.

Email:
support_at@strong-eu.com

Servicio Sólido

Soporte Experto

Cobertura Ampliada

Image 5: Visual representation of Strong's reliable support, highlighting the 4-year protection and contact email for assistance.

