

[Manuals.plus](#) /

› [Gidrox](#) /

› Gidrox GNV 11000W Tri-Fuel Inverter Generator Instruction Manual

Gidrox GNV

Gidrox GNV 11000W Tri-Fuel Inverter Generator Instruction Manual

Model: GNV

INTRODUCTION

This manual provides essential information for the safe and efficient operation, maintenance, and troubleshooting of your Gidrox GNV 11000W Tri-Fuel Inverter Generator. Please read all instructions carefully before operating the generator. Keep this manual for future reference.



Image: The Gidrox GNV 11000W Tri-Fuel Inverter Generator, a compact and portable power solution.

IMPORTANT SAFETY INFORMATION

Always operate the generator outdoors in a well-ventilated area to prevent carbon monoxide poisoning. Keep children and pets away from the generator during operation. Ensure proper grounding before use. Do not operate in rain or wet conditions. Refer to all warning labels on the generator.



Image: Overview of advanced safety features including CO Sensor, Overload Protection, and Low Oil Shutoff.

Carbon Monoxide (CO) Safety

Your generator is equipped with a CO Sensor that automatically shuts down the unit if dangerous carbon monoxide levels are detected. This feature is designed for safety but does not replace the need for proper ventilation.

Overload Protection

The generator includes overload protection to prevent damage to the unit and connected appliances. If an overload occurs, the circuit breaker will trip. Reduce the load and reset the breaker.

Low Oil Shutoff

The engine will automatically shut down if the oil level drops below a safe operating threshold, protecting the engine from damage.

SETUP

Unpacking and Initial Assembly

Carefully remove the generator and all components from the packaging. The package includes essential accessories for immediate use.

PACKAGING CONTENT



① NEMA 5-20P

② OIL DIPSTICK

③ SPARK PLUG SOCKET WRENCH

④ NEMA L14-30P TO TT-30A

⑤ NEMA L14-30P

⑥ NEMA 4-50P 50A



NG HOSE (3/4")



LPG HOSE



ENGINE OIL



DUST COVER

Image: Contents of the generator packaging, including various plugs, oil dipstick, spark plug wrench, NG hose, LPG hose, engine oil, and dust cover.

Attach the wheels and handle as per the assembly instructions provided in the separate quick start guide. The large all-terrain wheels are designed for easy movement.



Image: A person pulling the generator using its handle and large all-terrain wheels, demonstrating its portability.

Adding Engine Oil

Before first use, add the supplied engine oil to the crankcase. Use the provided funnel and extension hose for easier filling. The generator requires approximately 0.36 gallons of engine oil. Ensure the oil level is at the full mark on the dipstick.

Battery Connection

Connect the battery terminals as instructed. Ensure a secure connection for reliable electric starting.

Fueling the Generator

The Gidrox GNV 11000W is a tri-fuel generator, capable of running on Gasoline, Propane (LPG), or Natural Gas (NG).

- **Gasoline:** Fill the 8.7-gallon fuel tank with unleaded gasoline. Do not overfill.
- **Propane (LPG):** Connect the supplied LPG hose to a propane tank and the generator's inlet.
- **Natural Gas (NG):** Connect the supplied NG hose to a natural gas source and the generator's inlet.



Image: Visual guide showing battery connection, engine oil fill, and fuel tank fill steps.

Grounding the Generator

Always properly ground the generator before operation to prevent electrical shock. Consult local electrical codes for proper grounding procedures.

OPERATING INSTRUCTIONS

Control Panel Overview

Familiarize yourself with the control panel components before starting the generator.




Image: Detailed diagram of the generator's control panel, labeling the engine start/stop, digital panel meter, circuit breakers, ATS switch, charging port, fuel switch, and various AC outlets.

Starting the Generator

The generator features a push-button electric start with remote and manual backup options.

1. Ensure the generator is on a level surface and properly grounded.
2. Select the desired fuel type using the fuel switch.
3. Turn the engine switch to the 'ON' position.
4. Press and hold the 'START' button or use the remote start feature.
5. Allow the engine to warm up for a few minutes before connecting electrical loads.

Fuel Switching

The innovative dial-start system allows for effortless fuel switching in seconds. To switch fuels, ensure the generator is running, then turn the fuel selector dial to the desired fuel type. The engine will automatically adjust.

TRI-FUEL INVERTER GENERATOR

11,000W
MAX. POWER

CO SENSOR
GIDROX
TRI-FUEL SERIES

Fuel Type	Starting Watts	Running Watts
Gasoline (Red)	11000	9000
Propane (Blue)	9900	8100
Natural Gas (Green)	8910	7290

Image: The Gidrox Tri-Fuel Inverter Generator demonstrating its compatibility with gasoline, propane, and natural gas, along with their respective wattage outputs.

Connecting Electrical Loads

The generator is equipped with multiple outlets:

- **50A (14-50R) Outlet:** For heavy-duty applications like luxury RVs or whole-house backup.
- **30A (L14-30R) 240V Outlet:** For whole-house backup.
- **120V 20A GFCI Outlets:** For standard household appliances.

All outlets are protected by waterproof rubber covers and GFCI safety. Ensure the total wattage of connected devices does not exceed the generator's running wattage.

The advertisement features a black and orange Gidrox GNV11000T inverter generator positioned on a wet stone patio at night. In the background, a two-story house with warm interior lighting is visible. The generator's control panel and outlets are clearly shown. Overlaid on the image is the Gidrox logo and the text 'WHOLE HOME BACKUP POWER 50A ULTRA OUTLET READY WHEN YOU NEED IT'. At the bottom, a row of icons represents various appliances: a heater, refrigerator, E-Grill, microwave, washer, and power tools.

GIDROX

WHOLE HOME BACKUP POWER
50A ULTRA OUTLET
READY WHEN YOU NEED IT

GNV11000T
INVERTER GENERATOR

Heater Refrigerator E-Grill Microwave Washer Power Tools

Image: The Gidrox Inverter Generator positioned outside a house, illustrating its capability for whole-home backup power via its 50A ultra outlet, ready for various appliances.

ECO Mode

Engage ECO mode for maximum fuel efficiency and reduced noise levels when the power demand is low. The generator will automatically adjust engine speed to match the load.

WHY CHOOSE INVERTER GENERATORS




Image: The Gidrox Inverter Generator running in ECO mode, highlighting its ability to reduce noise and fuel consumption.

ATS Ready

The generator is equipped with a dedicated ATS port for seamless integration with an automatic transfer switch (sold separately). This allows for automatic power transfer during outages.



Image: The Gidrox Inverter Generator connected to an Automatic Transfer Switch (ATS) system, indicating its readiness for automatic backup power during emergencies.

Official Product Videos

Video: Gidrox 11000W Inverter Generator. This video provides an overview of the generator's features and capabilities.

Video: Gidrox Tri-Fuel Inverter Generator for Home Backup. This video demonstrates the generator's use for home backup power.

MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your generator.

Oil Changes

Change the engine oil after the first 20 hours of operation, and then every 100 hours or annually, whichever comes first. Refer to the engine oil fill image in the Setup section for guidance.

Spark Plug Maintenance

Inspect the spark plug periodically. Clean or replace it as needed using the supplied spark plug wrench.

Air Filter Cleaning

Clean the air filter regularly, especially in dusty conditions. A dirty air filter can reduce engine performance and increase fuel consumption.

Carburetor Draining (for Gasoline)

If storing the generator for an extended period, especially when using gasoline, drain the carburetor bowl to prevent fuel degradation and starting issues. This helps prevent clogs and ensures easier starts after storage.

Storage

When storing the generator, especially for long periods, ensure the fuel system is properly prepared (drained for gasoline, shut off for propane/natural gas). Cover the generator with the provided dust cover to protect it from elements.

TROUBLESHOOTING

This section addresses common issues you might encounter with your generator.

Problem	Possible Cause	Solution
Engine does not start	No fuel, low oil, battery not connected, spark plug issue, fuel switch incorrect.	Check fuel level/connection, add oil, connect battery, inspect spark plug, ensure correct fuel selection.
No power output	Circuit breaker tripped, ECO mode engaged with high load, overload.	Reset circuit breaker, disengage ECO mode if necessary, reduce connected load.
CO Sensor shutdown	High carbon monoxide levels detected.	Move generator to a well-ventilated outdoor area. Do not operate indoors.
Engine runs rough	Stale fuel, dirty air filter, spark plug issue.	Use fresh fuel, clean/replace air filter, inspect/replace spark plug.

SPECIFICATIONS

Feature	Detail
Brand	Gidrox
Model Number	GNV
Starting Wattage	11000 watts
Running Wattage	11000 watts

Feature	Detail
Fuel Type	Gasoline, Propane (LPG), Natural Gas (NG)
Engine Type	Inverter
Ignition System	Electric start
Tank Volume	8.7 gallons
Runtime	Up to 21 hours (at 25% load)
Noise Level	62-65dB
Product Dimensions (L x W x H)	26" x 19" x 24"
Special Features	Automatic Idle Control, CO Sensor, Remote Start, Super Quiet, Tri-Fuel, ATS Ready
Included Components	Dust Cover, Engine Oil, LPG Hose, NG Hose, Plugs and Tool Kit

WHY CHOOSE INVERTER GENERATORS



VS



THD<3%



THD<25%

65 dB



90 dB

Low fuel consumption



High fuel consumption

Lower Emissions(EPA)



Higher Emissions

INVERTER GENERATOR

OPEN-FRAME GENERATOR

Image: Comparison highlighting the benefits of an inverter generator (THD<3%, 65dB, low fuel consumption, lower emissions) over an open-frame generator.

WARRANTY AND SUPPORT

Warranty Information

Your Gidrox GNV 11000W Tri-Fuel Inverter Generator comes with a 3-Year Limited Warranty. This warranty covers material and manufacturing defects. Please refer to the warranty card included with your product for full details and registration instructions.

Customer Support

For technical assistance, parts, or warranty claims, please contact Gidrox customer support. Contact information can be found on the warranty card or the official Gidrox website.



Image: Gidrox customer care representatives ready to assist with product inquiries and support.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B0GCMLJ3K8>

More documents and user manuals: <https://manuals.plus/>