




BRITISH GENERAL NX13ASWIL-G 13A Switched Socket Instruction Manual

[Home](#) » [BRITISH GENERAL](#) » **BRITISH GENERAL NX13ASWIL-G 13A Switched Socket Instruction Manual** 

BRITISH GENERAL NX13ASWIL-G 13A Switched Socket Instruction Manual



Contents

- 1 Safety Warning
- 2 Wiring Instructions
 - 2.1 Power Off
 - 2.2 Replacing an existing accessory
 - 2.3 New installation
 - 2.4 Connection (See diagram)
 - 2.5 Complete Installation & Test
- 3 Additional Advice for Decorative Products
- 4 Technical
- 5 Batch Code explanation
- 6 Care
- 7 Environmental Protection
- 8 Address/Helpline
- 9 Documents / Resources
- 10 Related Posts

Safety Warning

For your safety, this product must be installed in accordance with local. Building Regulations. **If in any doubt, or where required by the law, consult a competent person who is registered with an electrical self-certification scheme.** Further information is available online or from your Local Authority.

Please read carefully and use in accordance with these safety wiring instructions. Before commencing any electrical work ensure the supply is switched off at the mains. Either by switching off the consumer unit or by removing the appropriate fuse or turning off MCB (trip).

Wiring should be in accordance with the latest edition of the IET regulations (BS 7671). To prevent fire hazard always use cable of the correct rating & type for the application.

Warning do not exceed the load rating of this device as stated on the rear of the product.

Wire Identification — Twin & Earth Cable

Note – As from 1st April 2004 new colour codes for hard wire installations were introduced.

EARTH = Green/Yellow Sleaving

NEUTRAL = Black (pre Apr 04) / Blue (after Apr 04) N

LIVE = Red (pre Apr 04) / Brown (after Apr 04)



Wiring Instructions

Power Off

Before commencing work always isolate the power at the consumer unit / fuse box.

***Note** — If your installation uses a four-lug metal mounting box, remove the top and bottom lugs or bend fully back.

Replacing an existing accessory

1. Unscrew the accessory from the wall/mounting box.
2. Note the cable connections:

There will generally be three different wiring configurations, this illustration shows 2 wires of each colour connected to each terminal (there could be 1 or 3 wires of each colour connected to each terminal) plus an additional connection between the mounting box earth terminal and the socket earth terminal.


New installation

1. Install mounting box (metal or moulded) for either flush or surface mounting, ensuring appropriate size of product (Mounting box to be purchased separately).
2. Select the most suitable entry point of the mounting box (knock-out) and route the cables through. If a metal box is used, a cable grommet should be fitted to the entry point.
3. Cables should be prepared so a sufficient conductor length reaches the terminals. Strip the ends of the individual conductors leaving an adequate length bare to enter terminals.


Connection (See diagram)

1. Line up the new accessory to mounting box and take note of where each terminal is Located.
2. Connect each wire to the matching terminal. An earth connection should always be made between the mounting box earth terminal and the accessory earth terminal, where fitted. All bare earth wires must be sheathed with green/yellow sleeving. When connecting the new accessory ensure that only the bare end of the wire enters the terminal and no bare wires are visible.
3. Tighten terminal screws securely. (Do not over tighten)
4. This socket is fitted with two linked terminals to provide a dual earth facility. This is for use in “clean” installations where additional earth capacity is required to comply with Regulation 6071EE Wiring Regulations.


- Single 13 Amp Switched Socket.



- Double 13 Amp Switched Socket.



- Double 13 Amp Switched Socket-Outboard Rockers.



Complete Installation & Test

1. Carefully position the accessory into the mounting box, ensuring that no wires are trapped between the plate and the wall and secure with screws (do not over tighten) then insert screw covers (optional).
2. Once the installation has been completed correctly, replace the fuse/ reset MCB (trip), switch the power back on at the consumer unit and test.

Additional Advice for Decorative Products

Fixing method varies depending on which product range is supplied. Always ensure wall surface is reasonably flat and smooth, with no bumps or projections. Metal frontplates **WITH** screw fixing holes, fix the unit to the back box using two fixing screws supplied. All Decorative products **MUST** have an earth connection between the frontplate and back box. Frontplates **WITHOUT** screw fixing holes. These products comprise main unit with integral gasket, and frontplate as separate item. Fix unit to back box using two fixing screws supplied. Clip frontplate onto main assembly, ensuring screwdriver notch is located bottom right hand corner.

To remove plate, place medium size flat bladed screwdriver in notch and lever off against gasket.

Technical

- **Voltage:** 220-240V ac
- **Frequency:** 50/60Hz
- **Rating:** 13A
- **Terminal capacity:** 3 x 2.5mm² 3 x 4mm² 2 x 6.0mm²
- **Min box depth (profiled plates):** 25mm
- **Min box depth (flat plates):** 35mm

ASIA Approved

The ASIA quality mark is evidence that the product has been independently tested to comply with the relevant clauses of the applicable standards.



Batch Code explanation

yyWxx Manufacturing date code, year of manufacture (yy) and week of manufacture (Wxx)

Care

To maintain the high quality appearance of decorative finish switches and sockets, BG Electrical recommend the use of a soft cloth periodically to clean the front face. When installing a decorative product please ensure that the wall is decorated, finished and free of moisture prior to installation. BG Electrical recommends avoiding using, but not restricted to, these substances from becoming in contact with the decorative metal front-plates when cleaning or decorating:

- Adhesive tape, including low tack masking tape
- Solvents
- White spirit
- Multi surface cleaners
- Industrial multipurpose cleaning wipes
- Wet wipes

Using items like those listed above may cause a degrading effect to the front-plates lacquer/plated finish, although the function will remain unaffected.

Environmental Protection



This symbol is known as the “Crossed-out Wheelie Bin Symbol”. When this symbol is marked on a product or battery, it means that it should not be disposed of with your general household waste. Some chemicals contained within electrical/ electronic products or batteries can be harmful to health and the environment. Only dispose of electrical/electronic/ battery items in separate collection schemes, which cater for the recovery and recycling of materials contained within. Your co-operation is vital to ensure the success of these schemes and for the protection of the environment.

Address/Helpline

Luceco PLC

Stafford Park 1
Telford TF3 3BD
ENGLAND

(EU) Luceco SE

C/ Bobinadora 1-5
08302 Mataro
SPAIN

If you have further technical assistance you can get in touch with our

Technical Helpline on: +44 (0)3300 249 279 technical.support@bgelectrical.co.uk



Documents / Resources

