



CP electronics EBDHS-AD High Bay Presence Detectors Installation Guide

[Home](#) » [CP electronics](#) » CP electronics EBDHS-AD High Bay Presence Detectors Installation Guide 

Contents

- 1 CP electronics EBDHS-AD High Bay Presence Detectors
- 2 Dimensions (mm)
- 3 Wiring
- 4 Presence or absence detection
- 5 Detection pattern
 - 5.1 Walk towards
- 6 Alignment marks
- 7 Masking shields
- 8 Masking shield application
- 9 Installation
- 10 Default Settings
- 11 Testing
- 12 Technical Data
- 13 Accessories & associated products
 - 13.1 Part Number/ Description
- 14 CP Electronics
- 15 Documents / Resources
 - 15.1 References
- 16 Related Posts





CP electronics EBDHS-AD High Bay Presence Detectors



Warning: This device should be installed by a qualified electrician in accordance with the latest edition of the IEE wiring regulations.

Dimensions (mm)



Wiring

Dimming outputs


Basic insulation only. Although low voltage, this is not an SELV output and should be treated as if mains potential. Use mains rated wiring.

Single channel dimming

Switches the luminaire with occupancy and maintains illuminance. Dims and switches using optional centre

biased retractive switch.


Key



1. Neutral
2. Live
3. 10A circuit protection if required
4. Load
5. Centre biased retractive switch, 230V (for absence detection)
6. Dimming ballast

Switches channel 1 only with occupancy, optional override switch. No dimming output.

Key



1. Neutral
2. Live

3. 10A circuit protection if required
4. Load
5. Centre biased retractive switch, 230V (for absence detection)

Presence or absence detection


The unit ships with presence detection as default.

- To change over to absence detection, press and release the external switch 5 times within the first minute of power up. The LED will turn on red for 30 seconds to indicate absence mode has been selected.
- To change back to presence detection, repeat the above procedure – the LED will flash red for 30 seconds to indicate presence mode has been selected.


To use absence detection a retractive (momentary) switch must be connected between the 2 terminals on the diagram. Note that this will be switching mains voltage.

Note: the above adjustments can also be made using the optional UHS5 or UNLCDHS handsets.

Detection pattern



Walk across



Height/Range Diameter

- **15m:** 40m

- **10m:** 26m
- **6m:** 16m
- **3m:** 9m


Walk towards



Height/Range Diameter

- **15m:** 30m
- **10m:** 20m
- **6m:** 12m
- **3m:** 8m

Alignment marks



The sensor head has 4 alignment marks. These correspond to the 4 outer passive infrared sensors under the lens. Use these marks to align with aisles and corridors to ensure the best detection characteristics.

Masking shields

The detector includes two clip-on masking shields, enabling precise masking of the detection shape for aisles and corners as well as narrowing the detection diameter.



1. Lateral trim pattern for slot style detection.
2. Radial trim pattern for narrowing the detection diameter.

Ensure all infra-red (IR) programming is completed before affixing the masking shields to the detector.

Masking shield application

Aisles

- Trim the masks laterally to reduce the detection width for aisles.




a	b	c	d	e
1	wa 18m x 40m wt 13.5m x 30m	wa 11.7m x 26m wt 9m x 20m	wa 7.2m x 16m wt 5.4m x 12m	wa 4m x 9m wt 3.6m x 8m
2	wa 12.8m x 40m wt 9.6m x 30m	wa 8.3m x 26m wt 6.4m x 20m	wa 5.1m x 16m wt 3.8m x 12m	wa 2.8m x 9m wt 2.5m x 8m
3	wa 8.8m x 40m wt 6.6m x 30m	wa 5.7m x 26m wt 4.4m x 20m	wa 3.5m x 16m wt 2.6m x 12m	wa 1.9m x 9m wt 1.7m x 8m
4	wa 4.4m x 40m wt 3.3m x 30m	wa 2.8m x 26m wt 2.2m x 20m	wa 1.7m x 16m wt 1.3m x 12m	wa 0.9m x 9m wt 0.8m x 8m

Key

- **a.** Trim line
- **b.** 15m Mounting height
- **c.** 10m Mounting height
- **d.** 6m Mounting height
- **e.** 3m Mounting height
- **wa** = walk across
- **wt** = walk towards


Install shields to detector



- Align trimmed shields with sensor head alignment marks and aisle

Narrow detection

- Trim the masks along radial lines to narrow the detection diameter.




a	b	c	d	e
1	wa 35.6m wt 26.7m	wa 23.1m wt 17.8m	wa 14.2m wt 10.6m	wa 8m wt 7.1m
2	wa 25.2m wt 18.9m	wa 16.3m wt 12.6m	wa 10m wt 7.5m	wa 5.6m wt 5m
3	wa 18m wt 13.5m	wa 11.7m wt 9m	wa 7.2m wt 5.4m	wa 4m wt 3.6m
4	wa 12.8m wt 9.6m	wa 8.3m wt 6.4m	wa 5.1m wt 3.8m	wa 2.8m wt 2.5m
5	wa 8.8m wt 6.6m	wa 5.7m wt 4.4m	wa 3.5m wt 2.6m	wa 1.9m wt 1.7m

Key

- **a.** Trim line
- **b.** 15m Mounting height
- **c.** 10m Mounting height
- **d.** 6m Mounting height
- **e.** 3m Mounting height
- **wa** = walk across
- **wt** = walk towards

Install shields to detector




- Align trimmed shields with sensor head alignment marks and aisle.

Installation

This device is designed to be flush ceiling-mounted. See page 20 for additional mounting options.


- Do not site the unit where direct sunlight might enter the sensor.
- Do not site the sensor within 1m of any lighting, forced air heating or ventilation.
- Do not fix the sensor to an unstable or vibrating surface.

Create cut out




- Cut a 64mm diameter hole in the ceiling.

Wire stripping




- Strip the wires as shown opposite. Presence detector does not require earth conductor.

Wire in plugs & connect to detector




- Wire in plug/s, using wiring diagram on page 3 as a guide. Connect the plug/s to the detector.

Clamp cable



- Continue tightening the screws until the clamp bar snaps out and is tightly engaged against the cable/s. The cable clamp must clamp the outer sheath only.

Install detector



- Bend the springs up and push detector through hole in ceiling. When fully inserted the springs snap back to hold the device in place.

WARNING: To avoid injury, take care when bending springs.



Default Settings

- **Time out:** 20 minutes.
- **LUX on level:** 9
- **LUX off level:** 9
- **Sensitivity:** 9
- **Detection:** Presence

Adjustments can be made using the optional UHS5 or UNLCDHS handsets.



Testing

Presence Detection



1. Power up the sensor. The load should come on immediately.
2. Vacate the room or remain very still and wait for the load to switch off (this should take less than 20 minutes).
3. Enter the room or make some movement and check that the load switches on.


Absence Detection



1. Power up the sensor. Switch the load on.
2. Vacate the room and wait for the load to switch off (this should under than 20 minutes).

3. Enter the room, the load will remain off until you switch it on again.

Technical Data

Part code	EBDHS-AD
Weight	0.200kg
Supply voltage AC	230 VAC +/- 10%
Supply frequency	50Hz
Circuit protection	10A
Power consumption parasitic	305mW
Terminal capacity	2.5mm ²
Max load:	
Incandescent lighting	10A
Fluorescent lighting	10A
Compact fluorescent lighting	10A
LED lighting	10A
Resistive heaters	10A
Fans and ventilation equipment	10A
Low voltage halogen	10A
Number of drivers/ballasts	Up to 10
Time out range	10 seconds to 99 minutes
Working temperature range	-10 to 35°C
Humidity	5 to 95% non-condensing
Material (casing)	Flame retardant ABS and PC/ABS
Insulation class	2
IP rating	40
Compliance	 EMC-2014/30/EU, LVD-2014/35/EU

Accessories & associated products

Part Number/ Description



- **DBB:** Surface mounting box



- **DBB-EXT:** Surface mount back box extender



- **EBD-ENCIP1:** Pre-drilled 64mm hole IP65 detector enclosure



- **EXD-HSC:** Extended wiring housing



- **UHS5:** Compact, programming/commissioning handset



- **UHS7:** Compact, user handset



- **UNLCDHS:** Universal LCD IR handset/commissioning handset



CP Electronics

- Brent Crescent, London NW10 7XR
- t. +44 (0)333 900 0671
- enquiry@cpelectronics.co.uk
- www.cpelectronics.co.uk
- connect with us    




cpelectronics.co.uk/cp/409





Due to our policy of continual product improvement CP Electronics reserves the right to alter the specification of this product without prior notice.

WD409 Issue 11 Installation Guide, EBDHS-AD

Documents / Resources

	<p>CP electronics EBDHS-AD High Bay Presence Detectors [pdf] Installation Guide EBDHS-AD, High Bay Presence Detectors, EBDHS-AD High Bay Presence Detectors, Presence Detectors, Detectors</p>
---	--

References

-  [Technical Guides | Support Library | CP Electronics](#)
-  [Presence and Absence Detection Explained | Knowledge Hub | CP Electronics](#)
-  [Walk Towards and Walk Across explained | Knowledge Hub | CP Electronics](#)
-  [Presence Detectors and Energy Efficient Lighting Control Systems | CP Electronics](#)