



DELUX KM17DB Mechanical Keyboard User Manual

[Home](#) » [DELUX](#) » DELUX KM17DB Mechanical Keyboard User Manual 

Contents

- [1 DELUX KM17DB Mechanical Keyboard](#)
- [2 Product Information](#)
- [3 Product Usage Instructions](#)
- [4 Package contents](#)
- [5 User instruction](#)
- [6 Indicators](#)
- [7 F1-F8 Multimedia function](#)
- [8 Lighting effect](#)
- [9 Driver Installation Instruction](#)
- [10 Documents / Resources](#)
- [11 Related Posts](#)



DELUX KM17DB Mechanical Keyboard



Product Information

The KM17DB is a mechanical keyboard that offers a range of features including customizable button settings, lighting settings, and recovery settings. The keyboard also includes function keys F1 to F8 for quick access to various commands.

Product Usage Instructions

1. Connect the keyboard to your computer using the USB cable provided.
2. Turn on your computer and wait for it to detect the keyboard.
3. To customize the button settings, press the A button and use the numbered keys (1-5) to assign specific functions to each key.
4. To customize the lighting settings, press the C button and use the numbered keys (1-5) to select different lighting modes.
5. To access recovery settings, press the D button.
6. Use the function keys (F1-F8) for quick access to various commands such as volume control, media playback, and screen brightness.

Thank you for choosing our mechanical keyboard. Please read the user manual carefully before using this product.

Package contents

- Keyboard-1
- User manual -1
- Type-C Cable –1

System requirement:

Compatible with Windows 7 /Windows 8 /Windows 10/MAC

User instruction

The Code way

- 2.46 mode: Press FS key for 3 seconds. insert the uss receiver when the indicator flashes quickly. The indicator will stay on after code matching is finished.
- BT mode: Press F10/F11/F12 key for 3 seconds. It comes into BT matching mode when the indicator flashes quickly. Activate BT mode in the device and click to choose the keyboard. The indicator will stay on after BT code matching is finished. BT name:DELUX5.0 and DELUX3.0
- Wired mode: Connect the computer with USB cable. it can work when it is indentified by the computer.

Device changing

- Click on the corresponding key of F9-F12 to change the mode between 2.4G and BT1-BT2-BT3. If it doesn't work, please press FN+ESC to try again.
- Switch to BT device: Connection is done when the corresponding BT indicator flashes slowly and stays on finally. But if the corresponding BT indicator flashes slowly for 180 seconds and then goes out, the code matching will not be successful and will be automatically exited.









- Switch to z as mode: insert the uss receiver. connection is done when the green indicator flashes slowly and stays on finally. But if the corresponding indicator flashes slowly for 180 seconds and then goes out, the code matching will not be successful and will be automaticall exited. (When the keyboard is in wireless mode, the USB cable is only for charging but not for wired mode.

Indicators



Indicator	Flash slowly	Flash quickly	Stay on	Go out
①	/	/	Numeric state	Numeric state is off
②	/	/	Uppercase state	Uppercase state is off
③	Connection state after mode changing	State in code matching	Successful code matching	Non-working mode
④	Battery in low voltage	Shut down after flashing 10 times in low voltage	Charging state	Wireless mode/ Fully charged state in wired mode.

F1-F8 Multimedia function

F1  screen brightness down	F2  screen brightness up
F3  Display all running programs on the desktop at the same time	F4  Start station showing all the softwares
F5  last play	F6  Start/Stop
F7  Next play	F8  Mute

FN+ESC: Lock/open the FN key, the indicator goes out/stays on. (This function is only supported in Windows.)

- After locking the FN key, FI-F8 key only shows multimedia function and ry-F12 keys are for mode changing between 2.4g and BI mode. But FI-F12 original function can be showed by pressing FN+FI-F12.

- After unlocking the FN key, click FI-F12 key and it shows the original function. But multimedia function can be showed by pressing ENtra-r8

Lighting effect

FN+MENU: cycle to change the light mode

FN + + V: adjust the lighting brightness

EN + + -: adjust the lighting speed

After installing the driver, enter the customized lighting mode by pressing FN+DEL

In customized lighting mode, please press FN+del again to enter in customized state and the light under the FN key flashes. After that the light can be customized to be on or off. Press N+beL again to save and exit also will save and exit without any action in 30s

- It will be in sleep mode without any action for 180 seconds, but it can be woken up by pressing any key.
- is custom uncton should be used with the driver.
- WIN MAC system can be changed by the switch in the bottom.
- Wired and wireless mode can also be changed by the switch in the bottom.

Driver Installation Instruction

Driver Installation

Download the driver from the official website. You can set the keys, macro and lighting of the keyboard by using the driver.

Driver Settings

Open the setting interlace of the driver to set the keys, macro and lighting. M1/ M2/M3 three groups of configuration files can be set, and the top of the interface is the menu. (Please connect the keyboard to the device, otherwise the driver can't be opened.

Button Settings

Click M1/M2/M3 and click the key to be set. And then click the “Keyboard”/ “Mago Definition”/ “Multimedia” on the left for setting, Input the key you want to set or select the multimedia function settings in the drop-down menu. After the setting is successtul, click “OK and apply to complete the setting



Keyboard Key Settings

Click the key to be set, select “Keyboard” and input the key you want to set. Click “OK” and apply to complete the setting.

Macro Key Settings

Click the key to be set and select “Macro Definition”. Select the macro command that has been set. Click “OK” and apply to complete the setting

Multimedia Key Settings

Click the key to be set, select “Multimedia”, and select the multimedia function in the drop-down menu to set. Click “OK” and apply to complete the setting.

Macro Settings

Click “Macro Editor” for setting under the corresponding configuration file. Right-click in the “Macro List” position, select “New Macro” and input the macro name. Select the corresponding macro name and click “Start Recording Macro”. During recording, you can input the keys you want on the keyboard, and then click “Stop Recording Macro”. Set the properties and save it. Instruction of importing macro: In the key setting, click the key to be set, select the macro name in the “Macro Definition”, and then click “OK” and apply to complete the setting.

Lighting Settings

Click “Light” to set the overall lighting effect of the keyboard, select different lighting modes in the drop-down menu, and click “Apply” to make the keyboard display different lighting effects. Users can adjust the brightness and speed by themselves.

Recovery Settings

Click “Restore Default” in the lower left corner of the interface, and click “Apply” to restore the keyboard to factory default. (You need to do this respectively for M1/M2/M3 to make them in factory default.)

Documents / Resources

	DELUX KM17DB Mechanical Keyboard [pdf] User Manual KM17DB Mechanical Keyboard, KM17DB, Mechanical Keyboard, Keyboard
--	---