



DrayTek Vigor2765 Series 35b Security Router User Guide

[Home](#) » [DrayTek](#) » DrayTek Vigor2765 Series 35b Security Router User Guide 

DrayTek Vigor2765 Series 35b Security Router User Guide



Intellectual Property Rights (IPR) Information

Copyrights © All rights reserved. This publication contains information that is protected by copyright. No part may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language without written permission from the copyright holders.

Trademarks The following trademarks are used in this document:

- Microsoft is a registered trademark of Microsoft Corp.
- Windows 7, 8, 10, 11 and Explorer are trademarks of Microsoft Corp.
- Apple and Mac OS are registered trademarks of Apple Inc.
- Other products may be trademarks or registered trademarks of their respective manufacturers.

Contents

- [1 Safety Instructions and Approval](#)
- [2 Package Content](#)
- [3 Panel Explanation](#)
- [4 Hardware Installation](#)
- [5 Network Connection for ax series](#)
- [6 Software Configuration](#)
- [7 Customer Service](#)
- [8 Documents / Resources](#)
 - [8.1 References](#)
- [9 Related Posts](#)

Safety Instructions and Approval

Safety Instructions

- Read the installation guide thoroughly before you set up the router.
- The router is a complicated electronic unit that may be repaired only by authorized and qualified personnel. Do not try to open or repair the router yourself.
- Do not place the router in a damp or humid place, e.g. a bathroom.
- Do not stack the routers.
- The router should be used in a sheltered area, within a temperature range of 0 to +45 Celsius.
- Do not expose the router to direct sunlight or other heat sources. The housing and electronic components may be damaged by direct sunlight or heat sources.
- Do not deploy the cable for LAN connection outdoor to prevent electronic shock hazards.
- Keep the package out of reach of children.
- When you want to dispose of the router, please follow local regulations on conservation of the environment.

Warranty

We warrant to the original end user (purchaser) that the router will be free from any defects in workmanship or materials for a period of two (2) years from the date of purchase from the dealer. Please keep your purchase receipt in a safe place as it serves as proof of date of purchase. During the warranty period, and upon proof of purchase, should the product have indications of failure due to faulty workmanship and/or materials, we will, at our discretion, repair or replace the defective products or components, without charge for either parts or labor, to whatever extent we deem necessary to restore the product to proper operating condition. Any replacement will consist of a new or re-manufactured functionally equivalent product of equal value, and will be offered solely at our discretion. This warranty will not apply if the product is modified, misused, tampered with, damaged by an act of God, or subjected to abnormal working conditions. The warranty does not cover the bundled or licensed software of other vendors. Defects which do not significantly affect the usability of the product will not be covered by the warranty. We reserve the right to revise the manual and online documentation and to make changes from time to time in the contents hereof without obligation to notify any person of such revision or changes.



Declaration of Conformity

Hereby, DrayTek Corporation declares that the radio equipment type Vigor2765 is in compliance with Directive 2014/53/EU.

The full text of the EU declaration of conformity is available at the following internet address:


<https://fw.draytek.com.tw/Vigor2765/Document/CE/>

Manufacturer: DrayTek Corp.

Address: No.26, Fushing Rd., Hukou, Hsinchu Industrial Park, Hsinchu 303, Taiwan

Product: Vigor2765 Wireless Series

Frequency Information for Europe area:

2.4GHz WLAN	For ac model, 2400MHz – 2483MHz, max. TX power: 19.79dBm *1For ax model, 2400MHz – 2483MHz, max. TX power: 19.81dBm *1
5GHz WLAN	For ac model, 5150MHz – 5350MHz, max. TX power: 22.74dBm *2 5470MHz – 5725MHz, max. TX power: 29.88dBm *2 For ax model, 5150MHz – 5350MHz, max. TX power: 22.70dBm *2 5470MHz – 5725MHz, max. TX power: 29.47dBm *2
	Requirements in AT/BE/BG/CZ/DZ/DK/EE/FR/DE/IS/IE/IT/EL/ES/ CY/LV/LI/LT/LU/HU/MT/NL/NO/PL/PT/RO/SI/SK/TR/FI/SE/CH/HR. 5150MHz~5350MHz is for indoor use only.

(*1: for 2.4GHz WLAN model; *2: for 5GHz WLAN model)

This product is designed for DSL and 2.4GHz /5GHz WLAN network .

throughout the EC region

UK CA Declaration of Conformity

Hereby, DrayTek Corporation declares that the radio equipment type Vigor2765 series router is in compliance with Regulation SI 2017 No. 1206.


Manufacturer: DrayTek Corp.

Address: No. 26, Fushing Rd., Hukou, Hsinchu Industrial Park, Hsinchu 303, Taiwan

Product: Vigor2765 Wireless Series

Importer: CMS Distribution Ltd: Bohola Road, Kiltimagh, Co Mayo, Ireland

Frequency Information for UK area:

2.4GHz WLAN	For ac model, 2400MHz – 2483MHz, max. TX power: 19.79dBm *1For ax model, 2400MHz – 2483MHz, max. TX power: 19.81dBm *1
5GHz WLAN	For ac model, 5150MHz – 5350MHz, max. TX power: 22.74dBm *2 5470MHz – 5725MHz, max. TX power: 29.88dBm *2 For ax model, 5150MHz – 5350MHz, max. TX power: 22.70dBm *2 5470MHz – 5725MHz, max. TX power: 29.47dBm *2
	Requirements in UK. 5150MHz~5350MHz is for indoor use only.

(*1: for 2.4GHz WLAN model; *2: for 5GHz WLAN model)

This product is designed for DSL and 2.4GHz /5GHz WLAN network use in the UK & Ireland.

Federal Communication Commission Interference Statement.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference, and
2. This device may accept any interference received, including interference that may cause undesired operation.

RF Exposure Warning

This equipment must be installed and operated in accordance with provided instructions and the antenna(s) used for this transmitter must be installed to provide a separation distance of at least 20 cm from all persons and must not be co-located or operating in conjunction with any other antenna or transmitter. End-users and installers must be provided with antenna installation instructions and transmitter operating conditions for satisfying RF exposure compliance.

USA Local Representative	Company name	ABP International Inc.		
	Address	13988 Diplomat Drive Suite 180 Dallas TX 75234		
	ZIP Code	75234	E-mail	rmesser@abptech.com
	Contact Person	Mr. Robert Messer	Tel.	19728311600

Caution

Any changes or modifications not expressly approved by the grantee of this device could void the user's authority to operate the equipment.

The antenna/transmitter should be kept at least 20 cm away from human body.



More update, please visit www.draytek.com.

*The external power supply used for each product will be model dependent

		1	2	3	4	5	6	7	8	9
A	Manufacturer	CWT	CWT	CWT	CWT	CWT	APD	APD	APD	APD
B	Address	No. 222 , Sec.2, Nankan Rd., Luj hu Township, Taoyuan County 338, Taiwan	No. 222 , Sec.2, Nankan Rd., Luj hu Township, Taoyuan County 338, Taiwan	No. 222 , Sec.2, Nankan Rd., Luj hu Township, Taoyuan County 338, Taiwan	No. 222 , Sec.2, Nankan Rd., Luj hu Township, Taoyuan County 338, Taiwan	No. 222 , Sec.2, Nankan Rd., Luj hu Township, Taoyuan County 338, Taiwan	No.5, Lane 83, Lung-Sou St., Taoyuan City 330, Taiwan	No.5, Lane 83, Lung-Sou St., Taoyuan City 330, Taiwan	No.5, Lane 83, Lung-Sou St., Taoyuan City 330, Taiwan	No.5, Lane 83, Lung-Sou St., Taoyuan City 330, Taiwan
C	Model identifier	2ABB012F UK	2ABB018F UK	2ABL024F UK	2ABL030F UK	2ABN036F UK	WA-12M12FG	WB-18D12FG	WA-24Q12FG	WA-36A12FG
		2ABB012F EU	2ABB018F EU	2ABL024F EU	2ABL030F EU	2ABN036F EU	WA-12M12FK	WB-18D12FK	WA-24Q12FK	WA-36A12FK
D	Input voltage	100~240V	100~240V	100~240V	100~240V	100~240V	100~240V	100~240V	100~240V	100~240V
E	Input AC frequency	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz
	Output voltage DC	12.0V	12.0V	12.0V	12.0V	12.0V	12.0V	12.0V	12.0V	12.0V
F	Output current	1.0A	1.5A	2.0A	2.5A	3.0A	1.0A	1.5A	2.0A	3.0A
G	Output power	12.0W	18.0W	24.0W	30.0W	36.0W	12.0W	18.0W	24.0W	36.0W
H	Average active efficiency	84.9%	86.2%	87.6%	87.8%	89.8%	83.7%	85.4%	88.6%	88.2%
I	Efficiency at low load10%	73.6%	78.0%	81.3%	83.3%	83.7%	74.5%	80.5%	86.4%	85.4%
J	No-load power consumption	0.07W	0.07W	0.07W	0.07W	0.07W	0.07W	0.10W	0.07W	0.10W

External power supply (Power Adapter) information. For more update, please visit www.draytek.com.


Package Content

Take a look at the package content. If there is anything missed or damaged, please contact DrayTek or dealer immediately.


Vigor router ac series & ax series




Quick Start Guide, Antenna



RJ-45 Cable (Ethernet)



RJ-11 to RJ-11 Cable (Annex A)



RJ-11 to RJ-45 Cable (Annex B)




RJ-45 to RJ-45 Cable (Annex B)




The type of the power adapter depends on the country that the router will be installed. * The maximum power consumption is **17-23 Watt**.


UK-type Power Adapter




EU-type Power Adapter



USA/Taiwan-type Power Adapter



AU/NZ-type Power Adapter













Note Remove the protective film from the router before use to ensure ventilation.

Panel Explanation

Vigor2765ac






LED	Status		Explanation
 (Activity)	Blinking		The router is powered on and running normally.
	Off		The router is powered off.
 (DSL)	Orange	On	The DSL link up, waiting for the Internet connection.
		Blinking	Slowly – The DSL connection is ready for training. Quickly – The DSL connection is synchronizing.
	Green	On	The router is ready to access to the Internet through DSL link.
		Blinking	The data is transmitting.
 (Wireless LAN On/Off/WPS)	On (Green)		The wireless access point is ready.
	Blinking (Green)		The data is transmitting via wireless connection based on the rate of 2.4GHz.
	Blinking (Orange)		Blinks with one second cycle for two minutes. The WPS function is active.
	Off		The wireless access point is turned off.
 (Wireless LAN On/Off/WPS)	On (Green)		The wireless access point is ready.
	Blinking (Green)		The data is transmitting via wireless connection based on the rate of 5GHz.
	Blinking (Orange)		Blinks with one second cycle for two minutes. The WPS function is active.
 (LAN1/2/3/4)	On		The LAN port is connected.
	Blinking		The data is transmitting.
	Off		The LAN port is disconnected.
 (USB)	On		A USB device is connected and active.
	Blinking		The data is transmitting.










Interface	Description
WLAN ON/OFF/WPS	WLAN On – Press the button and release it within 2 seconds. When the wireless function is ready, the green LED will be on. WLAN Off – Press the button and release it within 2 seconds to turn off the WLAN function. When the wireless function is not ready, the LED will be off. WPS – When WPS function is enabled by web user interface, press this button for more than 2 seconds to wait for client's device making network connection through WPS.
Factory Reset	Restore the default settings. Usage: Turn on the router (ACT LED is blinking). Press the hole and keep for more than 5 seconds. When you see the ACT LED begins to blink rapidly than usual, release the button. Then the router will restart with the factory default configuration.
USB1~USB2	Connector for a USB device (for 3G/4G USB Modem or printer).
P1~P4	Connectors for local networked devices.
DSL	Connector for accessing the Internet.
I/O	Power Switch.
PWR	Connector for a power adapter.

Vigor2765Vac




LED	Status	Explanation
 (Activity)	Blinking	The router is powered on and running normally.
	Off	The router is powered off.
 (DSL)	Orange	On The DSL link up, waiting for the Internet connection.
		Blinking Slowly – The DSL connection is ready for training. Quickly – The DSL connection is synchronizing.
	Green	On The router is ready to access to the Internet through DSL link.
		Blinking The data is transmitting.
	On	The phone connected to this port is off-hook.





 	Off	The phone connected to this port is on-hook.
	Blinking	A phone call comes.
 (Wireless LAN On/Off/WPS)	On (Green)	The wireless access point is ready.
	Blinking (Green)	The data is transmitting via wireless connection based on the rate of 2.4GHz.
	Blinking (Orange)	Blinks with one second cycle for two minutes. The WPS function is active.
	Off	The wireless access point is turned off.
 (Wireless LAN On/Off/WPS)	On (Green)	The wireless access point is ready.
	Blinking (Green)	The data is transmitting via wireless connection based on the rate of 5GHz.
	Blinking (Orange)	Blinks with one second cycle for two minutes. The WPS function is active.
 ~LAN1/2/3/4)	On	The LAN port is connected.
	Blinking	The data is transmitting.
	Off	The LAN port is disconnected.
 (USB)	On	A USB device is connected and active.
	Blinking	The data is transmitting.










Interface	Description
WLAN ON/OFF/WPS	WLAN On – Press the button and release it within 2 seconds. When the wireless function is ready, the green LED will be on. WLAN Off – Press the button and release it within 2 seconds to turn off the WLAN function. When the wireless function is not ready, the LED will be off. WPS – When WPS function is enabled by web user interface, press this button for more than 2 seconds to wait for client's device making network connection through WPS.
Factory Reset	Restore the default settings. Usage: Turn on the router (ACT LED is blinking). Press the hole and keep for more than 5 seconds. When you see the ACT LED begins to blink rapidly than usual, release the button. Then the router will restart with the factory default configuration.
USB1~USB2	Connector for a USB device (for 3G/4G USB Modem or printer).
P1~P4	Connectors for local networked devices.
DSL	Connector for accessing the Internet.
Phone2/Phone1	Connector of analog phone for VoIP communication.
I/O	Power Switch.
PWR	Connector for a power adapter.

Vigor2765ax



LED	Status		Explanation
 ACT	Off		The system is not ready or is failed.
	Blinking		The system is ready and can work normally.
	Blinking with WLAN		WPS is enabled and waiting for the response from the wireless client.
 SL	Orange	On	The DSL link up, waiting for the Internet connection.Slowly – The DSL connection is ready for training.Quickly – The DSL connection is synchronizing.
		Blinking	
	Green	On	The router is ready to access to the Internet through DSL link. The data is transmitting.
		Blinking	
 WLAN	Off		Wireless function is not ready.
	On		Wireless function is ready.
	Blinking		Data is transmitting (sending/receiving).
	Blinking with WLAN		WPS is enabled and waiting for the response from the wireless client.
 USB	On		A USB device is connected and active.
	Blinking		The data is transmitting.

	Interface	Description
	WLAN ON/OFF WPS	Wireless band will be switched /changed according to the button pressed and released. For example, 2.4G (On) and 5G (On) – in default. 2.4G (Off) and 5G (On) – pressed and released the button once. 2.4G (On) and 5G (Off) – pressed and released the button twice. 2.4G (Off) and 5G (Off) – pressed and released the button three times.WPS – When WPS function is enabled by web user interface, press this button for more than 2seconds. The router will wait for any wireless client connecting to it through WPS.
		Power switch.
	 PWR	PWR: Connector for a power adapter.


	 LAN P4-P1	Connectors for local network devices. Left LED on – The port is connected. Left LED off – The port is disconnected. Left LED Blinking – The data is transmitting. Right LED on -The port is connected with 1000Mbps. Right LED off – The port is connected with 10/100 Mbps.
	 DSL	Connector for accessing the Internet.
	 USB	Connector for USB devices (for 3G/4G USB Modem or printer).
	Factory Reset	Restore the default settings. Usage: Turn on the router. Press the button and keep for more than 10 seconds. Then the router will restart with the factory default configuration.

Hardware Installation

This section will guide you to install the router through hardware connection and configure the router's settings through web browser. Before starting to configure the router, you have to connect your devices correctly.

Network Connection for ac series


1. Connect the DSL interface to the land line jack with a DSL line cable.
2. Connect one port of 4-port switch to your computer with a RJ-45 cable. This device allows you to connect 4 PCs directly.
3. Connect detachable antennas to the router.
4. Connect one end of the power cord to the power port of this device. Connect the other end to the wall outlet of electricity.
5. Power on the router.
6. Check the ACT and DSL, LAN LEDs to assure network connection.



(For the detailed information of LED status, please refer to section 2.)

Network Connection for ax series


1. Connect the cable Modem/DSL Modem/Media Converter to any WAN port of router with Ethernet cable (RJ-45).
2. Connect one port of 4-port switch to your computer with a RJ-45 cable. This device allows you to connect 4 PCs directly.
3. Connect one end of the power cord to the power port of this device.
Connect the other end to the wall outlet of electricity.
4. Power on the router.
5. Check the ACT and WAN LEDs to assure network connection.



Wall-Mounted Installation for ac series

Vigor router has keyhole type mounting slots on the underside.

1. Drill two holes on the wall. The distance between the holes shall be 168mm.
2. Fit screws into the wall using the appropriate type of wall plug.
3. With the screws installed, the router can be slotted into place.




Note The recommended drill diameter shall be 6.5mm (1/4").

4. When you finished about procedure, the router has been mounted on the wall firmly.

Wall-Mounted Installation for ax series

Vigor router has keyhole type mounting slots on the underside.

1. Drill two holes on the wall. The distance between the holes shall be 100.75mm. The recommended drill diameter shall be 6.5mm (1/4").
2. Fit screws into the wall using the appropriate type of screw plug.
3. Hang the Vigor router directly onto the screws.



Software Configuration

To access Internet, please finish basic configuration after completing the hardware installation.

The **Quick Start Wizard** is designed for you to easily set up your router for Internet access. You can directly

access the **Quick Start Wizard** via Web Configurator.

Make sure your PC connects to the router correctly.



Note You may either simply set up your computer to get IP dynamically from the router or set up the IP address of the computer to be the same subnet as the default IP address of Vigor router 192.168.1.1. For the detailed information, please refer to the section – Trouble Shooting in the User's Guide.

Open a web browser on your PC and type <http://192.168.1.1>. A pop-up window will open to ask for username and password. Please type “admin/admin” as the Username/Password and click Login. Here, we take Vigor2765 series as an example.

The login page for the DrayTek Vigor2765 Series features a red header with the brand name and model. Below this is a black 'Login' button. The main area contains two input fields: 'Username' with 'admin' entered and 'Password' with masked characters. A 'Login' button is positioned below the password field. A security warning message is displayed, advising that logging in without encryption is not recommended and providing a link to learn more. The footer contains the copyright notice for DrayTek Corp.

DrayTek Vigor2765 Series

Login

Username: admin

Password:

Login

Security Warning: You are logging in without encryption which is not recommended. To login securely [click here](#).

Copyright© 2000-2022 DrayTek Corp. All Rights Reserved.

Now, the **Main Screen** will pop up. Click **Wizards>>Quick Start Wizard**.

The main screen dashboard provides a comprehensive overview of the router's status. It includes a top navigation bar, a left sidebar with various management tools, and a central area with multiple data tables. The 'System Information' table shows basic router details. The 'IPv4 LAN Information' table lists network interfaces and their configurations. The 'IPv4 Internet Access' table details connection methods and status. The 'Interface' table shows the physical and logical state of various ports. The 'Security' table provides an overview of security features. The 'Quick Access' and 'Certificate Status' sections offer additional configuration options and alerts.

DrayTek Vigor2765 Series

Dashboard

System Information

Item	Value
Host Name	Vigor2765-06
Router Name	DrayTek
Firmware Version	4.2.2-STD
OS Version	10.5B-00-SP-00-07
System Uptime	00:20:22
Current Time	Sat Jan 01 2000 00:20:20
Build Date/Time	May 17 2022 11:05:29
LAN MAC Address	100:10:AA:10:80:C8

IPv4 LAN Information

Interface	IP Address	Mask	Gateway	Static IP
LAN1	192.168.1.1	255.255.255.0	192.168.1.1	Static
LAN2	192.168.1.2	255.255.255.0	192.168.1.1	Static
LAN3	192.168.1.3	255.255.255.0	192.168.1.1	Static

IPv4 Internet Access

Line / Mode	IP Address	MAC Address	Up Time
WAN1 (VDSL2 / Bridge)	Disconnected	00:10:AA:10:80:C8	00:00:00
WAN2 (Ethernet)	Disconnected	00:10:AA:10:80:C8	00:00:00
WAN3 (USB)	Disconnected	00:10:AA:10:80:C8	00:00:00

Interface

Interface	Line / Mode	Up / Down	Speed
WAN1	Connected	0 / 0	100Mbps
LAN1	Connected	0 / 0	100Mbps
LAN2	Connected	0 / 0	100Mbps
LAN3	Connected	0 / 0	100Mbps
USB	Connected	0 / 0	100Mbps

Security

Feature	Status
VPN	Connected
VPN	Connected
VPN	Connected
VPN	Connected

Quick Access

- System Settings
- Dynamic DNS
- TR-069
- User Management
- IMPP Block
- Schedule
- System / Mail Alert
- RADIUS
- Forward Object Setting
- Data Flow Monitor

Certificate Status

- Expired (0)
- Expire within 30 days (0)
- Unknown (0)
- OK (0)
- Not Valid Yet (0)



Note The home page will change slightly in accordance with the router you have.

The first screen of Quick Start Wizard is entering login password. After typing the password, please click Next.

Enter login password

Please enter an alpha-numeric string as your **Password** (Max 83 characters)

Old Password

New Password

Confirm Password

Password Strength: Weak Medium Strong

Strong password requirements:

1. Have at least one upper-case letter and one lower-case letter.
2. Including non-alphanumeric characters is a plus.

Hint: If you want to keep the password unchanged, leave the password blank and press "Next" button to skip this process.

[< Back](#) [Next >](#) [Finish](#) [Cancel](#)

On the next page as shown below, please select the WAN interface that you use. If DSL interface is used, please choose WAN1; if Ethernet interface is used, please choose WAN2; if 3G USB modem is used, please choose WAN3. Then click Next for next step. WAN1, WAN2 and WAN3 will bring up different configuration page. Here, we take WAN1 (ADSL/VDSL2) as an example.

Select WAN Interface

Select WAN Interface:

Display Name:

Physical Mode: **ADSL / VDSL2**

DSL Mode:

Physical Type:

VLAN Tag insertion(ADSL):

Tag value (0~4095)

Priority (0~7)

VLAN Tag insertion (VDSL2) :

Tag value (0~4095)

Priority (0~7)

[< Back](#) [Next >](#) [Finish](#) [Cancel](#)

On the next page as shown below, please select the appropriate protocol according to the information from your ISP. For example, you should select PPPoE mode if the ISP provides you PPPoE interface. Then click Next for next step.

PPPoE/PPPoA

1. Choose **WAN1** as WAN Interface and click the **Next** button; you will get the following page.

Quick Start Wizard

Connect to Internet

WAN 1	
Protocol	PPPoE / PPPoA
For ADSL Only:	
Encapsulation	PPPoE LLC/SNAP
VPI	0 Auto detect
VCI	33
Fixed IP	<input type="radio"/> Yes <input checked="" type="radio"/> No(Dynamic IP)
IP Address	
Subnet Mask	
Default Gateway	
Primary DNS	8.8.8.8
Second DNS	8.8.4.4

< Back Next > Finish Cancel

2. After finished the above settings, simply click **Next**.

Quick Start Wizard

Set PPPoE / PPPoA

WAN 1	
Service Name (Optional)	2765
Username	84005755@hinet.net
Password	••••••••
Confirm Password	••••••••

< Back Next > Finish Cancel

3. Please manually enter the Username/Password provided by your ISP. Then click **Next** for viewing summary of such connection.

Quick Start Wizard

Please confirm your settings:

WAN Interface:	WAN1
Physical Mode:	ADSL / VDSL2
VPI:	1
VCI:	32
Protocol / Encapsulation:	PPPoE / LLC
Fixed IP:	No
Primary DNS:	8.8.8.8
Secondary DNS:	8.8.4.4

< Back Next > Finish Cancel

4. Click **Finish**. A page of **Quick Start Wizard Setup OK!!!** will appear. Then, the system status of this protocol will be shown.
5. Now, you can enjoy surfing on the Internet.

MPoA / Static or Dynamic IP

1. Choose WAN1 as WAN Interface and click the Next button; you will get the following page.

Quick Start Wizard

Connect to Internet

WAN 1	
Protocol	PPPoE / PPPoA
For ADSL Only:	
Encapsulation	PPPoE LLC/SNAP
VPI	0 Auto detect
VCI	33
Fixed IP	<input type="radio"/> Yes <input checked="" type="radio"/> No(Dynamic IP)
IP Address	
Subnet Mask	
Default Gateway	
Primary DNS	8.8.8.8
Second DNS	8.8.4.4

< Back Next > Finish Cancel

2. Please type in the IP address/mask/gateway information originally provided by your ISP. Then click **Next** for viewing summary of such connection.

Quick Start Wizard

Connect to Internet

WAN 1	
Protocol	MPoA / Static or Dynamic IP
For ADSL Only:	
Encapsulation	1483 Bridged IP LLC
VPI	0 Auto detect
VCI	33
Fixed IP	<input type="radio"/> Yes <input checked="" type="radio"/> No(Dynamic IP)
IP Address	
Subnet Mask	
Default Gateway	
Primary DNS	8.8.8.8
Second DNS	8.8.4.4

< Back Next > Finish Cancel

3. Click Finish. A page of Quick Start Wizard Setup OK!!! will appear. Then, the system status of this protocol will be shown.
4. Now, you can enjoy surfing on the Internet.

Customer Service

If the router cannot work correctly after trying many efforts, please contact your dealer/DrayTek for further help right away. For any questions, please feel free to send e-mail to "support@draytek.com".




Be a Registered Owner

Web registration is preferred. You can register your Vigor router via <https://myvigor.draytek.com>

Firmware & Tools Updates

Due to the continuous evolution of DrayTek technology, all routers will be regularly upgraded. Please consult the DrayTek web site for more information on newest firmware, tools and documents. <https://www.draytek.com>

Documents / Resources

	<p>DrayTek Vigor2765 Series 35b Security Router [pdf] User Guide Vigor2765 Series 35b Security Router, Vigor2765 Series, 35b Security Router, Security Router, Router</p>
	<p>DrayTek Vigor2765 Series 35b Security Router [pdf] User Guide Vigor2765 Series 35b Security Router, Vigor2765 Series, 35b Security Router, Security Router, Router</p>
	<p>DrayTek Vigor2765 Series 35b Security Router [pdf] User Guide Vigor2765 Series 35b Security Router, Vigor2765 Series, Vigor2765 Series Security Router, 35 b Security Router, Security Router, 35b Router, Router</p>

References

- [🏠 Home | DrayTek](#)
- [📄 Index of /](#)
- [📄 Index of /Vigor2765/Document/CE](#)
- [📄 MyVigor - DrayTek](#)
- [🏠 Home | DrayTek](#)