



e2S IS-mC1 Intrinsically Safe Round Combined Unit Instruction Manual

[Home](#) » [e2S](#) » e2S IS-mC1 Intrinsically Safe Round Combined Unit Instruction Manual 

Contents

- [1 IS-mC1 Intrinsically Safe Round Combined Unit](#)
- [2 IS-mC1 Minialert Intrinsically Safe Round Combined Unit](#)
- [3 Product Information](#)
- [4 Product Usage Instructions](#)
- [5 Introduction](#)
- [6 Description](#)
- [7 Intrinsic Safety Certification](#)
- [8 Electrical System Design For Installation In](#)
- [9 Electrical System Design For Installation In Hazardous Areas Using Galvanic Isolators](#)
- [10 IECEX Approval](#)
- [11 EU Declaration of Conformity](#)
- [12 UKCA Declaration of Conformity](#)
- [13 Documents / Resources](#)
 - [13.1 References](#)
- [14 Related Posts](#)



IS-mC1 Intrinsically Safe Round Combined Unit



IS-mC1 Minialert Intrinsically Safe Round Combined Unit

The IS-mC1 is a combined unit that includes a sounder section and a tone generator. The sounder section has a volume control and tone selection switches for customization of the sound output. The unit is CE marked for compliance with European Explosive Atmospheres and EMC Directives. It is also certified with ATEX standards.

Product Information

- Simplified block diagram – see Fig 1 in user manual
- Complies with standards: EN IEC 60079-0:2018, EN60079-11:2012, IEC60079-26:2014
- CE marked for compliance with European Explosive Atmospheres and EMC Directives
- Certified with ATEX standards

Product Usage Instructions

1. Make sure the unit is installed in a safe, intrinsically safe location before use.
2. To adjust the volume, use the + and – buttons labeled S2 on the sounder section.
3. To select a tone, use the tone selection switches labeled S3 on the sounder section.
4. Refer to the user manual for further customization options and safety information.

Introduction

The IS-mC1 minimalist is an ATEX, IECEx and UKEX certified intrinsically safe combined sounder/beacon unit which produces both a loud audio warning and a visual warning and can be installed in a hazardous area. The sounder section has forty-nine first stage alarm sounds that can be selected by internal switches and each one can be externally changed to a second or third stage alarm sound. The beacon section can be set internally for a flash rate of either 1Hz or 2Hz. The combined unit sounder and beacon can be operated simultaneously from one barrier or from separate barriers if independent operation is required. The IS-mC1 Combined Unit can be used in all gas groups IIA IIB and IIC.


Description

Fig 1 shows a simplified block diagram of an IS-mC1 minimalist sounder section. The device operates immediately power is applied to the sounder + and – terminals which are duplicated to allow a second sounder to

be connected in parallel, or for an end of line monitoring resistor to be installed. The output tone is defined by the positions of the six internal switches and this tone can be changed to a second or third stage alarm tone by connecting terminals S2 or S3 to 0V. The tone generator is crystal controlled to ensure that when two sounders connected to the same power supply are started at the same time the output tones remain synchronized.

Supply Voltage

The IS-mC1 minimalist unit has been designed to operate in a hazardous area from a 24V dc supply via 28V 93mA resistive ATEX and IECEx certified Zener Barriers or Galvanic Isolators. The unit may be tested or used in safe areas without a Zener Barrier or Galvanic Isolator, but at supply voltages above 16V the internal current limit will function and therefore it is recommended that they are not operated continuously with a direct supply greater than 16V.



Intrinsic Safety Certification

ATEX certificate

The IS-mC1 combined minimalist unit complies with the following standards:-

EN IEC 60079-0:2018

EN60079-11:2012


IEC60079-26:2014



II 1G Ex ia IIC T4 Ga (-40°C ≤ Ta ≤ +60°C)

The EC-Type Examination Certificate SIRA 05ATEX2084X has been issued by the Notified Body Sira. This confirms compliance with the European ATEX Directive 2014/34/EU for Group II, Category 1G equipment. The sounder carries the Community Mark and subject to local codes of practice, may be installed in any of the EEA member countries. This instruction sheet describes installations which conform to EN60079:Part14:2008 Electrical Installation in Hazardous Areas. When designing systems for installation outside the UK, the local Code of Practice should be consulted.

1. The certification marking is as follows:



2. The equipment may be used in zones 0, 1 and 2 with flammable gases and vapors with apparatus groups IIA, IIB & IIC and with temperature classes T1, T2, T3 and T4.
3. The equipment is only certified for use in ambient temperatures in the range -40°C to +60°C and should not be used outside this range.
4. The certificate number has an 'X' suffix, which indicates that the certificate contains one of more special conditions for safe use. Those installing or inspecting the equipment should refer to this section of the certificate.
5. The equipment has not been assessed as a safety-related device (as referred to by Directive 2014/34/EU Annex II, clause 1.5).
6. Installation of this equipment shall be carried out by suitably-trained personnel in accordance with the applicable code of practice.
7. Repair of this equipment shall only be carried out by the manufacturer or in accordance with the applicable code of practice.
8. The certification of this equipment relies on the following materials used in its construction:

Enclosure: ABS Plastic

Lens: Polycarbonate

If the equipment is likely to come into contact with aggressive substances, then it is the responsibility of the user to take suitable precautions that prevent it from being adversely affected, thus ensuring that the type of protection is not compromised.

"Aggressive substances" – e.g. acidic liquids or gases that may attack metals, or solvents that may affect polymeric materials.

"Suitable precautions" – e.g. regular checks as part of routine inspections or establishing from the material's data sheet that it is resistant to specific chemicals.

SPECIAL CONDITIONS FOR SAFE USE (as stated in the EC Type Examination Certificate SIRA 05ATEX2084X)

Conditions for IS-mC1 Combined Sounder / Beacon

The equipment has an ingress protection rating of IP65. However, if it has been supplied without cable entry devices, then the user shall ensure that the devices that are fitted will provide an ingress protection that is appropriate to the environment in which it is installed i.e. IP20 or better. If only one of the two cable entries are used, then the unused entry 'knockout' shall be left intact or fitted with a blanking device that ensures ingress protection appropriate to the environment in which it is installed i.e. IP20 or better.

The total capacitance connected to sounder terminals + wrt – (i.e. the capacitance of the cable plus any other capacitance) shall not exceed 83nF.

The enclosure is non-conducting and may generate an ignition-capable level of electrostatic charges under certain extreme conditions. The user should ensure that the equipment is not installed in a location where it may be subjected to external conditions that might cause a build-up of electrostatic charges on non-conducting surfaces, additionally, cleaning of the equipment should be done only with a damp cloth.

The equipment shall only be supplied via Sounder Terminals + w.r.t. Sounder Terminals – from a barrier having a maximum open circuit voltage U_o that is $< 28V$ and a maximum short circuit current I_o that is $< 93mA$, where I_o is resistively limited. The barrier shall be ATEX certified by a notified body.

If not already fitted optional internal wiring connections between Sounder Terminals + / – and Beacon Terminals + / – may be fitted by the user. The wiring used for such connections shall have a minimum radial thickness of insulation of 0.5mm.

Zones, Gas Groups and Temperature Classification

The IS-mC1 minialert unit has been certified Ex ia IIC T4 Ga. When connected to an approved system it may be installed in:

- **Zone 0** explosive gas air mixture continuously present.
- **Zone 1** explosive gas air mixture likely to occur in normal operation.
- **Zone 2** explosive gas air mixture not likely to occur, and if it does, it will only exist for a short time.

Be used with gases in groups:

- Group A propane
- Group B ethylene
- Group C hydrogen

Having a temperature classification of:

- T1 450°C
- T2 300°C
- T3 200°C
- T4 135°C

Sounder + and – Terminals

Power is supplied to the sounder section via the sounder input terminals + and – on the sounder PCB (see Fig 2) and the terminals have the following input safety parameters:

- $U_i = 28V$
- $I_i = 93mA$
- $P_i = 660mW$
- $C_i = 0$
- $L_i = 0$

The IS-mC1 combined sounder section may be powered from an ATEX certified Zener barrier or galvanic isolator which have output parameters equal to or less than 28V, 93mA and 660mW, where I_o is resistively limited. The cable parameters stated on the selected Zener barrier or galvanic isolator certificate must be observed.

Sounder S2 and S3 Terminals

When terminals S2 or S3 are connected to 0V (- terminal) the sounder output tone changes to the second or third stage alarm respectively. The input safety parameters for these terminals are:

- $U_i = 28V$
- $I_i = 0mA$

Because the permitted input current is zero, these terminals may only be connected to a diode return barrier, an intrinsically safe relay or a galvanic isolator, all of which must have been certified by an EC Notified Body. Only diode return barriers with a voltage drop of less than 0.9V may be used. Alternatively, these terminals may be connected directly to a mechanically activated switch within the hazardous area.

Beacon + and – Terminals

Power is supplied to the beacon section via the beacon input terminals + and – on the beacon PCB (see Fig 2) and the terminals have the following input safety parameters:

- $U_i = 28V$
- $I_i = 660mA$
- $P_i = 1.2W$
- $C_i = 0$
- $L_i = 0$

The IS-mC1 combined beacon section may be powered from any 28V, 660mA 1.2W ATEX certified Zener barrier or galvanic isolator. The cable parameters stated on the selected Zener barrier or galvanic isolator certificate must be observed.




Fig 2: Location of field terminals and controls.

Other intrinsic safety certifications

Please contact European Safety Systems Ltd. for details of non-European intrinsic safety approvals.

Installation

The IS-mC1 minialert combined unit should only be installed by trained competent personnel.

Mounting

The IS-mC1 minialert combined unit may be secured to any flat surface by inserting two mounting screws through the back of the round base (see figure 3). The enclosure provides IP65 protection and is suitable for installation in exterior locations provided that the area around the two mounting screws through the back of the base molding has been sealed and that suitable cable glands with the required IP rating have been used.

Installation procedure

- Unscrew the combined unit security screw and remove the sounder/beacon section from the base by turning it anti-clockwise. Ensure that the 'O' ring seal remains in place.
- Remove the required 20mm knockout section(s) depending on system wiring and mount the base to a flat surface by inserting two screws through the back of the base.
- Fit the required number of 20mm cable glands or conduit entries into the base and connect the field wiring to the appropriate sounder terminals as shown in section 6 and fig 2 of this manual. The power supply terminals + and – are duplicated so that sounders may be connected in parallel, or an end of line monitoring resistor may be fitted.
- Select the required sounder output tone by positioning the six switches as shown in Table 1 and Fig 2.
- Apply power to the sounder and adjust the internal volume control to provide the required sound level.
- Check that the 'O' ring seal is correctly located on the sounder/beacon section (see Fig. 2) and insert the sounder/beacon section into the base. Push it fully home and turn it clockwise to align the moldings before tightening the security screw.




Fig 3: Mounting Combined Unit Base.

Electrical System Design For Installation In

Hazardous Areas Using Zener Barriers

Sounder single stage alarm

If the control switch is in the positive supply, or the power supply is being turned on and off, only a single channel Zener barrier is required as shown in Fig 4. This circuit may also be used if the sounder is being controlled by a mechanically activated switch on the hazardous area side of the barrier.




Fig 4: Sounder single stage alarm using single channel barrier.

If the control switch must be in the negative supply, the circuit shown in Fig 5 may be used. Any diode return barrier certified Ex ia by a EC Notified Body may be used, providing its voltage drop is less than 0.9V.




Fig 5: Sounder single stage alarm using two channel barrier.

Sounder multi-stage alarm

Connecting terminal S2 to 0V activates the second stage alarm, and similarly terminal S3 for the third stage alarm. Fig 6 shows how the diode return barriers may be used. If only two stages of alarm are required the third stage barrier should be omitted, the 28V 93mA barrier and the single diode return channel may then be contained in one package.




Fig 6: Sounder multi stage alarm using Zener barriers.

Beacon operation

The beacon can be operated from the same Zener barrier being used to power the sounder (see Fig 7) or from a separate barrier if the sounder and beacon need to operate independently (see Fig 8). A Diode return barrier can be used if the sounder second and third stage tones are required.

NOTE: If the beacon is operated from the same barrier as the sounder then the sounder and beacon boards must be connected together as shown in Fig 7 using connecting wires that have a minimum radial thickness of insulation of 0.5mm. Also the barrier used must meet the requirements for the sounder section (see section 4.3).




Fig 7: Combined Unit wired for simultaneous operation using one Zener barrier.




Fig 8 Combined Unit wired for independent operation using separate Zener barriers.

Electrical System Design For Installation In Hazardous Areas Using Galvanic Isolators

Galvanic isolators do not require a high integrity earth connection. For small systems where a high integrity earth is not already available, the use of galvanic isolators often reduces the overall installation cost and simplifies design.

Sounder single stage alarm

The IS-mC1 minialert combined unit may be powered by any galvanic isolator having output parameters within the limits specified in section 4.3, which has been certified Ex ia by an EC Notified Body. The combined unit may be controlled by turning the galvanic isolator on and off, or by a mechanically activated switch on the hazardous area side of the isolator.




Fig 9 Sounder single stage alarm using galvanic isolator.

Beacon operation

The beacon can be operated from the same isolator being used to power the sounder (see Fig 10) or from a separate isolator if the sounder and beacon need to operate independently (see Fig 11).

NOTE: If the beacon is operated from the same isolator as the sounder then the sounder and beacon boards must be connected together as shown in Fig 11 using connecting wires that have a minimum radial thickness of insulation of 0.5mm. Also the isolator used must meet the requirements for the sounder section (see section 4.3).

Tone Number	Tone Description	Switch Settings 1 2 3 4 5 6	Second Stage Alarm	Third Stage alarm
Tone 1		0 0 0 0 0 0	Tone 2	Tone 5
Tone 2		1 0 0 0 0 0	Tone 17	Tone 5
Tone 3		0 1 0 0 0 0	Tone 2	Tone 5
Tone 4		1 1 0 0 0 0	Tone 6	Tone 5
Tone 5		0 0 1 0 0 0	Tone 3	Tone 20
Tone 6		1 0 1 0 0 0	Tone 7	Tone 5
Tone 7		0 1 1 0 0 0	Tone 10	Tone 5
Tone 8		1 1 1 0 0 0	Tone 2	Tone 5
Tone 9	Continuous 340Hz	0 0 0 1 0 0	Tone 15	Tone 2
Tone 10	Alternating 800/1000Hz @ 0.25s intervals	1 0 0 1 0 0	Tone 7	Tone 5
Tone 11	Slow whoop 500/1200Hz @ 0.3Hz with 0.5s gap repeated Sw	0 1 0 1 0 0	Tone 2	Tone 5

Tone 12	beeping 500/1000Hz @ 1Hz	1 1 0 1 0 0	Tone 4	Tone 5
Tone 13	Continuous 2400Hz	0 0 1 1 0 0	Tone 15	Tone 5
Tone 14	Sweeping 2400/2900Hz @ 7Hz Sweeping 2400/2900Hz @ 1 Hz Siren 500/1200/500Hz @ 0.3Hz	1 0 1 1 0 0	Tone 4	Tone 5
Tone 15	Sawtooth 1200/500Hz @ 1Hz – <i>D.I.N.</i> Alternating 2400/2900	0 1 1 1 0 0	Tone 2	Tone 5
Tone 16	Hz @ 2Hz Intermittent 1000Hz @ 1Hz Alternating 800/1000H	1 1 1 1 0 0	Tone 18	Tone 5
Tone 17	z @ 0.875Hz Intermittent 2400Hz @ 1Hz Intermittent 800Hz 0.25s ON, 1s OFF Continuous 800Hz	0 0 0 0 1 0	Tone 2	Tone 27
Tone 18	Intermittent 660Hz 150Ns ON, 150ms OFF	1 0 0 0 1 0	Tone 2	Tone 5
Tone 19	<i>Alternating 544Hz (100ms) / 440Hz (400ms) – NFS 32-001</i>	0 1 0 0 1 0	Tone 2	Tone 5
Tone 20	Intermittent 660Hz 1.8s ON, 1.8s OFF	1 1 0 0 1 0	Tone 2	Tone 5
Tone 21	Sweep 1400Hz to 1600Hz up 1s 1600Hz to 1400Hz down 0.5s	0 0 1 0 1 0	Tone 2	Tone 5
Tone 22	Continuous 660Hz	1 0 1 0 1 0	Tone 2	Tone 5
Tone 23	Alternating 554/440Hz @ 1Hz Intermittent 544Hz @ 0.875Hz	0 1 1 0 1 0	Tone 6	Tone 5
Tone 24	Intermittent 800Hz @ 2Hz Sweeping 800/1000Hz @ 50Hz S	1 1 1 0 1 0	Tone 29	Tone 5
Tone 25	sweeping 2400/2900Hz @ 50Hz Simulated bell	0 0 0 1 1 0	Tone 29	Tone 5
Tone 26	Continuous 554Hz Continuous 440Hz	1 0 0 1 1 0	Tone 2	Tone 15
Tone 27	Sweeping 800/1000Hz @ 7Hz Continuous 300Hz	0 1 0 1 1 0	Tone 26	Tone 5
Tone 28	Sweeping 660/1200 @ 1Hz Two Tone Chime Intermittent 745 Hz	1 1 0 1 1 0	Tone 2	Tone 5
Tone 29	Alternating 1000/2000Hz @ 0.5s – Singapore	0 0 1 1 1 0	Tone 7	Tone 5
Tone 30	420Hz @ 0.625s – Australian Alert	1 0 1 1 1 0	Tone 2	Tone 5
Tone 31	500-1200Hz 3.75s / 0.25s – Australian Evacuate	0 1 1 1 1 0	Tone 26	Tone 5
Tone 32	Continuous 1000Hz Continuous 2000Hz	1 1 1 1 1 0	Tone 26	Tone 15
Tone 33	Intermittent 800Hz 0.25s ON 1s OFF	0 0 0 0 0 1	Tone 2	Tone 5
Tone 34	<i>Alternating 544Hz (100ms) / 440Hz (400ms) – NFS 32-001</i>	1 0 0 0 0 1	Tone 38	Tone 45
Tone 35	Motor Siren – Slow rise to 1200Hz Motor Siren – Slow rise to 800Hz Continuous 1200Hz	0 1 0 0 0 1	Tone 36	Tone 5
Tone 36	Motor Siren – Slow rise to 2400Hz Intermittent 1000Hz 1s ON , 1s OFF	1 1 0 0 0 1	Tone 35	Tone 5
Tone 37	Sawtooth 1200/500Hz @ 1Hz – <i>D.I.N.</i> (PFEER P.T.A.P)	0 0 1 0 0 1	Tone 9	Tone 45
Tone 38	Intermittent 1000Hz 1s ON, 1s OFF – PFEER General Alarm	1 0 1 0 0 1	Tone 34	Tone 45
Tone 39	420Hz @ 0.625s – Australian Alert	0 1 1 0 0 1	Tone 23	Tone 17
Tone 40	500-1200Hz 3.75s / 0.25s – Australian Evacuate	1 1 1 0 0 1	Tone 31	Tone 27
Tone 41		0 0 0 1 0 1	Tone 2	Tone 5
Tone 42		1 0 0 1 0 1	Tone 2	Tone 5
Tone 43		0 1 0 1 0 1	Tone 2	Tone 5
Tone 44		1 1 0 1 0 1	Tone 2	Tone 5
Tone 45			Tone 38	Tone 34

Tone 46	0 0 1 1 0 1	Tone 47	Tone 37
Tone 47	1 0 1 1 0 1	Tone 46	Tone 37
Tone 48	0 1 1 1 0 1	Tone 49	Tone 5
Tone 49	1 1 1 1 0 1	Tone 26	Tone 37
	0 0 0 0 1 1		




Fig 10 Combined Unit wired for simultaneous operation using one isolator.




Fig 11 Combined Unit wired for independent operation using separate isolators

Cable Parameters

The maximum permitted cable parameters are as specified on the certificate of the Zener barrier or galvanic isolator that has been selected for the installation. Normally the limits are not restrictive, but care should be taken not to exceed a capacitive limit of 83nF for installations when very long cables are used.

Volume Control

The output level of the IS-mC1 Combined Sounder / Beacon can be set by adjusting the volume control potentiometer (see Fig 2).

Maintenance

The sounder should be regularly inspected to ensure that it has not been damaged. Frequency of inspection depends upon environmental conditions, but initially we recommend that this should be done annually. No attempt should be made to repair a faulty ISmA1 sounder. Suspect sounders must be returned to European Safety Systems Ltd. or to your local agent for repair.

Guarantee

Sounders that fail within the guarantee period should be returned to European safety Systems Ltd. It is helpful if a brief description of the fault symptoms is provided.

Customer Comments

European Safety Systems Ltd. is always pleased to receive comments from customers about our products and services. All communications are acknowledged and whenever possible, suggestions are implemented.

IECEX Approval

The IS-mC1 Combined Sounder / Beacon has also been approved to the IECEx scheme.

The installation requirements for IS-mC1 combined sounder / beacon approved to the IECEx scheme are the same as the installation requirements for IS-mC1 combined sounder / beacon approved to the ATEX directive.




- Certificate No. IECEx SIR 06.0045X
- Marking: Ex ia IIC T4 Ga (Ta = -40°C to +60°C)

- Standards: IEC 60079-0:2017
IEC 60079-11:2011
IEC 60079-26:2014-10

CONDITIONS OF CERTIFICATION (as stated on the IECEx Certificate of Conformity IECEx SIR 06.0045X)

- The equipment has an ingress protection rating of IP65. However, if it has been supplied without a cable entry device, then the user shall ensure that the devices that are fitted will provide an ingress protection that is appropriate to the environment in which it is installed i.e. IP20 or better. If only one of the two cable entries are used, then the unused entry 'knockout' shall be left intact or fitted with a blanking device that ensures ingress protection appropriate to the environment in which it is installed
i. e. IP20 or better.
- The total capacitance connected to Sounder Terminals + w.r.t. Terminals – (i.e. the capacitance of the cable plus any other capacitance) shall not exceed 83nF.
- The enclosure is non-conducting and may generate an ignition-capable level of electrostatic charges under certain extreme conditions. The user should ensure that the equipment is not installed in a location where it may be subjected to external conditions that might cause a build-up of electrostatic charges on non-conducting surfaces, additionally, cleaning of the equipment should be done only with a damp cloth.
- The equipment shall only be supplied via Sounder Terminal + w.r.t. Sounder Terminal – from a barrier having a maximum open circuit voltage U_o that is $< 28V$ and a maximum short circuit current I_o that is $< 93mA$, where I_o is resistively limited.
- If not already fitted optional internal wiring connections between Sounder Terminals + / – and Beacon Terminals + / – may be fitted by the user. The wiring used for such connections shall have a minimum radial thickness of insulation of 0.5mm.

The IS-mC1 combined sounder / beacon is marked with the certification requirements for the ATEX and IECEx and approvals.

IS-mC1 Combined Sounder / Beacon	
	II 1G Ex ia IIC T4 Ga (-40°C ≤ Ta ≤ +60°C)
	Sounder Terminal + w.r.t. Terminal -
	2813 Ui = 28V Ii = 93mA Pi = 660mW Ci = 0 Li = 0
	Sounder Terminals S2&S3 w.r.t. Terminal -
	Ui = 28V Ii = 0mA
	SIRA 05ATEX2084X
	IECEx SIR 06.0045X
	Beacon Terminal + w.r.t. Terminal -
	Ui = 28V Ii = 660mA Pi = 1.2W Ci = 0 Li = 0
	Year / Ser. No.
	09 / 1MCR000001
WARNING: TO AVOID A POSSIBLE ELECTROSTATIC CHARGE ONLY CLEAN WITH A DAMP CLOTH	
	
<i>european safety systems ltd.</i>	<i>London W3 7QH UK</i>
	<i>www.e2s.com</i>


UKEX Approval

The IS-mC1 Sounder has also been approved to the UKEX scheme.

The installation requirements for IS-mC1 sounders approved to the UKEX scheme are the same as the installation requirements for IS-mC1 sounders approved to the ATEX directive.

- Certificate No. CSAE 21UKEX2553X
- Marking: Ex ia IIC T4 Ga (Ta = -40°C to +60°C)
- Standards: EN IEC 60079-0:2018
EN60079-11:2012
IEC60079-26:2014

The IS-mC1 sounders are marked with the certification requirements for the UKEX approval.




FM Approval

The IS-mC1 Combined Sounder / Beacon has also been FM Listed.

- Marking: IS Class I, Zone 0, AEx ia IIC T4 IS Class I, Division 1, Groups A, B, C, D

See the Control Drawings D 5037 Sheets 1 and 2 for installation details and entity parameters.



- Notified Body for EU type Examination (Module B): Sira Certification Service
Notified Body No.: 2813
CSA Group Netherlands B.V, Utrechtseweg 310, 6812 AR, Arnhem, Netherlands
- EU-type Examination Certificate (Module B): SIRA 05ATEX2084X
- Notified Body for Quality Assurance Notification / Conformity to EU-type based on quality assurance of the production process (Module D):
Sira Certification Service
Notified Body No.: 2813
CSA Group Netherlands B.V, Utrechtseweg 310, 6812 AR, Arnhem, Netherlands
- Quality Assurance Notification (Module D): SIRA 05 ATEX M342
- Provisions fulfilled by the equipment: II 1 G Ex ia IIC T4 Ga (-40 °C ≤ Ta ≤ +60 °C) or
I M1 Ex ia I Ma (-40 °C ≤ Ta ≤ +60 °C)
- Standards applied: EN IEC 60079-0:2018
EN 60079-11:2012
IEC 60079-26:2014

Regulation EU No. 305/2011: Construction Products Regulation (CPR) – IS-mA1 (tones 2, 3, 9, 15, 16, 17) only

- Notified Product Certification Body for Certificate of Constancy of VdS Schadensverhütung GmbH
- Performance or EC Type Examination Certificate and continuous Notified Body No.: 0786
- surveillance, assessment and evaluation of factory production control: Amsterdamer Str 172-174, 50735 Köln, Germany
- Certificate of Constancy of Performance or EC Type Examination Certificate: 0786-CPD-20338
Standards applied: EN 54-3:2001 + A1:2002 + A2:2006

Directive 2014/30/EU: Electromagnetic Compatibility Directive (EMC)

- Standards applied: EN 61000-6-1:2007
EN 61000-6-2:2005
EN 61000-6-3:2007 / A1:2011 / AC: 2012
EN 61000-6-4:2007 / A1: 2011

Directive 2011/65/EU: Restriction of the use of certain hazardous substances in electrical and electronic equipment (RoHS)

The product and all the components contained within it are in accordance with the restriction of the use of hazardous substances in electrical and electronic equipment, including amendment by Directive 2015/863/EU.

Regulation (EC) 1907/2006: Registration, Evaluation, Authorization and Restriction of Chemicals (REACH) The product and all the components contained within it are free from substances of very high concern.

Other Standards and Regulations

EN 60529:1992+A2:2013 – Degrees of protection provided by enclosures (IP code) – enclosure rated IP65

On behalf of European Safety Systems Ltd., I declare that, on the date the equipment accompanied by this declaration is placed on the market, the equipment conforms with all technical and regulatory requirements of the above listed directives, regulations and standards.

This Declaration is issued under the sole responsibility of the manufacturer.

Martin Streetz
Quality Assurance Manager

Document No.:
Date and Place of Issue:

DC-011_Issue_J London, 23/12/2020

UKCA Declaration of Conformity

Manufacturer: European Safety Systems Ltd.
Impress House, Mansell Road, Acton
London, W3 7QH
United Kingdom

Equipment Type: IS-mA1, IS-mA2, IS-mA3, IS-mB1, IS-mC1, IS-mA1M

Directive UKSI 2016:1107 (as amended by UKSI 2019:696) – Schedule 3A, Part 1 : Product or Protective System
Intended for use in Potentially Explosive Atmospheres (UKCA)

- Notified Body for UK type Examination (Module B): Sira Certification Service
- Notified Body No.: 0518
Rake Lane, Eccleston, Chester CH4 9JN, UK
- UK-type Examination Certificate (Module B): CSAE 21UKEX2553X
Notified Body for Quality Assurance Notification / Conformity to EU-type based on quality assurance of the production process (Module D):
Sira Certification Service
Notified Body No.: 0518
Rake Lane, Eccleston, Chester CH4 9JN, UK
- Quality Assurance Notification (Module D): CSAE 22UKQAN0046
- Provisions fulfilled by the equipment: II 1 G Ex ia IIC T4 Ga (-40 °C ≤ Ta ≤ +60 °C) or
I M1 Ex ia I Ma (-40 °C ≤ Ta ≤ +60 °C)
- Standards applied: EN IEC 60079-0:2018
EN 60079-11:2012
IEC 60079-26:2014

Regulation EU No. 305/2011: Construction Products Regulation (CPR) – IS-mA1 (tones 2, 3, 9, 15, 16, 17) only

- Notified Product Certification Body for Certificate of Constancy of Performance or EC Type Examination
Certificate and continuous surveillance, assessment and evaluation of factory production control: VdS
Schadensverhütung GmbH
Notified Body No.: 0786
Amsterdamer Str 172-174, 50735 Köln, Germany
- Certificate of Constancy of Performance or EC Type Examination Certificate: 0786-CPD-20338
- Standards applied: EN 54-3:2001 + A1:2002 + A2:2006

Directive 2014/30/EU: Electromagnetic Compatibility Directive (EMC)

- Standards applied: EN 61000-6-1:2007
EN 61000-6-2:2005
EN 61000-6-3:2007 / A1:2011 / AC: 2012
EN 61000-6-4:2007 / A1: 2011

Directive 2011/65/EU: Restriction of the use of certain hazardous substances in electrical and electronic equipment (RoHS)

The product and all the components contained within it are in accordance with the restriction of the use of hazardous substances in electrical and electronic equipment, including amendment by Directive 2015/863/EU.

Regulation (EC) 1907/2006: Registration, Evaluation, Authorisation and Restriction of Chemicals (REACH) The product and all the components contained within it are free from substances of very high concern.

Other Standards and Regulations

EN 60529:1992+A2:2013 – Degrees of protection provided by enclosures (IP code) – enclosure rated IP65

On behalf of European Safety Systems Ltd., I declare that, on the date the equipment accompanied by this declaration is placed on the market, the equipment conforms with all technical and regulatory requirements of the above listed directives, regulations and standards.

This Declaration is issued under the sole responsibility of the manufacturer.

Martin Streetz

Quality Assurance Manager

Document No.: DC-088_Issue_A

Date and Place of Issue: London, 04/02/2022


E2S Telephone: +44 (0)20 8743 8880

Fax: +44 (0)20 8740 4200

Email: sales@e2s.com www.e2s.com

DC-088_Issue_A (IS-Mini) – Page 2 of 2 – QAF_252_Issue_5

Documents / Resources

	<p>e2S IS-mC1 Intrinsically Safe Round Combined Unit [pdf] Instruction Manual IS-mC1 Intrinsically Safe Round Combined Unit, IS-mC1, Intrinsically Safe Round Combined Unit, Safe Round Combined Unit, Round Combined Unit, Combined Unit</p>
---	---

References

-  [E2S Warning Signals - Signalling devices for hazardous areas, fire and industrial environments.](#)

[marine, onshore and offshore applications and wide area sirens and alarms.](#)

Manuals+.