



Ecolink WST-220 Wireless Contact Instruction Manual

[Home](#) » [Ecolink](#) » Ecolink WST-220 Wireless Contact Instruction Manual 

*Ecolink WST-220 Wireless Contact
Instruction Manual*

WST-200 Wireless Contact

Contents

- [1 Specifications](#)
- [2 Enrolling](#)
- [3 Mounting](#)
- [4 Replacing the Battery](#)
- [5 FCC Compliance Statement](#)
- [6 Warranty](#)
- [7 Documents / Resources](#)
 - [7.1 References](#)
- [8 Related Posts](#)

Specifications

Frequency: 433.92MHz
Battery: 3V lithium CR2032
Battery life: 5-8 years
Magnet gap: 5/8th inch max

Operating Temperature: 32°-120°F (0°-49°C)
Operating Humidity: 5-95% RH non condensing
Compatible with DSC 433MHz receivers
Supervisory signal interval: 60 min(approx.)

Enrolling

Each product has a label with a unique 6 digit serial number. You will need this serial number to add this contact to your security system. Refer to your specific control panel or wireless receiver installation instructions for details on adding a new contact.

Mounting

Included with the contact is double sided tape for the contact and the magnet. For reliable bonding ensure the surface is clean and dry. Apply the tape to the sensor and then to the desired location. Apply firm pressure for several seconds. It is not recommended to mount the tape at temperatures below 50°F, although after 24 hours the bond will hold at low temperatures.

One side of the sensor is marked with 3 lines; this indicates the location of the reed switch. The magnet should be mounted facing this side of the sensor, and it must be no further than 5/8 of an inch from the sensor.

Interchangeable covers

The contact comes from the factory assembled with a white cover, but included are optional brown covers. To change the cover simply slide the front cover to disengage it from the sensor then remove. Replace with the brown cover ensuring the Top (as marked on the inside of the cover) points away from the battery. You should hear a click when the cover engages and disengages from the sensor. You do not need to replace the back plastic because once mounted the back is not visible. To replace the magnet cover you will need to gently pry the white cover off with a flat head screw driver and snap the brown cover in place.

Replacing the Battery

When the battery is low a signal will be sent to the control panel. To replace the battery:

1. Slide the top cover to disengage it from the sensor, then remove to reveal the battery.
2. Replace with a CR2032 battery ensuring the + side of the battery faces towards you.
3. Re-attached the cover, ensure the Top (as marked on the inside of the cover) points away from the battery. You should hear a click when the cover engages properly.

Note: Removing the cover will trigger a zone tamper signal to the control panel

FCC Compliance Statement

This equipment has been tested and found to comply with the limits for Class B digital devices, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Re-orient or relocate the receiving antenna

- Increase the separation between the equipment and receiver
- Connect the equipment to an outlet on a different circuit from the receiver
- Consult the dealer or an experienced radio/TV contractor for help.

Warning: Changes or modifications not expressly approved by Ecolink Intelligent Technology Inc. could void the user's authority to operate the equipment.

This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

FCC ID:XQC-WST200 IC: 9863B-WST200

Warranty

Ecolink Intelligent Technology Inc. warrants that for a period of 2 years from the date of purchase that this product is free from defects in material and workmanship. This warranty does not apply to damage caused by shipping or handling, or damage caused by accident, abuse, misuse, misapplication, ordinary wear, improper maintenance, failure to follow instructions or as a result of any unauthorized modifications. If there is a defect in materials and workmanship under normal use within the warranty period Ecolink Intelligent Technology Inc. shall, at its option, repair or replace the defective equipment upon return of the equipment to the original point of purchase. The foregoing warranty shall apply only to the original buyer, and is and shall be in lieu of any and all other warranties, whether expressed or implied and of all other obligations or liabilities on the part of Ecolink Intelligent Technology Inc. neither assumes responsibility for, nor authorizes any other person purporting to act on its behalf to modify or to change this warranty, nor to assume for it any other warranty or liability concerning this product. The maximum liability for Ecolink Intelligent Technology Inc. under all circumstances for any warranty issue shall be limited to a replacement of the defective product . It is recommended that the customer check their equipment on a regular basis for proper operation.



© 2016 Ecolink Intelligent Technology Inc.

2055 Corte Del Nogal
 Carlsbad, California 92011
 1-855-632-6546
www.discoverecolink.com
 PN WST200 R1.03

Documents / Resources

<p>WST-220 Wireless Contact</p> <p>Model: WST-220 Part #: WST-220-01 Revision: 1.03</p> <p>WARNING: This device contains lithium-ion batteries. Improper handling or disposal of these batteries can result in fire, explosion, or release of toxic substances. Always use proper handling and disposal procedures. For more information, see the user manual.</p> <p>REGULATORY INFORMATION: This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.</p> <p>FCC ID: XQC-WST200 IC: 9863B-WST200</p> <p>Copyright: © 2016 Ecolink Intelligent Technology Inc. All rights reserved. No part of this document may be reproduced, stored in a retrieval system, or transmitted, in any form or by any means, without the prior written permission of Ecolink Intelligent Technology Inc.</p>	<p>Ecolink WST-220 Wireless Contact [pdf] Instruction Manual WST-220, Wireless Contact</p>
--	---

References

- [Ecolink Intelligent Security and Home Automation Products - Ecolink](#)

Manuals+