



Jahy2Tech AP021C Wireless Video Microphone User Manual

[Home](#) » [Jahy2Tech](#) » Jahy2Tech AP021C Wireless Video Microphone User Manual 

Contents

- [1 Jahy2Tech AP021C Wireless Video Microphone](#)
- [2 Features](#)
- [3 APplications](#)
- [4 Packing List](#)
- [5 Specifications](#)
- [6 Functions](#)
- [7 Microphone transmitter functions](#)
- [8 RECEIVER FUNCTION](#)
- [9 Charging case specification](#)
- [10 Safety Instructions](#)
- [11 FCC Requirement](#)
- [12 Documents / Resources](#)
- [13 Related Posts](#)

Jahy2Tech

Jahy2Tech AP021C Wireless Video Microphone



Features

- Original lightning connector, no more worry about IOS ecosystem, and safe to use.
- three-in-one universal receiver, lavalier design, compact and convenient.
- 2.4G wireless transmission technology, stable transmission distance can be up to 120 meters.
- Real-time monitoring, free switching of three volume levels.
- Three noise reduction modes can be switched freely, to meet accurate pickup in any complex environment.
- Support 100% audio storage, no more worry about loss.
- The microphone can be used as a recording pen alone, and the recording can be saved synchronously anytime and anywhere in any environment.
- Microphone and receiver with 3.5 mm cable which is used for camera can last 12 hours continuous interviews.
- Equipped with a charging case, the transmitter and receiver are more convenient to store and charge; interviews,
- The charging case has a large battery of 2000mAh that can be recharged, which is the first choice for travel and make a Live.

Applications

Live, vlog, Video-shooting, Interview and others.

Packing List

- Charging case(two mic and one receiver) 1PCS
- Microphone transmitter 2PCS
- 3 in 1 Receiver 1PCS
- Audio cable 1PS
- CHARGING CABLE 1PCS
- gcable 1PCS

- Earphone 1PCS
- Wind-proof User manual 2PCS

Specifications

Charging case

- input voltage: DC 4,8V-5,4V
- Charging time: 90 mins
- Battery capacity: 2000 mAh
- Recharge times: recharge 3 times for microphone and receiver
- Weight: about 128.2g
- Charging case size: 111 79"34.4mm


Microphone specification

- Frequency: 2,4GHz
- Battery: 230mAh
- Latency: 25 ms
- Working time: 12 hrs every spots range. 20-20KHZ
- Charging time: about 80 mins DC: 4.8-5.4V
- Weight: about 14g
- Sensitivity: -26 dBFS S/N
- Ratio: 64 dB
- Microphone size: 4/.1 15.04 15.61mm

Receiver Specification

- frequency: 2.4GHz
- Battery: 230mAh
- Latency: 25 ms
- Working time: 12 hrs
- Frequency response range: 20-20KHZ
- Charging time: about 80 mins
- DC: 4,8-54V
- Microphone size: 47.5"13.47"7.95mm
- Weight: about 18.7g

Functions



1. Charging case indicator light
2. Indicator light on the receiver
3. Type-C charging port
4. Lightning receiver
5. 3.5mm monitoring port
6. Power IMute key 2 43.5 mm adapter cable port
7. Indicator light on the microphone "2"
8. 1type-C receivers
9. Reset key on the transmitter 2
10. Power Reset button
11. TF memory card slot 2
12. Volumelnoise key

Microphone transmitter functions

No.	State	Operation	Light
1	Power on	1.Open the charging case and take out the microphone 2.Click the power button	Green light for one second
2	Power off	1.Put it in the charging case and close the cover 2,Press power button for 3 secs	/
3	Search for pairing	No pairing object	Green light flashes slowly
4	Paired	Connection succeeded	Green light is always on
5	Clear pairing/re-pairing	Three-click the power button within 10 secs after power on	Red and green light flashes quickly
6	Mute/pick-up	Click the power button to switch mute/pick-up Mute: stop recording Pick-up: start recording	/
			Mute: the green light flashes quickly
			Pick-up: Green light is always on
7	Charging	Put it in the charging case and close the cover	Charging: Blue light flashes
			Fully charged: Blue light off
8	Low power	Below 3.3 V voltage	Red light flashes quickly
9	Automatic power-off	Below 3.3V or no connection for over 15 minutes	Light off
10	TF card automatic Recording	After the connection is successful, it will automatically enter the TF card recording mode.	Green light is always on
11	Use the microphone as a recorder alone (no pair with receiver)	Click the power button to switch to start recording / stop recording (auto save the file)	Blue light flashes slowly when recording and green light flashes slowly when stopping recording
12	when the microphone has no TF card	Recording fails	Blue light is always on
13	The microphone has a TF card but the TF card is damaged	Recording fails	Blue light is always on

RECEIVER FUNCTION

No.	State	Operation	Light
1	Power on	1.Open the charging case and take out the receiver 2.Click the power button	Green light for one second
2	Power off	1.Put it in the charging case and close the cover 2,Press power button for 3 secs	/
3	Search for pairing	No pairing object	Green light flashes slowly
4	Paired	Connection succeeded	Green light is always on
5	Clear pairing/re-pairing	Three-click the power button within 10 secs after power on	Red and green light flashes quickly
6	Charging	Put it in the charging case and close the cover Mute: stop recording Pick-up: start recording	Charging: white light flashes
			Fully charged: white light off

7	Mute/pick-up	Click the power button to switch mute/pick-up Mute: stop recording Pick-up: start recording	Mute: the green light flashes quickly
			Pick-up: Green light is always on
8	Low power	Below 3.3 V voltage	Red light flashes quickly
9	Automatic power-off	Below 3.3V or no connection for over 15 minutes	Light off
10	Volume level switch	Click the volume key	The three levels are cycled in turn
			The prompt tone are as follows: "Beep" (Level 1) "Beep" "Beep" (Level 2) "Beep" "Beep" "Beep" (Level 3)
			The indicator lights are as follows: Red light flashes once (level 1) Red light flashes twice (level 2) Red light flashes three times (level 3)
11	Noise reduction level switch	Double click the noise key	The three levels are cycled in turn
			The prompt tone are as follows: "Dong" (Level 1) "Dong Dong" (Level 2) "Dong Dong Dong" (Level 3)
			The indicator lights are as follows: Green light flashes once (level 1) Green light flashes twice (level 2) Green light flashes three times (level 3)

Charging case specification

No.	State	Operation	Light
1	Charge the case	Charging with Type-C cable	Charging: red light is always on
			Fully charged: the light is off
2	Battery level indicator of charging case	Open the case/indicator light:100%-75%	Green light is on for 10 secs
		Open the case/indicator light:74%-36%	Blue light is on for 10 secs
		Open the case/indicator light:35%-13%	Red light flashes
3	Charge two transmitters	Put two transmitters in the case and close the cover	Charging: the green, blue light flashes
			Fully charged: corresponding lights are off
4	Charge the receiver	Put the receiver in the case and close the cover	Charging: white light flashes
			Fully charged: white light is off
5	Charge multiple device	Put two transmitters and receiver in the case and close the cover	Charging: White, blue and green light flashes alternately in turn
			Fully charged: corresponding lights are off


Note. The Ih card will automatically save a new recording every time, the capacity of the memory card is full, the oldest recording file will be automatically deleted.

Connection instruction




After taking out the device, the indicator lights of the microphones on the receiver and transmitter are always green, it is paired successfully.

Mobile phone connection instruction



Plug the Lightning receiver/Type-C receiver into the Lightning port/Type-C port of the mobile phone, and the green light of the receiver is always on, and the microphone can be used to pick up sound.

Camera connection instructions



Plug the 3.5mm cable into the receiver and the 3.5mm hole of the camera respectively, the green light of the receiver is always on, and the microphone can be used to pick up sound.

Windows Notebook Operation

Turn on the receiver and connect the TPYE-C port to the TPYE-C jack of the computer, or insert the 3.5 adapter cable to the audio input jack, click the speaker icon at the bottom right of the computer, and then open the Sound settings Sound setting option and then click the bottom of the page to select “voice Input” option, select the corresponding “Microphone” option to Confirm. click

Desktop Windows operation

Turn on the receiver, plug in the 3.5mm adapter cable to the audio input port of the host computer, click the “Speaker” icon at the bottom right of the computer, and then open the sound settings, the “Sound” setting option, and then click the “Sound Input” option at the bottom of the page, and select the corresponding “Microphone” option to confirm.


MacBook operation

Turn on the receiver and connect the TPYE-C port to the TPYE-C socket of the MacBook. On the MacBook, select the “Settings” option, then click the “Sound”, then select the “Sound output” option, click to select “Speaker”, and then confirm; then select the “Sound input” option, click to select “Microphone -Wireless microphone. Click Confirm to use.


Turn on OTG (only for Android system)



Step 1:
Enter the setting page




Step 2:
Enter other setting



Step 3:
Click to connect


Take the OPPO A72 model as an example

Instructions for installing the receiver to the camera



Before installing to the camera, use the receiver's back clip to clip on the camera shoe and then fix it.

Wool cover installation instruction



Align the plastic buckle of the wool cover with the groove of the transmitter, insert it and then rotate 90° clockwise to fix it.

Label Meanings

According to the test results obtained based on RL2004/108/EG (Electromagnetic Compatibility Directive) and RL2006/95/EG (Low Voltage Directive), this product complies with the limits specified in the European Community EMC (Electromagnetic Compatibility) Directive, integration of relevant laws from its member states. FC Changes or modifications not expressly approved by the complying party may cause the user to lose permission to operate the device. This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference. (2) This device must accept any interference received, including interference that may cause undesired operation. This symbol indicates that, according to the WEEE (Waste of Electrical and Electronic Equipment) Directive (2012/19/EU) and national laws, this type of waste should not be discarded along with your household waste, as it contains potentially hazardous substances that may pose a negative impact on the environment and human health. It should be handed over to an authorized WEEE collection facility for recovery and recycle. Herewith you will be helping effective utilization of natural resources. For more information on the disposal of WEEE products, please contact your local municipality, waste management bureau or household waste disposal service.

Safety Instructions

To avoid electric shock, overheating, fire, radiation, explosion, mechanical risk and injury or property loss due to improper use, please read and observe the following items before use:

1. Please check if the power of the connected equipment matches with that of this product before operation. Adjust the volume to proper level during operation. Do not operate at over-power or high-volume level for extended time to avoid product malfunction or hearing impairment.
2. If there is any abnormality during use (e.g., smoke, strange odor), please kill the power switch and unplug from power source, then send the product to the local dealer for repair.
3. Keep this product and its accessories in a dry and ventilated area. Do not store in a humid or dusty area for extended time. Keep away from fire, rain, liquid intrusion, bumping, throwing, vibrating, or from blocking any ventilation openings, to prevent malfunction.
4. Please abide by safety rules during operation. Do not use the product in places prohibited by laws or regulations to avoid an accident.

Do not disassemble or repair the product by yourself to avoid injury. If you have any questions or require any services, please contact our local dealer. About This Manual This manual contains up-to-date technical specifications as of printing. However specifications contained herein may not conform to your particular product since Takstar is constantly improving its products. For the latest version/more information please visit our website: <https://www.takstar.com/>. Specifications, devices or accessories available may vary from region to region. If you have any questions, please contact our local dealer.

FCC Requirement

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy, and if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Documents / Resources

	Jahy2Tech AP021C Wireless Video Microphone [pdf] User Manual AP021C-2, AP021C2, 2A5JD-AP021C-2, 2A5JDAP021C2, AP021C Wireless Video Microphone, AP021C, Wireless Video Microphone
--	--