



LUMINTOP D2 Compact 1000 Lumen USB-C Rechargeable LED Torch User Manual

[Home](#) » [LUMINTOP](#) » LUMINTOP D2 Compact 1000 Lumen USB-C Rechargeable LED Torch User Manual 

LUMINTOP

D2 Compact 1000 Lumen USB-C Rechargeable LED Torch
User Manual

Contents

- [1 Specifications](#)
- [2 Features](#)
- [3 Operation Instruction](#)
- [4 USB Type-C Charging](#)
- [5 Low Voltage Warning](#)
- [6 About the Battery](#)
- [7 Warnings](#)
- [8 Warranty](#)
- [9 Documents / Resources](#)
 - [9.1 References](#)

Specifications

ANSI/ NEMA FL1		Eco	Low	Med	High	Turbo	Strobe/SOS
Output	Osram	15LM	130LM	350LM	550LM	1000LM	550LM
	Nichia	10 LM	100 LM	240 LM	400 LM	700 LM	400 LM
Runtime		6D	20h	6h.30mIn	5h	5min+2h 40min	/
Distance (Max)		Osram: 475m/ Nichia:337m					
Intensity (Max)		Osram: 56500cd/ Nichia:28400cd					
Impact Resistant		1.5m					

Notice: The above approximate data are lab-tested by using a 5000mAh 21700 Li-ion battery, it may vary due to the difference of environment and batteries. The runtime on turbo is accumulated due to over-heat protection.

Features

Emitter: Osram LED or Nichia LED

Output(Max) : ~1000 lm (Osram)

Intensity (Max): ~56500cd (Osram)

Beam distance (Max): 475m (Osram)

Optic: Aluminum, smooth

Lens: Dual sides AR coat anti-reflecting glass

Modes: 5 modes plus Strobe and SOS

Battery: 1 X 21700 Li-ion (excluded)

Body: Aluminum with hard-coat anodizing

Switch: Electronic side switch

Ingress rating: Equivalent to IPX8

Weight: Approximately ~85g without cells

Size: 37*25.4*115mm

Operation Instruction

1. **ON/OFF:** One click of the switch.
2. **Output change:** From ON, press and hold the switch to ramp the output from Low-Med-High, release the button to select the output (with memory).
3. **Turbo:** 2 quick clicks on the switch.
4. **Strobe/SOS:** 3 clicks the switch to go to Strobe, and another 3 clicks will go to SOS.
5. **Eco:** Press and hold the switch from OFF.
6. **Lock-out/ Unlock:** 4 clicks the switch from OFF. Momentary Low is available when pressing the switch.
Another 4 clicks or loosen the threads and cut off the electricity to unlock the flashlight.
7. **Switch back-lit light ON/ OFF:** 5 clicks the switch from OFF.

USB Type-C Charging

The flashlight can be charged with the built-in USB Type-C charging port, the maximum charging current is 2A, 5V/2A adapter is recommended.

When it's in the charging process, the indicator is blinking and constant on when it's fully charged.

Low Voltage Warning

The backup light on the button will blink on the green when the battery voltage is 3V; the output will downshift automatically to Low when it's 2.8V.

About the Battery

- Use only reputable 21700 cells of known origin. Quality high drain cells from Samsung, Panasonic / Sanyo, Sony, or LG are recommended.
- Remove or recharge the cell when the low voltage indication is given by the Lamp.
- The extraordinary energy density that the cells offer also means that hazardous conditions are created when a cell is short-circuited or damaged. Always treat cells with respect and properly dispose of damaged cells.

Warnings

1. Keep away from children.
2. Do not point the light directly at a person, animal, moving vehicles or flammable materials.
3. Do not throw into fire in case of explosion.
4. To charge the battery three months a time if long time no uses.

Warranty


1. 30 days of purchase: Free repair or replacement with manufacturing defects.
2. 5 years of purchase: Lumintop will repair the products free of charge within 5 years of purchase (products with built-in battery 2 years, battery 1 year) if problems develop with normal use.
3. Lifetime warranty: If repair is required after guaranty period, we'll charge for parts accordingly.
4. This warranty does not cover normal wear and tear, improper maintenance, abuse, force majeure damage, or defaults by human factors.

		
https://lumintop.com/	https://www.facebook.com/lumintop	https://twitter.com/lumintop

Made in China
LUMINTOP TECHNOLOGY CO., LTD
Address: 11th Floor, Block B , Tianhengda Industrial Park,
No.2 Chengxin Road, Longgang District, Shenzhen, China
Web: www.lumintop.com
Tel.: +86-755-88838666
E-mail: service@lumintop.com



Documents / Resources

	LUMINTOP D2 Compact 1000 Lumen USB-C Rechargeable LED Torch [pdf] User Manual D2 Compact 1000 Lumen USB-C Rechargeable LED Torch, Compact 1000 Lumen USB-C Rechargeable LED Torch, USB-C Rechargeable LED Torch, Rechargeable LED Torch, LED Torch
---	---

References

- [User Manual](#)

[Manuals+](#), [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.