



# User Manual

Code: ATLO-AC-HW4A-TUYA

WIRELESS PIR DETECTOR WITH LIGHT INTENSITY MEASUREMENT **ATLO-AC-HW4A-TUYA** Wi-Fi,  
Tuya Smart

## Warning!

Please read the user manual included in this work as it contains important information related with safety of installation and use of the device.

Only persons who read the user manual may use the device.

The user manual must be kept because it may be required in the future. The device is to be used exclusively for purposes specified in this user manual.

The device must be unpacked prior to starting-up. After removing the packaging make sure the device is in working order.

If the product has defects, it should not be used until it is repaired.

The product is intended for use at home and commercial use and may not be used for other than intended use.

The manufacturer is not liable for damages resulting from not adhering to the rules contained in the user manual, therefore, we recommend to follow the aforementioned safety rules for operation and maintenance of the device. In this way you will ensure yourself safety and avoid causing damage to the device.

The manufacturer and the supplier are not liable for losses or damages arising out of the product, including financial or intangible losses, loss of profits, income, data, pleasure from use of the product or other products related with it - indirect, incidental or consequential loss or damage. The above provisions apply whether the loss or damage concerns:

1. Deterioration of quality or the lack of operation of the products or products related with it due to damage as well as the lack of access to the product when it is undergoing repair, which results in stoppage the loss of user's time or a break in business activity;
2. Improper results of operation of the product or products related with it;
3. It applies to losses and damages according to any legal category, including negligence and other losses, termination of a contract, expressed or implied guarantee and strict liability (even if the manufacturer or the supplier was notified about the possibility of occurrence of such damages).

### Safety measures:

Particular attention at designing was directed to quality standards of the device where ensuring safety of operation is the most important factor.

The device must be secured against contact with caustic, staining and viscous fluids.

The device was designed in such a way that it restarts operation when power supply is restored after a break.

**Attention! We recommend using protections to further protect the device from possible overvoltages in installations. Surge protectors are effective protection against accidental pass to the device voltages higher than the rated. Damages caused by pass the voltages higher than specified in manual, are not under warranty.**

Turn off the device before transporting it.

Prior to connecting the device to a power source check whether the supplied voltage is consistent with rated voltage specified in the user manual.

### Proper product disposal:

A marking of a crossed out waste bin indicates that the product may not be disposed together with other household waste in the entire EU. To avoid possible damage to the natural environment of health due to uncontrolled waste disposal, therefore, it should be handed over for recycling, propagating in this way sustainable use of natural resources.

To return a worn-out product, use a collection and disposal system of this type of equipment or contact a seller from whom it was purchased. He will then be recycled in an environmentally-friendly way.

Digital Passive Infra Red detector to ceiling mount.

The device has the ability to work with the Tuya Smart application for mobile devices.

Tuya is an international home automation platform that connects thousands of products made by different manufacturers. The system can support all the most popular communication protocols such as Wi-Fi, Zigbee, Bluetooth.

In the Tuya Smart application for the wireless PIR detector, there are two states: "Human status" (human presence) and "No one state" (state without human presence). These states inform about the detection or lack of movement in the sensor's coverage zone: "Human status" (human presence) - if active, it means that the detector has detected human movement and a notification is sent to the Tuya application. If the detector does not detect any movement after 40 seconds, it changes to "No one state" (state without human presence), displaying the "No one came" status in the application. This state lasts until the detector detects movement, which causes the switch to the "Human status" state (human presence). It is incorrect to test the detector and the application immediately after startup and configuration. The correct way is to leave the detector's detection area for at least 50 seconds and return to testing.

After the status changes, the time to connect to the Wi-Fi network is 5 seconds.



|                                |                                                                                                                                                                                                                                                                                            |
|--------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Support:                       | Tuya Smart                                                                                                                                                                                                                                                                                 |
| Operation way:                 | <ul style="list-style-type: none"> <li>• Ceiling Motion Sensor</li> <li>• Light intensity measurement</li> </ul>                                                                                                                                                                           |
| Light intensity measurement:   | 0 ... 100001 Lux                                                                                                                                                                                                                                                                           |
| Detection range:               | 6 m - Motion Detector                                                                                                                                                                                                                                                                      |
| Detection angle:               | 360 °                                                                                                                                                                                                                                                                                      |
| Alarm signaling:               | Signal to the Tuya Smart mobile application                                                                                                                                                                                                                                                |
| Frequency range:               | 2.4 GHz WiFi - IEEE 802.11 b/g/n                                                                                                                                                                                                                                                           |
| Radio communication range:     | The range limited only by the availability of the Wi-Fi network                                                                                                                                                                                                                            |
| Battery:                       | 2 x 1.5V, type AAA/LR03 battery (included)                                                                                                                                                                                                                                                 |
| Current consumption:           | ≤ 55 µA - Standby<br>≤ 135 mA - Alarm signaling                                                                                                                                                                                                                                            |
| Main features:                 | Low battery level alarm ≤ 2.4 V                                                                                                                                                                                                                                                            |
| Mobile phones support:         | It is possible to operate via the Wi-Fi network from the mobile application on the iOS, Android systems : <ul style="list-style-type: none"> <li>• The <a href="#">Tuya Smart</a> free application on Android</li> <li>• The <a href="#">Tuya Smart</a> free application on iOS</li> </ul> |
| Operation temp:                | -10 °C ... 50 °C                                                                                                                                                                                                                                                                           |
| Permissible relative humidity: | ≤ 95 % (non-condensing)                                                                                                                                                                                                                                                                    |
| Color:                         | White                                                                                                                                                                                                                                                                                      |



# User Manual

Code: ATLO-AC-HW4A-TUYA

WIRELESS PIR DETECTOR WITH LIGHT INTENSITY MEASUREMENT **ATLO-AC-HW4A-TUYA** Wi-Fi,  
Tuya Smart

|             |              |
|-------------|--------------|
| Weight:     | 0.04 kg      |
| Dimensions: | Ø 61 x 34 mm |
| Guarantee:  | 2 years      |

Place for batteries 2 x 1.5V AAA



In the kit



PACKAGE

|                                  |                    |
|----------------------------------|--------------------|
| Dimensions (L x W x H): 0x0x0 mm | Gross Weight: 0 kg |
|----------------------------------|--------------------|