

Z-Wave Protocol Implementation Conformance Statement

Door/Window Sensor 2

General Information

| | |
|--------------------------------|----------------|
| Product Identifier: | FGDW-002 |
| Brand Name: | FIBARO |
| Product Version: | HW: 2 FW: 3.02 |
| Z-Wave Certification #: | ZC10-19076578 |

Product Features

| | |
|-------------------------------------|---|
| Firmware Updatable | Updatable by Consumer by RF |
| Supported Notification Types | Access Control Heat Alarm Home Security Power Management |
| Battery Type | ER14250 or CR2 |
| Battery Quantity | 1 |
| Sensors | Air Temperature |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | No |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Technical Information

| | |
|--|---------|
| Z-Wave Frequency: | Israel |
| Z-Wave Product ID: | 0x7000 |
| Z-Wave Product Type: | 0x0702 |
| Z-Wave Hardware Platform: | ZM5101 |
| Z-Wave Development Kit Version: | 6.51.09 |

Association Group Information

| Group # / Max | Description |
|---------------|--|
| Nodes | |
| 1 / 1 | “Lifeline” reports the device status and allows for assigning single device only (main controller by default). |
| 2 / 5 | 2nd Association Group – “On/Off” is assigned to the device status - Hall effect sensor (sends Basic Set command frames). |
| 3 / 5 | 3rd Association Group – “Tamper” is assigned to the TMP switch (sends alarm command frames). |

Supported Command Classes (18):

| | |
|------------------------------|--------------------------|
| Application Status | Association Group Info |
| Association V2 | Basic |
| Battery | Configuration |
| CRC16 Encapsulation | Device Reset Locally |
| Firmware Update Meta-Data V4 | Manufacturer Specific V2 |
| Multi-Channel Association V3 | Notification V5 |
| Powerlevel | Security S0 |
| Sensor Multilevel V5 | Version V2 |
| Wake Up V2 | Z-Wave Plus Info V2 |

Controlled Command Classes (1):

| |
|-------|
| Basic |
|-------|