


Sunco

Lighting made better.

User Manual

Recessed LED 6" Baffle Slim Downlight

SKU: DL_BS6_NL-WH-2760K




support@sunco.com
(844) 334-9938



What's in the Box?

Nightlight Downlight



Let there be light!
(literally)




x1

Light Fixture



x1

Junction Box



x1

Installation Template




x3

Wire Nuts

Get Your Gear (Not Included)



Tape



Hole Saw



Ladder



Wire Strippers

Before You Start

Safety Information

To reduce the risk of fire, electric shock, or physical injury:

- Turn off circuit breaker before installing this fixture.
- This product should be installed by a person familiar with the construction and operation of the product the hazards involved. Safety eyeglasses and gloves are recommended.
- Abide by related regional and local laws or regulations.
- Proper grounding is required to ensure safety.
- Do not alter, relocate, or remove wiring during installation.
- Do not make or alter any open holes in wiring enclosure or electrical components during installation.
- Check for shipping damage before insatalling. If the product is damaged, do not use it.
- Keep fixture away from corrosive substances.
- Suitable for damp locations at temperature ranging from -4°F to 113°F. Not for use where directly exposed to water.
- Clean the fixture regularly to ensure proper operation. Do not clean with harsh solvents.
- Use safety precautions and abide by regional and local laws or regulations.
- This product is not compatible with 3rd party sensors.
- This product is not compatible with photo controls.
- This product is not compatible with occupancy sensors.
- This product is not compatible with timing devices.

This device complies with Part 15 of the FCC rules.


Operation is subject to the following two conditions:

- 1) This device may not cause harmful interference.**
- 2) This device must accept any interference that may cause undesired operation. Please review all instructions carefully prior to installation.**

WARNING:


Cancer & Reproductive Harm- www.P65Warnings.ca.gov

Quickstart Guide




Step 1

Use template to cut hole.




Step 2

Connect supply & junction wires.



Step 3


Attach fixture to junction box.



Step 4


Insert fixture into ceiling.

Installation Guide




STEP 1

- Turn off circuit breaker before installation.
- Cut out 6.33" housing size on Installation Template, then tape onto ceiling in desired location.
- Cut ceiling hole using Installation Template as a guide.



STEP 2


- Open junction box and remove appropriate knockout.



STEP 3

- Connect supply and junction wires using wire nuts:
 - Black to Black (Live)
 - White to White (Neutral)
- Tuck connected wires inside junction box and close the cover.


Installation Guide (Cont.)



STEP 4

Insert junction box through ceiling hole.


- a. New Construction Applications: Secure to studs, joists, or similar fixed structural units.
- b. Remodel Applications: Do not require to secure to studs, joists, or similar fixed structural units.



STEP 5

a. Attach fixture to junction box using connector as shown on image (1). Tighten connector by hand (2).

b. Push up spring clips and insert fixture into ceiling. Turn on circuit breaker and test light.



STEP 6

Note: To toggle between downlight and nightlight, turn wall switch and night light off, wait 3 seconds, then switch on.

To reset fixture, turn off, wait 5 seconds, then turn on.

Product Details

Recommended Dimmers

Brand	Model
LUTRON	P-PKG1WB-WH
LUTRON	MACL-153M-WH
LUTRON	PD-6WCL-WH
LUTRON	AYCL-153P-WH
LUTRON	DVCL-153P-WH
LEVITON	D26HD-2RW
KASA SMART	HS220
KASA SMART	HS220P3

Scan for the full
compatible dimmer list!



Specifications

Voltage	120 V	Average Lifetime	50,000 Hours
Wattage	14 W	Lumens	1200 lm
Wattage Equivalency	140 W	Moisture Rating	Damp Rated
Beam Angle	90°	CRI	80+
Weight	0.85 lbs	Usage	Indoor
Housing Material	Plastic + Metal J-Box	IC Rated	Yes
Dimmable	YES	Warranty	7 Years

Common Troubleshooting

Feeling in the dark about an issue with your product? No worries! Our troubleshooting section is here to shed some light and provide you with easy-to-follow solutions for any problem. If you

still need some assistance, please feel free to contact us with any questions. Our team of lighting experts are happy to help brighten your day.

Installation

Light isn't turning on.

Double check if fixture is properly connected and circuit breaker hasn't been tripped.

Light isn't bright enough.

Check proper wattage and for unobstructed fixture.

Dimming

Light not dimming to lowest setting.

Ensure minimum dimmer load requirement is met.

Light not dimming smoothly.

Verify dimmer compatibility with fixture.

Light not compatible with dimmer switch.

Check light-dimmer compatibility. Consider purchasing compatible switch if necessary.

Flickering

Light is flickering when turning on.

Check that fixture wiring connections are secure.

Light flickering with other lights on the same circuit.

Check that the lights on the same circuit are not overloading the circuit.

Light flickering when turned on.

Verify fixture compatibility and that it is grounded.

Light flickering when dimmed.

Verify dimmer switch compatibility.

Buzzing

Fixture buzzing with power outages.

Verify light is connected to surge protector securely.

Fixture buzzing with appliances or electronic devices.

Look for nearby interferences that can cause buzzing. Such as televisions, radios, computers, etc.

Fixture buzzing when dimmed.

Verify dimmer switch compatibility.

Sunco

Lighting made better.

support@sunco.com
(844) 334-9938

REV1.0