



Release Notes

FortiManager 7.4.6



FORTINET DOCUMENT LIBRARY

<https://docs.fortinet.com>

FORTINET VIDEO LIBRARY

<https://video.fortinet.com>

FORTINET BLOG

<https://blog.fortinet.com>

CUSTOMER SERVICE & SUPPORT

<https://support.fortinet.com>

FORTINET TRAINING & CERTIFICATION PROGRAM

<https://www.fortinet.com/training-certification>

FORTINET TRAINING INSTITUTE

<https://training.fortinet.com>

FORTIGUARD LABS

<https://www.fortiguard.com>

END USER LICENSE AGREEMENT

<https://www.fortinet.com/doc/legal/EULA.pdf>

FEEDBACK

Email: techdoc@fortinet.com



December 20, 2024

FortiManager 7.4.6 Release Notes

02-746-1092551-20241220

TABLE OF CONTENTS

Change Log	6
FortiManager 7.4.6 Release	7
Supported models	7
FortiManager VM subscription license	7
Management extension applications	8
Supported models for MEA	8
Minimum system requirements	8
Special Notices	10
Upgrading from 7.4.3 to 7.4.6 with FIPS mode enabled	10
Device blueprint header	10
Shell access has been removed	10
Enable fcp-cfg-service for Backup Mode ADOMs	11
System Templates include new fields	11
Custom certificate name verification for FortiGate connection	11
Additional configuration required for SSO users	12
When using VPN Manager, IPSEC VPN CA certificates must be re-issued to all devices after upgrade	12
FortiGuard web filtering category v10 update	12
FortiManager 7.2.3 and later firmware on FortiGuard	13
Configuration backup requires a password	13
FortiManager-400E support	13
Serial console has changed for FortiManager deployments on Xen	14
OpenXen in PV mode is not supported in FortiManager 7.4.1	14
Default GUI theme changed	14
Option to enable permission check when copying policies	14
Management Extensions visibility in the GUI	15
Install On column for policies	15
SD-WAN Orchestrator removed in 7.2	15
Changes to FortiManager meta fields	15
Setup wizard requires FortiCare registration	16
Access lists as ADOM-level objects	16
View Mode is disabled in policies when policy blocks are used	16
Reconfiguring Virtual Wire Pairs (VWP)	16
Scheduling firmware upgrades for managed devices	16
Modifying the interface status with the CLI	17
SD-WAN with upgrade to 7.0	17
Citrix XenServer default limits and upgrade	17
Multi-step firmware upgrades	18
Hyper-V FortiManager-VM running on an AMD CPU	18
SSLv3 on FortiManager-VM64-AWS	18

Upgrade Information	19
Downgrading to previous firmware versions	19
Firmware image checksums	19
FortiManager VM firmware	20
SNMP MIB files	21
Product Integration and Support	22
Supported software	22
Web browsers	23
FortiOS and FortiOS Carrier	23
FortiADC	23
FortiAnalyzer	23
FortiAnalyzer-BigData	24
FortiAuthenticator	24
FortiCache	24
FortiCASB	24
FortiClient	24
FortiDDoS	24
FortiDeceptor	25
FortiFirewall and FortiFirewallCarrier	25
FortiMail	25
FortiPAM	25
FortiProxy	26
FortiSandbox	26
FortiSASE	26
FortiSOAR	26
FortiSRA	27
FortiSwitch ATCA	27
FortiTester	27
FortiToken	27
FortiWeb	27
Virtualization	27
Feature support	28
Language support	29
Supported models	30
FortiGate models	30
FortiGate special branch models	33
FortiCarrier models	35
FortiCarrier special branch models	37
FortiADC models	37
FortiAnalyzer models	38
FortiAnalyzer-BigData models	39
FortiAuthenticator models	39
FortiCache models	39
FortiDDoS models	40
FortiDeceptor models	40
FortiFirewall models	40
FortiFirewallCarrier models	41
FortiMail models	42

FortiPAM models	42
FortiProxy models	43
FortiSandbox models	43
FortiSOAR models	43
FortiSRA models	44
FortiSwitch ATCA models	44
FortiTester models	44
FortiWeb models	45
FortiExtender MODEM firmware compatibility	45
Resolved issues	46
AP Manager	46
Device Manager	46
FortiSwitch Manager	47
Others	47
Policy and Objects	48
System Settings	48
Known issues	49
New known issues	49
Policy & Objects	49
Existing known issues	49
AP Manager	49
Device Manager	50
FortiSwitch Manager	50
Others	51
Policy & Objects	51
Script	52
System Settings	52
Appendix A - FortiGuard Distribution Servers (FDS)	53
FortiGuard Center update support	53
Appendix B - Default and maximum number of ADOMs supported	54
Hardware models	54
Virtual Machines	54

Change Log

Date	Change Description
2024-12-18	Initial release.
2024-12-20	Updated Known issues on page 49 .

FortiManager 7.4.6 Release

This document provides information about FortiManager version 7.4.6 build 2588.



The recommended minimum screen resolution for the FortiManager GUI is 1920 x 1080. Please adjust the screen resolution accordingly. Otherwise, the GUI may not display properly.

This section includes the following topics:

- [Supported models on page 7](#)
- [FortiManager VM subscription license on page 7](#)
- [Management extension applications on page 8](#)

Supported models

FortiManager version 7.4.6 supports the following models:

FortiManager	FMG-200F, FMG-200G, FMG-300F, FMG-400G, FMG-410G, FMG-1000F, FMG-1000G, FMG-2000E, FMG-3000F, FMG-3000G, FMG-3100G, FMG-3700F, and FMG-3700G.
FortiManager VM	FMG_VM64, FMG_VM64_ALI, FMG_VM64_AWS, FMG_VM64_AWSOnDemand, FMG_VM64_Azure, FMG_VM64_GCP, FMG_VM64_IBM, FMG_VM64_HV (including Hyper-V 2016, 2019, and 2022), FMG_VM64_KVM, FMG_VM64_OPC, FMG_VM64_XEN (for both Citrix and Open Source Xen).



For access to container versions of FortiManager, contact [Fortinet Support](#).

FortiManager VM subscription license

The FortiManager VM subscription license supports FortiManager version 6.4.1 and later. For information about supported firmware, see [FortiManager VM firmware on page 20](#).

See also [Appendix B - Default and maximum number of ADOMs supported on page 54](#).

Management extension applications

The following section describes supported models and minimum system requirements for management extension applications (MEA) in FortiManager 7.4.6.



FortiManager uses port TCP/443 or TCP/4443 to connect to the Fortinet registry and download MEAs. Ensure that the port is also open on any upstream FortiGates. For more information about incoming and outgoing ports, see the [FortiManager 7.0 Ports Guide](#).

As of FortiManager 7.4.0, the *Management Extensions* pane is only visible in the GUI when docker status is enabled and at least one MEA is enabled and downloaded. For more information about enabling and using the MEAs, see the Management Extensions documentation in the [FortiManager Documents Library](#).

Supported models for MEA

You can use any of the following FortiManager models as a host for management extension applications:

FortiManager	FMG-3000F, FMG-3000G, FMG-3700F, and FMG-3700G.
FortiManager VM	FMG_VM64, FMG_VM64_ALI, FMG_VM64_AWS, FMG_VM64_AWSOnDemand, FMG_VM64_Azure, FMG_VM64_GCP, FMG_VM64_IBM, FMG_VM64_HV (including Hyper-V 2016, 2019, and 2022), FMG_VM64_KVM, FMG_VM64_OPC, FMG_VM64_XEN (for both Citrix and Open Source Xen).

Minimum system requirements

By default FortiManager VMs use the following system resource settings:

- 4 vCPU
- 16 GB RAM
- 500 GB disk space

Starting with FortiManager 7.0.0, RAM and CPU is capped at 50% for MEAs. (Use the `config system docker` command to view the setting.) If FortiManager has 8 CPUs and 16 GB RAM, then only 4 CPUs and 8 GB RAM are available to MEAs by default, and the 4 CPUs and 8 GB RAM are used for all enabled MEAs.

Some management extension applications have minimum system requirements that require you to increase system resources. The following table identifies the minimum requirements for each MEA as well as the recommended system resources to function well in a production environment.

MEA minimum system requirements apply only to the individual MEA and do not take into consideration any system requirements for resource-sensitive FortiManager features or multiple, enabled MEAs. If you are using multiple MEAs, you must increase the system resources to meet the cumulative need of each MEA.

Management Extension Application	Minimum system requirements	Recommended system resources for production*
FortiAIOps	<ul style="list-style-type: none"> • 8 vCPU • 32 GB RAM • 500 GB disk storage 	No change
FortiSigConverter	<ul style="list-style-type: none"> • 4 vCPU • 8 GB RAM 	No change
FortiSOAR	<ul style="list-style-type: none"> • 4 vCPU • 8 GB RAM • 500 GB disk storage 	<ul style="list-style-type: none"> • 16 vCPU • 64 GB RAM • No change for disk storage
Policy Analyzer	<ul style="list-style-type: none"> • 4 vCPU • 8 GB RAM 	No change
Universal Connector	<ul style="list-style-type: none"> • 1 GHZ vCPU • 2 GB RAM • 1 GB disk storage 	No change
Wireless Manager (FortiWLM)	<ul style="list-style-type: none"> • 4 vCPU • 8 GB RAM 	No change

*The numbers in the *Recommended system resources for production* column are a combination of the default system resource settings for FortiManager plus the minimum system requirements for the MEA.

Special Notices

This section highlights some of the operational changes that administrators should be aware of in 7.4.6.

Upgrading from 7.4.3 to 7.4.6 with FIPS mode enabled

When FIPS mode is enabled, upgrading from 7.4.3 to 7.4.6 might fail due to the following error message: "FIPS firmware signature verification failed". The following steps should be taken as workaround:

1. Backup FortiManager-v7.4.3-fips-cc mode DB.
2. Disable FortiManager-v7.4.3-fips mode to normal mode.
3. Upgrade FortiManager-v7.4.3 normal mode to v7.4.6.
4. FortiManager-v7.4.6 enable fips-cc mode.
5. Restore FortiManager-v7.4.3-fips DB on FortiManager-v7.4.6-fips.

Note that you do not need to follow this workaround if upgrading from 7.4.4 or 7.4.5 to 7.4.6.

Device blueprint header

The device blueprint header is updated in FortiManager 7.4.4, and the new format is required when importing model devices from a CSV file. If you have existing CSV files that are used as a template to import model devices, the header must be updated to use the new format.

To update the header for an existing CSV file:

1. In the FortiManager 7.4.4 or later GUI, go to *Device Manager > Device & Groups*.
2. From the *Add Device* dropdown, select *Device Blueprint*.
3. Select an existing blueprint and click *Generate CSV*.
4. Open the new CSV file and copy the header.
5. Open the existing CSV file and paste the new header, replacing the old header from previous versions.

Shell access has been removed

As of FortiManager 7.4.4, shell access has been removed.

The following CLI variables have been removed, which were previously used to enable shell access:

```
config system admin setting
    set shell-access {enable | disable}
    set shell-password <passwd>
```

The following CLI command has been removed, which was previously used to access shell when enabled:

```
execute shell
```

Enable fcp-cfg-service for Backup Mode ADOMs

When performing a configuration backup from the CLI of FortiGates managed by FortiManager in Backup Mode ADOMs, you must enable the "fcp-cfg-service" using the following command on the FortiManager:

```
config system global
    set fcp-cfg-service enable
end
```

System Templates include new fields

Beginning in FortiManager 7.4.3, the *Hostname*, *Timezone*, *gui-device-latitude*, and *gui-device-longitude* fields have been added to System Templates.

System Templates created before upgrading to 7.4.3 must be reconfigured to specify these fields following the upgrade. If these fields are not specified in a System Template, the default settings will be applied the next time an install is performed which may result in preferred settings being overwritten on the managed device.

Custom certificate name verification for FortiGate connection

FortiManager 7.4.3 introduces a new verification of the CN or SAN of a custom certificate uploaded by the FortiGate admin. This custom certificate is used when a FortiGate device connects to a FortiManager unit. The FortiGate and FortiManager administrators may configure the use of a custom certificate with the following CLI commands:

FortiGate-related CLI:

```
config system central-management
    local-cert Certificate to be used by FGFM protocol.
    ca-cert CA certificate to be used by FGFM protocol.
```

FortiManager-related CLI:

```
config system global
    fgfm-ca-cert set the extra fgfm CA certificates.
    fgfm-cert-exclusive set if the local or CA certificates should be used exclusively.
    fgfm-local-cert set the fgfm local certificate.
```

Upon upgrading to FortiManager 7.4.3, FortiManager will request that the FortiGate certificate must contain the FortiGate serial number either in the CN or SAN. The tunnel connection may fail if a matching serial number is not found. If the tunnel connection fails, the administrator may need to re-generate the custom certificates to include serial number.

Alternatively, FortiManager 7.4.3 provides a new CLI command to disable this verification. Fortinet recommends to keep the verification enabled.

```
config system global
```

`fgfm-peercert-withoutsn` set if the subject CN or SAN of peer's SSL certificate sent in FGFM should include the serial number of the device.

When the CLI setting `fgfm-peercert-withoutsn` is disabled (default), the FortiGate device's certificate must include the FortiGate serial number in the subject CN or SAN. When the CLI setting `fgfm-peercert-withoutsn` is enabled, the FortiManager unit does not perform the verification serial number in subject CN or SAN.

Additional configuration required for SSO users

Beginning in 7.4.3, additional configuration is needed for FortiManager Users declared as wildcard SSO users.

When configuring Administrators as wildcard SSO users, the `ext-auth-accprofile-override` and/or `ext-auth-adom-override` features, under *Advanced Options*, should be enabled if the intent is to obtain the ADOMs list and/or permission profile from the SAML IdP.

When using VPN Manager, IPSEC VPN CA certificates must be re-issued to all devices after upgrade

When FortiManager is upgraded to 7.4.2 or later, it creates a new CA <ADOM Name>_CA3 certificate as part of a fix for resolved issue 796858. See [Resolved Issues in the FortiManager 7.4.2 Release Notes](#). These certificates are installed to the FortiGate devices on the next policy push. As a result, the next time any IPSEC VPNs which use FortiManager certificates rekey, they will fail authentication and be unable to re-establish.

The old CA <ADOM Name>_CA2 cannot be deleted, as existing certificates rely on it for validation. Similarly, the new CA <ADOM Name>_CA3 cannot be deleted as it is required for the fix. Therefore, customers affected by this change must follow the below workaround after upgrading FortiManager to v7.4.2 or later.

A maintenance period is advised to avoid IPSEC VPN service disruption.

Workaround:

Re-issue *all* certificates again to *all* devices, and then delete the old CA <ADOM Name>_CA2 from all devices. Next, regenerate the VPN certificates.

To remove CA2 from FortiManager, *Policy & Objects > Advanced > CA Certificates* must be enabled in feature visibility.

FortiGuard web filtering category v10 update

Fortinet has updated its web filtering categories to v10, which includes two new URL categories for AI chat and cryptocurrency web sites. In order to use the new categories, customers must upgrade their Fortinet products to one of the versions below.

- FortiManager - Fixed in 6.0.12, 6.2.9, 6.4.7, 7.0.2, 7.2.0, 7.4.0.
- FortiOS - Fixed in 7.2.8 and 7.4.1.
- FortiClient - Fixed in Windows 7.2.3, macOS 7.2.3, Linux 7.2.3.
- FortiClient EMS - Fixed in 7.2.1.

- FortiMail - Fixed in 7.0.7, 7.2.5, 7.4.1.
- FortiProxy - Fixed in 7.4.1.

Please read the following CSB for more information to caveats on the usage in FortiManager and FortiOS.

<https://support.fortinet.com/Information/Bulletin.aspx>

FortiManager 7.2.3 and later firmware on FortiGuard

Starting in FortiManager 7.2.1, a setup wizard executes to prompt the user for various configuration steps and registration with FortiCare. During the execution, the FortiManager unit attempts to communicate with FortiGuard for a list of FortiManager firmware images currently available on FortiGuard – older and newer.

In the case of FortiManager 7.2.2, a bug in the GUI prevents the wizard from completing and prevents the user from accessing the FortiManager unit. The issue has been fixed in 7.2.3 and later and a CLI command has been added to bypass the setup wizard at login time.

```
config system admin setting
    set firmware-upgrade-check disable
end
```

Fortinet has not uploaded FortiManager 7.2.3 and later firmware to FortiGuard in order to work around the GUI bug, however, the firmware is available for download from the [Fortinet Support website](#).

Configuration backup requires a password

As of FortiManager 7.4.2, configuration backup files are automatically encrypted and require you to set a password. The password is required for scheduled backups as well.

In previous versions, the encryption and password were optional.

For more information, see the [FortiManager Administration Guide](#).

FortiManager-400E support

FortiManager 7.4.2 and later does not support the FortiManager-400E device.

FortiManager 7.4.2 introduces an upgrade of the OpenSSL library to address known vulnerabilities in the library. As a result, the SSL connection that is setup between the FortiManager-400E device and the Google Map server hosted by Fortinet uses a SHA2 (2048) public key length. The certificate stored on the BIOS that is used during the setup of the SSL connection contains a SHA1 public key length, which causes the connection setup to fail. Running the following command shows the key length.

```
FMG400E # conf sys certificate local
(local)# ed Fortinet_Local
(Fortinet_Local)# get
name : Fortinet_Local
password : *
comment : Default local certificate
```

```
private-key :
certificate :
Subject: C = US, ST = California, L = Sunnyvale, O = Fortinet, OU = FortiManager, CN
       = FL3K5E3M15000074, emailAddress = support@fortinet.com
Issuer: C = US, ST = California, L = Sunnyvale, O = Fortinet, OU = Certificate
       Authority, CN = support, emailAddress = support@fortinet.com
Valid from: 2015-03-06 16:22:10 GMT
Valid to: 2038-01-19 03:14:07 GMT
Fingerprint: FC:D0:0C:8D:DC:57:B6:16:58:DF:90:22:77:6F:2C:1B
Public key: rsaEncryption (1024 bits)
Signature: sha1WithRSAEncryption
Root CA: No
Version: 3
Serial Num:
1e:07:7a
Extension 1: X509v3 Basic Constraints:
CA:FALSE
...
(Fortinet_Local)#
```

Serial console has changed for FortiManager deployments on Xen

As of FortiManager 7.4.1, the serial console for Xen deployments has changed from hvc0 (Xen specific) to ttyS0 (standard).

OpenXen in PV mode is not supported in FortiManager 7.4.1

As of FortiManager 7.4.1, kernel and rootfs are encrypted. OpenXen in PV mode tries to unzip the kernel and rootfs, but it will fail. Therefore, OpenXen in PV mode cannot be used when deploying or upgrading to FortiManager 7.4.1. Only HVM (hardware virtual machine) mode is supported for OpenXen in FortiManager 7.4.1.

Default GUI theme changed

As of FortiManager 7.4.1, the default GUI theme is *Jade*. The default theme can be changed from *System Settings > Settings*.

Option to enable permission check when copying policies

As of 7.4.0, a new command is added in the CLI:

```
config system global
  set no-copy-permission-check {enable | disable}
```

end

By default, this is set to `disable`. When set to `enable`, a check is performed when copying policies to prevent changing global device objects if the user does not have permission.

Management Extensions visibility in the GUI

As of FortiManager 7.4.0, the *Management Extensions* pane is only visible in the GUI when docker status is enabled and at least one management extension application (MEA) is enabled and downloaded. For more information about enabling and using the MEAs, see the Management Extensions documentation in the [FortiManager Documents Library](#).

Install On column for policies

Prior to version 7.2.3, the 'Install-on' column for policies in the policy block had no effect. However, starting from version 7.2.3, the 'Install-on' column is operational and significantly impacts the behavior and installation process of policies. It's important to note that using 'Install-on' on policies in the policy block is not recommended. If required, this setting can only be configured through a script or JSON APIs.

SD-WAN Orchestrator removed in 7.2

Starting in 7.2.0, the SD-WAN Orchestrator is no longer available in FortiManager. Instead, you can use the *SD-WAN Overlay Template* wizard to configure your SD-WAN overlay network.

For more information, see [SD-WAN Overlay Templates](#) in the FortiManager Administration Guide.

Changes to FortiManager meta fields

Beginning in 7.2.0, FortiManager supports policy object metadata variables.

When upgrading from FortiManager 7.0 to 7.2.0 and later, FortiManager will automatically create ADOM-level metadata variable policy objects for meta fields previously configured in System Settings that have per-device mapping configurations detected. Objects using the meta field, for example CLI templates, are automatically updated to use the new metadata variable policy objects.

Meta fields in *System Settings* can continue to be used as comments/tags for configurations.

For more information, see [ADOM-level meta variables for general use in scripts, templates, and model devices](#).

Setup wizard requires FortiCare registration

Starting in FortiManager 7.2.1, the FortiManager Setup wizard requires you to complete the *Register with FortiCare* step before you can access the FortiManager appliance or VM. Previously the step was optional.

For FortiManager units operating in a closed environment, contact customer service to receive an entitlement file, and then load the entitlement file to FortiManager by using the CLI.

Access lists as ADOM-level objects

Starting in 7.2.0, FortiManager supports IPv4 and IPv6 access lists as ADOM-level object configurations from FortiGate. Previously, access lists were controlled by the device database/FortiGate configuration.

After upgrading to 7.2.0 from an earlier release, the next time you install changes to a FortiGate device with an IPv4 or IPv6 access list, FortiManager will purge the device database/FortiGate configuration which may have previously contained the access list. To address this, administrators can re-import the FortiGate policy configuration to an ADOM's policy package or re-create the IPv4/IPv6 access list in the original package.

View Mode is disabled in policies when policy blocks are used

When policy blocks are added to a policy package, the *View Mode* option is no longer available, and policies in the table cannot be arranged by *Interface Pair View*. This occurs because policy blocks typically contain policies with multiple interfaces, however, *View Mode* is still disabled even when policy blocks respect the interface pair.

Reconfiguring Virtual Wire Pairs (VWP)

A conflict can occur between the ADOM database and device database when a Virtual Wire Pair (VWP) is installed on a managed FortiGate that already has a configured VWP in the device database. This can happen when an existing VWP has been reconfigured or replaced.

Before installing the VWP, you must first remove the old VWP from the device's database, otherwise a policy and object validation error may occur during installation. You can remove the VWP from the device database by going to *Device Manager > Device & Groups*, selecting the managed device, and removing the VWP from *System > Interface*.

Scheduling firmware upgrades for managed devices

Starting in FortiManager 7.0.0, firmware templates should be used to schedule firmware upgrades on managed FortiGates. Attempting firmware upgrade from the FortiManager GUI by using legacy methods may ignore the *schedule upgrade* option and result in FortiGates being upgraded immediately.

Modifying the interface status with the CLI

Starting in version 7.0.1, the CLI to modify the interface status has been changed from `up/down` to `enable/disable`.

For example:

```
config system interface
  edit port2
    set status <enable/disable>
  next
end
```

SD-WAN with upgrade to 7.0

Due to design change with SD-WAN Template, upgrading to FortiManager 7.0 may be unable to maintain dynamic mappings for all SD-WAN interface members. Please reconfigure all the missing interface mappings after upgrade.

Citrix XenServer default limits and upgrade

Citrix XenServer limits ramdisk to 128M by default. However the FMG-VM64-XEN image is larger than 128M. Before updating to FortiManager 6.4, increase the size of the ramdisk setting on Citrix XenServer.

To increase the size of the ramdisk setting:

1. On Citrix XenServer, run the following command:
`xenstore-write /mh/limits/pv-ramdisk-max-size 536,870,912`
2. Confirm the setting is in effect by running `xenstore-ls`.

`limits = ""`
`pv-kernel-max-size = "33554432"`
`pv-ramdisk-max-size = "536,870,912"`
`boot-time = ""`

3. Remove the pending files left in `/run/xen/pygrub`.



The ramdisk setting returns to the default value after rebooting.

Multi-step firmware upgrades

Prior to using the FortiManager to push a multi-step firmware upgrade, confirm the upgrade path matches the path outlined on our support site. To confirm the path, please run:

```
dia fwmanager show-dev-upgrade-path <device name> <target firmware>
```

Alternatively, you can push one firmware step at a time.

Hyper-V FortiManager-VM running on an AMD CPU

A Hyper-V FMG-VM running on a PC with an AMD CPU may experience a kernel panic. Fortinet recommends running VMs on an Intel-based PC.

SSLv3 on FortiManager-VM64-AWS

Due to known vulnerabilities in the SSLv3 protocol, FortiManager-VM64-AWS only enables TLSv1 by default. All other models enable both TLSv1 and SSLv3. If you wish to disable SSLv3 support, please run:

```
config system global
set ssl-protocol tlsv1
end
```

Upgrade Information



Prior to upgrading your FortiManager, please review the FortiManager Upgrade Guide in detail as it includes all of the necessary steps and associated details required to upgrade your FortiManager device or VM, including recommended upgrade paths.

See the *FortiManager Upgrade Guide* in the [Fortinet Document Library](#).



Before upgrading FortiManager, check ADOM versions. Check the ADOM versions supported by the destination firmware and the current firmware. If the current firmware uses ADOM versions not supported by the destination firmware, upgrade ADOM versions in FortiManager before upgrading FortiManager to the destination firmware version.

For example, FortiManager 7.2 supports ADOM versions 6.4, 7.0, and 7.2, but FortiManager 7.4 supports ADOM versions 7.0, 7.2, and 7.4. Before you upgrade FortiManager 7.2 to 7.4, ensure that all ADOM 6.4 versions have been upgraded to ADOM version 7.0 or later. See the *FortiManager Upgrade Guide* in the [Fortinet Document Library](#).

This section contains the following topics:

- [Downgrading to previous firmware versions on page 19](#)
- [Firmware image checksums on page 19](#)
- [FortiManager VM firmware on page 20](#)
- [SNMP MIB files on page 21](#)

Downgrading to previous firmware versions

FortiManager does not provide a full downgrade path. You can downgrade to a previous firmware release by using the GUI or CLI, but doing so results in configuration loss. A system reset is required after the firmware downgrade process has completed. To reset the system, use the following CLI commands via a console port connection:

```
execute reset {all-settings | all-except-ip}  
execute format {disk | disk-ext4 | disk-ext3}
```

Firmware image checksums

The MD5 checksums for all Fortinet software and firmware releases are available at the Customer Service & Support portal, <https://support.fortinet.com>. After logging in, go to *Download > Firmware Image Checksums*, enter the image file name including the extension, and select *Get Checksum Code*.

FortiManager VM firmware

Fortinet provides FortiManager VM firmware images for Amazon AWS, Amazon AWSOnDemand, Citrix and Open Source XenServer, Linux KVM, Microsoft Hyper-V Server, and VMware ESX/ESXi virtualization environments.

Amazon Web Services

- The 64-bit Amazon Machine Image (AMI) is available on the AWS marketplace.

Citrix XenServer and Open Source XenServer

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiManager VM installation.
- `.out.OpenXen.zip`: Download the 64-bit package for a new FortiManager VM installation. This package contains the QCOW2 file for the Open Source Xen Server.
- `.out.CitrixXen.zip`: Download the 64-bit package for a new FortiManager VM installation. This package contains the Citrix XenServer Virtual Appliance (XVA), Virtual Hard Disk (VHD), and OVF files.

Google Cloud Platform

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiManager VM installation.
- `.out.gcp.zip`: Download the 64-bit package for a new FortiManager VM installation.

Linux KVM

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiManager VM installation.
- `.out.kvm.zip`: Download the 64-bit package for a new FortiManager VM installation. This package contains QCOW2 that can be used by qemu.

Microsoft Azure

The files for Microsoft Azure have AZURE in the filenames, for example `<product>_VM64_AZURE-v<number>-build<number>-FORTINET.out.hyperv.zip`.

- `.out`: Download the firmware image to upgrade your existing FortiManager VM installation.

Microsoft Hyper-V Server

The files for Microsoft Hyper-V Server have HV in the filenames, for example, `<product>_VM64_HV-v<number>-build<number>-FORTINET.out.hyperv.zip`.

- `.out`: Download the firmware image to upgrade your existing FortiManager VM installation.
- `.hyperv.zip`: Download the package for a new FortiManager VM installation. This package contains a Virtual Hard Disk (VHD) file for Microsoft Hyper-V Server.



Microsoft Hyper-V 2016 is supported.

Oracle Private Cloud

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiManager VM installation.
- `.out.opc.zip`: Download the 64-bit package for a new FortiManager VM installation.

VMware ESX/ESXi

- `.out`: Download the 64-bit firmware image to upgrade your existing VM installation.
- `.ovf.zip`: Download either the 64-bit package for a new VM installation. This package contains an Open Virtualization Format (OVF) file for VMware and two Virtual Machine Disk Format (VMDK) files used by the OVF file during deployment.



For more information see the [FortiManager Data Sheet](#) available on the Fortinet web site. VM installation guides are available in the [Fortinet Document Library](#).

SNMP MIB files

You can download the *FORTINET-FORTIMANAGER-FORTIANALYZER.mib* MIB file in the firmware image file folder. The Fortinet Core MIB file is located in the main FortiManager version 5.00 file folder.

Product Integration and Support

This section lists FortiManager 7.4.6 support of other Fortinet products. It also identifies what FortiManager features are supported for managed platforms and what languages FortiManager supports. It also lists which Fortinet models can be managed by FortiManager.

The section contains the following topics:

- [Supported software on page 22](#)
- [Feature support on page 28](#)
- [Language support on page 29](#)
- [Supported models on page 30](#)
- [FortiExtender MODEM firmware compatibility on page 45](#)

Supported software

FortiManager 7.4.6 supports the following software:

- [Web browsers on page 23](#)
- [FortiOS and FortiOS Carrier on page 23](#)
- [FortiADC on page 23](#)
- [FortiAnalyzer on page 23](#)
- [FortiAnalyzer-BigData on page 24](#)
- [FortiAuthenticator on page 24](#)
- [FortiCache on page 24](#)
- [FortiCASB on page 24](#)
- [FortiClient on page 24](#)
- [FortiDDoS on page 24](#)
- [FortiDeceptor on page 25](#)
- [FortiFirewall and FortiFirewallCarrier on page 25](#)
- [FortiMail on page 25](#)
- [FortiPAM on page 25](#)
- [FortiProxy on page 26](#)
- [FortiSandbox on page 26](#)
- [FortiSASE on page 26](#)
- [FortiSOAR on page 26](#)
- [FortiSRA on page 27](#)
- [FortiSwitch ATCA on page 27](#)
- [FortiTester on page 27](#)
- [FortiToken on page 27](#)
- [FortiWeb on page 27](#)
- [Virtualization on page 27](#)



To confirm that a device model or firmware version is supported by the current firmware version running on FortiManager, run the following CLI command:

```
diagnose dvm supported-platforms list
```



Always review the Release Notes of the supported platform firmware version before upgrading your device.

Web browsers

FortiManager 7.4.6 supports the following web browsers:

- Microsoft Edge 114
- Mozilla Firefox version 96
- Google Chrome version 114

Other web browsers may function correctly, but are not supported by Fortinet.

FortiOS and FortiOS Carrier



The *FortiManager Release Notes* communicate support for FortiOS versions that are available at the time of the FortiManager 7.4.6 release. For additional information about other supported FortiOS versions, please refer to the FortiManager compatibility chart in the [Fortinet Document Library](#).

See [FortiManager compatibility with FortiOS](#).

FortiManager 7.4.6 supports the following versions of FortiOS and FortiOS Carrier:

- 7.4.0 to 7.4.6
- 7.2.0 to 7.2.10
- 7.0.0 to 7.0.16

FortiADC

FortiManager 7.4.6 supports the following versions of FortiADC:

- 7.4.0 and later
- 7.2.0 and later
- 7.1.0 and later

FortiAnalyzer

FortiManager 7.4.6 supports the following versions of FortiAnalyzer:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

FortiAnalyzer-BigData

FortiManager 7.4.6 supports the following versions of FortiAnalyzer-BigData:

- 7.2.0 and later
- 7.0.0 and later

FortiAuthenticator

FortiManager 7.4.6 supports the following versions of FortiAuthenticator:

- 6.6.0 and later
- 6.5.0 and later
- 6.4.0 and later
- 6.3.0 and later

FortiCache

FortiManager 7.4.6 supports the following versions of FortiCache:

- 4.2.0 and later
- 4.1.0 and later
- 4.0.0 and later

FortiCASB

FortiManager 7.4.6 supports the following versions of FortiCASB:

- 23.2.0 and later

FortiClient

FortiManager 7.4.6 supports the following versions of FortiClient:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later
- 6.4.0 and later

FortiDDoS

FortiManager 7.4.6 supports the following versions of FortiDDoS:

- 7.0.0 and later
- 6.6.0 and later
- 6.5.0 and later
- 6.4.0 and later
- 5.7.0 and later
- 5.6.0 and later

Limited support. For more information, see [Feature support on page 28](#).

FortiDeceptor

FortiManager 7.4.6 supports the following versions of FortiDeceptor:

- 5.3.0 and later
- 5.2.0 and later
- 5.1.0 and later
- 5.0.0 and later
- 4.3.0 and later

FortiFirewall and FortiFirewallCarrier

FortiManager 7.4.6 supports the following versions of FortiFirewall and FortiFirewallCarrier:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

FortiMail

FortiManager 7.4.6 supports the following versions of FortiMail:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

FortiPAM

FortiManager 7.4.6 supports the following versions of FortiPAM:

- 1.4.0 and later
- 1.3.0 and later
- 1.2.0 and later
- 1.1.0 and later
- 1.0.0 and later

FortiProxy

FortiManager 7.4.6 supports configuration management for the following versions of FortiProxy:

- 7.4.0 to 7.4.5
- 7.2.2, 7.2.3, 7.2.7, and 7.2.9
- 7.0.7 to 7.0.18



Configuration management support is identified as *Management Features* in these release notes. See [Feature support on page 28](#).

FortiManager 7.4.6 supports logs from the following versions of FortiProxy:

- 7.4.0 to 7.4.5
- 7.2.0 to 7.2.11
- 7.0.0 to 7.0.18
- 2.0.0 to 2.0.5
- 1.2.0 to 1.2.13
- 1.1.0 to 1.1.6
- 1.0.0 to 1.0.7

FortiSandbox

FortiManager 7.4.6 supports the following versions of FortiSandbox:

- 4.4.0 and later
- 4.2.0 and later
- 4.0.0 and 4.0.1
- 3.2.0 and later

FortiSASE

For more information about compatibility, see the [FortiSASE Release Notes](#).

FortiSOAR

FortiManager 7.4.6 supports the following versions of FortiSOAR:

- 7.4.0 and later
- 7.3.0 and later
- 7.2.0 and later

FortiSRA

FortiManager 7.4.6 supports the following versions of FortiSRA:

- 1.1.0 and later
- 1.0.0 and later

FortiSwitch ATCA

FortiManager 7.4.6 supports the following versions of FortiSwitch ATCA:

- 5.2.0 and later
- 5.0.0 and later
- 4.3.0 and later

FortiTester

FortiManager 7.4.6 supports the following versions of FortiTester:

- 7.3.0 and later
- 7.2.0 and later
- 7.1.0 and later

FortiToken

FortiManager 7.4.6 supports the following versions of FortiToken:

- 3.0.0 and later

FortiWeb

FortiManager 7.4.6 supports the following versions of FortiWeb:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

Virtualization

FortiManager 7.4.6 supports the following virtualization software:

Public Cloud

- Amazon Web Service AMI, Amazon EC2, Amazon EBS
- Alibaba Cloud
- Google Cloud Platform

- IBM Cloud
- Microsoft Azure
- Oracle Cloud Infrastructure

Private Cloud

- Citrix XenServer 7.2
- OpenSource XenServer 4.2.5
- Microsoft Hyper-V Server 2016, 2019, and 2022
- Nutanix
 - AHV 20220304 and later
 - AOS 6.5 and later
 - NCC 4.6 and later
 - LCM 3.0 and later
- RedHat 9.1
 - Other versions and Linux KVM distributions are also supported
- VMware ESXi versions 6.5 and later

Feature support

The following table lists FortiManager feature support for managed platforms.

Platform	Management Features	FortiGuard Update Services	VM License Activation	Reports	Logging
FortiGate	✓	✓	✓	✓	✓
FortiCarrier	✓	✓	✓	✓	✓
FortiADC		✓	✓		
FortiAnalyzer			✓	✓	✓
FortiAuthenticator					✓
FortiCache			✓	✓	✓
FortiClient		✓		✓	✓
FortiDDoS			✓	✓	✓
FortiDeceptor		✓			
FortiFirewall	✓				✓
FortiFirewall Carrier	✓				✓
FortiMail		✓	✓	✓	✓

Platform	Management Features	FortiGuard Update Services	VM License Activation	Reports	Logging
FortiPAM		✓	✓	✓	✓
FortiProxy	✓	✓	✓	✓	✓
FortiSandbox		✓	✓	✓	✓
FortiSOAR		✓	✓		
FortiSwitch ATCA	✓				
FortiTester		✓			
FortiWeb		✓	✓	✓	✓
Syslog					✓

Language support

The following table lists FortiManager language support information.

Language	GUI	Reports
English	✓	✓
Chinese (Simplified)	✓	✓
Chinese (Traditional)	✓	✓
French	✓	✓
Japanese	✓	✓
Korean	✓	✓
Portuguese		✓
Spanish		✓

To change the FortiManager language setting, go to *System Settings > Admin > Admin Settings*, in *Administrative Settings > Language* select the desired language on the drop-down menu. The default value is *Auto Detect*.

Russian, Hebrew, and Hungarian are not included in the default report languages. You can create your own language translation files for these languages by exporting a predefined language from FortiManager, modifying the text to a different language, saving the file as a different language name, and then importing the file into FortiManager. For more information, see the *FortiManager Administration Guide*.

Supported models

The following tables list which FortiGate, FortiCarrier, FortiDDoS, FortiAnalyzer, FortiMail, FortiSandbox, FortiSwitch ATCA, FortiWeb, FortiCache, FortiProxy, FortiAuthenticator, and other Fortinet product models and firmware versions can be managed by a FortiManager or send logs to a FortiManager running version 7.4.6.



Software license activated LENC devices are supported, if their platforms are in the supported models list. For example, support of FG-3200D indicates support of FG-3200D-LENC.

This section contains the following topics:

- [FortiGate models on page 30](#)
- [FortiGate special branch models on page 33](#)
- [FortiCarrier models on page 35](#)
- [FortiCarrier special branch models on page 37](#)
- [FortiADC models on page 37](#)
- [FortiAnalyzer models on page 38](#)
- [FortiAnalyzer-BigData models on page 39](#)
- [FortiAuthenticator models on page 39](#)
- [FortiCache models on page 39](#)
- [FortiDDoS models on page 40](#)
- [FortiDeceptor models on page 40](#)
- [FortiFirewall models on page 40](#)
- [FortiFirewallCarrier models on page 41](#)
- [FortiMail models on page 42](#)
- [FortiPAM models on page 42](#)
- [FortiProxy models on page 43](#)
- [FortiSandbox models on page 43](#)
- [FortiSOAR models on page 43](#)
- [FortiSRA models on page 44](#)
- [FortiSwitch ATCA models on page 44](#)
- [FortiTester models on page 44](#)
- [FortiWeb models on page 45](#)

FortiGate models

The following FortiGate models are released with FortiOS firmware. For information about supported FortiGate models on special branch releases of FortiOS firmware, see [FortiGate special branch models on page 33](#).

Model	Firmware Version
FortiGate: FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70F, FortiGate-71F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-DSL, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-90G, FortiGate-91E, FortiGate-91G, FortiGate-100F, FortiGate-101F, FortiGate-120G, FortiGate-121G, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300E, FortiGate-301E, FortiGate-400E, FortiGate-400F, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-401F, FortiGate-500E, FortiGate-501E, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-800D, FortiGate-900D, FortiGate-900G, FortiGate-901G, FortiGate-1000D, FortiGate-1000F, FortiGate-1001F, FortiGate-1100E, FortiGate-1101E, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3200F, FortiGate-3201F, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3600E-DC, FortiGate-3601E, FortiGate-3700D, FortiGate-3700F, FortiGate-3701F, FortiGate-3800D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate-4800F, FortiGate-4801F FortiGate 5000 Series: FortiGate-5001E, FortiGate-5001E1 FortiGate 6000 Series: FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC FortiGate 7000 Series: FortiGate-7000E, FortiGate-7000F, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC FortiGate DC: FortiGate-400F-DC, FortiGate-401F-DC, FortiGate-401E-DC, FortiGate-800D-DC, FortiGate-900G-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-DC, FortiGate-3000F-ACDC, FortiGate-3001F-DC, FortiGate-3001F-ACDC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC FortiWiFi: FWF-40F, FWF-40F-3G4G, FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-80F-2R, FWF-81F-2R, FWF-80F-2R-3G4G-DSL, FWF-81F-2R-3G4G-DSL, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE FortiGate VM: FortiGate-ARM64-AWS, FortiGate-ARM64-Azure, FortiGate-ARM64-GCP, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-Xen FortiGate Rugged: FGR-60F, FGR-60F-3G4G, FGR-70F, FGR-70F-3G4G	7.4

Model	Firmware Version
FortiGate: FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70F, FortiGate-71F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-DSL, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-90G, FortiGate-91E, FortiGate-91G, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-120G, FortiGate-121G, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300E, FortiGate-301E, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-400F, FortiGate-401E, FortiGate-401F, FortiGate-500E, FortiGate-501E, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-800D, FortiGate-900D, FortiGate-900G, FortiGate-901G, FortiGate-1000D, FortiGate-1000F, FortiGate-1001F, FortiGate-1100E, FortiGate-1101E, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3200F, FortiGate-3201F, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3601E, FortiGate-3700D, FortiGate-3700F, FortiGate-3701F, FortiGate-3800D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate-4800F, FortiGate-4801F FortiGate 5000 Series: FortiGate-5001E, FortiGate-5001E1 FortiGate 6000 Series: FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC FortiGate 7000 Series: FortiGate-7000E, FortiGate-7000F, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC FortiGate DC: FortiGate-400F-DC, FortiGate-401F-DC, FortiGate-401E-DC, FortiGate-800D-DC, FortiGate-900G-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-DC, FortiGate-3000F-ACDC, FortiGate-3001F-DC, FortiGate-3001F-ACDC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC, FortiGate-4800F-DC, FortiGate-4801F-DC FortiWiFi: FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-80F-2R, FWF-80F-2R-3G4G-DSL, FWF-81F-2R, FWF-81F-2R-3G4G-DSL, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE FortiGate VM: FortiGate-ARM64-AWS, FortiGate-ARM64-Azure, FortiGate-ARM64-GCP, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager	7.2

Model	Firmware Version
FortiOS-VM: FOS-VM64, FOS-VM64-HV, FOS-VM64-KVM, FOS-VM64-Xen	
FortiGate Rugged: FGR-60F, FGR-60F-3G4G, FGR-70F, FGR-70F-3G4G	
FortiGate: FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70F, FortiGate-71F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate- 80F-Bypass, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-91E, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-400F, FortiGate-401E, FortiGate-401F, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600D, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-800D, FortiGate-900D, FortiGate-1000D, FortiGate-1100E, FortiGate-1101E, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3601E, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate 5000 Series: FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1 FortiGate DC: FortiGate-400F-DC, FortiGate-401F-DC, FortiGate-401E-DC, FortiGate- 800D-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate- 1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate- 3000D-DC, FortiGate-3000F-DC, FortiGate-3000F-ACDC, FortiGate-3001F-DC, FortiGate- 3001F-ACDC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate- 3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate- 3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate- 3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate- 4401F-DC FortiWiFi: FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-80F-2R, FWF-81F-2R, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE FortiGate VM: FortiGate-ARM64-AWS, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate- VMX-Service-Manager FortiOS-VM: FOS-VM64, FOS-VM64-HV, FOS-VM64-KVM, FOS-VM64-Xen FortiGate Rugged: FGR-60F, FGR-60F-3G4G	7.0

FortiGate special branch models

The following FortiGate models are released on special branches of FortiOS. FortiManager version 7.4.6 supports these models on the identified FortiOS version and build number.

For information about supported FortiGate models released with FortiOS firmware, see [FortiGate models on page 30](#).

FortiOS 7.2

FortiGate Model	FortiOS Version	FortiOS Build
FortiGate-30G	7.2.8	6390
FortiGate-200G, FortiGate-201G	7.2.8	6397
FortiWiFi-30G	7.2.8	6390

FortiOS 7.0

FortiGate Model	FortiOS Version	FortiOS Build
FortiGate-50G-DSL	7.0.12	7353
FortiGate-50G-SFP	7.0.12	7192
FortiGate-50G-SFP-POE	7.0.12	7257
FortiGate-51G-SFP-POE	7.0.12	7257
FortiGate-80F-DSL	7.0.15	7272
FortiGate-90G, FortiGate-91G	7.0.15	7288
FortiGate-120G, FortiGate-121G	7.0.15	7277
FortiGate-900G, FortiGate-900G-DC, FortiGate-901G, FortiGate-901G-DC	7.0.15	7266
FortiGate-1000F, FortiGate-1001F	7.0.15	7267
FortiGate-3200F	7.0.15	7278
FortiGate-3201F	7.0.15	7273
FortiGate-3700F, FortiGate-3701F	7.0.15	7286
FortiGate-4800F, FortiGate-4800F-DC, FortiGate-4801F, FortiGate-4801F-DC	7.0.15	7286
FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC	7.0.15	0247
FortiGate-7000E, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC	7.0.15	0247
FortiGate-7000F, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC	7.0.15	0247

FortiGate Model	FortiOS Version	FortiOS Build
FortiGateRugged-70F, FortiGateRugged-70F-3G4G	7.0.15	7284
FortiWiFi-50G-5G	7.0.12	7192
FortiWiFi-50G-DSL	7.0.12	7353
FortiWiFi-50G-SFP	7.0.12	7192
FortiWiFi-80F-2R-3G4G-DSL	7.0.15	7272
FortiWiFi-81F-2R-3G4G-DSL	7.0.15	7272

FortiCarrier models

The following FortiCarrier models are released with FortiCarrier firmware.

For information about supported FortiCarrier models on special branch releases of FortiCarrier firmware, see [FortiCarrier special branch models on page 37](#).

Model	Firmware Version
FortiCarrier: FortiCarrier-2600F, FortiCarrier-2601F, FortiCarrier-3000D, FortiCarrier-3000F, FortiCarrier-3001F, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3200F, FortiCarrier-3201F, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3700F, FortiCarrier-3701F, FortiCarrier-3800D, FortiCarrier-3960E, FortiCarrier-3980E, FortiCarrier-4200F, FortiCarrier-4201F, FortiCarrier-4400F, FortiCarrier-4401F, FortiCarrier-4800F, FortiCarrier-4801F FortiCarrier 5000 Series: FortiCarrier-5001E, FortiCarrier-5001E1 FortiCarrier 6000 Series: FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC FortiCarrier 7000 Series: FortiCarrier-7000E, FortiCarrier-7000F, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC FortiCarrier-DC: FortiCarrier-2600F-DC, FortiCarrier-2601F-DC, FortiCarrier-3000D-DC, FortiCarrier-3000F-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC, FortiCarrier-4200F-DC, FortiCarrier-4201F-DC, FortiCarrier-4400F-DC, FortiCarrier-4401F-DC FortiCarrier-VM: FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-Azure, FortiCarrier-ARM64-GCP, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-KVM, FortiCarrier-VM64-IBM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen	7.4

Model	Firmware Version
<p>FortiCarrier: FortiCarrier-2600F, FortiCarrier-2601F, FortiCarrier-3000D, FortiCarrier-3000F, FortiCarrier-3001F, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3200F, FortiCarrier-3201F, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3700F, FortiCarrier-3701F, FortiCarrier-3800D, FortiCarrier-3960E, FortiCarrier-3980E, FortiCarrier-4200F, FortiCarrier-4201F, FortiCarrier-4400F, FortiCarrier-4401F, FortiCarrier-4800F, FortiCarrier-4801F</p> <p>FortiCarrier 5000 Series: FortiCarrier-5001E, FortiCarrier-5001E1</p> <p>FortiCarrier 6000 Series: FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC</p> <p>FortiCarrier 7000 Series: FortiCarrier-7000E, FortiCarrier-7000F, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC</p> <p>FortiCarrier-DC: FortiCarrier-2600F-DC, FortiCarrier-2601F-DC, FortiCarrier-3000D-DC, FortiCarrier-3000F-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC, FortiCarrier-4200F-DC, FortiCarrier-4201F-DC, FortiCarrier-4400F-DC, FortiCarrier-4401F-DC</p> <p>FortiCarrier-VM: FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-Azure, FortiCarrier-ARM64-GCP, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen</p>	7.2
<p>FortiCarrier: FortiCarrier-2600F, FortiCarrier-2601F, FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-3980E</p> <p>FortiCarrier 5000 Series: FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1</p> <p>FortiCarrier-DC: FortiCarrier-2600F-DC, FortiCarrier-2601F-DC, FortiCarrier-3000D-DC, FortiCarrier-3000F-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC</p> <p>FortiCarrier-VM: FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen, FortiCarrier-ARM64-KVM</p>	7.0

FortiCarrier special branch models

The following FortiCarrier models are released on special branches of FortiOS Carrier. FortiManager version 7.4.6 supports these models on the identified FortiOS Carrier version and build number.

For information about supported FortiCarrier models released with FortiOS Carrier firmware, see [FortiCarrier models on page 35](#).

FortiCarrier 7.0

FortiCarrier Model	FortiCarrier Version	FortiCarrier Build
FortiCarrier-3200F	7.0.15	7278
FortiCarrier-3201F	7.0.15	7273
FortiCarrier-3700F, FortiCarrier-3701F	7.0.15	7331
FortiCarrier-4800F, FortiCarrier-4800F-DC, FortiCarrier-4801F, FortiCarrier-4801F-DC	7.0.15	7286
FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC	7.0.15	0247
FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC	7.0.15	0247
FortiCarrier-7000F, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC	7.0.15	0247

FortiADC models

Model	Firmware Version
FortiADC: FortiADC-100F, FortiADC-120F, FortiADC-200D, FortiADC-200F, FortiADC-220F, FortiADC-300D, FortiADC-300F, FortiADC-400D, FortiADC-400F, FortiADC-420F, FortiADC-700D, FortiADC-1000F, FortiADC-1200F, FortiADC-1500D, FortiADC-2000D, FortiADC-2000F, FortiADC-2200F, FortiADC-4000D, FortiADC-4000F, FortiADC-4200F, FortiADC-5000F FortiADC VM: FortiADC-VM	7.4

Model	Firmware Version
FortiADC: FortiADC-100F, FortiADC-120F, FortiADC-200D, FortiADC-200F, FortiADC-220F, FortiADC-300D, FortiADC-300F, FortiADC-400D, FortiADC-400F, FortiADC-700D, FortiADC-1000F, FortiADC-1200F, FortiADC-1500D, FortiADC-2000D, FortiADC-2000F, FortiADC-2200F, FortiADC-4000D, FortiADC-4000F, FortiADC-4200F, FortiADC-5000F FortiADC VM: FortiADC-VM	7.1, 7.2

FortiAnalyzer models

Model	Firmware Version
FortiAnalyzer: FortiAnalyzer-150G, FortiAnalyzer-300F, FortiAnalyzer-300G, FortiAnalyzer-400E, FortiAnalyzer-800F, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-2000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3510G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E FortiAnalyzer VM: FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-AWS-OnDemand, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-Azure-OnDemand, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-Xen	7.4
FortiAnalyzer: FortiAnalyzer-150G, FortiAnalyzer-300F, FortiAnalyzer-300G, FortiAnalyzer-400E, FortiAnalyzer-800F, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-2000E, FortiAnalyzer-3000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3500E, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3510G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E FortiAnalyzer VM: FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-AWS-OnDemand, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-Azure-OnDemand, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-Xen	7.2
FortiAnalyzer: FortiAnalyzer-150G, FortiAnalyzer-200F, FortiAnalyzer-300F, FortiAnalyzer-300G, FortiAnalyzer-400E, FortiAnalyzer-800F, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-2000E, FortiAnalyzer-3000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3500E, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E FortiAnalyzer VM: FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-ALI-OnDemand, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-Azure-OnDemand, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-GCP-OnDemand, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-Xen	7.0

FortiAnalyzer-BigData models

Model	Firmware Version
FortiAnalyzer-BigData: FortiAnalyzer-BigData-4500F FortiAnalyzer-BigData VM: FortiAnalyzer-BigData-VM64	7.2
FortiAnalyzer-BigData: FortiAnalyzer-BigData-4500F FortiAnalyzer-BigData VM: FortiAnalyzer-BigData-VM64	7.0

FortiAuthenticator models

Model	Firmware Version
FortiAuthenticator: FAC-200E, FAC-300F, FAC-400E, FAC-800F, FAC-2000E, FAC-3000E, FAC-3000F FortiAuthenticator VM: FAC-VM	6.6
FortiAuthenticator: FAC-200E, FAC-300F, FAC-400E, FAC-800F, FAC-2000E, FAC-3000E, FAC-3000F FortiAuthenticator VM: FAC-VM	6.5
FortiAuthenticator: FAC-200D, FAC-200E, FAC-300F, FAC-400C, FAC-400E, FAC-800F, FAC-1000C, FAC-1000D, FAC-2000E, FAC-3000D, FAC-3000E, FAC-3000F FortiAuthenticator VM: FAC-VM	6.4
FortiAuthenticator: FAC-200D, FAC-200E, FAC-300F, FAC-400C, FAC-400E, FAC-800F, FAC-1000C, FAC-1000D, FAC-2000E, FAC-3000D, FAC-3000E FortiAuthenticator VM: FAC-VM	6.3

FortiCache models

Model	Firmware Version
FortiCache: FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3000E, FCH-3900E FortiCache VM: FCH-KVM, FCH-VM64	4.1, 4.2
FortiCache: FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3900E FortiCache VM: FCH-VM64	4.0

FortiDDoS models

Model	Firmware Version
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-2000F, FortiDDoS-3000F FortiDDoS VM: FortiDDoS-VM	7.0
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-2000F, FortiDDoS-3000F FortiDDoS VM: FortiDDoS-VM	6.6
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-2000F, FortiDDoS-3000F FortiDDoS VM: FortiDDoS-VM	6.5
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-2000F, FortiDDoS-3000F FortiDDoS VM: FortiDDoS-VM	6.4
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-2000F FortiDDoS VM: FortiDDoS-VM	6.3
FortiDDoS: FortiDDoS-200B, FortiDDoS-400B, FortiDDoS-600B, FortiDDoS-800B, FortiDDoS-900B, FortiDDoS-1000B, FortiDDoS-1200B, FortiDDoS-1500E, FortiDDoS-2000B, FortiDDoS-2000E	5.6, 5.7

FortiDeceptor models

Model	Firmware Version
FortiDeceptor: FDC-100G, FDC-1000F, FDC-1000G FortiDeceptor Rugged: FDCR-100G FortiDeceptor VM: FDC-VM	5.0, 5.1, 5.2, 5.3, 6.0
FortiDeceptor: FDC-1000F, FDC-1000G FortiDeceptor Rugged: FDCR-100G FortiDeceptor VM: FDC-VM	4.3

FortiFirewall models

Some of the following FortiFirewall models are released on special branches of FortiFirewall firmware. FortiManager version 7.4.6 supports these models on the identified FortiFirewall firmware version and build number.

FortiFirewall 7.4

Model	Firmware Version
FortiFirewall: FortiFirewall-1801F, FortiFirewall-2600F, FortiFirewall-3001F, FortiFirewall-3501F, FortiFirewall-3980E, FortiFirewall-4200F, FortiFirewall-4400F, FortiFirewall-4401F, FortiFirewall-4801F	7.4

Model	Firmware Version
FortiFirewall DC: FortiFirewall-3980E-DC, FortiFirewall-4200F-DC, FortiFirewall-4400F-DC, FortiFirewall-4401F-DC	
FortiFirewall-VM: FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.4

FortiFirewall 7.2

Model	Firmware Version
FortiFirewall: FortiFirewall-3980E, FortiFirewall-4200F, FortiFirewall-4400F, FortiFirewall-4401F, FortiFirewall-4801F	7.2
FortiFirewall DC: FortiFirewall-4200F-DC, FortiFirewall-4401F-DC	
FortiFirewall-VM: FortiFirewall-VM64, FortiFirewall-VM64-KVM	

FortiFirewall 7.0

Model	Firmware Version	Firmware Build (for special branch)
FortiFirewall: FortiFirewall-3001F	7.0.10	4955
FortiFirewall: FortiFirewall-3501F	7.0.10	4955
FortiFirewall: FortiFirewall-3980E	7.0	
FortiFirewall DC: FortiFirewall-3980E-DC		
FortiFirewall-VM: FortiFirewall-VM64, FortiFirewall-VM64-KVM		

FortiFirewallCarrier models

Some of the following FortiFirewallCarrier models are released on special branches of FortiFirewallCarrier firmware. FortiManager version 7.4.6 supports these models on the identified FortiFirewallCarrier firmware version and build number.

Model	Firmware Version
FortiFirewallCarrier: FortiFirewallCarrier-1801F, FortiFirewallCarrier-2600F, FortiFirewallCarrier-3501F, FortiFirewallCarrier-3980E, FortiFirewallCarrier-4200F, FortiFirewallCarrier-4400F, FortiFirewallCarrier-4401F	7.4
FortiFirewallCarrier DC: FortiFirewallCarrier-1801F-DC, FortiFirewallCarrier-4200F-DC, FortiFirewallCarrier-4401F-DC	
FortiFirewallCarrier-VM: FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	
FortiFirewallCarrier: FortiFirewallCarrier-2600F, FortiFirewallCarrier-3980E, FortiFirewallCarrier-4200F, FortiFirewallCarrier-4400F, FortiFirewallCarrier-4801F	7.2

Model	Firmware Version
FortiFirewallCarrier DC: FortiFirewallCarrier-4200F-DC	
FortiFirewallCarrier-VM: FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	
FortiFirewallCarrier-VM: FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.0

FortiFirewall special branch models

Model	Firmware Version	Firmware Build
FortiFirewallCarrier: FortiFirewallCarrier-1801F, FortiFirewallCarrier-4401F	7.2.6	4609
FortiFirewallCarrier: FortiFirewallCarrier-3001F	7.0.10	4955
FortiFirewallCarrier: FortiFirewallCarrier-3501F	7.0.10	4940

FortiMail models

Model	Firmware Version
FortiMail: FE-200F, FE-400F, FE-900F, FE-2000E, FE-2000F, FE-3000E, FE-3000F, FE-3200E	7.4
FortiMail VM: FML-VM, FortiMail Cloud	
FortiMail: FE-60D, FE-200D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-2000E, FE-2000F, FE-3000E, FE-3000F, FE-3200E	7.2
FortiMail VM: FML-VM, FortiMail Cloud	
FortiMail: FE-60D, FE-200D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-1000D, FE-2000E, FE-2000F, FE-3000D, FE-3000E, FE-3000F, FE-3200E	7.0
FortiMail VM: FML-VM, FortiMail Cloud	

FortiPAM models

Model	Firmware Version
FortiPAM: FortiPAM-1000G, FortiPAM-3000G	1.0, 1.1, 1.2, 1.3, 1.4
FortiPAM VM: FortiPAM-AWS, FortiPAM-Azure, FortiPAM-GCP, FortiPAM-HyperV, FortiPAM-KVM, FortiPAM-VM64	

FortiProxy models

Model	Firmware Version
FortiProxy: FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G FortiProxy VM: FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-OPC, FortiProxy-VM64	7.4
FortiProxy: FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G FortiProxy VM: FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-VM64	7.2
FortiProxy: FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G FortiProxy VM: FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-OPC, FortiProxy-VM64	7.0
FortiProxy: FPX-400E, FPX-2000E, FPX-4000E FortiProxy VM: FortiProxy-KVM, FortiProxy-VM64	1.0, 1.1, 1.2, 2.0

FortiSandbox models

Model	Firmware Version
FortiSandbox: FSA-500F, FSA-500G, FSA-1000D, FSA-1000F, FSA-1500G, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3000F, FSA-3500D FortiSandbox DC: FSA-1000F-DC FortiSandbox-VM: FortiSandbox-AWS, FortiSandbox-Cloud, FSA-VM	4.2, 4.4
FortiSandbox: FSA-500F, FSA-1000D, FSA-1000F, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3000F, FSA-3500D FortiSandbox DC: FSA-1000F-DC FortiSandbox-VM: FortiSandbox-AWS, FortiSandbox-Cloud, FSA-VM	4.0
FortiSandbox: FSA-500F, FSA-1000D, FSA-1000F, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D FortiSandbox DC: FSA-1000F-DC FortiSandbox-VM: FortiSandbox-AWS, FSA-VM	3.2

FortiSOAR models

Model	Firmware Version
FortiSOAR VM: FortiSOAR-VM	7.2, 7.3, 7.4

FortiSRA models

Model	Firmware Version
FortiSRA: FortiSRA-1000G, FortiSRA-3000G	1.0, 1.1
FortiSRA-VM: FortiSRA-Azure, FortiSRA-HyperV, FortiSRA-KVM, FortiSRA-VM64	

FortiSwitch ATCA models

Model	Firmware Version
FortiController: FTCL-5103B, FTCL-5903C, FTCL-5913C	5.2
FortiSwitch-ATCA: FS-5003A, FS-5003B	5.0
FortiController: FTCL-5103B	
FortiSwitch-ATCA: FS-5003A, FS-5003B	4.3

FortiTester models

Model	Firmware Version
FortiTester: FortiTester-100F, FortiTester-2000D, FortiTester-2000E, FortiTester-2000F, FortiTester-2500E, FortiTester-3000E, FortiTester-3000F, FortiTester-4000E, FortiTester-4000F FortiTester VM: FortiTester-VM, FortiTester-VM-ALI-BYOL, FortiTester-VM-ALI-PAYG, FortiTester-VM-AWS-BYOL, FortiTester-VM-AWS-PAYG, FortiTester-VM-AZURE-BYOL, FortiTester-VM-AZURE-PAYG, FortiTester-VM-GCP-BYOL, FortiTester-VM-GCP-PAYG, FortiTester-VM-IBM-BYOL, FortiTester-VM-IBM-PAYG, FortiTester-VM-KVM, FortiTester-VM-OCI-BYOL, FortiTester-VM-OCI-PAYG	7.3
FortiTester: FortiTester-100F, FortiTester-2000D, FortiTester-2000E, FortiTester-2000F, FortiTester-2500E, FortiTester-3000E, FortiTester-3000F, FortiTester-4000E, FortiTester-4000F FortiTester VM: FortiTester-VM, FortiTester-VM-ALI-BYOL, FortiTester-VM-ALI-PAYG, FortiTester-VM-AWS-BYOL, FortiTester-VM-AWS-PAYG, FortiTester-VM-AZURE-BYOL, FortiTester-VM-AZURE-PAYG, FortiTester-VM-GCP-BYOL, FortiTester-VM-GCP-PAYG, FortiTester-VM-IBM-BYOL, FortiTester-VM-IBM-PAYG, FortiTester-VM-KVM, FortiTester-VM-OCI-BYOL, FortiTester-VM-OCI-PAYG	7.2
FortiTester: FortiTester-60F, FortiTester-100F, FortiTester-2000D, FortiTester-2000E, FortiTester-2000F, FortiTester-2500E, FortiTester-3000E, FortiTester-3000F, FortiTester-4000E, FortiTester-4000F FortiTester VM: FortiTester-VM, FortiTester-VM-ALI-BYOL, FortiTester-VM-ALI-PAYG, FortiTester-VM-AWS-BYOL, FortiTester-VM-AWS-PAYG, FortiTester-VM-AZURE-BYOL, FortiTester-VM-AZURE-PAYG, FortiTester-VM-GCP-BYOL, FortiTester-VM-GCP-PAYG, FortiTester-VM-IBM-PAYG, FortiTester-VM-KVM, FortiTester-VM-OCI-BYOL, FortiTester-VM-OCI-PAYG	7.1

FortiWeb models

Model	Firmware Version
FortiWeb: FortiWeb-100D, FortiWeb-100E, FortiWeb-100F, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-400F, FortiWeb-600D, FortiWeb-600E, FortiWeb-600F, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-1000F, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer	7.4
FortiWeb: FortiWeb-100D, FortiWeb-100E, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-600D, FortiWeb-600E, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-1000F, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer	7.2
FortiWeb: FortiWeb-100D, FortiWeb-100E, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-600D, FortiWeb-600E, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer	7.0

FortiExtender MODEM firmware compatibility

See the [FortiOS Release Notes](#) for a list of MODEM firmware filename and version for each FortiExtender model and where in the world the MODEMs are compatible.

Resolved issues

The following issues have been fixed in 7.4.6. To inquire about a particular bug, please contact [Customer Service & Support](#).

AP Manager

Bug ID	Description
1076200	Policy install fails due to FortiManager installs unexpected changes related to "<wifi_intf> address".
1081136	FortiManager is trying to delete and create ssid interface subnet address after upgrade.

Device Manager

Bug ID	Description
952422	IPsec templates created by SDWAN Overlay does not create tunnels for all the underlay interfaces.
1039591	The Link Status entries are blank under the Interfaces >>> Network.
1041440	Some FortiGate platforms (FGT-40F & FGT-60F) do not support the "ip-managed-by-fortiipam" and FortiGate refuses to take the configuration from FortiManager; hence users will be experiencing the install error.
1053194	If the "system interface speed" attribute is changed from the FortiManager, it may potentially cause an installation failure. Modifying the "system interface speed" is not currently supported on the FortiManager and must be done on the FortiGate side.
1063635	FortiManager does not support the "FortiWiFi-80F-2R-3G4G-DSL".
1063835	FortiManager ZTP installation to FortiGate versions 7.2.8 and lower may fail due to differing default "ssh-kex-algo" settings between FortiManager and FortiGate.
1074717	An error might be observed when the SD-WAN template health check name contains a space, displaying the following message: "Bad health check name...".
1075052	Occasionally, installations may fail on FortiGates in HA mode due to a "Serial number does NOT match" error. This can happen if the HA device's serial number on FortiManager does not immediately update after a failover.

Bug ID	Description
1075281	Unable to add FortiAnalyzer to FortiManager when "fgfm-peer-cert-without-sn" is enabled.
1075747	SD-WAN Monitor does not display the members under the SD-WAN Rules (Map View or Table View). This issue is most likely to occur when "priority-zone" is configured.
1080414	CSV import fails to set metadata variables due to old header format ("name").
1099824	FortiManager may push the ICAP and WAF profile configurations to low-end FortiGate models that do not support these features, potentially causing installation failures.

FortiSwitch Manager

Bug ID	Description
1075021	Users with the "admin profile" rights cannot access the <i>FortiSwitch Manager</i> .

Others

Bug ID	Description
998198	When upgrading ADOM, the upgrade process fails with the following error: "invalid value - can not find import template 'XYZ'".
1003711	During the FortiGate HA upgrade, both the primary and secondary FortiGates may reboot simultaneously, which can disrupt the network. This issue is more likely to occur in FortiGates that require disk checks, leading to longer boot times.
1058185	FortiProxy policies not imported if the policies have either internet service or IPv6 used in the source or destination.
1078947	Repeatedly testing the URL rating on FortiManager (<code>diagnose fmupdate test fgd-url-rating...</code>) may cause the "fgdsvr daemon" to crash.

Policy and Objects

Bug ID	Description
978136	Occasionally, installation may fail due to an error message, "Waiting for another session", which prevents policies from being installed from FortiManager. During this issue, the following message may also appear: "Blocked by session id(XYZ) username(n/a)". This issue may be caused by a signal loss between the child and parent security console processes, leading the parent process to continue waiting for a copy result.
986256	When creating the application list on the FortiManager, if the Category ID is set to 33 or 34, the installation does not display any errors. However, these invalid categories cannot be set on the FortiGate. Consequently, the assigned application list entry will be created without a specific category and will default to the "block" action. This behavior may cause network interruptions.
991720	FortiManager still has an option to enable the "match-vip" through the policy package for "allow" policies. However, this is not supported anymore on the FortiGates.
1029921	Under the "Web Application Firewall" security profiles, users are unable to disable the signatures through the GUI.
1071226	Policy Lookup is not showing result as highlighted when the sections are not expended.
1074686	FortiManager fails to import NAC policies.
1076659	When policy package configured with policy block, installation to multiple devices may have copy fail errors if combined length of the Policy Block name and Policy name is greater than 35 characters and if the total number of such policies exceeds 1000.
1077964	After ZTNA server real server address type changes from FQDN to IP, the policy installation may fail; FortiManager pushes ZTNA server config with wrong order.
1079678	FortiManager does not provide any warning when there is a "deny all" policy in the middle of a Policy Package. This can be still seen on the "task monitor".

System Settings

Bug ID	Description
1047252	Incorrect warning message displayed in FortiManager GUI during upgrade from Feature build to Mature build.

Known issues

Known issues are organized into the following categories:

- [New known issues](#)
- [Existing known issues](#)

To inquire about a particular bug or to report a bug, please contact [Fortinet Customer Service & Support](#).

New known issues

The following issues have been identified in version 7.4.6.

Policy & Objects

Bug ID	Description
969923	The "View Mode" button, which is used to check the interface in Pair View, is missing in the Firewall Policy under Policy Packages.

Existing known issues

The following issues have been identified in a previous version of FortiManager and remain in FortiManager 7.4.6.

AP Manager

Bug ID	Description
1032762	Since FortiOS 7.4.4 now supports the selection of multiple 802.11 protocols and has trimmed the band options, importing FortiOS 7.4.3 AP profiles may result in some bands and channels being un-matched or unset.
1041445	The AP attributes do not automatically update in the <i>AP Manager</i> .
1050466	The 802.11ax-5g AP profile is missing for all FortiAPs that support WiFi 6.

Device Manager

Bug ID	Description
973365	<p>FortiManager does not display the IP addresses of FortiGate interfaces configured with DHCP addressing mode.</p> <p>Workaround:</p> <p>Disable Addressing Mode from DHCP to Manual in FortiManager Device DB, then retrieve from FortiGate and IP will be updated successfully.</p>
974925	<p>The NTP Server setting may not display the correct configuration. This issue might occur on managed devices running FortiOS version 7.4.2 or higher.</p> <p>Workaround:</p> <p>Edit NTP server setting under CLI configuration.</p>
980362	<p>The Firmware Version column in <i>Device Manager</i> incorrectly shows "Upgrading FortiGate from V1 to V2" even after a successful upgrade has been completed.</p>
1004220	<p>The SD-WAN Overlay template creates route-map names that exceed the 35-character limit.</p>
1062545	<p>When using the backslash "\" in the preshared key of IPSEC settings, the install may fail.</p>
1063850	<p>FortiManager is attempting to install a "PRIVATE KEY" with every installation, even after retrieving the config.</p>
1086303	<p>An installation error may occur when binding and installing the created VLAN interface to the software switch due to <code>ip-managed-by-fortiipam</code>. No issues have been observed with the installation of VLAN interfaces or physical interfaces.</p> <p>Workaround:</p> <p>Use a script (CLI template) on device database on FortiManager to unset "<code>ip-managed-by-fortiipam</code>" under wan interface (every time before installation), and then install the configuration.</p>

FortiSwitch Manager

Bug ID	Description
1110598	<p>Unable to add per device mapping config for FortiSwitch VLAN.</p> <p>Workaround:</p> <p>A script can be run on "Policy Package or ADOM Database". The following is an example:</p> <pre>config fsp vlan edit "vlan200" set vlanid 200 set _dhcp-status disable config interface set ip-managed-by-fortiipam disable end</pre>

Bug ID	Description
	<pre> config dynamic_mapping edit "FortiGate-80F-POE"-"root" set _dhcp-status disable config interface set vlanid 20 end config dhcp-server set dns-service default set ntp-service default set timezone-option default end next end next end </pre>

Others

Bug ID	Description
830592	Upgrade of ADOM type FortiProxy is not supported.
1019261	<p>Unable to upgrade ADOM from 7.0 to 7.2, due to the error "Do not support urlfilter-table for global scope webfilter profile".</p> <p>Workaround:</p> <p>Run the following script against the ADOM DB:</p> <pre> config webfilter profile edit "g-default" config web unset urlfilter-table end next end </pre>
1049457	When FortiAnalyzer is added as a managed device, users may encounter an issue in the FortiManager GUI when expanding the log details.
1080463	An admin with access to a specific ADOM can view the database and clone objects to another ADOM, even if they do not have direct access to it.

Policy & Objects

Bug ID	Description
845022	SDN Connector failed to import objects from VMware VSphere.

Bug ID	Description
971065	When the number of Custom Internet Services exceeds 256, installation fails due to this limitation.
1025012	<p>Configuring the SSL/SSH inspection profile may result in the following error: "The server certificate replacement mode cannot support category exemptions."</p> <p>Workaround:</p> <ol style="list-style-type: none"> 1. Modify the SSL/SSH inspection profiles. 2. Toggle from <i>Protecting SSL Server</i> to <i>Multiple Clients Connecting to multiple Servers</i>. 3. Remove the categories from the <i>Exempt from SSL inspection</i> list. 4. Toggle back to <i>Protecting SSL Server</i> and click OK. 5. Then install.
1030914	Copy and paste function in GUI removes name of the policy rule and adds unwanted default security profiles (SSL-SSH no-inspection and default PROTOCOL OPTIONS).
1057228	Importing the SDN Objects, with multiple tags, will add multiple entries listed as SDN objects; when clients add anything into the filters section, browser immediately redirects to an error page showing: "Oops! Sorry, an unexpected error has occurred"
1079128	ZTNA Server Per-Device Mapping may display a copy error failure if a new per-device mapping is created without specifying the object interface.
1086603	Unable to create local-in policy with ISDB objects

Script

Bug ID	Description
931088	Unable to delete VDOMs using the FortiManager script. Interfaces remain in the device database, causing the installation to fail.
1085374	FortiManager does not support exporting the TCL scripts via CLI.

System Settings

Bug ID	Description
825319	FortiManager fails to promote a FortiGate HA member (running on firmware 7.2.0 to 7.2.4) to the Primary.
1063040	<p>Unable to import a local certificate into FortiManager. This issue may occur if the certificate is encrypted with a newer OpenSSL version that FortiManager does not yet support.</p> <p>Workaround:</p> <p>Convert the latest certificate to the legacy format before uploading it to FortiManager.</p>

Appendix A - FortiGuard Distribution Servers (FDS)

In order for FortiManager to request and retrieve updates from FDS, and for FortiManager to serve as an FDS, please configure the necessary settings on all devices between FortiManager and FDS, or between FortiManager and FortiGate devices based on the following items:

- FortiManager accesses FDS for antivirus and attack updates through TCP/SSL port 443.
- If there is a proxy server between FortiManager and FDS, FortiManager uses port 443 to communicate with the proxy server in *tunnel* mode by default. Alternatively, you can configure web proxy to use *proxy* mode using port 80. For more information, see the [FortiManager Administration Guide](#).

FortiGuard Center update support

You can configure FortiManager as a local FDS to provide FortiGuard updates to other Fortinet devices and agents on your network. The following table lists which updates are available per platform:

Platform	Update Service	Query Service
FortiGate	✓	✓
FortiADC	✓	
FortiCache	✓	
FortiCarrier	✓	✓
FortiClient	✓	
FortiDeceptor	✓	✓
FortiDDoS	✓	
FortiEMS	✓	
FortiMail	✓	✓
FortiProxy	✓	✓
FortiSandbox	✓	✓
FortiSOAR	✓	
FortiTester	✓	
FortiWeb	✓	

Appendix B - Default and maximum number of ADOMs supported

This section identifies the supported number of ADOMs for FortiManager hardware models and virtual machines.

Hardware models

FortiManager supports a default number of ADOMs based on hardware model.

Some hardware models support an ADOM subscription license. When you purchase an ADOM subscription license, you increase the number of supported ADOMs. For example, you can purchase an ADOM subscription license for the FMG-3000G series, which allows you to use up to a maximum of 8000 ADOMs.

Other hardware models do not support the ADOM subscription license. For hardware models that do not support the ADOM subscription license, the default and maximum number of ADOMs is the same.

FortiManager Platform	Default number of ADOMs	ADOM license support?	Maximum number of ADOMs
200G Series	30		30
300F Series	100		100
400G Series	150		150
1000F Series	1000		1000
2000E Series	1200		1200
3000G Series	4000	✓	8000
3700G Series	10,000	✓	12,000

For FortiManager F series and earlier, the maximum number of ADOMs is equal to the maximum devices/VDOMs as described in the [FortiManager Data Sheet](#).

Virtual Machines

FortiManager VM subscription license includes five (5) ADOMs. Additional ADOMs can be purchased with an ADOM subscription license.

For FortiManager VM perpetual license, the maximum number of ADOMs is equal to the maximum number of Devices/VDOMs listed in the [FortiManager Data Sheet](#).



- FortiManager-VM subscription licenses are fully stackable.
 - For FortiManager-VM perpetual licenses, only the number of managed devices is stackable.
-



www.fortinet.com

Copyright© 2024 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet's Chief Legal Officer, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet's internal lab tests. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.