

Distributed Worldwide by American Music and Sound
925 Broadbeck Drive, Suite 220
Newbury Park, CA 91320 U.S.A.
Tel: (800) 431-2609 Fax: (800) 431-3129

©2022 CAD Audio Rev00 0622



WIRELESS
WX1000BP

User Guide



Introduction

Enjoy the easy and exciting performance that the WX1000BP provides for your next performance. CAD Audio has been creating valued product since 1931 and prides itself on developing and supporting the live performer. Our concept was straightforward – develop a high value wireless microphone system that can cope with today's challenging RF environment that is both easy to operate and exciting to use.

The WX1000BP is a Frequency Agile UHF Wireless Body Pack System which operates in the 555.1 - 579.85MHz frequency band and features 100 channels for optimum clarity of signal. Auto-scan and IR sync functions make set up and channel-changing a breeze. Enjoy up to 12 hours of run time using two AA batteries, with a battery level indicator on both the transmitter and receiver, so you'll know when you need to replace them. All metal construction and included rack mounting hardware help ensure your equipment will stand up to even the toughest conditions. System includes head-worn mic, lavalier mic, and guitar cable.

The WX1000BP includes the following features:

- Frequency Agile Design (100 switchable frequencies)
- Use up to 20 systems at the same time
- Up to 295' (90m) range between transmitter and receiver
- Rugged, all metal construction
- Auto scan finds the optimal frequency setting
- IR sync wirelessly matches transmitter and receiver frequencies
- Transmitter features battery life indicator
- Transmitter utilizes 2 AA Batteries with >12 Hrs of operation
- Rack mounting hardware and antenna relocation kit included
- Head-worn and lavalier microphones and guitar/instrument cable included
- 2 Year Warranty

Operating Instruction

- Power on/off
- Volume Up: short press (▲)
- Volume Down: short press (▼)
- Synchronizing: short press the middle "SET" button, the system will enter into its pairing mode

Bring the transmitter 2" (5cm) close to the "IR indicator" on the left of the front panel, and the receiver and transmitter will be synchronized

- **Frequency Setting Manually:** Long press (▲) to enter the manual setting mode. Press (▲) and (▼) to select channel 0-99
- **Frequency Automatic Scanning Feature:** Long press (▼) to enter auto-scanning mode, and the system will scan for the best possible frequency to eliminate radio interference
- **Lock/unlock Setting:** press (▲)(▼) at the same time, the "LOCK SIGN" on the LCD screen will display or conceal

FCC Statemen

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment.

Receiver RX1000 (Fro

1. Antenna
2. IR node
3. RF peak indicator
4. AF peak indicator
5. Channel display
6. Frequency display
7. Mute indicator
8. Set Frequency
Channel up/down
9. Power on/off



1. Antenna jack
2. XLR-type balanced output
3. 1/4" unbalanced output
4. DC power jack (use included supp




Specifications WX100

Frequency Response.....	30Hz - 1
Frequency Range.....	555.1MHz - 579.85
Frequency Mode.....	
Channels.....	
Receiver Sensitivity.....	<108
Signal-to-Noise Ratio.....	
Harmonic Distortion.....	
Dynamic Range.....	>10
Delay.....	
Operating Range.....	278' (85m) in open area, 196' (60m) indoor
Audio Output.....	XLR balanced out

Antenna Plug.....	1x TNC, 50Ω
Power Requirements.....	DC 12V
Dimensions	16" x 12.1" x 2.8" (40.5cm x 30.7cm x 7.1cm)
Weight	3.3Lbs (1.5kg)

Bodypack TX1000 Transmitter

1. Antenna
2. Audio input jack
3. Power Switch
4. LCD display
5. Battery compartment



Ces dispositifs opèrent sur une non-interférence, non-protection. Should the user seek to obtain protection for radio services operating in the same TV bands, a licence is required. For further details, consult the Science and Economic Development Canada's CRTC Procedures Circular CPC-2-18, Voluntary Licence/Licence-Exempt Wireless Microphones in the TV Bands.

Individuals with cardiac pacemakers and other similar medical devices should consult with their physician before using any RF devices. Though the output level of this wireless system is below 50 milliwatts, the proximity of the transmitter to the implant device could pose a threat.

As with any wireless product, environmental conditions can reduce or in some cases prohibit a successful connection between the transmitter and the receiver.

This device complies with Part 15 of the FCC Rules. Most users of CAD Audio wireless products in the United States do not need a license for operation. However, the rules for unlicensed operation state that this device may not operate in excess of 50 milliwatts and it must not cause harmful interference to other wireless devices, and must accept interference received from other devices. Wireless products must also meet FCC factory standards and rules. The FCC reserves the right to change these rules at any time. For more information contact the FCC at 1-888-CALL-FCC (TTY: 1-888-TELL-FCC) or visit the FCC's wireless microphone website at:

www.fcc.gov/cgb/wirelessmicrophone

This device complies with Industry Canada licence-exempt RSS standard(s).
Operation is subject to the following two conditions: (1) this device may not
cause interference, and (2) this device must accept any interference, including
interference that may cause undesired operation of the device.

Under Industry Canada regulations, this radio transmitter may only operate using an antenna of a type and maximum (or lesser) gain approved for the transmitter by Industry Canada. To reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropically radiated power (e.i.r.p.) is not more than that necessary for successful communication.

Conformément à la réglementation d'Industrie Canada, le présent émetteur radio peut fonctionner avec une antenne d'un type et d'un gain maximal (ou inférieur) approuvé pour l'émetteur par Industrie Canada. Dans le but de réduire les risques de brouillage radioélectrique à l'intention des autres utilisateurs, il est choisi le type d'antenne et son gain de sorte que la puissance isotrope rayonnée équivalente (p.i.r.e.) ne dépasse pas l'intensité nécessaire à l'établissement d'une communication satisfaisante.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.