

Evaluates: MAX33049E

General Description

The MAX33049E evaluation kit is a fully assembled and tested board. It demonstrates the functionality of the MAX33049E full-duplex 20Mbps RS-485 transceiver with $\pm 25V$ fault protection and $\pm 40kV$ ESD Human Body Model (HBM) for A/B and Y/Z data lines.

Features

- Easy Evaluation of the MAX33049E
- Power/Ground Connections Through Screw Terminal Blocks
- Screw Terminal Blocks for RS-485 Signals
- Test Points for Measuring All Signals
- Resistors and TVS Footprints for External Protection Devices
- Proven PCB Layout
- Fully Assembled and Tested

[Ordering Information](#) appears at end of data sheet.

Quick Start

Required Equipment

- MAX33049E EV kit
- +5V, 500mA DC power supply
- Signal/function generator that can generate a 10MHz square wave signal (**Note:** The EV kit can accept input signals up to 20Mbps. Ensure the signal swing does not exceed the Absolute Maximum Limits.)
- Oscilloscope

Procedure

1. Verify all jumpers are in their default setting. See [Table 1](#).
2. With the +5V power supply disabled, connect the positive terminal to the VCC test point. Connect the negative terminal to one of the GND test points.
3. Set the signal/function generator to output a 2.5MHz (5Mbps) square wave between 0V to 5V.
4. Connect the positive terminal of the signal/function generator to DI (TP6) and negative terminal to any GND test point on the board.
5. Turn on the +5V DC power supply, and then enable the signal/function generator output.
6. Connect an oscilloscope probe to RO (TP5) and verify that the signal matches the DI input .

EV Kit Photo



001

Table 1. MAX33049E EV Kit Jumper Position Description

JUMPER	SHUNT POSITION	FEATURE
J3	1-2	DE = V_{CC}, driver enabled
	2-3	DE = GND, driver disabled
J4	1-2	$\overline{RE}$ = V_{CC}, receiver disabled
	2-3	$\overline{RE}$ = GND, receiver enabled
J5	Closed	A is connected to Y (loopback configuration)
	Open	A is not connected to Y
J6	Closed	B is connected to Z (loopback configuration)
	Open	B is not connected to Z

Default options are bold.

Table 2. MAX33049E EV Kit Test Points Description

REFERENCE DESIGNATOR	SIGNAL
TP1	V _{CC}
TP2	GND
TP3	GND
TP4	GND
TP5	RO
TP6	DI
TP7	A
TP8	B
TP9	Z
TP10	Y

Table 3. MAX33049E EV Kit Terminal Blocks and Headers Description

REFERENCE DESIGNATOR	PIN NUMBER	SIGNAL
J1	1	V _{CC}
	2	GND
J2	1	V _{CC}
	2	RO
	3	DI
	4	GND
J7	1	GND
	2	Y
	3	Z
	4	B
	5	A

Detailed Description of Hardware

The MAX33049E EV kit is a fully assembled and tested circuit board for evaluating the MAX33049E full-duplex RS-485/RS-422 transceiver with $\pm 25\text{V}$ fault protection and $\pm 40\text{kV}$ ESD Human Body Model (HBM) protection. The EV kit can be powered with a +3.0V to +5.5V supply.

The EV kit allows all the input and output functions to be exercised without the need for additional external components. Jumper configurations are shown in [Table 1](#), test points are listed in [Table 2](#), and screw terminal blocks and headers are listed in [Table 3](#).

Decoupling Capacitors

The MAX33049E EV kit can be powered by connecting a +3.0V to +5.5V power supply to the screw terminals or adjacent test points for V_{CC} and GND at the top of the evaluation board. A $0.1\mu\text{F}$ decoupling capacitor is next to the V_{CC} pin of the RS-485 transceiver (U1). Additionally, the EV kit includes a $22\mu\text{F}$ tantalum capacitor installed next to the J1 terminal block in case of unfiltered supplies.

Input/Output Connections

The MAX33049E EV kit includes connections for data input (DI) and receiver output (RO). Logic I/O is connected through a 0.1in header, J2, on the left side of the board to allow wire connections to a microcontroller.

Connections to an RS-485 bus are made with screw terminal block J7 on the right side of the board. There are two input bus signals, A and B, for noninverting and inverting signals, respectively, and two corresponding output signals, Y and Z.

Test points are available on the board and appropriately labeled for all digital and bus I/O signals.

On-Board Termination

A properly terminated RS-485 bus is terminated at each end, and the characteristic impedance of the twisted pair the cable is typically 120Ω . The MAX33049E EV kit provides on-board 120Ω termination (R2) between the Y and Z driver outputs and 120Ω (R1) between the A and B receiver inputs. If the EV kit is evaluated with an already terminated system, remove the on-board 120Ω terminations.

External Protection

The MAX33049E has integrated high ESD protection with a $\pm 40\text{kV}$ Human Body Model (HBM), $\pm 15\text{kV}$ Air-Gap Discharge, and $\pm 10\text{kV}$ Contact Discharge.

The MAX33049E EV kit provides options for added external protection. Swap out the 0Ω series resistors R3–R6 on the A, B, Y and/or Z lines for other protection components and/or install TVS diodes on D1–D4 footprints.

For applications that require high-voltage transient protection, such as surge transients, external protection is needed on the bus lines. Choose TVS diodes with a clamp voltage below $\pm 30\text{V}$ and ensure external protection added to the bus lines does not slew the signals at required operating data rate.

Evaluating ESD Protection

The MAX33049E EV kit can be used to evaluate ESD performance for the MAX33049E, based on the IEC 61000-4-2 standard. Without added external protection, the EV kit can verify the ESD performance up to $\pm 10\text{kV}$ Contact Discharge and $\pm 15\text{kV}$ Air-Gap Discharge. Follow the IEC 61000-4-2 guidelines for a proper test setup. Apply ESD stresses on the terminal block J7 for signal A, B, Y, and Z. Place a bleeding resistor cable and an earth ground return as close as possible to where the stress is applied. See [Figure 1](#).




Figure 1. IEC 61000-4-2 ESD Test Setup

Lab Connection

To evaluate the full-duplex functionality using only the MAX33049E EV kit, set the EV kit in the loopback configuration by closing J5 (which connects A and Y) and J6 (which connects B and Z). A signal generator connected to DI allows verification of the bus signals and the receiver output. See [Figure 2](#).




Figure 2. Connection Diagram

Ordering Information


PART	TYPE
MAX33049EEVKIT#	EV Kit

#Denotes RoHS compliance.


MAX33049E EV Kit Bill of Materials

REF DES	QTY	MFG PART #	MANUFACTURER	VALUE	DESCRIPTION
C1	1	GCM155L81E104KE02	MURATA	0.1UF	CAP; SMT (0402); 0.1UF; 10%; 25V; X8L; CERAMIC
C2	1	GRM21BD71A226ME44	MURATA	22UF	CAP; SMT (0805); 22UF; 20%; 10V; X7T; CERAMIC
J1	1	1727010	PHOENIX CONTACT	1727010	CONNECTOR; FEMALE; THROUGH HOLE; GREEN TERMINAL BLOCK; RIGHT ANGLE; 2PINS
J2	1	PBC04SAAN	SULLINS ELECTRONICS CORP.	PBC04SAAN	CONNECTOR; MALE; THROUGH HOLE; BREAKAWAY; STRAIGHT; 4PINS; -65 DEGC TO +125 DEGC
J3, J4	2	PBC03SAAN	SULLINS	PBC03SAAN	CONNECTOR; MALE; THROUGH HOLE; BREAKAWAY; STRAIGHT; 3PINS; -65 DEGC TO +125 DEGC
J5, J6	2	PCC02SAAN	SULLINS	PCC02SAAN	CONNECTOR; MALE; THROUGH HOLE; BREAKAWAY; STRAIGHT THROUGH; 2PINS; -65 DEGC TO +125 DEGC
J7	1	1727049	PHOENIX CONTACT	1727049	CONNECTOR; THROUGH HOLE; GREEN TERMINAL BLOCK; RIGHT ANGLE; 5PINS
R1, R2	2	CRCW0805120R FK	VISHAY DALE	120	RES; SMT (0805); 120; 1%; +/- 100PPM/DEGC; 0.1250W
R3–R6	4	RC1608J000CS;C R0603-J/-000ELF;RC0603JR-070RL	SAMSUNG ELECTRONICS;BOURNS;YAGEO PH	0	RES; SMT (0603); 0; 5%; JUMPER; 0.1000W
TP1	1	5010	KEYSTONE	N/A	TEST POINT; PIN DIA=0.125IN; TOTAL LENGTH=0.445IN; BOARD HOLE=0.063IN; RED; PHOSPHOR BRONZE WIRE SIL;
TP2–TP4	3	5011	KEYSTONE	N/A	TEST POINT; PIN DIA=0.125IN; TOTAL LENGTH=0.445IN; BOARD HOLE=0.063IN; BLACK; PHOSPHOR BRONZE WIRE SILVER PLATE FINISH;
TP5, TP6	2	5012	KEYSTONE	N/A	TEST POINT; PIN DIA=0.125IN; TOTAL LENGTH=0.445IN; BOARD HOLE=0.063IN; WHITE; PHOSPHOR BRONZE WIRE SILVER PLATE FINISH;
TP7–TP10	4	5127	KEYSTONE	N/A	TEST POINT; PIN DIA=0.125IN; TOTAL LENGTH=0.445IN; BOARD HOLE=0.063IN; BLUE; PHOSPHOR BRONZE WIRE SILVER PLATE FINISH;
U1	1	MAX33049EASD+	ANALOG DEVICES	MAX33049EASD+	EVKIT PART - IC; MAX33049EASD; PACKAGE CODE: SOIC_N; PACKAGE OUTLINE DRAWING: R-14; SOIC14
PCB	1	MAX33049E	MAXIM	PCB	PCB:MAX33049E
D1–D4	4	SM30T26CAY	ST MICROELECTRONICS	25.7V	DIODE; TVS; SMC (DO-214AB); PIV=25.7V; IF=0.2UA;


MAX33049E EV Kit PCB Layout




MAX33049E EV Kit—Top Silkscreen



MAX33049E EV Kit PCB Layout—Top Layer




MAX33049E EV Kit PCB Layout—Layer 2 (GND Layer)




MAX33049E EV Kit PCB Layout—Layer 3 (VCC Layer)

MAX33049E EV Kit PCB Layout (continued)



MAX33049E EV Kit PCB Layout—Bottom Layer



MAX33049E EV Kit—Bottom Silkscreen

Revision History

REVISION NUMBER	REVISION DATE	DESCRIPTION	PAGES CHANGED
0	12/24	Initial release	—

Notes

ALL INFORMATION CONTAINED HEREIN IS PROVIDED “AS IS” WITHOUT REPRESENTATION OR WARRANTY. NO RESPONSIBILITY IS ASSUMED BY ANALOG DEVICES FOR ITS USE, NOR FOR ANY INFRINGEMENTS OF PATENTS OR OTHER RIGHTS OF THIRD PARTIES THAT MAY RESULT FROM ITS USE. SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE. NO LICENSE, EITHER EXPRESSED OR IMPLIED, IS GRANTED UNDER ANY ADI PATENT RIGHT, COPYRIGHT, MASK WORK RIGHT, OR ANY OTHER ADI INTELLECTUAL PROPERTY RIGHT RELATING TO ANY COMBINATION, MACHINE, OR PROCESS, IN WHICH ADI PRODUCTS OR SERVICES ARE USED. TRADEMARKS AND REGISTERED TRADEMARKS ARE THE PROPERTY OF THEIR RESPECTIVE OWNERS. ALL ANALOG DEVICES PRODUCTS CONTAINED HEREIN ARE SUBJECT TO RELEASE AND AVAILABILITY.