



WTIM WEEKLY PROGRAMMABLE ELECTRONIC TIMER

■ Description

- Standard 17.5mm wide, 35mm din rail mount.
- Original functions: 16 (on/off) holiday settings in one year, Ext port (100m).
- Combine 16 On/Off Settings, 32 Pulse Output and Count-down together.
- Suitable for electrical & industrial appliances.
- Superior quality, powerful function and high precision. With lithium battery inside, so it works if powered off.

■ Specifications

- Rated voltage: AC 220V, AC 110V 50/60Hz
- Voltage ranging: rated voltage (+10%)
- Hysteresis: ≥ 2 sec/day(20°C)
- On/Off operation: 16 On/Off
- 32 times pulse output
- 16 times holiday settings
- Pulse: 1sec-99sec
- Count down: 1sec-99min99sec
- Display: LCD
- Power consumption: approx. 3VA
- Weight: 90g
- Service life: 105 rated loading
- Mechanical life: 10^5
- Switching contact: 1 changeover switch
- Load capacity: relative load: cos ϕ =1
16A/250VAC
Lagging load: cos ϕ =0.8
4A/250 V
Lamp load: 1000w
- Battery life expectancy: 3 years (CR2032)
- Ambient temperature: -10~+50°C (indoor)
- Ambient humidity: 35~85%

■ Dimensions



■ Connections



■ Attention

1. Press "On" & "Off" → On → Press "On" & "Off" → Off → Press "On" & "Off" → Off
2. When count down is running and Ext on is set, and then Count-down can also be externally controlled.
3. When setting Ext off, Ext input won't work and the timer runs according to previous procedure or pulse. When setting Ext on, Ext input works (Auto on/off). If Ext switch is off, all the procedures or pulse won't work; if Ext switch is on, vice versa.
4. Press "Menu" & "-" for 3 sec, the procedure will turn off. And no setting will be saved. Press "Res", all the procedures will be cleared.

