

size 60×60

01\_24.10.12

CIO-MB30W2C-8K-EX03

30W出力対応モバイルバッテリー

SMARTCOBY Ex03

SLIM PLUG & CABLE

取扱説明書

1.はじめに

お買い上げありがとうございます。ご使用の前に「取扱説明書」をよくお読みの上、正しくお使いください。

もくじ

1. はじめに

2. 注意事項

3. 付属品

4. 仕様

5. 対応急速充電規格

6. 各部名称

7. 使用方法

8. 製品保証

2

2.注意事項

警告

死亡や重傷に結びつく恐れがある内容です。

注意

重傷を負う可能性及び、物的損害に結びつく恐れがある内容です。

警告

本製品が異常な発熱、異臭、異物が入った場合は直ちに使用を中止してください。

分解及び改造は絶対に行わないでください。火災・感電・怪我の原因となります。

お子様だけでご使用、幼児の手の届くところで使用しないでください。

本製品を水につけたり、濡れさせないようにしてください。また濡れた手で電源プラグに触れないでください。感電・発火・火災・感電・破裂などの原因となります。

高温となる場所での使用、設置、保管は避けてください。また火の中へ投入しないでください。

本製品を落としたり、重いものを上のにせたり、衝撃をあてないでください。感電・故障・怪我の原因となります。

電源プラグは、家庭用コンセントに差までしっかりと差し込みご使用ください。差し込みが不十分だと、接触不良などによって火災や感電の原因となります。

タコ足配線での使用はおめください。火災の原因となります。

本製品は熱を発する装置から離して使用してください。

3

注意

① 本家の用途以外に使用しないでください。

① 本製品を引火性のある油、化学製品、可燃性のものの近くで使用しないでください。

① 本製品は防水構造ではありません。水などの液体がからまない場所での使用・保存をしてください。

① 本製品を使用するときは、USBコネクタの形状を確認し正しい向き、方向で挿入してください。無理な挿入は故障・怪我の原因となります。

① 本製品にデバイス機器を接続する場合は、必ずデバイス機器の注意事項・マニュアルに従って正しく使用してください。

① 本製品を充電中、使用中は本製品が熱くなる場合がございますので取り扱いにご注意ください。またデバイスが満充電、本製品が満充電に近づくと、通常の温度に戻ります。

① Power Delivery (PD) 充電を行う際は、PD対応デバイス機器に対し、PD対応ケーブルをご使用いただく必要があります。

① Quick Charge4.0+ (QC4.0+) 充電を行う際は、QC4.0+対応デバイス機器に対し、QC4.0+対応ケーブルをご使用頂く必要があります。

① 本製品を長時間使用しないときは、本製品を家庭用コンセントから抜いてください。故障の原因となります。

4

4.仕様

製品名: SMARTCOBY Ex03 SLIM PLUG & CABLE 2INP9/58/55  
型番: CIO-MB30W2C-8K-EX03  
内蔵バッテリー: 4000mAh/7.4V (29.6Wh) モバイルバッテリー: 4000mAh x2pcs  
充電電圧: 5V 定格容量: 4200mAh  
AC入力: 100-240VAC、50-60Hz、0.8A  
USB A (USB-C / Cable / C2): 5V=3A/9V=2.22A / 12V=1.67A / 15V=1.34A / 20V=1.5A (Max 30W)  
USB (C1 Cable / C2): 5V=3A/9V=3A / 12V=2.5A / 15V=2A / 20V=1.5A (Max 30W)  
PPS 5V-11V=3A(Max 33W) USB (C1 Cable + C2): 5V=3A(Max 15W)  
USB (C1 Cable / C2): 5V=3A/9V=3A / 12V=2.5A / 15V=2A / 20V=1.5A (Max 30W)  
PPS 3.3V-11V=3A(Max 33W) USB (C1 Cable + C2): 5V=3A(Max 15W)  
USB (C1 Cable / C2): 5V=3A/9V=3A / 12V=2.5A / 15V=2A / 20V=1.5A (Max 30W)  
PPS 3.3V-11V=3A(Max 33W) USB (C1 Cable + C2): 5V=3A(Max 15W)  
サイズ: 約115x67.5x22mm 重量: 約223g  
サイクル回数: 約300回 充電時間: 約130分 専用ケーブル長さ: 約172mm

5.対応急速充電規格

PD3.0 / QC4.0+ / PPS

6

6.各部名称

Front

Back

Side

① バッテリー残量表示LED (※表示: 完全充電マーク)  
② USB-Cポート (入出力)  
③ EX03専用充電ケーブル  
④ バッテリー残量確認タッチセンサー  
⑤ 専用脱着式ケーブル接続用Cポート  
⑥ ACコンタクトプラグ

※⑤のCポートには本製品専用の脱着充電ケーブルをご使用ください。専用充電ケーブル以外での使用による故障・損傷は保証外となります。

7

7.使用方法

■本製品への蓄電方法 (2通りの蓄電方法があります)

1. コンセントに接続し蓄電する。(充電器モード)  
2. USB-Cポート経由で蓄電する。(モバイルバッテリーモード)

■デバイスへの充電方法 (モバイルバッテリーモード)  
USB-Cケーブルを使用して、本製品とデバイスを接続し充電を行います。自動的に充電が始まります。自動的に充電が始まらない場合は、バッテリー残量確認タッチセンサーにタッチしてください。  
※急速充電 (Power Delivery / Quick Charge) を行うためには、急速充電に対応したデバイスと、急速充電に対応した充電ケーブルが必要となります。  
※モバイルバッテリーモードはCポートで最大33Wの充電に対応しています。

■デバイスへの充電方法 (充電器モード)  
本製品をコンセントに接続した状態で専用脱着式ケーブル、もしくはUSB-Cケーブルを使用して本製品とデバイスを接続し充電を行います。自動的に充電が始まります。自動的に充電が始まらない場合は、本製品正面下部の「バッテリー残量確認タッチセンサー」を押してください。  
※急速充電 (Power Delivery / Quick Charge) を行うためには、急速充電に対応したデバイスと、急速充電に対応した充電ケーブルが必要となります。  
※接続したデバイスが充電して充電されます。  
※充電モードは単ポートで最大33Wの充電に対応しています。

8

8.製品保証

この度は株式会社CIOの製品をご購入いただき誠にありがとうございます。商品に初期不良などの不具合がある場合、レビューの前にご連絡ください。初期不良品として交換対応を実施させていただきます。正しくご使用いただいた状態で保証期間内に発生した故障の場合も交換対応を実施させていただきます。

納品書兼保証書もしくは、販売店シートが保証書の代わりとなりますので大切に保管してください。

※商品の保証は原則、交換対応とさせていただきます。返品・返金は承っておりませんのでご了承ください。

以下の場合保証は実施いたしかねますので、ご了承ください。  
1. 使用上の取り扱い不注意による事故(落下や水没など)。  
2. 使用者による任意での内部改造による故障。  
3. 火災・水害などによる故障。

11

製品お問い合わせ窓口

https://connectinternationalone.co.jp/contact/customer/

QRお問い合わせフォームまたは下記メールアドレスよりお問い合わせください。

メールアドレス: customer@connectinternationalone.co.jp

保証書 [CIO-MB30W2C-8K-EX03]  
販売店名

保証期間: 1年  
お買い上げ年月日: 年 月 日

12

CIO 公式 LINE アカウント

フォローしてね!

メリット01 LINEでカスタマーサポート  
故障時や使い方が分からない場合など、チャットだからスムーズ! LINEで簡単にお問合せOK! 是非お気軽にご利用ください。

メリット02 LINE限定クーポン  
Amazonや楽天市場などでご利用いただける超お得なクーポンをLINEでいち早く公開! SALEや新商品の情報も盛りだくさんです!

COUPON & SALE  
お得なクーポン セール情報

QRコードでLINEの友達を追加  
QRコードをスマートフォンでスキャンしてください。

13

CIO 公式 YouTube アカウント

チャンネル登録してね!

メリット01 市場未公開情報ゲット!  
開発中の商品情報や開発話などをいち早く公開! 市場未公開の商品情報をCIO社員が詳しく解説します!

メリット02 欲しい商品が見つかる!  
新しくスマホやPCを買ったけどどんな充電器、製品が最適なんだろう... CIOの製品の特長を分かりやすく解説! あなたに合うベストな製品が見つかる!

QRコードでYouTubeのチャンネル登録  
QRコードをスマートフォンでスキャンしてください。

14

01\_24.10.12

CIO-MB30W2C-8K-EX03

30W Output Power Bank

SMARTCOBY Ex03

SLIM PLUG & CABLE

USER MANUAL

CIO Co., Ltd.

Founded in 2017 in Osaka, Japan, CIO Co., Ltd. is a manufacturing and sales company focused on dealing with the latest gadgets and smartphone accessories. With the concept of "Delivering the latest, most exciting gadgets", the company offers its products through its e-commerce site and physical stores. We always pay attention to the latest technology and continuously strive to develop products that increase the level of convenience for users. We offer high quality products in accordance with Japanese standards, but at the same time, we offer high cost performance as only an overseas manufacturer can. It is our pleasure to provide convenient gadgets to our customers.

1. Introduction

Thank you for your purchase. Please read the "USER MANUAL" carefully before use and use it correctly.

Contents

1. Introduction

2. Precautions

3. Accessories

4. Specifications

5. Supported Fast Charging Protocols

7. How to Use

8. Warranty

12-13

2.Precautions

Warning

This is content that could lead to death or serious injury.

Caution

There is a possibility of serious injury or damage to property.

Warning

Stop using this product immediately if it makes any noise, generates unusual heat, has an unusual odor, or contains a foreign object.

Children should not use this product alone. Do not use this product within the reach of children.

Do not immerse the product in water or allow it to get wet. Do not touch the power plug with a wet hand. Otherwise, it may cause heat generation, fire, fire, electric shock, or explosion.

Please do not use, leave or store the product in a high temperature environment. Do not drop this product into fire, or give it a strong shock. Failure to do so may result in electric shock, malfunctions or injuries.

Plug the power cord into a household wall outlet when using. Failure to do so may result in fire or electric shock.

Do not use this product overloaded. It may result in fire.

This product should be used away from heat-generating equipment.

4

Caution

① Do not use this product for any purpose other than its intended use.

① Do not use this product near flammable oils, chemicals or flammable materials. This product is not waterproof.

① Use and store the product in a place where it will not be exposed to water or other liquids.

① When using this product, check the shape of the USB connector and insert it in the correct direction and orientation. Forced insertion may cause malfunction or injury.

① When connecting the device to this product, be sure to follow the precautions and manuals of the device to use it correctly.

① Please note that this product may become hot while charging or using it. Also, as the device is fully charged and this product approaches full charge, it will return to normal temperature.

① When using Power Delivery (PD) charging, it is necessary to use a PD-compatible cable with a PD-compatible device.

① When charging QuickCharge4.0+ (QC4.0+), it is necessary to use a QC4.0+ compatible cable for QC4.0+ compatible devices.

① Unplug this product from the power outlet when not using it for a long period of time. Failure to do so may result in a malfunction.

5

3. Accessories

CIO-MB30W2C-8K-EX03 ■ User's Manual  
Detachable cable for EX03 (USB-C to USB-C)

4. Specifications

SMARTCOBY Ex03 SLIM PLUG & CABLE 2INP9/58/55  
Model: CIO-MB30W2C-8K-EX03  
Capacity: 4000mAh/7.4V/29.6Wh / Battery Cell: 4000mAh\*2pcs  
AC Input: 100-240VAC 50-60Hz 0.8A  
USB Input (USB-C / Cable / C2): 5V=3A/9V=2.22A / 12V=1.67A / 15V=1.34A / 20V=1.5A (Max 30W)  
USB Output (AC charger mode)  
USB (C1 Cable / C2): 5V=3A/9V=3A / 12V=2.5A / 15V=2A / 20V=1.5A (Max 30W)  
PPS 5V-11V=3A (Max 33W)  
USB (C1 Cable + C2): 5V=3A (Max 15W)  
USB Output (Mobile power mode)  
USB (C1 Cable / C2): 5V=3A/9V=3A / 12V=2.5A / 15V=2A / 20V=1.5A (Max 30W)  
PPS 3.3V-11V=3A (Max 33W)  
USB (C1 Cable + C2): 5V=3A (Max 15W)  
Size : Approx. 115x67.5x22mm Weight : Approx. 223g  
Lifecycle : approx. 300 times Recharge Time : approx. 130 minutes  
Dedicated cable length: approx. 172mm

5. Supported Fast Charging Protocols

PD3.0 / QC4.0+ / PPS

6

6. Names of Each Part

Front

Back

Side

① Remaining Battery Indicator in % and Charging Animation  
② USB-C (Input / Output)  
③ Detachable charging cable  
④ Touch sensor to check battery level  
⑤ Dedicated detachable cable connection C port  
⑥ AC outlet plug

※⑤のCポートには本製品専用の脱着充電ケーブルをご使用ください。専用充電ケーブル以外での使用による故障・損傷は保証外となります。

7

7. How to Use

■How to store electricity in this product  
There are two ways to store electricity.

1. Connect to an outlet to store electricity. (AC charger mode)  
2. Store power via USB-C port. (Mobile battery mode)

■How to charge the device (Mobile battery mode)  
Connect this product and your device to charge using a USB-C cable. If charging does not start automatically, press the "battery level check touch area" at the bottom of the front of the product.  
\*A device and a cable that support fast charging technology (Power Delivery / Quick Charge) are required.  
\*Mobile battery mode supports up to 30W charging with a single port.

■How to charge the device (AC charger mode)  
While this product is connected to a power outlet, use the dedicated detachable cable or USB-C cable to connect this product and your device to charge. If charging does not start automatically, press the "battery level check touch area" at the bottom of the front of the product.  
\*A device and a cable that support fast charging technology (Power Delivery / Quick Charge) are required.  
\*The connected device will be charged first.  
\*AC charger mode supports up to 30W charging with a single port.

9

How to Charge Two Devices Simultaneously

Connect and charge your device using both the detachable charging cable and the USB-C port on the bottom of the unit. If charging does not start automatically, please touch the touch area to check the remaining battery power or reconnect the cable.  
\*Fast charging is disabled when charging two devices at the same time. When charging two devices at the same time, a total of up to 15W will be distributed to each device. (Common to both charger mode and battery mode)

10

8. Warranty

Thank you for purchasing CIO product. If the product has any defects such as initial malfunction, please contact us before reviewing. We will replace it as an initial malfunction product. In case of malfunction occurred within the warranty period or correct use, we will also replace it.

Invoice/warranty or dealer's receipt will become warranty so please keep it. The product will be guaranteed for replacement with it.

Please note that we do not accept returns or refunds.

Please note that the warranty cannot be provided in the following cases.  
1. Accident due to careless handling while using it. (e.g. dropping, submerging and so on.)  
2. Failure due to any internal modification by the user.  
3. Failure due to fire or water damage.

11

Support Information

Email address: smartcoby@connectinternationalone.co.jp

One Year Warranty [CIO-MB30W2C-8K-EX03]  
Dealer's Name

The date of purchase:

12

CIO Co., Ltd.

Stay Updated with All the Latest News!

We will be posting information about our new crowdfunding project, new products, and special discounts.

13