140mm

180mm

R4000 V3.0

Portable Power Station

Model:R4000

The products and materials described in the manual will be changed at any time due to technical upgrades. The company reserves the final right to change and explain the contents of the manual.

01

CONTENTS

1. Safety Instructions 01
2. Product Introduction 02
3. User guide 03
3.1 Product appearance introduction 03
3.2 Introduction of Display /Touch Icons 04
3.3 AC charging 05
3.4 Solar charging 05
3.5 Car Charging 06
3.6 Smart Extra Battery 06
3.7 APP Control (compatible power supply) 07
3.8 Power Saving Mode 08
3.9 Power station settings 08
4. FAQ 08
5. Troubleshooting 09
6. Package Contents 09
7. Statement 09
8. Contact us 09

1.Safety Instructions

1. Safety Instructions 01

1.Safety Instructions

1. Read all instructions before using the portable power station.
2. Be sure to operate the product in a dry and well-ventilated place, and if it gets wet, dry it thoroughly before use.
3. To reduce the risk of loss, close monitoring is required when using this product near children.
4. Do not use this product when the power cord or plug is damaged, or if the product is damaged in any way.
5. Do not touch the AC interface with metal, eliminate it may cause electric shock, fire and other dangers.
6. During charging or using the product, do not block the product vents, otherwise it may cause permanent damage to the product.
7. Please do not expose the product to fire and water.
8. Please keep the product away from strong magnetic fields to avoid the occurrence of strong static electricity or strong magnetic field interference that may affect the normal operation of the product.
9. Please use the safe operation equipment for the product, the company does not assume any responsibility for the damage caused by the third party equipment.
10. Do not disassemble the product and if the product needs service or maintenance, please find a professional technician.
11. Improper use: falling or excessive force may cause damage to the product.
12. When disposing of used batteries, please separate batteries of different electrochemical systems.
13. In case of fire, dry powder fire extinguisher can be used or immersed in water.
14. Be sure to keep the product away from fire and heat sources.

2.Specifications

General Info

Net weight: Approximately 45KG (100lbs)
Size: 540*360*390mm (21.26*14.20*15.35in)
Battery capacity: 3456Wh (48V 72Ah)
Wi-Fi: Supported
Bluetooth: Supported
UPS (uninterruptible power supply) : Supported

02

2.Product Introduction

Input Ports
AC:120V~132V~,12A~,1200~,1650~1760~Watts
Solar:7~21~40V,<=15A, Single port 600W Max, three ports 2000W Max
DC:Max 300W Max

Output Ports
AC: 230V~240V 10A~,Max 2400W Max(Surge 3600W Max)
230V,50Hz Total output 4000W Max (Peak 6000W Max)
USB-A:5V~2.4A,Max 12W,2 Ports
USB-C:5V~3A,9V~2.22A,20V~3A, Single port 100W Max
USB-C:5V~3A,12V~3A,20V~5A, Single port 100W Max
Car port:12V~10A, 120W Max

Battery Info
Battery type: LFP (Lithium Iron Phosphate
Battery protection: Overcharge protection, Low temperature protection, Over discharge protection, Over charge protection, Overload protection, Short circuit protection, Over current protection

Environmental Operating Temperature
Operating Temperature: (0°~40°C)32°F~104°F)
Storage Temperature: (-20°~45°C)-4°F~113°F)recommend (25~30°C)
Operating humidity range: 25~35%

Certification

03

3.User guide

3.1 Product appearance introduction

3.2 Introduction of Display /Touch Icons

04

Number	Function Introduction
1	Battery capacity: Current the battery capacity is displayed in real-time.
2	Battery icon: Icon of current the battery interface, you can set the function, pass 2 Eds details.
3	Extra: Icon, Icon for the extra battery, you can set the function, pass 2 Eds details.
4	Input: Icon, Icon of current the charging interface, you can set the function, pass 2 Eds details.
5	AC charging time: remaining time of the AC charging, it displays when the AC is charging.
6	Solar charging time: remaining time of the solar charging, it displays when the solar is charging.
7	Extra charging time: remaining time of the extra charging, it displays when the extra is charging.
8	Output: Icon, Icon of current the discharging interface, you can set the function.
9	AC: Icon, Icon of current the AC interface, you can set the function.
10	AC output time: remaining time of the AC output, it displays when the AC is discharging.
11	DC: Icon, Icon of current the DC output function.
12	Power: Icon, Icon of current the power output, you can set the function.
13	Extra battery: extra
14	LED: extra
15	High temperature warning: extra
16	Bluetooth: Icon, displayed when Bluetooth is turned on.
17	WiFi: Icon, displayed when WiFi is turned on.

3.3 AC charging

The AC charging current adopts MPPT(Maximum Power Point Tracking) technology, and the charging power can be adjusted through the AC charging Pass Mode(Standard Mode/Peak Mode/Mute Mode). The maximum input of AC charging is 1650W. Under the Peak Mode, the AC charging power can reach the maximum 1650W. Under the Mute Mode, can reach 200W(the Mute Mode is used for AC charging technology to reduce the noise. The default Output power of Lockers charging is Mute Mode, and the charging power is adjustment needs to be set in the mode switch of the product.

When the AC input current continuous to be abnormally larger than 23A (220V-240V) 230V-240V input voltage, the AC charging will automatically stop to ensure the safety of the product. The AC charging will automatically restart after the current is back to the normal range. The AC charging can be resumed. When the AC input current is too high, it may cause the power protection to trigger, causing the AC charging to stop. In this case, please reduce the AC charging power and try again.

When the AC input power is too low, the AC charging power will decrease automatically to ensure the stability of the system. If the AC input power is too low, the AC charging may not be activated. In this case, pay attention to whether the household line can cut for 23A current if the above conditions are met and, please switch to standard charge or mute mode for charging.

05

3.4 Solar charging

Users can charge the product by connecting solar panels in series as shown in the figure.



3.5 Car Charging

3.6 Smart Extra Battery

The R4000 power station can act as an extra extra battery for expansion connection, which can effectively extend the power supply time of the equipment.
When using the product for extra battery connection, please connect it according to the specifications of the extra battery connection port.
Please note that in the connection state, the rated maximum output power based on the single side the battery capacity is superimposed.
The extra battery connection port provided by our company for connecting to extra# charging to the product has its special protection mode to ensure the battery safety, as shown in the figure below.

3.7 APP Control (compatible power supply)

The Portable power station APP (compatible Power Supply) Function. You connect the power grid and the AC input of the product through the AC charging cable, and the electrical appliance can use the AC output of the product. The product can also be charged by the solar panel and the car charger at the same time. When idle, the power will automatically switch to the battery power supply mode of the product within 10min. It is recommended to use only one device during use, and do not use it in the car or other vehicles to avoid damage to the vehicle circuit. The product can also be used as a UPS uninterruptible power supply, which can ensure the power supply to the electrical appliances in the event of a power outage. Note: 1.When AC charging and AC output active, the UPS function (non-automatic) kicks up to activate the UPS function.
2. To ensure the UPS function, the input power of the AC charge port should not exceed 1650W. The maximum output range is 100~120V, the maximum power of the AC output port should not exceed 1200W, and the total output power should not exceed 1650W. If the input power of the AC charging port exceeds the power of the devices at the same time, the power will be cut off. The power will be restored in 10 s. If the power and turn off the AC output.



3.8 UPS function (uninterruptible power supply)

06

3.9 APP operation guide

3.9.1 APP download



3.9.2 Bluetooth connection power station

Open the APP and enter the interface, and automatically search for nearbyBluetooth and turn on.
Enable Bluetooth pairing, you can switch the interface language to Chinese, English and Japanese.
Click Add to scan and search for power station.
Click on the corresponding power station to connect to the power station.
If after the connection is successful, AP P0000 ESS will be displayed in the Bluetooth device bar

07

3.9.3 WiFi connection:
Open the APP and enter the interface, and click the ALLPOWERS name to pop up the WiFi connection UI.
Click the 10 icon in the WiFi connection interface and enter the WiFi setting in the WiFi connection interface.
Select the corresponding WiFi signal and enter the password to connect.
Enter the WiFi connection interface, and click the ALLPOWERS name to pop up the WiFi connection interface.
Click the 10 icon in the WiFi connection interface and enter the WiFi setting in the WiFi connection interface.
Select the corresponding WiFi signal and enter the password to connect.
If the WiFi connection is successful, the name of the power station and whether the power station is online will be displayed as shown in the figure below.

3.9.4 Home APP Operation instructions

08

3.9.5 Charging power working mode setting: can be set to Fast Mode/Standard Mode/Mute Mode.
Fast Mode: Fast charging, you can switch the interface language to Chinese, English and Japanese.
Mute Mode: Frequency setting, when AC is not input or output, the frequency can be switched to 50Hz or 60Hz.
Mute Mode: Mute mode, in normal mode, the power station will not shut down automatically after turning on AC/DC in power saving mode, when turn on AC/DC, if the output power exceeds 100W, it will automatically shut down after 24 hours. Mute mode: It is recommended to discharge the battery to 30% and recharge to 80% every three months to ensure the battery life and performance of the product.
2. Bluetooth settings: turn on or off the Bluetooth function.
3. Wi-Fi settings: turn on or off the Wi-Fi function, view the network status, stand mode, standard mode, and fast charging modes.
4. WiFi settings: turn on or off the WiFi function, view the network status, and set the WiFi connection.



3.10 Power saving settings

1. Power saving: Set the power saving time, and the power station will shut down automatically after turning on AC/DC in power saving mode, when turn on AC/DC, if the output power exceeds 100W, it will automatically shut down after 24 hours.
2. Forced quick shutting, turn on or off the power station control panel switch.
3. Bluetooth settings: turn on or off the Bluetooth function.
4. Wi-Fi settings: turn on or off the Wi-Fi function, view the network status, stand mode, standard mode, and fast charging modes.
5. WiFi settings: turn on or off the WiFi function, view the network status, and set the WiFi connection.

4. FAQ

1. What type of battery does the product use?
The product uses high-quality lithium iron phosphate batteries(LFP).
2. What equipment can the AC output port of the product carry?
The AC output port of the product can carry 230V~240V 10A~,Max 2400W Max(Surge power 6000W) 230V,50Hz Total output 4000W, which can supply power to most household appliances.
It is recommended that you confirm the power of the electrical appliance and ensure that the total power of the electrical devices is less than the rated power.
3. How to know how long the product can supply power?
The product can display the remaining time of the battery, which can be estimated for devices with stable power consumption.

4. Is the product charging?
The product can display the remaining time and the battery percentage when it is charging, and the battery percentage has a breathing animation effect.
5. How to clean this product?
Please use a dry cloth or a damp cloth, clean cloth or paper towel.
6. How to store the product?
When storing, please turn off the product first, and then store it in a dry, ventilated place with a temperature of 25~30°C and a humidity of 25~35%. If the product is not used for a long time, it is recommended to discharge the battery to 30% and recharge it to 80% every three months to ensure the battery life and performance of the product.
7. Can this product be brought on the plane?
Yes.
8 Can voltagecan charge and discharge?
Yes, the product supports simultaneous charging and discharging.
9. Is the rated capacity of the product consistent with the target capacity in the user manual?
The capacity indicated in the user manual is the rated capacity of the battery pack of this product. The actual capacity may be affected by factors such as ambient temperature and battery pressure. Therefore, the actual output capacity of the product is lower than the capacity specified in the user manual, and deploy the final product.

10. Is the product charging?
The product can display the remaining time and the battery percentage when it is charging, and the battery percentage has a breathing animation effect.
11. How to clean this product?
Please use a dry cloth or a damp cloth, clean cloth or paper towel.
12. How to store the product?
When storing, please turn off the product first, and then store it in a dry, ventilated place with a temperature of 25~30°C and a humidity of 25~35%. If the product is not used for a long time, it is recommended to discharge the battery to 30% and recharge it to 80% every three months to ensure the battery life and performance of the product.
13. Can this product be brought on the plane?
Yes.
14 Can voltagecan charge and discharge?
Yes, the product supports simultaneous charging and discharging.
15. Is the rated capacity of the product consistent with the target capacity in the user manual?
The capacity indicated in the user manual is the rated capacity of the battery pack of this product. The actual capacity may be affected by factors such as ambient temperature and battery pressure. Therefore, the actual output capacity of the product is lower than the capacity specified in the user manual, and deploy the final product.

5. Troubleshooting

Refer Tips to enter the LCD interface to view related faults.

Problem	Solution
Charging has temporarily stopped	Automatic recovery after ambient temperature returns.
Charging high temperature protection	Stop charging, check the product vents is blocked or not, and ensure the ambient temperature is normal.
Discharge high temperature protection	Automatic recovery after ambient temperature returns.
Discharge high temperature protection	Stop discharge, check the product vents is blocked or not, and ensure the ambient temperature is normal.
Total output (AC/DC) overload protection	Reduce part of the load and turn on the power switch again.
DC discharge overcurrent	Remove the load and turn on the DC transmit again.
AC discharge overload	Remove the load and turn on the AC transmit again.
AC discharge short circuit	Remove the load, repair the fault and turn on the AC transmit again.
PV input overvoltage	Remove the overvoltage input and wait wait exceeds the rated voltage input range before restarting.
Other faults (ALLPOWERS Service)	Please consult customer service for details

6. Package Contents

7. Statement

Before using this product, please read the user manual of the product to ensure correct use and understand the relevant safety and warranty terms. The company reserves the right to modify the manual content without prior notice. If the product is damaged or affects, or result in product damage and property damage. Once you use this product, you are deemed to have understood, recognized and accepted all terms and conditions of the manual and agree to be bound by the relevant terms and conditions. If you have any questions or ambiguities during the use, please contact ALLPOWERS in time. Responsibility for all losses caused by the user's failure to use the product in accordance with the user manual.
The company reserves the right to modify the product appearance and functions without prior notice. Interpretation of this document and all related documents of the product.
The company reserves the right to modify the product specifications and parameters and the ALLPOWERS official website for the latest product information.
The product is not intended for use in applications that require extremely high reliability and safety, such as aerospace equipment, level communication equipment, nuclear power control equipment, medical life support equipment, or other applications that may pose a threat to personal safety. Users should fully assess the suitability of this product and take the risk by yourself. If the product is used in the above equipment or other applications, the company does not provide any guarantee for product quality, fitness for purpose, or suitability for specific applications.

8. Contact us

If you have any questions or need assistance with our products and services, please email: support@allpowers.com
Or visit our official website: www.allpowers.com

User Manual and Warranty Card

R4000 V3.0

ポータブル電源

型番:R4000

本製品の説明書は、製品の改良により、変更される場合があります。当社は、説明書の内容を変更する権利を留保します。

09

目 次

1. 安全上のご注意 10
2. 製品紹介 11
3. 使いかた 12
3.1 各部の名称 12
3.2 画面アイコンの説明方法 13
3.3 AC充電 14
3.4 ソーラー充電 15
3.5 車両充電 15
3.6 UPS(無停電装置)について 16
3.7 APP操作 16
3.8 ～3.9 17
4. よくあるご質問(FAQ) 18
5. トラブルシューティング 19
6. 同梱品一覧 19
7. 免責事項 19
8. お問い合わせ 19

1.安全上のご注意

1. 安全上のご注意 10

1.安全上のご注意

1. 本製品をご使用する前に、説明書をよくお読みください。
2. 本製品は乾燥した場所でご使用ください。濡れてしまった場合は、十分に乾燥させてからご使用ください。
3. お子様がいらっしゃる場合、本製品をご使用の際は、お子様の安全に十分ご注意ください。
4. 本製品の電源コードまたはプラグが損傷している場合、または本製品が何らかの損傷を受けている場合、本製品を使用しないでください。
5. 本製品のACインターフェースに金属を接触しないでください。感電、火災、その他の危険を引き起こす可能性があります。
6. 充電中または使用中は、本製品の通気口を塞がないでください。通気口を塞がないと、本製品に永久的な損傷を与える可能性があります。
7. 本製品を火や水にさらしないでください。
8. 本製品を強い磁気フィールドから遠ざけてください。強い磁気フィールドや強い電磁波干渉が発生し、本製品の通常の動作に影響を与える可能性があります。
9. 本製品の安全な操作に適した安全機器を使用してください。当社は、サードパーティの機器によって引き起こされた損害に対する責任を負いません。
10. 本製品を分解しないでください。本製品の修理またはメンテナンスが必要な場合は、専門の技術者にご相談ください。
11. 不適切な使用: 落下または過度の力は、本製品に損傷を与える可能性があります。
12. 使用済みバッテリーを廃棄する際は、異なる電気化学システムのバッテリーを分離してください。
13. 火災の場合、ドライパウダー消火器を使用するか、水に浸すことができます。
14. 本製品を火や熱源から遠ざけてください。

2.製品紹介

2. 製品紹介 11

2.製品紹介

バッテリー容量: 3456Wh (48V 72Ah)
Wi-Fi機能: 対応
Bluetooth機能: 対応
UPS機能: (無停電電源装置) : 対応

入力ポート
AC:120V~132V~,12A~,1200~,1650~1760~Watts
PV:7~21~40V,<=15A,シングル最大600W、3ポート合計最大2000W
USB-C:7~21~40V,<=15A,シングル最大600W、3ポート合計最大2000W
AC:120V~132V~,12A~,1200~,1650~1760~Watts

出力ポート
AC:230V~240V 10A~,Max 2400W
230V,50Hz 総出力4000W (ピーク6000W)
USB-A:5V~2.4A,Max 12W,2ポート
USB-C:5V~3A,12V~3A,20V~5A,シングル最大100W
USB-C:5V~3A,9V~2.22A,20V~3A,シングル最大100W
Car port:12V~10A, 120W Max

バッテリーストレージ
リン酸鉄(LFP)リチウムイオンバッテリー
過充電保護、過放電保護、過電流保護、過負荷保護、短絡保護、過電流保護

温度範囲
作動温度範囲: (0°~40°C)
推奨温度範囲: (25°~30°C)
保管温度範囲: (-20°~45°C)
作動湿度範囲: (25~35%)

認証

3.使いかた

3. 使いかた 12
3.1 各部の名称 12
3.2 画面アイコンの説明方法 13
3.3 AC充電 14
3.4 ソーラー充電 15
3.5 車両充電 15
3.6 UPS(無停電装置)について 16
3.7 APP操作 16
3.8 ～3.9 17

3.1 各部の名称

3.2 画面アイコンの説明方法

10

番号	機能紹介
1	バッテリーレベル: バッテリーの現在の容量をリアルタイムで表示します。
2	バッテリーアイコン: 現在の充電インターフェイスのアイコンです。2Eds の詳細を渡します。
3	拡張: アイコン、拡張バッテリーのアイコンです。2Eds の詳細を渡します。
4	入力: 現在の充電インターフェイスのアイコンです。2Eds の詳細を渡します。
5	AC 充電時間: AC 充電の残り時間。AC 充電中に表示されます。
6	ソーラー充電時間: ソーラー充電の残り時間。ソーラー充電中に表示されます。
7	拡張充電時間: 拡張充電の残り時間。拡張充電中に表示されます。
8	出力: 現在の放電インターフェイスのアイコンです。アイコンを設定できます。
9	AC: 現在の AC インターフェイスのアイコンです。アイコンを設定できます。
10	AC 出力時間: AC 出力の残り時間。AC 放電中に表示されます。
11	DC: 現在の DC 出力機能のアイコンです。
12	電源: 現在の電源出力のアイコンです。アイコンを設定できます。
13	拡張バッテリー: 拡張バッテリーのアイコンです。
14	LED: 拡張
15	高温警告: 拡張
16	Bluetooth: Bluetooth がオンになっている場合に表示されます。
17	WiFi: WiFi がオンになっている場合に表示されます。

3.3 AC充電

本製品のAC充電はGaN GaN(窒化ガリウム)技術を採用しており、高速充電モードと静音充電モードの2つの充電モードを提供します。AC充電の最大入力電力は1650Wです。静音充電モードでは、AC充電の最大電力は200Wです。ロッカーの充電のデフォルト出力モードは静音モードです。充電電力を調整するには、製品のモードスイッチを使用してください。



3.4 ソーラー充電

ソーラーパネルを直列にしてソーラーパネルを接続することで、本製品を充電することができます。

11

3.5 車両充電

3.6 拡張バッテリー

本製品は、ポータブル電源の拡張バッテリーとして使用でき、接続された拡張バッテリーの電力を効果的に延長することで、機器の電源供給時間を延長することができます。
拡張バッテリーを接続する場合は、バッテリー接続ポートの仕様に従ってください。
接続中は、定格最大出力は単一側のバッテリー容量を重ねます。
当社が提供する拡張バッテリー接続ポートは、バッテリーの安全性を確保するために、拡張バッテリーの特殊保護モードを備えています。
下の図に示すように、

3.7 UPS機能(無停電電源装置)

本製品は内蔵の充電器、ソーラーチャージャー、車両充電器を使用して、家庭用コンセントからAC入力を充電することができます。製品は同時に充電することも、AC出力ポートから電力を供給することもできます。製品を車両や他の車両で使用する場合は、車両回路を損傷しないように、同時に1台の機器のみを使用することをお勧めします。
当社のUPS(無停電電源)機能は、ACの電源供給が中断した場合、製品の安全性を確保するために、AC出力ポートへの電力供給を自動的に停止します。AC充電とAC出力が同時に有効になっている場合、UPS機能(非自動)をトリガーするには手動でスイッチを入れる必要があります。
1. AC充電とAC出力が同時に有効になっている場合、UPS機能(非自動)をトリガーするには手動でスイッチを入れる必要があります。
2. UPS機能を確保するには、AC充電ポートの入力電力は1650Wを超えないようにしてください。出力範囲は100~120Vです。AC出力ポートの最大電力は1200Wを超えないようにしてください。総出力は1650Wを超えないようにしてください。充電ポートの入力電力が機器の電力を超えると、電源が切れます。10秒後に電源が復旧します。

3.8 ～3.9 APP操作

3.8.1 アプリのダウンロード

12

3.8.2 Bluetooth接続ポータブル電源

Bluetooth を開いてペアリングし、APP を開いてBluetooth を検索してオンにします。
Bluetooth ペアリングを有効にし、インターフェイス言語を中国語、英語、日本語に切り替えます。
[追加] をクリックして電源コンセントをスキャンします。
電源コンセントをクリックして電源コンセントに接続します。
接続が成功すると、APP P0000 ESS が Bluetooth デバイスバーに表示されます。

3.8.3 WiFi接続

ワイヤーが正常に接続されたら、APP の [デバイス] ページに移動し、電源コンセントの名前をクリックして、[ワイヤレス] ページに移動します。
ワイヤーが正常に接続されたら、[ワイヤレス] ページに移動し、[WiFi] をクリックして、[WiFi] ページに移動します。
WiFi ネットワークをクリックして、パスワードを入力して接続します。
接続が成功すると、電源コンセントの名前とステータスが表示されます。

13

3.8.4 アプリの操作

3.8.5 充電モード設定

充電モードは、高速充電モードと、高速充電モード、ミュートモードの3つです。
ACが有効になっていない場合、周波数を50Hzまたは60Hzに切り替えることができます。
ACが有効になっている場合、ACをオンにすると、電源コンセントは24時間後に自動的にシャットダウンします(設定可能な時間:1時間、2時間、4時間、8時間)。
2. Bluetooth 設定: Bluetooth 機能をオンまたはオフにします。
3. Wi-Fi 設定: Wi-Fi 機能をオンまたはオフにします。ネットワークステータス、スタンドモード、スタンダードモード、および高速充電モードを表示します。
4. WiFi 設定: WiFi 機能をオンまたはオフにします。ネットワークステータスを表示し、WiFi 接続を設定します。

14

3.8.6 節電設定

1. 節電設定: 節電時間を設定すると、電源コンセントは自動的にシャットダウンします。
2. 強制クイックシャットダウン: 電源コンセントのスイッチをオンにします。
3. Bluetooth 設定: Bluetooth 機能をオンまたはオフにします。
4. Wi-Fi 設定: Wi-Fi 機能をオンまたはオフにします。ネットワークステータス、スタンドモード、スタンダードモード、および高速充電モードを表示します。
5. WiFi 設定: WiFi 機能をオンまたはオフにします。ネットワークステータスを表示し、WiFi 接続を設定します。

4.よくあるご質問(FAQ)

1.本製品はどのタイプのバッテリーを使用しますか?
本製品は高品質のリン酸鉄リチウムバッテリーを使用しています。
2.本製品のACポートは何を運ぶことができますか?
本製品のAC出力ポートは、230V~240V 10A~,Max 2400W Max(Surge 6000W) 230V,50Hz 総出力4000W(ピーク6000W)の電力を供給することができ、ほとんどの家庭用電子機器に電力を供給することができます。
ご使用の電気機器の電力を確認し、定格電力が本製品の総電力を超えないことを確認することをお勧めします。
3.製品は何時間電力を供給できますか?
製品は残り時間を表示することができます。
4.製品は充電されていますか?
製品は残り時間とバッテリー残量を表示することができ、バッテリー残量表示には呼吸アニメーションがあります。
5.製品のお手入れ方法?
乾いた布または湿った布、清潔な布または紙タオルを使用してください。
6.製品の保管方法?
保管する前に、まず製品をオフにしてください。次に、乾燥した換気の良い場所で、25~30°Cの温度と25~35%の湿度で保管してください。製品を長期間使用しない場合は、バッテリーを30%まで放電し、3ヶ月ごとに80%まで再充電することをお勧めします。これにより、バッテリーの寿命とパフォーマンスを確保します。
7.この製品を飛行機に持ち込めますか?
はい、持ち込むことができます。
8.充電と放電は同時に行えますか?
はい、充電と放電は同時に行うことができます。
9.製品の定格容量は、ユーザーマニュアルの目的容量と一致していますか?
ユーザーマニュアルに記載されている容量は、この製品のバッテリーパックの定格容量です。実際の容量は、周囲の温度やバッテリー圧力などの要因により影響を受ける可能性があります。したがって、この製品の実際の出力容量は、ユーザーマニュアルに記載されている容量よりも小さくなります。したがって、ユーザーは、実際の使用状況に応じて、ユーザーマニュアルに記載されている容量を考慮して、最終製品を展開することをお勧めします。
10.製品は充電されていますか?
はい、製品は残り時間とバッテリー残量を表示することができ、バッテリー残量表示には呼吸アニメーションがあります。
11.製品のお手入れ方法?
乾いた布または湿った布、清潔な布または紙タオルを使用してください。
**12.製品