

MS-6115 Multifunction Power Meter Instructions

Please read the following instructions carefully before connecting this meter to electrical appliances.

WARNING!

Do not plug two or more meters together!

Indoor use only!

Not position the energy meter so that it is difficult to disconnect it from the supply!

IMPORTANT

Don't plug in an appliance where the load exceeds 10 Amp. Always ensure the plug of any appliance is fully inserted into the meter outlet. If cleaning of the meter is required, remove from mains power and wipe meter with a dry cloth.

KEYBOARD DEFINITION

1. **MASTER CLEAR:** Clear all data in memory including current time and all programs.
2. **UP:** Set current time, price, price programs combined with buttons **SET**; exchange 12-24 hour mode during clock display state.
3. **SET:** Set current time, price, price programs combined with buttons **UP**.
4. **FUNC:** Exchange display state.

GENERAL FEATURES

1. Display current clock.
2. Display line voltage.
3. Display line current.
4. Display line power.
5. Display and memory accumulative total electric quantity.
6. Display and memory total on time and total electric charge,.
7. Display and memory total on time and total electric charge of price1.
8. Display and memory total on time and total electric charge of price2.
9. Display line frequency.
10. Display power factor.
11. Adjustable price / kWh

11 combinations of day or blocks of days available as follows:

MO

TU

WE

TH

FR

SA

SU

MO,TU, WE, TH, FR

MO,TU, WE, TH, FR, SA

SA, SU

MO, TU, WE, TH, FR, SA, SU

BATTERY

Insert the 3 pcs battery(LR44/AG13) according to the correct direction indication, close the cover of battery.Press master clear button after insert battery.now the power meter is now ready to be set up for use.



Note: 1. The cover must be in place before use.

2. The battery must be taken out if not use for long time.

THE DATA DISPLAY

Press **FUNC** button the data displays as follows:

VOLTac → AMP → WATT →KWh →TOTAL PRICE;TOTAL ON TIME → PRICE1 → PRICE2

↑ _____ ↓

- 1.The meter will display current clock and line voltage, frequency, if plug in socket after insert battery without any operation.
2. Press **FUNC** button once and release, the meter will display current clock and line current, power factor.
3. Press **FUNC** button once again and release, the meter will display current clock and real power, power factor.
4. Press **FUNC** button once again and release, the meter will display current clock and accumulative **KWh**,power factor.
5. Press **FUNC** button once again and release, the meter will display total on time and total electric charge.
6. Press **FUNC** button once again and release, the meter will display total on time of price 1 and total electric charge of price 1.
7. Press **FUNC** button once again and release, the meter will display total on time of price 2 and total electric charge of price 2.
8. Press **FUNC** button once again and release, the meter will come back to display current time and line voltage.

Press and hold **FUNC** button for 5 seconds to clear accumulative total electric quantity and total electric charge during display state of total electric charge or total electric charge of price 1 or total electric charge of price 2.

9. LCD display **----**when total electric quantity, total electric charge overflow, the **OVER** will flash at the same time.

SETTING CURRENT CLOCK

1. Press **FUNC** button until the **CLOCK** displays in LCD.

2. Press **SET** button once time, The "**WEEK DAY**" will flash at same time, the clock change to **SET** mode. you can set the current clock now.
3. Press **UP** button to set the "**WEEK DAY**".
4. Press **SET** button once time again and release, The "**HOURL**" will flash. the "**WEEK DAY**" will stop flashing and keep display.
5. Press **UP** button to set the "**HOURL**".
6. Press **SET** button once time again and release, The "**MINUTE**" will flash. the "**HOURL**" will stop flashing and keep display.
7. Press **UP** button to set the "**MINUTE**".
8. Press **SET** button once time again and release, the time come back to **CLOCK** display mode.
9. Press **UP** button during the **CLOCK** display state, change 12-24 hour mode.

To reset incorrect time, repeat above steps.

After finish setting, Plug the meter into a regular **240** Volts power outlet, Plug in an appliance that you want to use and turn the mains power on. Now the meter begins to measure the consumption of the appliance and detect the equipment that uses too much electricity at once.

SETTING PRICE OF COST/kWh

Press and hold **FUNC** button for 5 seconds during display state of voltage or current or power.

1. Setting **price 1**:
 - a. Press **SET** button once and release, **SET** display, the first digital **COST/kWh** flash, press **UP** button to set it.
 - b. Press **SET** button once again and release, the second digital **COST/kWh** flash, press **UP** button to set it.
 - c. Press **SET** button once again and release, the third **COST/kWh** flash, press **UP** button to set it.
 - d. Press **SET** button once again and release, the fourth **COST/kWh** flash, press **UP** button to set it.
 - e. Press **SET** button once again and release, the radix point **COST/kWh** flash, press **UP** button to set it.
 - f. Press **SET** button once again and release, the weekday flash, press **UP** button to set it.
 - g. Press **SET** button once again and release, the hour of **ON TIME** flash, press **UP** button to set it.
 - h. Press **SET** button once again and release, the minute of **ON TIME** flash, press **UP** button to set it.
2. Setting **price 2**:

Press **FUNC** button once and release after finish Setting price 1. Setting price 2, repeat above steps.

STAND BY MODE

Display of LCD will disappear without any operation after AC power off for 10 seconds. Press any key come back To display.

SPECIFICATIONS

Power supply	240V AC 50Hz
Max. load	10A, 2400W
Measure voltage range	200-276V AC
Measure voltage accuracy	+/-1%
Measure current range	0.01-10A
Measure current accuracy	+/-1% or +/-0.01 A
Measure power range	0.2W-2760W
Measure power accuracy	+/-1% or +/-0.2W
Accumulative electric quantity range	0 -9999.9kWh
Measure frequency range	45-65Hz
Clock accuracy	+/- 1 minute per month
Power cost	<0.5W
Operating temperature	-10 °C to +40 °C
Battery	3x1.5V LR44/AG13
Battery life	about 3 months without AC power

Distributed by

Electus Distrubution Pty Ltd.

320 Victoria Road, Rydalmere, NSW 2116 Australia.

Phone: 1300 738 555

Facsimile: 1300 738 500

www.electusdistribution.com.au

Made in China



WARNING – KEEP BUTTON BATTERIES OUT OF REACH OF CHILDREN

- If swallowed a lithium button battery may lead to serious or fatal injury in as little as 2 hours, due to chemical burns and potential perforation of the oesophagus
- All button batteries must be kept away from children regardless if they are new or used.
- If you suspect your child has swallowed or inserted a button battery immediately call the 24-hour Poisons Information Centre on 13 11 26 (Australia) or 0800 764 766 (New Zealand) for fast, expert advice.
- If your child is having difficulty breathing contact 000 (Australia) or 111 (New Zealand).
- Dispose of used button batteries immediately and safely out of the reach of children. A battery can still be dangerous even when it can no longer operate the device.
- As soon as you have finished using a button battery, put sticky tape around both sides of it. This will make it harder for children to swallow the button battery and avoid the risk of the battery catching fire.
- Immediately dispose of button batteries immediately out of reach of children, or recycle using a child resistant container and take used cells to your local battery collection centre.