



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

## Release Letter

|          |                                     |
|----------|-------------------------------------|
| Product: | <b><i>Configuration Manager</i></b> |
| Version: | <b><i>7.30.0064</i></b>             |

This letter contains latest information about the above mentioned software.

### 1. General

Configuration Manager is a generic configuration tool for all Bosch IP Network Video Products, both software modules and hardware devices.

It is used for configuration and licensing of the various products.

Configuration Manager 7.30 is a feature release, based on version 7.21.0080.

It includes Video SDK 6.3 and latest plug-ins for VCA configuration.

Special features of Configuration Manager 7.30 are the support of the new CPP13 INTEOX cameras including the S&ST app management and the connectivity to Remote Portal.

This version supports English as main language. The other 10 languages are not fully translated yet.

Make sure to always use the latest released version.

Changes to last version marked [blue](#).



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

## 2. Important Notes

- Configuration Manager 7 has excluded support for Bosch Video Client and BVIP Lite Suite. Installing it over an existing installation of a previous version will encrypt the database with strong encryption and thus render it unusable for the older software.
- Configuration Manager 7.0 and higher are pure 64 bit applications and require a 64 bit Windows operating system.



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

### 3. New Features

- INTEOX and S&ST
  - App management and update handling have been improved.
- Remote Portal
  - A user can delete a camera from use with Remote Portal.
  - A user can set the image refresh according to available bandwidth.
- Configuration of DIP 7000 AIO's Microsoft iSCSI target CHAP password is supported.
- Live video dialog is reused between pages, reducing loading time.
- Live video dialog can be maximized. In addition, shortcuts have been added:
  - 'z': Enlarge dialog to original video size,
  - 'v' Maximize video dialog.
- Human Skin Temperature Detection (HTD) degree settings now support Fahrenheit.

### 4. Changes

- A security issue has been fixed. DLL injection attacks mitigated by preventing loading DLLs from current working directory
- Search is extended to also find device tags "Attribute" imported via CSV file.
- Factory default button added for S&ST environment and button wording improved.
- Action icons positions can be re-arranged.
- Read-only fields now allow copy.
- Snapshot view now also includes ONVIF cameras.



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

## 5. Restrictions; Known Issues

- On a MIC or AUTODOME with FW < 7.70 and VCA configured, using CM 7.20 will show all configured lines, fields and routes at a wrong position. Saving then will break the VCA configuration. Use CM 7.11 or 7.21 or higher instead.
- FLEXIDOME IP starlight 5000i (IR) cameras incorrectly show up as Device Type FLEXIDOME IP 4000i (IR)
- FTP address must be IP address only, URL is not supported.
- After changing the IP address of a device the settings page might not be updated automatically. Manual refresh might be required.
- Upload of a configuration file might be incomplete if it includes recording settings. It is recommended to check the settings manually.
- Special characters like '<:>@' are not allowed for names and passwords. If entered into devices using the Web GUI the Configuration Manager will not be able to access the devices.
- Saving empty password may cause I/O error message without effect for the setting.
- Database path must be re-written if previous installation did not use default path.
- 'Device info' dialog for Divar 700 only shows the general information tab and information that can be retrieved through the VideoSDK interfaces.
- No IPv6 & DNS check for VRM databases.
- For cameras with Intelligent Tracking function, "Click on object" is not supported by Configuration Manager.
- If no IPv6 network is available, the initial IP address configuration of DLA E-Series must be done by setting the PC's IP address in the range of the storage's default IP address 192.168.128.101 for discovery. Once set to a valid IP range, the Configuration Manager PC can be used with its standard IP address.
- Configuration Manager may run into an access violation when an ONVIF camera with pan and tilt but no zoom function is added to Video Streaming Gateway, e.g. like Axis M3007.
- For legacy devices, e.g. VideoJet 8008 or VideoJet 10, all tabs and buttons regarding motion detection are deactivated, thus motion detection cannot be configured.
- FTP accounts' passwords are not stored during Backup & Restore settings.
- User interface for the DIVAR AN 3000/5000 FW upgrade feature is only available in English.
- If the DIVAR AN 3000/5000 FW upgrade transfer is interrupted by a power or network failure the remote system might get in a state that it can't be upgraded again through Configuration Manager.  
In this case, the upgrade must be done manually through the WEB UI or locally on the device.
- A FW upload of a DIVAR AN 3000 or DIVAR AN 5000 can only be cancelled during the transfer phase. Once the file has been transferred to the device and the upgrade process has been started this cannot be cancelled anymore.
- For dual recording, Configuration Manager does not allow to assign the identical LUN to both recording entries.



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

- VCA tabs, e.g. Motion Detection may not be refreshed after firmware upgrade or downgrade. Manual refresh might be necessary.
- Device network settings configuration for VJD-7000 and VJD-8000 is not functional in the context menu of the device tree (right-click). The network configuration page shall be used instead.
- VRM-based ANR mode is no more supported.
- Only one LUN lock can be overwritten per device at a time. Acquiring of lock is done only when storage target is needed for recording.
- Upload of an invalid certificate will cause I/O errors displayed on page.
- With cameras running firmware 6.4x and 'Silent VCA' mode, a wrong VCA calibration tab may be displayed on 'event triggered' or 'scheduled' modes. A VCA profile must be selected first.
- Underscore character (" \_ ") and blank space are not allowed in common name in certificates.
- Once an authenticated is established, the user can still communicate with a device although the smart token might have been removed. To avoid unauthorised access, Configuration Manager should not be left accessible when the smart token with the client certificate is removed.
- With CPP7.3 AUTODOME and MIC cameras, an I/O error might be displayed on the 'Logs' tab. The device's web page can be used instead to access the logs and configure the syslog functionality.
- Due to security concerns, basic authentication is no more supported. As a result, firmware cannot be uploaded to a password-protected VJD-7000 running FW 54.8.x or older. An older version of Configuration Manager can be used instead, or the password removed temporarily.
- With certificate-based authentication, each Windows user should only use one Smart Card or user token for the same CA.
- If a storage array is reconfigured or cleared manually (e.g. by using console or SanTricity instead of Bosch tools), all LUNs of all targets of the storage array must be deleted from the VRM and then re-added again to update all necessary information.
- Custom table views do not support adding of dynamic content like e.g. user management or certificates.
- Configuration upload and download is not supported for cameras of the Remote Portal.
- Repository download that includes offline devices or devices not supporting a configuration file download will show an error which can be ignored. All parameters handled by Configuration Manager will be stored in repository.
- In rare cases only a partial VRM device tree is shown. Restart the Configuration Manager for a full display.
- Privacy masks and other orientation-related parameters must be checked and eventually re-assigned after rotating a camera.
- Uploading or exchanging certificates requires the device to be rebooted if running firmware below version 7.x.



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

- Stamping logo may sometimes lose transparency if converted by Configuration Manager. In this case, prepare logo with correct size and colors with other tools to avoid conversion.
- Using “export from memory” with pre-alarm recording exceeding the available memory will cause continuous recording on the account storage. Checking the memory requirement of the pre-alarm ring is advised to avoid unexpected memory consumption.

**Note:**

If multiple Configuration Managers are used in the network, maintaining the same or an overlapping set of devices simultaneously, unpredictable effects might occur when writing to the devices.

**Note:**

Due to the change to .NET 4.7.1 DiBos devices cannot be found by network scan if .NET 3.5 is not installed.

If required install .NET 3.5 in addition to the Configuration Manager installation package.



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

## 6. System Requirements

|                            |                                                                                         |
|----------------------------|-----------------------------------------------------------------------------------------|
| Hardware                   | Personal Computer                                                                       |
| CPU                        | Dual Core, 3.0 GHz or better                                                            |
| RAM                        | min. 2 GB                                                                               |
| OS                         | Windows Server 2019<br>Windows Server 2016<br>Windows 10 64 bit<br>Windows 7 SP1 64 bit |
| Graphic Card               | refer to Video SDK 6.34                                                                 |
| Ethernet Card              | min. 100 Mbps                                                                           |
| Sound Card                 | Recommended                                                                             |
| Software                   | Microsoft .NET 4.7.1                                                                    |
| Free Memory (Installation) | 250 MB (Configuration Manager, V-SDK)                                                   |

## 7. Component Versions

|              |           |
|--------------|-----------|
| RCP Plus SDK | 5.00.0027 |
| Symbol SDK   | 4.00.0041 |
| VCA SDK      | 4.30.0028 |
| Video SDK    | 6.34.0200 |
| PD SDK       | 1.20.0002 |

Open source license information is available in the 'doc' folder in the installation path.  
You may also visit the Bosch Security Systems Open Source Software page at  
<https://www.boschsecurity.com/xc/en/oss/>.

**Note:**

Video device proxies for DIVAR devices use OpenSSL for encrypted communication.



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

## 8. Features and Changes with former versions

### ***Changes with 7.21.0080***

- Fixes issues (with released build 77)
  - o where a VCA field was not properly displayed
  - o where the 'Traffic Detectors' checkbox on INTEOX cameras was not checked
  - o where the pan angle for VCA was inverted in relation to optical movement
- An issue with the installer signature has been fixed.

### ***New Features with 7.20.0067***

#### **INTEOX cameras**

- *App Management* menu introduced as part of *Service* menu
- Use Configuration Manager to download and install applications purchased in the S&ST App Store (please checkout out the respective training in our [Bosch Building Technologies Academy](#)) (link)
- Configuration of 3<sup>rd</sup>
- Configuration of new OSD capabilities of INTEOX camera

#### **Remote Portal**

- Benefit from remote access to manage your devices ***for free*** from anywhere where you have internet access → Please check out our [customer success story](#) (link)
- UX improvements
- Alternatively to updating device directly from the Bosch Remote Portal, it is possible to upload firmware files from the Configuration Manager from remote via the Remote Portal, as if you were locally connected

#### **VCA**

- Access to all streams and recordings during configuration

#### **VRM**

- Maintenance log export integrated into Configuration Manager

#### **Network**

- Subnet-crossing scan possibility introduced (independent of multicast)
- Proxy server support

#### **New Products**

- AUTODOME intex 7000i
- MIC intex 7100i - 2MP



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

- MIC intex 7100i – 8MP
- FLEXIDOME IP starlight 5000i (IR)
- DINION IP thermal 9000 RM

**Miscellaneous**

- Configuration Manager can automatically check the Bosch Security Download Area for new versions

Note: Check out our latest How-to Video on [YouTube](#) (link)



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

***Changes with 7.20.0067***

- UX improvements for VCA Task Script Editor
- Security improvements
- Fixes issues
  - o where “VCA silent” was not properly listed in “Profile to configure” dropdown menu
  - o for Camera Trainer
    - regarding sampling from playback
    - remote access to recording via Remote Portal
  - o regarding VCA when COM1 settings are configured
  - o regarding sorting functionality for VRMs
- input for BVMS Configuration Client stability improvements

***New Features with 7.11.0048***

- A start-up configuration for a VIDEOJET decoder running minimum firmware 10.0 can be defined using the IP Matrix functionality. Configuration Manager allows to define the initial layout and to populate the video windows by assigning cameras to it. No keyboard needs to be connected; and with automatic re-connect, the same view is re-established in case of a reboot of the decoder.
- Decoder log file can be downloaded via Configuration Manager. This is especially recommended when download of the log file is not working correctly via web browser.

***Changes with 7.11.0048***

- An issue that a NetApp storage with firmware 11.60 or higher could not be added to the system has been fixed.
- Various minor issues have been fixed.



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

***New Features with 7.10.0042*****Remote Portal**

- Navigation has improved to make Remote Portal and cloud access simpler and more intuitive.
- Automatic login if Remote Portal account credentials are configured.
- Batch commissioning of cameras into Remote Portal, considering minimum required IP camera firmware 6.40.

**New products**

- Support for the new FLEXIDOME IP 8000i with tele lens added.
- Support for soon to be released Monitor Wall 10 software and decoder firmware 10.0 added.
- Support for AVIOTEC IP starlight 8000 added.

**Usability**

- Device Health Monitor now includes iSCSI multi-pathing info in recording status.
- Password-protected database export added.
- Camera Trainer samples directory path is now configurable.

***Changes with 7.10.0042***

- Usability improvements for calibration and VCA configuration.
- Passwords can now be pasted into password fields; password confirmations can be pasted when visibility is on.
- Usability improvements for client certificate handling.
- URL scheme was introduced to allow Configuration Manager being called directly from web interface of IP cameras for VCA configuration.
- Various minor issues have been fixed.



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

### ***New Features with 7.01.0136***

#### **VCA 7.60 support**

- New filters 'height' and 'width' in addition to 'area' and 'aspect ratio'.
- New tamper detection 'camera moved' for cameras with gyro sensor.
- Metadata are configurable to include less content, supporting lower data rates for e.g. low bandwidth ITS applications.

### ***Changes with 7.01.0136***

- Various bug fixes, mainly in the VCA area.
- Updated Configuration Manager help file.



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

***New Features with 7.00.0111*****User Interface**

- Look-and-feel according to latest Bosch style guide, improvements on readability of form elements.
- Screen space optimization due to higher density of presented information, optionally vertical navigation bar.
- Scaling invariant user controls enable smooth support for high DPI screens.
- Avoiding horizontal scrolling by adaptive column reduction.
- New easy to use filters, supporting "Google"-like free text matching on various identifiers as well as down into device properties.
- VCA pages with new sub-navigation, larger video presentation for easier task setup, improved calibration and Camera Trainer pages, in-field editing, object filter page, and providing tooltips and direct links to help pages.

**Security**

- Strong password demand during first start of the program. Working without password prompts extra warning pop-up and requires specific user action.
- Certificate creation now allows including usage. This enables fully automated batch certificate creation for larger sets of devices. The creation dialog shows the progress of key creation.

**Cameras**

- Support for new AUTODOME IP 7000i and MIC IP 7100i with firmware 7.52, introducing changes and enhancements on picture settings and pre-position settings pages.
- Setting an alternate home position is now possible for applicable moving cameras.
- Support for new DINION and FLEXIDOME IP 3000i series with firmware 7.51.
- An RCP+ message and/or a SNMP trap from cameras, if time sync fails, can be configured.

**Storages**

- Assignment option for CHAP password on DSA E series storages added. Password must be from 12 to 16 characters long.

**Decoders**

- Playback permission is configurable for IP Matrix since decoder firmware 9.60.



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

### ***Changes with 7.00.0111***

- Support for Bosch Video Client (BVC) and BVIP Lite Suite is excluded.
- The configuration backup of the Configuration Repository is now referring to the MAC address of a device instead of the IP address.
- Network scan is now also possible for IPv6 networks.
- Context menu and some configuration pages cleaned-up for decoders.
- Improved feedback on firmware upload status and errors.
- The character '+' is not allowed anymore for camera passwords since it is also blocked in cameras from firmware 7.50 onwards.
- The image posting tab is moved from 'Network' to 'Recording', and a link to configure accounts was added.
- Secure crypto-coprocessor version is now displayed on camera's compatibility tab.



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

***New Features with 6.20.0102***

- New camera FLEXIDOME IP panoramic 7000 MP outdoor is supported.
- New Sony Minidome cameras SNC-EMX30, SNC-EMX30R, SNC-EMX32R, SNC-EMX50, SNC-EMX50R and SNC-EMX52R are supported.
- New Video Streaming Gateway version 7 is supported, allowing to configure up to 32 video inputs and a maximum of 255 inputs and relays each.
- New devices DIVAR IP all-in-one 5000/6000/7000 are supported.
- New devices VIDEOJET decoder 5000/7000/8000 are supported.
- New features from camera firmware 7.x are supported:
  - o IP address change possible without rebooting the camera.
  - o New field 'hostname' is supported.
  - o Audio multicast is supported.
  - o New function 'export from memory' allows recording export without SD card installed.
  - o New scene modes settings for AUTODOME IP 7000 and MIC IP 7000/9000i are supported.
  - o Preset calibration for thermal channel on MIC IP 9000i added.
  - o New account types for AWS Kinesis and S3 are supported for cameras supporting these.
- Camera Trainer is supported, including a link to training videos.
- On decoders, the alarm frame around a video window can be switched off or shown blinking or constantly.
- Passwords, also for WLAN access port, can be changed on multiple devices in parallel.
- Firmware upload for multiple devices of different platforms (CPP) in parallel allows selection of multiple firmware files for different platforms, automatically detecting target platform firmware.
- Minimum firmware version and Commercial Type Number (CTN) are displayed and can be searched for as well as exported in table view.



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

### ***Changes with 6.20.0102***

- Security improvements for the password vault.
- Filter functionality has been enhanced.
- Firmware update dialog improved.
- Fields 'unit name' and 'unit ID' renamed to 'device name' and 'device ID'.
- Scan and display of devices improved for devices with identical IP address.
- Improvements made for scanning and identifying DIVAR hybrid/network devices.
- Some missing tabs have been added for AVIOTEC camera.
- Enhanced feature list in 'Device info -> Capabilities' window.
- An issue with zoom threshold not stored with a privacy mask on AUTODOME is fixed.
- HW version field is removed from Devices tab.
- Various issues with VCA configuration and calibration fixed.
- Various smaller issues fixed.



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

***New Features with 6.10.0131***

- Backup of device configuration can be stored in a configuration repository. System backup allows assignment of a backup password and software sealing of device configuration after backup.
- New FLEXIDOME 8000i camera family is supported, including dual SD card functionality.
- Project files from Project Assistant app can now be imported.
- Camera Trainer configuration is supported.

***Changes with 6.10.0131***

- User interface improved and various display issues fixed.
- Various issues with network scan fixed.
- Various issues with VCA configuration fixed.
- Various issues with VRM and VSG fixed.
- Various issues with handling of certificates and with MicroCA fixed.
- Various issues with ONVIF devices fixed.
- Various issues with VIDEOJET decoder 8000 and IP Matrix fixed.
- Various smaller issues fixed.

***Changes with 6.01.0157***

- An issue with certificate key generation is fixed.
- An issue with wrong status shown after firmware upload is fixed.
- Some issues with IP Matrix configuration are fixed. E.g. a button was added to start IP Matrix configuration, setting the correct decoder as master.
- Some issues with table view are fixed.
- Various issues with VCA configuration are fixed and improvements introduced.
- It is now possible to set virtual alarm triggers 17 to 32 for Video Streaming Gateway (VSG).
- An issue with some sliders not being shown for DINION thermal 8000 is fixed.
- An issue where retention time was not configurable for VIP-X1600-XFM4 is fixed.
- CHM help files are updated.



From

BT-VS/ETP-MKP1

Product Management

Nuremberg

29.01.2021

***New Features with 6.00.0122*****• New Table View**

- o Table view is now embedded in Configuration Manager user interface as an alternative view to the tab view interface. It does not open a separate window anymore but switches views between the two alternatives.
  - o Device parameters are listed in an “Excel”-like view and are shown for all cameras that had been selected in this view.
  - o Device multi-select is also possible in this view, providing a detailed overview of actual settings and allowing changes to parameters in a fast and comfortable way.
  - o Custom table views provide means to focus on important and relevant settings, and together with extended import and export functions make configuration archiving and restoration an easy task.
  - o Architectural changes help retrieving device parameters up to hundred times faster, supporting the new table view to present multiple devices’ parameters quickly and smoothly.
- 
- A security assessment page has been added, providing an overview and status of the actually configured security level of the system
  - Support for CPP4/6/7/7.3 FW 6.50 feature additions and changes, including:
    - o Highly reliable SD card recording with life cycle monitoring
    - o H.265 B frames support in Installer menu
    - o Software Sealing
    - o Discover port configuration
    - o Possibility to increase the Power-over-Ethernet (PoE) demand signalled via LLDP
    - o Missing SD resolutions added to stream 1 options for CPP7.3 cameras
  - Cameras, also multiple, can be commissioned into Remote Portal.
  - Support for configuration of online cameras via the Remote Portal.
  - Support for motion recording in Video Streaming Gateway (VSG).
  - Support for reworked device replacement in Video Recording Manager (VRM).
  - Support for downloading DSA E2800 support bundle.
  - Support for VIDEOJET decoder firmware version 9.50, including configuration of new IP Matrix.
  - Support for recently introduced devices.



|                |                    |  |            |
|----------------|--------------------|--|------------|
| From           |                    |  | Nuremberg  |
| BT-VS/ETP-MKP1 | Product Management |  | 29.01.2021 |

### ***Changes with 6.00.0122***

- Configuration Wizard has been removed.  
This has mainly been used in combination with Bosch Video Client installations which are not in focus anymore since version 5.50 and above.
- Offline configuration has been removed.  
This has lost functionality due to recent firmware changes and was rarely used.
- Various smaller issues have been fixed.

For earlier history, please refer to release notes of Configuration Manager 5.x or before.