

# ThinkSystem DE4000H, DE6000H, and DE600S Storage Systems

## Installation and Setup Instructions for 4U Enclosures


Machine Types: DE4000H (7Y77), DE6000H (7Y80), and DE600S (7Y69)

## Prepare for installation | Stage 1


### Pre-setup

- Create an account and register your hardware at [datacentersupport.lenovo.com](http://datacentersupport.lenovo.com)
- Inventory cables and make note of the quantity.
- Confirm that your location provides 200-240V AC power.

### In the box



Shelf, bezel, and  
rackmount hardware



Shelf  
handles



Ethernet cables  
if ordered



I/O cables  
if ordered



SAS cables  
included only with  
the drive shelves




Power cables  
(two for each shelf)



### You provide



Phillips No2 screwdriver,  
flashlight, and ESD strap



4U rack  
space

A 19 in. (48.30 cm)  
rack to fit 4U shelves of the  
following dimensions:

**Height:** 6.87 in. (17.46 cm)  
**Width:** 17.66 in. (44.86 cm)  
**Depth:** 38.25 in (97.16 cm)  
**Max Weight:** 250 lb. (113 kg)



A supported browser  
for the management  
software



### HELPFUL LINKS

- **Lenovo Data Center Support Web site (worldwide):**  
<http://datacentersupport.lenovo.com>
- **Lenovo Data Center Support Web site (Chinese Mainland):**  
<http://support.lenovo.com.cn/EsWeb/>

Second Edition (February 2020)  
© Copyright Lenovo 2020.

LIMITED AND RESTRICTED RIGHTS NOTICE: If data or software is delivered pursuant to a General Services Administration (GSA) contract, use, reproduction, or disclosure is subject to restrictions set forth in Contract No. GS-35F-05925.

LENOVO, LENOVO logo, and THINKSYSTEM are trademarks of Lenovo. Microsoft and Windows are trademarks of the Microsoft group of companies. All other trademarks are the property of their respective owners.  
© 2020 Lenovo.

For Barcode Position Only

Printed in China  
(1P) P/N: SP47A30402

# Install hardware | Stage 2


## 1 Unpack the Hardware

Unpack the contents and inventory the contained hardware against the packing slip. Read through all the instructions before proceeding.

## 2 Install the Rails

Refer to the enclosed instructions for detailed information on how to install the rails. To download the instructions, go to [Lenovo Data Center Support Web site](#).


**NOTE:** Install hardware from the bottom of the rack up to the top to prevent the equipment from toppling over.




## 3 Install the Shelf

1. If lifting the shelf by hand, attach the four lift handles. Push up on each handle until it clicks into place.

**▲ CAUTION:** An empty shelf weighs approximately 132 lb (60 kg). A mechanized lift or four people using lift handles are required to safely move an empty shelf.



2. Supporting the shelf from the bottom, slide it into the cabinet. If the lift handles are used, remove them one set at a time as the shelf slides into the cabinet. To remove the handles, pull back on the release latch, push down, then pull away from the shelf.



## 4 Secure the Shelf

1. Insert screws into the first and third holes from the top of the shelf on both sides to secure it to the front of the cabinet.
2. Place two back brackets on each side of the upper rear section of the shelf. Insert screws into the first and third holes of each bracket to secure the back of the cabinet.




## 5 Install the Drives

1. Wrap the strap end of the ESD wristband around your wrist, and secure the clip end to a metal ground to prevent static discharges.
2. Starting at the front left slot of the top drawer, install each drive by gently positioning into the drive slot and lowering the raised drive handle until it clicks into place.

**NOTE:** If you are installing fewer than 60 drives, if you have solid-state drives (SSDs), or if your drives have different capacities:

- Maintain a minimum of 20 drives per shelf. Install drives in the front four slots in each drawer first, for adequate airflow for cooling.
- Distribute any remaining drives across the drawers. If possible, install an equal number of each type of drive in each drawer to allow for the creation of Drawer Loss Protected volume groups or disk pools.
- Distribute any SSDs evenly across the drawers.

3. Carefully slide the drawer back in by pushing the center and gently closing both latches.
4. Attach the front bezel.



**ATTENTION: Risk of equipment damage** — Stop pushing the drawer if you feel binding. Use the release levers at the front of the drawer to slide the drawer back out. Then, carefully reinsert the drawer into the slot.

# Cable storage | Stage 3

## Cable the Shelves

Cable the system according to your configuration. Examples are shown in this section. For more cabling options, see *ThinkSystem DE-Series Hardware Installation and Maintenance Guide for 4U Enclosures*.

### Cable a controller shelf and two drive shelves


**A**  
Example



- Storage cables

- 1 Cable controller A to IOM A of the first drive shelf.
- 2 Cable IOM A of the first drive shelf to IOM A of the second drive shelf.
- 3 Cable IOM B of the first drive shelf to IOM B of the second drive shelf.
- 4 Cable controller B to IOM B of the second drive shelf.

Example A: A DE4000H controller shelf with two DE600S drive shelves in a standard SAS configuration



### Cable a controller shelf and one drive shelf


**B**  
Example



- Storage cables

- 1 Cable controller A to IOM A.
- 2 Cable controller B to IOM B.

Example B: A DE4000H controller shelf with one DE600S drive shelf in a standard SAS configuration




## Power the Drive Shelves



| Power Cables

- ▲ **CAUTION:** Confirm the drive shelf power switches are off.
1. Connect the two power cables for each shelf to different power distribution units (PDUs) in the cabinet or rack.
  2. If you have drive shelves, turn on their two power switches first. Wait 2 minutes before applying power to the controller shelf.
  3. Turn on the two power switches on the controller shelf.
  4. Check the LEDs and seven-segment display on each controller. During the boot sequence, the seven-segment display will display various codes. After the controller has booted up, the shelf ID will be displayed.

Example: Power connections are on the rear of the shelf.



# Complete system setup and configuration | Stage 4


## Cable the Data Hosts

Cable the system according to your network topology.

### A Option

#### Direct-attach topology


- 1 Connect each host adapter directly to the host ports on the controllers.



### B Option

#### Fabric topology


- 1 Connect each host adapter directly to the switch.
- 2 Connect each switch directly to the host ports on the controllers.




## Connect and Configure the Management Connection

1. Using an Ethernet cable, connect to controller A port 1 (P1), to the ethernet port on your laptop.
2. Manually specify the following IP address and subnet mask on the laptop's Ethernet port that you have physically connected to the storage array:  
IP address: 192.168.128.100  
Subnet mask: 255.255.255.0
3. Use the laptop's browser to access the storage array's management software using the following IP address:  
IP address: 192.168.128.101
4. In the management software, go to the Hardware tab and select Show back of shelf under Controller Shelf. Highlight controller B, and then select Configure management ports to set the IP addresses for management port 1 on controller B. Do not configure management port 2. This port is reserved for Lenovo technical support. After you have configured controller B's management port, repeat for controller A.
5. Disconnect your laptop from the storage array and connect an Ethernet cable to management port 1 (labeled P1) on each DE4000H and DE6000H controller and connect the other end to your network.

DE4000H controller



DE6000H controller



## After Installing the Hardware

1. Use the ThinkSystem SAN OS software to configure and manage your storage arrays.
2. In the simplest network configuration, connect your controller to a web browser and use ThinkSystem System Manager for managing a single DE-series storage array.
3. In a more complex environment, use the ThinkSystem SAN Manager for managing multiple storage arrays.

