


103SW/SW-301

1050SW/SW-501

SERVICE MANUAL



Note : Refer to SW-900 service manual(B51-4228-00) if you need the microprocessor information.

* Refer to parts list on page 8.

SPECIFICATIONS

Amplifier

Power output

Phase switching

Input sensitivity and input impedance

RCA-type jack

Push-type terminals

Supply voltage

Rated power consumption

Speaker

Enclosure

Speaker units

Nominal impedance

Width

Height

Depth

Net weight

1050SW(SW-501)

150 watts RMS into 4 ohms,
from 20 Hz to 200 Hz, with no
more than 0.09%total
harmonic distortion

Normal, Reverse

70 mV (12 k-ohms)

1.7 V(15 k-ohms)

AC 110 V~120 V (1050SW)

150 watts

Ported

12 in (300 mm) polypropylene
cone

4 ohms

14.3 in (363 mm)

21.7 in (550 mm)

18.9 in (480 mm) with grille

53 lb (24 kg)

103SW(SW-301)

100 watts RMS into 4 ohms,
from 20 Hz to 200 Hz, with no
more than 0.09%total
harmonic distortion

Normal, Reverse

70 mV (12 k-ohms)

1.7 V(15 k-ohms)

AC 110 V~120 V(103SW)

110 watts

Ported

10 in (250 mm) polypropylene
cone

4 ohms

11.8 in (300 mm)

18.9 in (480 mm)

15.6 in (395 mm)

40 lb (18 kg)

Since Kenwood follows a policy of continuous advancement in development, these specifications may change without notice.

103SW/SW-301/1050SW/SW-501

CONTENTS/DISASSEMBLY FOR REPAIR/ADJUSTMENT


Contents

SPECIFICATIONS	Top cover	PC BOARD	3
CONTENTS	2	SCHEMATIC DIAGRAM	5
DISASSEMBLY FOR REPAIR	2	EXPLODED VIEW	7
ADJUSTMENT	2	PARTS LIST	8

DISASSEMBLY FOR REPAIR

< How to remove the front panel >


1. Remove the decoration plate (①) by a pincette to the bottom of the front panel, then remove the 3 screws (②).
 2. 103SW/SW-301: Remove the front panel in the upper slanting direction of the arrow (③).
- 1050SW/SW-501 : Remove the front panel just the frontwards.






ADJUSTMENT

No.	ITEM	INPUT SETTINGS	OUTPUT SETTINGS	AMPLIFIER SETTINGS	ALIGNMENT POINTS	ALIGN FOR	FIG.
Unless otherwise specified, the individual switches should be set as following : POWER : ON NO SIGNAL INPUT							
1	IDLE CURRENT	—	Connect a DC voltmeter to R611	VOLUME : 0	VR601	5 mV	(a)


(a)




1	
2	
3	
4	
5	
6	
7	



4



103SW/SW-301/1050SW/SW-501 EXPLODED VIEW (UNIT)



Parts with exploded numbers larger than 700 are not supplied.

* New Parts
Parts without **Parts No.** are not supplied.
Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.
Teile ohne **Parts No.** werden nicht geliefert.

1

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
103SW/SW-301 (103SW: KP type only)						
600	1A	*	A09-0753-05	BATTERY COVER	KP MCTEG	
601	2A	*	A29-0915-08	PVC TRIM FOR WINDOW		
602	2A	*	A29-0917-08	PVC TRIM FOR PANEL TOP		
603	1A	*	A29-0919-08	PANEL TOP W/PAINTING & LOGO		
603	1A	*	A29-0920-08	PANEL TOP W/PAINTING & LOGO	XY	
603	1A	*	A29-0920-08	PANEL TOP W/PAINTING & LOGO		
607	1A	*	A70-0404-05	REMOTE CONTROL ASSY		
611	2A	*	B06-1144-08	CLOTH FRAME ASSY		
612	2A	*	B10-3302-08	WINDOW	MIY KP MIEGY X T	
613	2A	*	B43-0302-04	BADGE		
Δ 620	1A	*	E03-0115-05	AC PLUG ADAPTER		
Δ 621	1B	*	E30-5432-08	AC CORD,181-SA-W541		
Δ 621	1B	*	E30-5438-08	AC CORD	C	
Δ 621	1B	*	E30-5439-08	AC CORD		
Δ 621	1B	*	E30-5440-08	AC CORD		
Δ 621	1B	*	E30-5442-08	AC CORD		
622	1C	*	E30-5466-08	AUDIO CORD	KP MIY C TEG X	
625	1C	*	F20-0702-08	ISOLATION SHEET 19X24		
630	2A,2B	*	J19-3988-08	CATCH BLACK(75)		
632	1B	*	J21-8750-08	AC CORD HOLDER		
633	1B	*	J42-0234-08	CORD BUSHING,3-703-244-021	KP MIY C TEG X	
640	2A	*	K29-0573-08	VOLUME KNOB W/PAINTING		
641	1C	*	K29-0576-08	LOW/PASS PUSH KNOB W/PAINTING		
642	1A	*	K29-0577-08	POWER PUSH KNOB W/PAINTING		
643	1A	*	K29-0578-08	TACT PUSH KNOB W/PAINTING	KP MIY C TEG X	
Δ 650	2C	*	L07-3010-05	POWER TRANSFORMER		
Δ 650	2C	*	L07-3011-05	POWER TRANSFORMER		
Δ 650	2C	*	L07-3012-05	POWER TRANSFORMER		
Δ 650	2C	*	L07-3013-05	POWER TRANSFORMER	X TEG C	
Δ 650	2C	*	L07-3014-05	POWER TRANSFORMER		
660	1A	*	J02-0622-08	FOOT		
-			B46-0096-53	WARRANTY CARD	KY Y KP MIY C TEGX	
-			B46-0310-03	WARRANTY CARD		
-			B46-0326-03	WARRANTY CARD		
-			B46-0330-03	WARRANTY CARD		
-			B59-1104-00	SERVICE STATIONS LIST	C Y	
-		*	B61-0886-00	INSTRUCTION MANUAL		
-		*	B61-0887-00	INSTRUCTION MANUAL		
-		*	B61-0888-00	INSTRUCTION MANUAL		
-		*	B61-0889-00	INSTRUCTION MANUAL	CY KP MIY C TEGX	
-		*	B61-0940-00	INSTRUCTION MANUAL		
-		*	H10-6447-08	PLYFOAM 310G/SET(TOP)		
-		*	H10-6448-08	PLYFOAM 310G/SET(BOTTOM)		
-		*	H21-1284-08	MIRAMAT 1640X540X0.5T	KP MIY C TEGX	
-		*	H25-2180-08	PROTECTION BAG		
-		*	H51-0979-08	CARTON		
-		*	H51-0980-08	CARTON		
-		*	H51-0981-08	CARTON	KP MIY C TEGX	
-		*	H51-0982-08	CARTON		
A		*	N44-4014-45	WOOD SCREW		
B		*	N35-4016-45	MACHINE SCREW(M4X16)		
C		*	N09-3668-05	WOOD SCREW	KP MIY C TEGX	
D		*	N44-3020-45	WOOD SCREW		

L : Scandinavia K : USA P : Canada R : Mexico
Y : PX(Far East, Hawaii) T : Europe E : Europe G : Germany
Y : AAFES(Europe) X : Australia M : Other Areas

Δ indicates safety critical components.

PARTS LIST

2

* New Parts
Parts without **Parts No.** are not supplied.
Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.
Teile ohne **Parts No.** werden nicht geliefert.

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks	
E F G H J		*	N09-3669-05 N89-3006-46 N83-3008-46 N89-3010-45 N89-3008-45	SCREW SCREW SCREW SCREW SCREW			
K L M N		*	N34-3010-45 N82-3010-45 N82-3008-46 N89-3008-46	SCREW SCREW SCREW SCREW			
SPK1	2A	*	T10-0782-15	SPEAKER 10,A25GU25-51C-D			KP
SPK1	2A	*	T10-0788-05	SPEAKER 10			MIXY
SPK1	2A	*	T10-0814-05	SPEAKER 10			C
SPK1	2A	*	T10-0822-05	SPEAKER 10	TEG		
1050SW/SW-501 (1050 SW: KP type only)							
600 601 602 603 603	1A 1B 1A 1A 1A	 * * *	A09-0753-05 A29-0915-08 A29-0916-08 A29-0909-08 A29-0921-08	BATTERY COVER PVC TRIM FOR WINDOW PVC TRIM FOR PANEL PANEL PANEL	KP MIETGX		
604 607 611 612 613	1B 1A 2A 1B 1A	 * * 	A29-0922-08 A70-0404-05 B06-1146-08 B10-3302-08 B43-0302-04	PANEL ,FRONT REMOTE CONTROL ASSY CLOTH FRAME ASSY WINDOW BADGE			
620 621 621 621 621 622	2A 1B 1B 1B 1B 1C	 	E03-0115-05 E30-5432-08 E30-5438-08 E30-5440-08 E30-5466-08	AC PLUG ADAPTER AC CORD,181-SA-W541 AC CORD AC CORD AUDIO CORD	MI KP MIEGY T		
625 630 632 633 640	1C 2A,2B 1B 1B 1B	 * * 	F20-0702-08 J19-3988-08 J21-8750-08 J42-0234-08 K29-0573-08	ISOLATION SHEET 19X24 CATCH BLACK(75) AC CORD HOLDER CORD BUSHING,3-703-244-021 VOLUME KNOB W/PAINTING			
641 642 643 650 650	1C 1B 1B 2C 2C	 * *	K29-0576-08 K29-0577-08 K29-0578-08 L07-3015-05 L07-3016-05	LOW/PASS PUSH KNOB W/PAINTING POWER PUSH KNOB W/PAINTING TACT PUSH KNOB W/PAINTING POWER TRANSFORMER POWER TRANSFORMER	KP MI		
650 650 660	2C 2C 1A	 * *	L07-3017-05 L07-3018-05 J02-0622-08	POWER TRANSFORMER POWER TRANSFORMER FOOT	TEG X		
- -							

L : Scandinavia K : USA P : Canada R : Mexico
Y : PX(Far East, Hawaii) T : Europe E : Europe G : Germany
Y : AAFES(Europe) X : Australia M : Other Areas

Δ indicates safety critical components.

* New Parts
Parts without **Parts No.** are not supplied.
Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.
Teile ohne **Parts No.** werden nicht geliefert.

3

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
A			N44-4014-45	WOOD SCREW		
B			N35-4016-45	MACHINE SCREW(M4X16)		
C			N09-3672-05	SCREW		
D			N62-3116-45	SCREW		
E			N09-3669-05	SCREW		
F			N89-3006-46	SCREW		
G			N83-3008-46	SCREW		
H			N89-3010-45	SCREW		
J			N89-3008-45	SCREW		
K			N34-3010-45	SCREW		
L			N82-3010-45	SCREW		
M			N82-3008-46	SCREW		
N			N89-3008-46	SCREW		
SPK1		*	T10-0785-05	SPEAKER 10	KPTEG	
SPK1		*	T10-0789-05	SPEAKER 10	MIX	
ELECTRIC PARTS						
D401,402		*	B30-1820-08	LED		
D403		*	B30-1821-08	LED		
D404		*	B30-1822-08	LED		
L401,402		*	B30-1819-08	LAMP,12V/60MA		
C101			CE04KW1C330M	ELECTRO 33UF 16WV		
C102			CC45FSL1H221K	CERAMIC 220PF K		
C103			CC45FSL1H101J	CERAMIC 100PF J		
C104			CC45FSL1H221K	CERAMIC 220PF K		
C105			CQ92FM1H103J	MYLAR 0.010UF J		
C106			CC45FSL1H220J	CERAMIC 22PF J		
C107			CE04KW1C470M	ELECTRO 47UF 16WV		
C108			CC45FSL1H101J	CERAMIC 100PF J		
C201			CQ92FM1H103J	MYLAR 0.010UF J		
C202			CC45FSL1H101J	CERAMIC 100PF J		
C203			CQ92FM1H184J	MYLAR 0.18UF J		
C204	3		CQ92FM1H473J	MYLAR 0.047UF J		
C204	5		CQ92FM1H563J	MYLAR 0.056UF J		
C205,206			CQ92FM1H184J	MYLAR 0.18UF J		
C207	5		CQ92FM1H393J	MYLAR 0.039UF J		
C207	3		CQ92FM1H473J	MYLAR 0.047UF J		
C208			CQ92FM1H184J	MYLAR 0.18UF J		
C209			CQ92FM1H333J	MYLAR 0.033UF J		
C210			CC45FSL1H101J	CERAMIC 100PF J		
C211			CQ92FM1H103J	MYLAR 0.010UF J		
C212			CC45FSL1H101J	CERAMIC 100PF J		
C213			CQ92FM1H473J	MYLAR 0.047UF J		
C214			CQ92FM1H124J	MYLAR 0.12UF J		
C215			CQ92FM1H273J	MYLAR 0.027UF J		
C217			CQ92FM1H103J	MYLAR 0.010UF J		
C218			CQ92FM1H473J	MYLAR 0.047UF J		
C219			CQ92FM1H124J	MYLAR 0.12UF J		
C220			CQ92FM1H393J	MYLAR 0.039UF J		
C221,222			CE04KW1H010M	ELECTRO 1.0UF 50WV		
C223,224			CE04KW1E100M	ELECTRO 10UF 25WV		
C225			CQ92FM1H473J	MYLAR 0.047UF J		
C226-229			CC45FSL1H221K	CERAMIC 220PF K		
C240			CC45FSL1H101J	CERAMIC 100PF J		
C241			CQ92FM1H103J	MYLAR 0.010UF J		
C401,402			CQ92FM1H104J	MYLAR 0.10UF J		

L : Scandinavia K : USA P : Canada R : Mexico
Y : PX(Far East, Hawaii) T : Europe E : Europe G : Germany
Y : AAFES(Europe) X : Australia M : Other Areas

Δ indicates safety critical components.

* New Parts
Parts without **Parts No.** are not supplied.
Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.
Teile ohne **Parts No.** werden nicht geliefert.

4

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
C403			CE04KW1A470M	ELECTRO 47UF 10WV		
C404			CK45FB1H102K	CERAMIC 1000PF K		
C405			CQ92FM1H104J	MYLAR 0.10UF J		
C406,407			CQ92FM1H473J	MYLAR 0.047UF J		
C408			CE04KW1A471M	ELECTRO 470UF 10WV		
C410,411			CQ92FM1H103J	MYLAR 0.010UF J		
C442			CE04KW1H4R7M	ELECTRO 4.7UF 50WV		
C443			CE04KW1A222M	ELECTRO 2200UF 10WV		
C601			CE04KW1E100M	ELECTRO 10UF 25WV		
C602			CC45FSL1H101J	CERAMIC 100PF J		
C603			CE04KW1E101M	ELECTRO 100UF 25WV		
C604,605			CC45FSL1H101J	CERAMIC 100PF J		
C606,607			CE04KW1J101M	ELECTRO 100UF 63WV		
C608,609			CC45FSL1H101J	CERAMIC 100PF J		
C610			CQ92FM1H473J	MYLAR 0.047UF J		
C611			CE04KW1H010M	ELECTRO 1.0UF 50WV		
C621			CE04KW1H010M	ELECTRO 1.0UF 50WV		
C631	3		CE04KW1A101M	ELECTRO 100UF 10WV		
C631	5		CE04KW1C221M	ELECTRO 220UF 16WV		
C651			CE04KW1H4R7M	ELECTRO 4.7UF 50WV		
C652			CE04KW1H2R2M	ELECTRO 2.2UF 50WV		
C655			CE04HW1A470M	NP-ELEC 47UF 10WV		
C656			CE04KW1C220M	ELECTRO 22UF 16WV		
C659			CE04KW1C220M	ELECTRO 22UF 16WV		
C660			CE04KW1H010M	ELECTRO 1.0UF 50WV		
C801-804			CQ92FM1H103J	MYLAR 0.010UF J		
C805,806		*	C90-5024-08	ELECTRO 10000UF 63WV		
C807,808			CK45FB1H103M	CERAMIC 0.010UF M		
C811,812			CE04KW1E222M	ELECTRO 2200UF 25WV		
C813			CE04KW1E101M	ELECTRO 100UF 25WV		
C851			CE04KW1H010M	ELECTRO 1.0UF 50WV		
C852			CK45FB1H102K	CERAMIC 1000PF K		
C853			CE04KW1C222M	ELECTRO 2200UF 16WV		
C871,872			CE04KW1E101M	ELECTRO 100UF 25WV		
C873,874			CC45FSL1H221K	CERAMIC 220PF K		
C875,876			CE04KW1E470M	ELECTRO 47UF 25WV		
C877,878			CE04KW1A470M	ELECTRO 47UF 10WV		
Δ C901			C91-1441-08	CERAMIC 4700PF 250WV		
Δ C902,903		*	C91-0211-08	FILM 4700PF 250WV		
JK101			E21-0279-08	SPEAKER TERMINAL		
JK102		*	E23-0224-08	RCA PIN JACK, LINE		
Δ F901	3		F05-1623-05	FUSE,1.6A/250V	ETGXCM	
Δ F901	3		F05-1623-05	FUSE,1.6A/250V	IY	
Δ F901	5		F06-2021-05	FUSE,2A/250V	ETGXMI	
Δ F901	3		F50-0072-05	FUSE,3.15A/125V	KP	
Δ F901	5		F50-0073-05	FUSE,4A/125V	KP	
Δ F902,903			F05-4016-05	FUSE,400MA/250V	XCMI	
Δ F902,903			F05-8013-05	FUSE,800MA/250V	ETGY	
Δ F902,903			F50-0062-05	FUSE,800MA/250V	KP	
Δ F904	3		F05-1623-05	FUSE,1.6A/250V	MIY	
Δ F904	5		F06-2021-05	FUSE,2A/250V	MI	
-		*	J13-0210-08	FUSE HOLDER		
X401		*	L78-0902-08	CRYSTAL		

L : Scandinavia K : USA P : Canada R : Mexico
Y : PX(Far East, Hawaii) T : Europe E : Europe G : Germany
Y : AAFES(Europe) X : Australia M : Other Areas

Δ indicates safety critical components.

103SW/SW-301/1050SW/SW-501
PARTS LIST

PARTS LIST

5

* New Parts
Parts without **Parts No.** are not supplied.
Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.
Teile ohne **Parts No.** werden nicht geliefert.

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
△ IC401			UPD75004CU-076	IC(4bit MICROPROCESSOR)		
△ IC402			LB1641	IC(MOTOR DRIVER)		
△ IC403			78L05A	IC(VOLTAGE REGULATOR/+5V)		
△ IC404			W02-3003-08	REMOTE PREAMP		
△ IC441			PST600C	IC(SYSTEM RESET)		
△ IC601			UPC1298V	IC(POWER AMP DRIVER)		
△ IC651			UPC1237HA	IC(POWER AMP)		
△ IC851			NJM2072D	IC		
△ Q251,252			2SC1815GR	TRANSISTOR		
△ Q253,254			2SA1015GR	TRANSISTOR		
△ Q401-403			2SC1815GR	TRANSISTOR		
△ Q405			2SC1815GR	TRANSISTOR		
△ Q441			2SC1815GR	TRANSISTOR		
△ Q601			2SC1846	TRANSISTOR		
△ Q602	5		2SC3281(R)	TRANSISTOR		
△ Q602	3	*	2SC5198	TRANSISTOR		
△ Q603	5		2SA1302(R)	TRANSISTOR		
△ Q603	3		2SA1941(R)	TRANSISTOR		
△ Q621			2SA1015GR	TRANSISTOR		
△ Q622			2SC2878A	TRANSISTOR		
△ Q631			2SC1815GR	TRANSISTOR		
△ Q651			2SC1815GR	TRANSISTOR		
△ Q652			2SA1015GR	TRANSISTOR		
△ Q851			2SC1815GR	TRANSISTOR		
△ Q871			2SB1274	TRANSISTOR		
△ Q872			2SD1913	TRANSISTOR		
△ ZD101,102			MTZJ30B	ZENER DIODE		
△ ZD401			MTZJ6.8B	ZENER DIODE		
△ ZD871,872			MTZJ16B	ZENER DIODE		
△ ZD873,874			MTZJ5.1B	ZENER DIODE		

L : Scandinavia
Y : PX(Far East, Hawaii)
Y : AAFES(Europe)
K : USA
T : Europe
X : Australia
P : Canada
E : Europe
M : Other Areas
R : Mexico
G : Germany

△ indicates safety critical components.

5

* New Parts
Parts without **Parts No.** are not supplied.
Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.
Teile ohne **Parts No.** werden nicht geliefert.

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
△ R103,104			RD14BB2H122J	RD 1.2K J 1/2W		
△ R425,426			RD14BB2E390J	RD 39 J 1/4W		
△ R603	3		RD14BB2C102J	RD 1.0K J 1/6W		
△ R603	5		RD14BB2C821J	RD 820 J 1/6W		
△ R606	5		RD14BB2C102J	RD 1.0K J 1/6W		
△ R607,608			RN14BK2E100J	RN 10 J 1/4W		
△ R609,610			RN14BK2E2R7J	RN 2.7 J 1/4W		
△ R611			R90-0826-05	MULTI-COMP 0.22X2 J 5W		
△ R612			RS14GB3A100J	FL-PROOF RS 10 J 1W		
△ R613	3		RD14BB2C184J	RD 180K J 1/6W	XCMI	
△ R613	5		RD14BB2C184J	RD 180K J 1/6W	XMI	
△ R613	3		RD14BB2C224J	RD 220K J 1/6W	KPETGY	
△ R613	5		RD14BB2C274J	RD 270K J 1/6W	KPETGY	
△ R614	5		RD14BB2C124J	RD 120K J 1/6W	KPETGY	
△ R614	3		RD14BB2C563J	RD 56K J 1/6W	XCMI	
△ R614	5		RD14BB2C753J	RD 75K J 1/6W	XMI	
△ R614	3		RD14BB2C823J	RD 82K J 1/6W	KPETGY	
△ R631	3		RD14BB2C153J	RD 15K J 1/6W	XCMI	
△ R631	5		RD14BB2C183J	RD 18K J 1/6W	XMI	
△ R631	3		RD14BB2C183J	RD 18K J 1/6W	KPETGY	
△ R631	5		RD14BB2C223J	RD 22K J 1/6W	KPETGY	
△ R663	5		RS14GB3A152J	FL-PROOF RS 1.5K J 1W	KPETGY	
△ R663	3		RS14GB3A561J	FL-PROOF RS 560 J 1W	XCMI	
△ R663	3		RS14GB3A821J	FL-PROOF RS 820 J 1W	KPETGY	
△ R801,802			RS14GB3A4R7J	FL-PROOF RS 4.7 J 1W	KPETGY	
△ R811			RN14BK2E151F	RN 150 F 1/4W		
△ R851	3		RS14GB3A181J	FL-PROOF RS 180 J 1W	XCMI	
△ R851	3		RS14GB3A221J	FL-PROOF RS 220 J 1W	KPETGY	
△ R871	3		RS14GB3A221J	FL-PROOF RS 220 J 1W	ETGY	
△ R871	3		RS14GB3A4R7J	FL-PROOF RS 4.7 J 1W	KPXCMI	
△ R872	3		RD14GB2H100J	FL-PROOF RD 10 J 1/2W	ETGY	
△ R872	3		RS14GB3A4R7J	FL-PROOF RS 4.7 J 1W	KPXCMI	
△ VR201		*	R31-0409-08	POTENTIOMETER CROSSOVER FREQ		
△ VR601		*	R31-0408-08	TRIMMING POT BIAS		
△ RY601			S51-2092-05	RELAY SPEAKER		
△ RY851			S51-2094-05	RELAY POWER		
△ SW201		*	S62-0207-08	SLIDE SWITCH SLOPE		
△ SW401		*	S70-0203-08	TACT SWITCH STANDBY		
△ SW901		*	S68-0202-08	POWER SWITCH		
△ SW902A		*	S31-2115-05	SLIDE SWITCH VOLTAGE	MICY	
△ D411,412			1SS133	DIODE		
△ D413			1SR139-100	DIODE		
△ D414-419			1SS133	DIODE		
△ D631			1SS133	DIODE		
△ D651-653			1SR139-100	DIODE		
△ D801	3	*	D3SBA20	DIODE		
△ D801	5		D5SBA20	DIODE		
△ D811-814			1SR139-100	DIODE		
△ D815			MTZJ5.1B	ZENER DIODE		
△ D851			1SR139-100	DIODE		
△ D852,853			1SS133	DIODE		
△ IC101			NJM4558L	IC(OP AMP X2)		
△ IC201-203			NJM4558L	IC(OP AMP X2)		
△ IC204			TC4066BP	IC(ANALOG/ DIGITAL SW)		

L : Scandinavia
Y : PX(Far East, Hawaii)
Y : AAFES(Europe)
K : USA
T : Europe
X : Australia
P : Canada
E : Europe
M : Other Areas
R : Mexico
G : Germany

△ indicates safety critical components.

KENWOOD CORPORATION

14-6,Dogenzaka 1-chome, Shibuya-ku, Tokyo, 150 Japan

KENWOOD SERVICE CORPORATION

P.O BOX 22745, 2201 East Dominguez St., Long Beach, CA 90801-5745, U.S.A.

Note:

Component and circuit are subject to modification to insure best operation under differing local conditions. This manual is based on Europe (E) standard, and provides information on regional circuit modification through use of alternate schematic diagrams, and information on regional component variations through use of parts list.