

WCR 100

WIRELESS REMOCON



사용설명서
User's guide
使用説明書



후방카메라.kr

www.abletech7.com

: 02-3400-0815

MODEL

TYPE



SPECIFICATION

Operating RF Frequency: 433MHz.
Coded System: 1527 Learning Code.
Working Voltage: Battery+12v/23A)
Working Current: <25mA
Transmitting Power: 10mW.
Wireless Operating Distance: 50m(Free Space).
Transmission Rate: 50 ~ 60KHz.
Frequency Deviation: +0.2MHz or -0.2MHz.
Size:38x58x12mm
About Working mode:
Momentary: Press the remote button,
the relay connects, release the remote button,
the relay disconnects.
Toggle: Press once the remote button,
the relay connects, press the remote button
twice, the relay disconnects.
Latching: Press the remote button A,
the relay connects, press the remote button B,
the relay disconnect

HOW TO USE

Avoid accidental personnel accidents or physical damage when operating at construction sites such as bus trucks, heavy equipment, or in tunnels. As an automatic voice guidance monitoring and alarm system to prevent. It is an automatic programming loudspeaker system that repeatedly induces various work safety such as voice and alarm sounds.

In addition, it is possible to prevent dangerous situations by calling with a remote control from a distance of 10 to 20 meters and broadcasting voice announcements.

HOW TO REGISTRATION



1. Open the cover of the remote control.
2. Open the cover of the alarm body.
3. Turn on the power switch of the main body and turn on the ID registration push button switch of the internal wireless receiver PCB for more than 2 seconds.
4. After confirming that the LED of the receiver PCB is blinking, turn on the transmission button of the remote control transmitter for more than 1 second.
5. The receiver LED turns off automatically and ID registration is completed.

Product Warranty

* We guarantee the product in accordance with consumer protection regulations

Product		Module	
Serial No.		Date.	
Name			
Add.			
Tel.			



Warranty period is within one year
from the date of purchase.

AS 문의 : 02-3400-0818

구입문의 : 02-3400-0815



서울시 송파구 문정동 법원로 11길 7
문정현대지식산업센터 6블록 C동 818호

FCC STATEMENT :

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

This device may not cause harmful interference, and

This device must accept any interference received, including interference that may cause undesired operation.

Warning: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

RF warning statement:

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.