



## MEAN WELL RSP-3000 Series Power Supply with Single Output Installation Guide

[Home](#) » [MEAN WELL](#) » MEAN WELL RSP-3000 Series Power Supply with Single Output Installation Guide 

### MEAN WELL RSP-3000 Series Power Supply with Single Output Installation Guide



## Contents

- [1 Dimension](#)
- [2 Features](#)
- [3 Applications](#)
- [4 GTIN CODE](#)
- [5 Description](#)
- [6 Model Encoding / Order Information](#)
- [7 SPECIFICATION](#)
- [8 Block Diagram](#)
- [9 Static Characteristics](#)
- [10 Derating Curve](#)
- [11 Efficiency vs Load \(48V Model\)](#)
- [12 Function Manual](#)
- [13 Mechanical Specification](#)
- [14 Mounting Instruction](#)
- [15 Installation Manual](#)
- [16 Documents / Resources](#)
  - [16.1 References](#)
- [17 Related Posts](#)

## Dimension

L	W	H
278	177.8	63.5(2U) mm
10.9	7	2.5(2U) Inch

## Features

- AC input 180~264VAC
- Built-in active PFC function
- High efficiency up to 91.5%
- Forced air cooling by built-in DC fan
- Output voltage programmable
- Active current sharing up to 9000W (2+1)
- Built-in remote ON-OFF control / remote sense /auxiliary power / power OK signal
- Protections: Short circuit / Overload / Over voltage / Over temperature
- Optional conformal coating
- 5years warranty

## Applications

- Factory control or automation apparatus
- Testand measurement instrument
- Laser related machine
- Burn-in facility
- Digital broadcasting

- RF application


## GTIN CODE

MW Search: <https://www.meanwell.com/service/GTIN.aspx>

## Description

RSP-3000 is a 3KW single output enclosed type AC/DC power supply. This series operates for 180~264VAC input voltage and offers the models with the DC output mostly demanded from the industry. Each model is cooled by the built-in fan with fan speed control, working for the temperature up to 70°C. Moreover, RSP-3000 provides vast design flexibility by equipping various built-in functions such as the output programming, active current sharing, remote ON-OFF control, auxiliary power, etc.

## Model Encoding / Order Information



## SPECIFICATION

MODEL		RSP-3000-12	RSP-3000-24	RSP-3000-48
OUTP UT	DC VOLTAGE	12V	24V	48V
	RATED CURRENT	200A	125A	62.5A
	CURRENT RANGE	0 ~ 200A	0 ~ 125A	0 ~ 62.5A
	RATED POWER	2400W	3000W	3000W
	RIPPLE & NOISE (max.) Note.2	150mVp-p	150mVp-p	200mVp-p
	VOLTAGE ADJ. RANGE	10.8 ~ 13.2V	22 ~ 28V	43 ~ 56V
	VOLTAGE TOLERANCE Note.3	±1.0%	±1.0%	±1.0%
	LINE REGULATION	±0.5%	±0.5%	±0.5%
	LOAD REGULATION	±0.5%	±0.5%	±0.5%


	SETUP, RISE TIME	1000ms, 80ms at full load		
	HOLD UP TIME (Typ.)	10ms at full load		
INPUT	VOLTAGE RANGE	180 ~ 264VAC    254 ~ 370VDC		
	FREQUENCY RANGE	47 ~ 63Hz		
	POWER FACTOR (Typ.)	0.95/230VAC at full load		
	EFFICIENCY (Typ.)	87.5%	90%	91.5%
	AC CURRENT (Typ.)	20A/180VAC    16A/230VAC		
	INRUSH CURRENT (Typ.)	60A/230VAC		
	LEAKAGE CURRENT	<2.0mA / 240VAC		
PROTECTION	OVERLOAD	100 ~ 112% rated output power		
		User adjustable continuous constant current limiting or constant current limiting with delay shutdown after 5 seconds, re-power on to recover		
	OVER VOLTAGE	13.8 ~ 16.8V	28.8 ~ 33.6V	57.6 ~ 67.2V
		Protection type : Shut down o/p voltage, re-power on to recover		
	OVER TEMPERATURE	Shut down o/p voltage, recovers automatically after temperature goes down		
FUNCTION	OUTPUT VOLTAGE PROGRAMMABLE(PV)	2.4 ~ 13.2V	4.8 ~ 28V	9.6 ~ 56V
		Please refer to the Function Manual.		
	CURRENT SHARING	Up to 9000W or (2+1) units. Please refer to the Function Manual.		
	AUXILIARY POWER(AUX)	12V@0.1A(Only for Remote ON/OFF control)		
	REMOTE ON-OFF CONTROL	Please refer to the Function Manual		
	REMOTE SENSE	Compensate voltage drop on the load wiring up to 0.25V. Please refer to the Function Manual.		
	ALARM SIGNAL OUTPUT	Power OK signal. Please refer to the Function Manual		
ENVIRONMENT	WORKING TEMP.	-20 ~ +70°C (Refer to "Derating Curve")		
	WORKING HUMIDITY	20 ~ 90% RH non-condensing		

RON MENT	STORAGE TEMP. , HUMIDITY	-40 ~ +85°C, 10 ~ 95% RH non-condensing		
	TEMP. COEFFICI ENT	±0.05%/°C (0 ~ 50°C)		
	VIBRATION	10 ~ 500Hz, 2G 10min./1cycle, 60min. each along X, Y, Z axes		
SAFE TY & EMC( Note 4)	SAFETY STAND ARDS	UL62368-1, CSA C22.2 No. 62368-1, TUV BS EN/EN62368-1, BSMI CNS14336-1, AS/NZS62368.1, IS13252(Part1)/IEC60950-1,EAC TP TC 004 approved		
	WITHSTAND VO LTAGE	I/P-O/P:3KVAC I/P-FG:2KVAC O/P-FG:0.5KVAC		
	ISOLATION RESI STANCE	I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C/ 70% RH		
	EMC EMISSION	Parameter	Standard	Test Level / Note
		Conducted	BS EN/EN55032 (CISPR 32)	Class B
		Radiated	BS EN/EN55032 (CISPR 32)	Class A
		Harmonic Current	BS EN/EN61000-3-2	—
		Voltage Flicker	BS EN/EN61000-3-3	—
	EMC IMMUNITY	BS EN/EN55035, BS EN/EN61000-6-2, BSMI CNS13438		
		Parameter	Standard	Test Level / Note
		ESD	BS EN/EN61000-4-2	Level 3, 8KV air ; Level 2, 4KV contact
		Radiated	BS EN/EN61000-4-3	Level 3
		EFT / Burst	BS EN/EN61000-4-4	Level 3
		Surge	BS EN/EN61000-4-5	Level 3, 2KV/Line-Earth ; Level 2, 1KV/Line-Line
		Conducted	BS EN/EN61000-4-6	Level 3
		Magnetic Field	BS EN/EN61000-4-8	Level 4
		Voltage Dips and Interrup tions	BS EN/EN61000-4-11	>95% dip 0.5 periods, 30 % dip 25 periods,>95% in interruptions 250 periods
OTHE RS	MTBF	677.3K hrs min. Telcordia SR-332 (Bell core) ; 75.2K hrs min. MIL-HDBK-217F ( 25°C)		
	DIMENSION	278*177.8*63.5mm (L*W*H)		
	PACKING	4Kg; 4pcs/16Kg/2.04CUFT		


## NOTE

1. All parameters NOT specially mentioned are measured at 230VAC input, rated load and 25°C of ambient temperature.
2. Ripple & noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 47uf parallel capacitor.
3. **Tolerance** : includes set up tolerance, line regulation and load regulation.
4. The power supply is considered a component which will be installed into a final equipment. All the EMC tests are been executed by mounting the unit on a 720mm\*360mm metal plate with 1mm of thickness. The final equipment must be re-confirmed that it still meets EMC directives. For guidance on how to perform these EMC tests, please refer to "EMI testing of component power supplies." (as available on [https://www.meanwell.com/Upload/PDF/EMI\\_statement\\_en.pdf](https://www.meanwell.com/Upload/PDF/EMI_statement_en.pdf))
5. The ambient temperature derating of 3.5°C/1000m with finless models and of 5°C/1000m with fan models for operating altitude higher than 2000m(6500ft).
  - Product Liability Disclaimer: For detailed information, please refer to <https://www.meanwell.com/serviceDisclaimer.aspx>

## Block Diagram




## Static Characteristics




INPUT	MODEL	12V	24V	48V
180~264VAC		2400W200A	3000W125A	3000W62.5A

## Derating Curve



## Efficiency vs Load (48V Model)




The curve above is measured at 230VAC.

## Function Manual

### 1. Remote Sense

- The Remote Sense compensates voltage drop on the load wiring up to 0.25V.




- Caution:** The power supply, by factory default(also the assumption for other sections), is shipped with, S & -V on CN2, as well as +S & +V, shorted by connector. When activating the Remote Sense, the +S signal


should be connected to the positive terminal of the load whereas -S sign alto the negative terminal of the load.

## 2. Output Voltage Programming (or, PV / remote voltage programming / remote adjust/ margin programming/ dynamic voltage trim)

- In addition to the adjust mention the built-in potentiometer, the output voltage can be trimmed to 20~110%(Typ.) of the nominal voltage by applying EXTERNAL VOLTAGE.




- Connecting an external DC source between on CN2, and . PV & -S +S & +V, -S & -V also need to be connected
- Please do not adopt PWM signal as the EXTERNAL VOLTAGE



MODEL	12V	24V	48V
PV Range	2.4 ~ 13.2V	4.8 ~ 28V	9.6 ~ 56V

- The rated current should change with the Output Voltage Programming accordingly






- **Caution:**

1. By factory default, the Output Voltage Programming is not activated, and are shorted by connector. Whenever PV(PIN3) PS(PIN4) and of CN2 this function is not needed to activate, as assumed in other sections' diagrams, please keep shorted ; otherwise, PV(PIN3) PS(PIN4) and of CN2 the power supply will have no output.
2. and of CN1 or CN2 must be disconnected if "Output Voltage Programming" function is used; otherwise, the internal PV(PIN3) PS(PIN4) electrical components may be damaged, and the power supply unit may thus be out of order.


### 3. Remote ON-OFF

- Remote ON-OFF is activated by the configuration with respect to CN1,CN2 and CN3 as shown in the following diagram.




- By factory default, and ) on CN2 are PV(PIN3) PS(PIN4) shorted by connector; likewise, and OLP(PIN9) OL-SD(PIN10) on CN3 are shorted when shipped.


#### **Example 3.2(A): Using external voltage source**



**Example 3.2(B): Using internal 12V auxiliary output**



**Example 3.2(C): Using internal 12V auxiliary output**




- **Connection Method**

		Example 3.2(A)	Example 3.2(B)	Example 3.2(C)
SW Logic	Power supply output ON	SW Open	SW Open	SW Close
	Power supply output OFF	SW Close	SW Close	SW Open

#### 4. Alarm Signal Output

- Alarm signal is sent out through " P OK " & " P OK GND2 " and pins on CN3. Please acknowledge an external voltage source is required for this P OK P OK GND P OK2 & P OK GND2 action.




- By factory default, and OLP(PIN9) OL-SD(PIN10) on CN3 are shorted by connector when shipped.

Function	Description	Output of alarm(P OK, Relay Contact)	Output of alarm(P OK2, TTL Signal)
P OK	The signal is "Low" when the power supply is above 80% of the rated output voltage, or, say, Power OK	Low(0.5V max at 500mA)	Low(0.5V max at 10mA)
	The signal turns to be "High" when the power supply is under 80% of the rated output voltage, or, say, Power Fail	High or open(External applied voltage, 500mA max.)	High or open(External applied voltage, 10mA max.)

**Table 3.1 Explanation of alarm**

**Fig. 4.2 Internal circuit of P OK (Relay, total is 10W)**




**Fig. 4.3 Internal circuit of P OK2 (Open collector method)**



## 6. Current Sharing with Remote Sense

**RSP-3000 has the built-in active current sharing function and can be connected in parallel, up to 3 units, to provide higher output power as exhibited below:**

- The power supplies should be paralleled using short and large diameter wiring and then connected to the load.
- Difference of output voltages among parallel units should be less than 0.2V.
- The total output current must not exceed the value determined by the following equation:
- Maximum output current at parallel operation (Rated current per unit) X (Number of unit) x0.9
- When the total output current is less than 3% of the total rated current, or say (3% of Rated current per unit) (Number of unit) the current shared among units may not be fully balanced.




- When remote sensing is used in parallel operation, the sensing wire must be connected only to the master unit
- Sense lines should be twisted in pairs to minimize noise pick-up.
- +S,-S CS and on CN1 or CN2 are connected mutually in parallel.
- Under parallel operation, the “output voltage programming” function is not available


## 7. Three Phase Connect

Users can exploit three units of RSP-3000(unit 1 ,unit 2,unit 3) to work with 3 power system. Please refer to following diagrams for configuration.


- **FIG. A: 3 3W 220VAC SYSTEM**



• FIG. B: 3 4W 220/380VAC SYSTEM  $\psi$




• FIG. C: 3 W 190/110VAC SYSTEM  $\psi_4$




## Mechanical Specification

(Unit: mm , tolerance 0.5mm)

Case No.982B




## Mounting Instruction



Hole No.	Recommended Screw Size	MAX. Penetration Depth L	Recommended mounting torque
1	M4	5mm	7~10Kgf-cm

- Control Pin No. Assignment : HRS DF11-8DP-2DS or equivalent (CN1,CN2)




Mating Housing	HRS DF11-8DS or equivalent
Terminal	HRS DF11-**SC or equivalent

- CN1 and CN2 are connected internally.

Pin No.	Function	Description
1	RCG	Remote ON-OFF Ground
2	RC	Remote ON-OFF
3	PV	Connection for output voltage programming
4	PS	Reference Voltage Terminal
5,7	-S	Negative sensing for remote sense
6	CS(Current Share)	Current Share
8	+S	Positive sensing for remote sense

- **Control Pin No. Assignment** : HRS DF11-10DP-2DS or equivalent (CN3)




Mating Housing	HRS DF11-10DS or equivalent
Terminal	HRS DF11-10SC or equivalent

Pin No.	Function	Description
1	P OK GND	Power OK Ground
2	P OK	Power OK Signal (Relay Contact)
3	P OK GND2	Power OK Ground
4	P OK2	Power OK Signal (TTL Signal)
5	RCG	Remote ON-OFF Ground
6	RC	Remote ON-OFF
7	AUXG	Auxiliary Ground
8	AUX	Auxiliary Output
9	OLP	Overload(OLP) type select
10	OL-SD	



- AC Input Terminal Pin No. Assignment

Pin No.	Assignment	Diagram	Maximum mounting torque
1	AC/L		18Kgf-cm
2	AC/N		
3	FG		


## Installation Manual

Please refer to : <http://www.meanwell.com/manual.html>

## User's Manual



## Symbols



- Industrial




- Automate



- Telecom



- Network



- EV



Downloaded from [Arrow.com](https://www.arrow.com).



## Documents / Resources

	<p><a href="#">MEAN WELL RSP-3000 Series Power Supply with Single Output</a> [pdf] Installation Guide RSP-3000-12, RSP-3000-24, RSP-3000-48, RSP-3000 Series Power Supply with Single Output, RSP-3000 Series, Power Supply with Single Output, Supply with Single Output, Single Output, Output</p>
--	--

## References

- [User Manual](#)

### [Manuals+](#), [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.