



# Milesight WS202 PIR &Light Sensor User Guide

[Home](#) » [Milesight](#) » Milesight WS202 PIR &Light Sensor User Guide 



## Contents

- [1 Milesight WS202 PIR &Light Sensor](#)
- [2 Safety Precautions](#)
- [3 Declaration of Conformity](#)
- [4 Product Introduction](#)
- [5 Features](#)
- [6 Hardware Introduction](#)
- [7 Hardware Overview](#)
- [8 Operation Guide](#)
- [9 General Settings](#)
- [10 Maintenance](#)
- [11 Installation](#)
- [12 Device Payload](#)
- [13 Documents / Resources](#)
  - [13.1 References](#)
- [14 Related Posts](#)

**Milesight WS202 PIR &Light Sensor**



## Safety Precautions

Milesight will not shoulder responsibility for any losses or damages resulting from not following the instructions of this operating guide.

- The device must not be modified in any way.
- Do not expose the PIR lens to direct sunlight.
- Do not paint or clean the PIR lens, or it will affect the detection of the device.
- Do not place the device where the temperature is below/above the operating range.
- Do not place the device close to objects with naked flames, , heat source (oven or sunlight), cold source, liquid and extreme temperature changes.
- The device is not intended to be used as a reference sensor, and Milesight will not take responsibility for any damages which may result from inaccurate readings.
- When installing the battery, please install it accurately, and do not install the reverse or wrong model.
- Remove the battery if the device will not be used for a long period of time. Otherwise, the battery will leak and damage the device.
- The device must never be subjected to shocks or impacts.

## Declaration of Conformity

WS202 is in conformity with the essential requirements and other relevant provisions of the CE, FCC, and RoHS.



**Copyright © 2011-2021 Milesight. All rights reserved.**

All information in this guide is protected by copyright law. Whereby, no organization or individual shall copy or reproduce the whole or part of this user guide by any means without written authorization from Xiamen Milesight IoT Co., Ltd.

For assistance, please contact Milesight technical support:

- **Email:** [iot.support@milesight.com](mailto:iot.support@milesight.com)
- **Tel:** 86-592-5085280
- **Fax:** 86-592-5023065
- **Address:** 4/F, No.63-2 Wanghai Road,

## Product Introduction

### Overview

WS202 is a PIR sensor based on passive infrared technology to detect a motion or occupancy. WS202 can detect whether there is a movement within the range of 6-8 m. Besides, WS202 equips with light sensor which can link PIR detection results to trigger scenes. WS202 can be widely used in smart homes, smart offices, schools, warehouses, etc. Sensor data are transmitted in real-time using the standard LoRaWAN® protocol. LoRaWAN® enables encrypted radio transmissions over long distances while consuming very little power. The user can get alarm through Milesight IoT Cloud or through the user's own Application Server.

### Features

- Built-in light sensor, combine PIR sensor to achieve triggers
- Up to 15 km communication range
- Easy configuration via NFC
- Standard LoRaWAN® support
- Compatible with Milesight IoT Cloud


## Hardware Introduction

### Packing List




1 x

WS202 Sensor



2 x

Wall Mounting Kits



1 x

3M Tape




1 x


Quick Guide

If any of the above items is missing or damaged, please contact your sales representative.

Hardware Overview



Dimensions (mm)



LED Patterns


Function	Action	LED Indicator
PIR Detection	PIR is triggered (network unregistered)	Red, blink once
	PIR is triggered (network registered)	Green, blink once
Network Status	Send join network requests	Red, blinks once
	Joined the network successfully	Green, blinks twice
Reboot	Press and hold the reset button for more than 3s	Slowly blinks
Reset to Factory Default	Press and hold the reset button for more than 10s	Quickly blinks

Operation Guide

## NFC Configuration

WS202 can be configured via an NFC-enabled smartphone.

1. Pull out the battery insulating sheet to power on the device. The indicator will light up in green for 3 seconds when device turns on.



2. Download and install the “Milesight ToolBox” App from Google Play or App Store.
3. Enable NFC on the smartphone and open Milesight ToolBox.
4. Attach the smartphone with NFC area to the device to read device information.



5. Basic information and settings of the device will be shown on ToolBox if it's recognized successfully. You can read and configure the device by tapping the Read/Write device on the App. In order to protect the security of the device, password validation is required when configuring via a new smartphone. The default password is 123456.

### Note:

1. Check the location of the smartphone NFC area and it's recommended to take off phone case.
2. If the smartphone fails to read/write configurations via NFC, move the phone away and back to try again.
3. WS202 can also be configured by ToolBox software via a dedicated NFC reader provided by Milesight IoT, you can also configure it via TTL interface inside the device.

## LoRaWAN Settings

LoRaWAN settings are used for configuring the transmission parameters in the LoRaWAN® network.

### Basic LoRaWAN Settings:

Go to Device -> Setting -> LoRaWAN Settings of ToolBox App to configure join type, App EUI, App Key and other information. You can also keep all settings by default.

Device EUI	<input type="text" value="24E124127A270222"/>
App EUI	<input type="text" value="24E124C0002A0001"/>
Application Port	<input type="text" value="85"/>
Join Type	<input type="text" value="OTAA"/>
Application Key	<input type="text" value="*****"/>
Spread Factor	<input type="text" value="SF10-DR2"/>
Confirmed Mode	<input type="checkbox"/>
Rejoin Mode	<input checked="" type="checkbox"/>
Set the number of packets sent	<input type="text" value="32"/> packets
ADR Mode	<input checked="" type="checkbox"/>

Parameters	Description
Device EUI	Unique ID of the device which can also be found on the label.
App EUI	Default App EUI is 24E124C0002A0001.
Application Port	The port used for sending and receiving data, default port is 85.
Join Type	OTAA and ABP modes are available.
Application Key	Appkey for OTAA mode, default is 5572404C696E6B4C6F52613230313823.
Device Address	DevAddr for ABP mode, default is the 5th to 12th digits of SN.
Network Session Key	Nwkskey for ABP mode, default is 5572404C696E6B4C6F52613230313823.
Application Session Key	Appskey for ABP mode, default is 5572404C696E6B4C6F52613230313823.
Spread Factor	If ADR is disabled, the device will send data via this spread factor.
Confirmed Mode	If the device does not receive ACK packet from a network server, it will resend data 3 times at most.
Rejoin Mode	Reporting interval $\leq 30$ mins: the device will send specific mounts of LoRaMAC packets to check connection status every 30 mins; If no reply after specific packets are being sent, the device will re-join.  Reporting interval $> 30$ mins: the device will send specific mounts of LoRaMAC packets to check connection status at every reporting interval; If no reply after

	specific packets are being sent, the device will re-join.
ADR Mode	Allow the network server to adjust data rate of the device.
Tx Power	Transmit power of the device.

**Note:**

1. Please contact sales representative for the device EUI list if there are many units.
2. Please contact sales representative if you need random App keys before purchase.
3. Select OTAA mode if you use Milesight IoT Cloud to manage devices.
4. Only OTAA mode supports rejoin mode.

**LoRaWAN Frequency Settings:**

Go to Setting->LoRaWAN Settings of ToolBox App to select the supported frequency and select channels to send uplinks. Make sure the channels match the LoRaWAN® gateway.

\* Support Frequency

AS923

<input checked="" type="checkbox"/>	-	923.2	+
<input checked="" type="checkbox"/>	-	923.4	+
<input type="checkbox"/>	-	922.2	+
<input type="checkbox"/>	-	922.4	+
<input type="checkbox"/>	-	922.6	+

If device frequency is one of CN470/AU915/US915, you can enter the index of the channel that you want to enable in the input box, making them separated by commas.

**Examples:**

- 1, 40: Enabling Channel 1 and Channel 40
- 1-40: Enabling Channel 1 to Channel 40
- 1-40, 60: Enabling Channel 1 to Channel 40 and Channel 60
- All: Enabling all channels
- Null: Indicates that all channels are disabled

• Support Frequency

AU915

Enable Channel Index ⓘ

0-71

Index	Frequency/MHz ⓘ
0 - 15	915.2 - 918.2
16 - 31	918.4 - 921.4
32 - 47	921.6 - 924.6
48 - 63	924.8 - 927.8

**Note:**

For the -868M model, the default frequency is EU868;  
For the -915M model, the default frequency is AU915.

## General Settings

Go to Device->Setting->General Settings of ToolBox App to change the reporting interval, etc.

Reporting Interval - 30 + min

Idle Time Reporting / s ⓘ

120

LED Indicator ⓘ ☒

Low Power Alarm Interval ⓘ - 360 + min

Change Password ☐

Parameters	Description
Reporting Interval	<p>The interval of reporting PIR, light status and battery level to the network server. Default : 30 mins</p> <p><b>Note:</b> WS202 will also report the “triggered” status of PIR sensor immediately when it detects motions.</p>



Idle Time Reporting/s	When the PIR sensor does not detect motion for a period of Idle Time , the device will report a “not triggered” status. Default: 120 s
LED Indicator	Enable or disable the light indicated in chapter <a href="#">2.4</a> . Note: The indicator of the reset button is not allowed to be disabled.
Low Battery Alarm Interval	The device will report low battery alarms according to this interval when the battery remaining capacity is lower than 10%.
Change Password	Change the password for ToolBox App to write this device.

### Threshold Settings

Users can define the Bright or Dark state via detection data of light sensor in threshold settings. Besides, when the PIR sensor is triggered and light status meets the threshold, WS202 will send alarms immediately. Otherwise, it will not send data right away.

Light State, Over/lux

Dark State, Below/lux

## Maintenance

### Upgrade

1. Download firmware from the Milesight website to your smartphone.
2. Open ToolBox App and click “Browse” to import firmware and upgrade the device.

Note:


1. Operation on ToolBox is not supported during the upgrade.
2. Only the Android version ToolBox supports the upgrade feature.

Status	Setting	Maintenance
SN	6538B2232131	
Model	WS202-470M	
Firmware Version	V1.1-a0	
Hardware Version	V1.0	
Manual Upgrade		
<div>Browse</div>		


### Backup

WS202 supports configuration backup for easy and quick device configuration in bulk. Backup is allowed only for devices with the same model and LoRa frequency band.

1. Go to the “Template” page on the App and save current settings as a template. You can also edit the template file.
2. Select one template file that saved in the smartphone and click “Write”, then attach it to another device to write the configuration.



**Note:** Slide the template item to the left to edit or delete the template. Click the template to edit the configurations.



### Reset to Factory Default

Please select one of the following methods to reset the device:


Via Hardware: Hold on the reset button for more than 10s. After the reset is complete, the indicator will blink in green twice, then the device will reboot.

Via Toolbox App: Go to Device -> Maintenance to tap "Reset", then attach a smartphone with NFC area to the device to complete the reset.

### Installation


#### 3M Tapes Fix:

Paste 3M tape to the back of the device, then tear the other side and place it on a flat surface.



#### Screw Fix:

Remove the back cover of the device, screw the wall plugs into the wall and fix the cover with screws on it, then install back the device.



#### Note:

1. Adjust the installation direction according to detection area requirements.
2. WS202 can be mounted on wall or ceiling. It's recommended to install at 1.5~2.5m from the floor.

3. Ensure the detection area not have moving objects like waving trees and fans.
4. Ensure the detection area is not blocked by curtains or barriers.

## Device Payload

All data are based on the following format (HEX):

Channel1	Type1	Data1	Channel2	Type2	Data2	Channel 3	...
1 Byte	1 Byte	N Bytes	1 Byte	1 Byte	M Bytes	1 Byte	...

For decoder examples, you can find at <https://github.com/Milesight-IoT/SensorDecoders>.

## Basic Information

WS202 reports basic information of device every time when it joins the network.

Channel	Type	Data Example	Description
ff	01(Protocol Version)	01	V1
	08 (Device SN)	61 27 a2 17 41 32	Device SN is 6127a2174132
	09 (Hardware Version)	01 40	V1.4
	0a (Software Version)	01 14	V1.14
	0f (Device Type)	00	Class A

## Example:

ff 09 01 00 ff 0a 01 02 ff 0f 00					
Channel	Type	Value	Channel	Type	Value
ff	09 (Hardware	0100 (V1.0)	ff	0a (Software Version)	0102 (V1.2)

	Version)				
Channel	Type	Value			
ff	0f (Device Type)	00 (Class A)			

## Sensor Data

WS202 reports sensor data and battery level according to reporting interval (30 mins by default) or when PIR or light status changes.

Channel	Type	Description
01	75 (Battery Level)	UINT8, Unit: %
03	00 (PIR Status)	01: PIR is triggered 00: PIR is not triggered
04	00 (Light Status)	01: Bright 00: Dark

#### Example:


01 75 64 03 00 01 04 00 01					
Channel	Type	Value	Channel	Type	Value
01	75 (Battery)	64 => 100%	03	00 (PIR Status)	01=> PIR is triggered
Channel	Type	Value			
04	00 (Light Status)	01=> Bright			

#### Downlink Commands

WS202 supports downlink commands to configure the device. The application port is 85 by default.

Channel	Type	Data Example	Description
ff	03 (Set Reporting Interval)	b0 04	b0 04 => 04 b0 = 1200s

#### Documents / Resources

	<a href="#">Milesight WS202 PIR &amp;Light Sensor</a> [pdf] User Guide WS202 PIR Light Sensor
---	--

#### References

- [GitHub - Milesight-IoT/SensorDecoders](#)

