



ONYX-MD116E 11.6 Inch LCD with LED Backlight User Manual

[Home](#) » [ONYX](#) » ONYX-MD116E 11.6 Inch LCD with LED Backlight User Manual 

ONYX-MD116E 11.6 Inch LCD with LED Backlight



ONYX-MD116E

11.6" LCD with LED Backlight
Intel® Elkhart Lake processor
Dual smart card readers for multiple-care workflow

Contents

- 1 Copyright Notice
- 2 Acknowledgments
- 3 Packing List
- 4 Safety & Warranty
- 5 Classification
- 6 Intended Use
- 7 FCC
- 8 UL Module Description
- 9 Safety Symbol Description
- 10 General Information
 - 10.1 Introduction
 - 10.2 Feature
 - 10.3 Specification
 - 10.4 Dimension
- 11 Hardware Installation
 - 11.1 Safety Precautions
 - 11.2 Quick Tour of ONYX-MD116/MD116I
- 12 Driver Installation
- 13 Miscellanea
 - 13.1 General Cleaning Tips
 - 13.2 Cleaning tools
 - 13.3 Scrap Computer Recycling
 - 13.4 MD116E Battery LED identification
 - 13.5 FCC Statement
- 14 Documents / Resources
 - 14.1 References
- 15 Related Posts

Copyright Notice

This document is copyrighted, 2023. All rights are reserved. The original manufacturer reserves the right to make improvements to the products described in this manual at any time without notice.

No part of this manual may be reproduced, copied, translated, or transmitted in any form or by any means without the prior written permission of the original manufacturer. Information provided in this manual is intended to be accurate and reliable. However, the original manufacturer assumes no responsibility for its use, nor for any infringements upon the rights of third parties, which may result from its use.

The material in this document is for product information only and is subject to change without notice. While reasonable efforts have been made in the preparation of this document to assure its accuracy, ONYX Healthcare Inc., assumes no liabilities resulting from errors or omissions in this document, or from the use of the information contained herein ONYX Healthcare Inc. reserves the right to make changes in the product design without notice to its users

Acknowledgments

- Intel® Pentium is registered trademarks of Intel® Corporation.
- Microsoft® Windows is a registered trademark of Microsoft® Corporation.

All other product names or trademarks are properties of their respective owners

Packing List

Before you begin installing your Mobile Medical Assistant, please make sure that the following items have been shipped:

- MD116E Mobile Medical Assistant

If any of these items are missing or damaged, you should contact your distributor or sales representative immediately.

Headquarters

Onyx Healthcare Inc.
4F, No.135, Lane 235, Pao-Chiao Rd.,
Hsin-Tien City, Taipei 231, Taiwan, R.O.C.
TEL: +886-2-8919-2188
FAX: +886-2-8919-1699
E-mail: sales@onyx-healthcare.com
<http://www.onyx-healthcare.com>

Worldwide Offices:

Onyx Healthcare Inc.
2F., No.135, Ln. 235, Baoqiao Rd., Xindian Dist.,
New Taipei City 231, Taiwan (R.O.C.)
TEL: +886-2-8919-2188
FAX: +886-2-8919-1699
E-mail: sales@onyx-healthcare.com
<http://www.onyx-healthcare.com>

Worldwide Offices:

Onyx Healthcare, USA Inc.
324W. Blueridge Ave., Orange,, CA 92865, USA
Tel : +1-714-792-0774
Fax: +1-714-792-0481
Email: usasales@onyx-healthcare.com
Onyx Healthcare EUROPE B.V.
Primulalaan 42, 5582 GL Waalre, Netherlands
Tel : +31-(0)499-745600
Email: eusales@onyx-healthcare.com

Onyx Healthcare (Shanghai) INC.
20F, unit D, GEM Building, No. 487 Tianlin Road, Shanghai, China
Tel: +86-021-64956588
Fax: +86-021-64956889
Email: cnsales@onyx-healthcare.com

Safety & Warranty

1. Read these safety instructions carefully.

2. Keep this user's manual for later reference.
3. Disconnect this equipment from any AC outlet before cleaning. Do not use liquid or spray detergents for cleaning. Use a damp cloth.
4. For pluggable equipment, the power outlet must be installed near the equipment and must be easily accessible.
5. Keep this equipment away from humidity.
6. Put this equipment on a reliable surface during installation. Dropping it or letting it fall could cause damage.
7. The openings on the enclosure are for air convection. Protect the equipment from overheating. **DO NOT COVER THE OPENINGS.**
8. Make sure the voltage of the power source is correct before connecting the equipment to the power outlet.
9. **Warning:** To avoid risk of electric shock, this equipment must only be connected to a supply mains with protective earth.
10. Position the power cord so that people cannot step on it. Do not place anything over the power cord.
11. All cautions and warnings on the equipment should be noted.
12. If the equipment is not used for a long time, disconnect it from the power source to avoid damage by transient over-voltage.
13. Never pour any liquid into an opening. This could cause fire or electrical shock.
14. Never open the equipment. For safety reasons, only qualified service personnel should open the equipment.
15. **Warning:** Do not modify this equipment without authorization of the manufacturer.
16. **Warning :** It is necessary for checking or replacing the battery pack every year.
17. When the tablet is under heavy loading, the battery may stop charging due to overheating. When this behavior happens, turn off the tablet before charging.
18. If any of the following situations arises, get the equipment **checked by service personnel:**
 - **a.** The power cord or plug is damaged.
 - **b.** Liquid has penetrated into the equipment.
 - **c.** The equipment has been exposed to moisture.
 - **d.** The equipment does not work well, or you cannot get it to work according to the users manual.
 - **e.** The equipment has been dropped and damaged.
 - **f.** The equipment has obvious signs of breakage.
19. **DO NOT LEAVE THIS EQUIPMENT IN AN UNCONTROLLED ENVIRONMENT WHERE THE STORAGE TEMPERATURE IS BELOW -20° C (-4°F) OR ABOVE 60° C (140° F). IT MAY DAMAGE THE EQUIPMENT.**
20. External equipment intended for connection to signal input/output or other connectors, shall comply with relevant UL / IEC standard (e.g. UL 1950 for IT equipment and ANSI/AAMI ES 60601-1: 2005 AND CAN/CSA-C22.2 No. 60601-1:08 / IEC 60601 series for systems – shall comply with the standard IEC 60601-1-1, Safety requirements for medical electrical systems. Equipment not complying with UL 60601-1 shall be kept outside the patient environment, as defined in the standard.

Caution:

It may cause the danger of explosion if battery is incorrectly replaced. Replace only with same or equivalent type recommended by the manufacturer.

Classification

1. Degree of protection against electric shock: not classified
2. Degree of protection against the ingress of water: IPX0
3. Mode of operation: Continuous
4. Type of protection against electric shock: Class I equipment
5. No Applied Part, No AP/APG

Intended Use

The MD116/MD116I is intended to serve as a computer for integration with hospital systems. MD116/MD116I is designed for general purpose medical computing with built-in CPU, memory, storage, thermal solution, enclosure in the hospital environment, for data collection and for displaying information.

The machine and power supply must not be used outdoors or in areas where an explosion hazard may occur. The user has to make sure the requirements from IEC 60601-1 are fulfilled, especially in combination from this machine with other electrical equipment. And it shall not be used for life supporting system. The latest version of this user manual is available for download from https://www.onyx-healthcare.com/service_en_3.php

FCC



UL Module Description



Tablet PC, ONYX-MD116 module is developed to suitable for the Classification Mark requirement

Safety Symbol Description

The following safety symbols are the further explanations for your reference.



MEDICAL – GENERAL MEDICAL EQUIPMENT AS TO ELECTRICAL SHOCK, FIRE AND MECHANICAL HAZARDS ONLY IN ACCORDANCE WITH ANSI/AAMI ES 60601-1 (2005) + AMD (2012) and CAN/CSA-C22.2 No. 6060-1 (2014).



Attention, consult ACCOMPANYING DOCUMENTS.



Stand-by



Ground wire Protective Ground wire.

General Information

Introduction

MD116E Mobile Medical Assistant is based on Intel® processor, which delivers a performance improvement of more than 100 percent compared to systems running traditional single-core processors. With four cores computing engines, MD116E can simultaneously execute four computing tasks. It accommodates one M.2 2280 Interface SATA /NVME SSD and one DDR4 SODIMM up to 32GB. The high brightness LCD, zero noise solution, integrated multimedia functions make them the perfect platform upon which to build comprehensive lifestyle computing applications. ONYX-MD116E includes all the features of a powerful computer into a slim and attractive chassis. It has a 11.6" 600 nits TFT display with 1920 x 1080 resolution. ONYX-MD116E owns Dual smart card

reader to support ID check. Combining ONYX-MD116E into your system can achieve both cost-saving and efficient improvements in common medical applications. ONYX-MD116E is your perfect choice.

ONYX-MD116E was regarded as Medical Device Data Systems (MDDS). It is a hardware product that transfer, store, convert formats, and display medical device data. MDDS are not intended to be used for active patient monitoring.

Feature

- Intel® Elkhart Lake N6415 Quad Core Processor
- Supports One DDR4L SODIMM up to 32GB
- Dual hot-swappable batteries for 24/7 operation
- ORION client compatible

Specification

Hardware Specifications

Processor	Intel® Pentium® Elkhart LakeN6415(6.5W) 1.20 GHz
System Memory	DDR4L SO-DIMM x1, Default 4 GB (Up to 32 GB)
OS Support	Microsoft® Windows 10/ Microsoft® Windows 11/Linux Ubuntu
Storage	M.2 Interface x1, 128/256/512GB/1TB(Optional)
Wireless Communication	802.11 a/b/g/n/ac/ac + BT5.2 (Optional Installation)
Camera	2 MP (Front) / 5 MP (Rear)
Touchscreen	Gorilla Glass 3
Digital Accelerometer	WE.2533020201601
Ambient Light Sensor	AMS.TSL25721FN
LTE+GPS	Sierra 7455(Optional) /EM7421 (Optional)
Function Keys	x2
LED Indicators	x2
USB	USB 3.0 x 2 (Type-C / Type-A)
Ethernet	Gigabit LAN x1
DC-In	DC-In Jack x1
Docking	Docking Connector x1
Battery Type	Polymer
Battery	Capacity 4545 mAh x2
Battery Run Time	MD116 Approx. 6 hrs / MD116I Approx.4 hrs
Speaker	2W x2

LCD Specifications

Model	MOHOTEC
Display Type	11.6" LCD (AUO base)
Max. Resolution	1920 x 1080
Contrast Ratio	800:1
Luminance (cd/m2)	600TYP
Back Light Life Time	>50,000 Hrs

Note

All ONYX LCD products are manufactured with High precision technology. However, there are a small number of defective pixels in all LCD panels that are not able to change color. This is a normal occurrence for all LCD displays from all manufacturers and should not be noticeable or objectionable under normal operation. All LCD panels are qualified for industry standard conditions in the following: total 7 dead pixels on a screen or if there are 3 within 1 inch square area of each other on the display.

Mechanical Specifications

Architecture	Close-frame
Color	Dark Gray
Mounting / Holder	VESA 75 Screw type:M4*8mm
Construction	3mm ABS + PC TYPE Plastic housing
Rear cover	magnesium
Dimension (WxHxD)	312 (W) x 239 (H) x 37 (D) mm
Net Weight	Approx. 1.8 kg

Power Supply Specifications

Model	Adapter FSP096-AHAN3
Input Voltage	100-240V AC @ 50-60 Hz
Output Voltage	12V, 8A, 96W max.

Model	Adapter EM11011H
Input Voltage	100-240V AC @ 50-60 Hz
Output Voltage	12V, 10A, 120W max.


Environmental Specifications

Operating Temperature	MD116E: 0°C ~ 40°C (32°F ~ 104°F)
Operating Humidity	30% to 75% RH, non-condensing
Operating Pressure	700 to 1060 hPa
Storage Temperature	-20°C ~ 60°C (-4°F ~ 140°F)
Storage Humidity	10%~95%@35°C, non-condensing
Storage Pressure	700 to 1060 hPa
Vibration	0.5G / 5 ~ 500Hz (Random) / operation
Shock	20G peak acceleration (11 msec. duration) / operation
Drop(with packaging)	80 cm (1 Corner, 3 Edge, 6 Surface)
EMI / Safety	CE/FCC Class B, UL60601-1, EN60601-1, E1, EN1789(compliance)

Touch Screen

Type	Projective Capacitive / 5-wire Resistive
Interface	USB interface
Light Transmission	> 80%

Dimension



Hardware Installation

Safety Precautions

Warning!



Always completely disconnect the power cord from your board whenever you are working on it. Do not make connections while the power is on, because a sudden rush of power can damage sensitive electronic components.

Caution!



Always ground yourself to remove any static charge before touching the board. Modern electronic devices are very sensitive to static electric charges. Use a grounding wrist strap at all times. Place all electronic components on a static-dissipative surface or in a static-shielded bag when they are not in the chassis

Quick Tour of ONYX-MD116/MD116I


Before you start to set up MD116E take a moment to become familiar with the locations and purposes of the controls, drives, connections and ports, which are illustrated in the figures below. When you place MD116E upright on the desktop, its front panel appears as shown in Picture 2-1.



Picture 2.1: Front View of MD116 Series

When you turn the Mobile Medical Assistant around and look at its

rear cover, the I/O port in left and right side, as shown in Picture 2-2. (The I/O section includes various I/O ports, including a DC-IN Jack, 1 Ethernet ports, 2 USB ports.). Top side have 2 smart card reader.



Picture 2.2 Rear view of MD116 Series IO Port

Turn On and Boot up into Windows OS

This section is for Windows operating system only. If you are installing a different operating system, please contact your vendor for installation details.

Your MD116E will begin loading Windows OS once you push the power button to turn power on. After less than one minute, Windows desktop screen will appear.

You can select the programs from the start menu in the left-down corner of the desktop screen.

When turn on unit and the electrical quantity of battery is high, the LED Indicators will be bright green.

When turn on unit and the electrical quantity of battery is low, the LED Indicators will be bright orange.


When the battery cannot be detected and connected with adapter, the LED Indicators will be bright blue.

Turn off

Turning off MD116E properly is important for system reliability. There are two ways to turn off the system.

1. On the start menu, click "shut down" and select "OK"
2. Push the power button and then the system will shut down automatically

Connectors

1.  **USB 3.0** These 9 Universal Serial Bus (USB) ports are available for connecting USB 3.0 devices.
2. **LAN (RJ-45) port.** This port allows Gigabit connection

Driver Installation

There are several installation ways depending on the driver package under different Operating Systems

Please follow the sequence below to install the drivers:

For Windows 10/11:

- Step 1 – Chipset Driver
- Step 2 – Graphics Driver
- Step 3 – SIO Driver
- Step 4 – TXE Driver
- Step 5 – Audio Driver
- Step 6 –BT Driver
- Step 7 –GPS Driver
- Step 8 – Ethernet on Docking Driver
- Step 9 – LAN Driver
- Step 10 – SMART CARD READER Driver

Miscellanea

General Cleaning Tips

You may need the following precautions before you begin to clean the computer. When you clean any single part or component for the computer, please read and understand the details below fully.

1. Never spray or squirt the liquids directly onto any computer component. If you need to clean the device, please rub it with a piece of dry cloth.
2. Be cautious of the tiny removable components when you use a vacuum cleaner to absorb the dirt on the floor.
3. Turn the system off before you start to clean up the component or computer.
4. Never drop the components inside the computer or get circuit board damp or wet.
5. Be cautious of all kinds of cleaning solvents or chemicals when you use it for the sake of cleaning. Some individuals may be allergic to the ingredients.
6. Try not to put any food, drink or cigarette around the computer.
7. ONYX Healthcare Inc. has tested and verified these cleaning disinfectants, CIDEX, Fireguard, Control III Disinfectant Germicide, Cavities, Dispatch Disinfectant Cleaner CLH69101, Peregrine 24 Disinfectant, can be used with MD116E. Use of any other disinfectants will void the warranty.

Cleaning tools

Although many companies have created products to help improve the process of cleaning your computer and peripherals users can also use household items to clean their computers and peripherals. Below is a listing of items you may need or want to use while cleaning your computer or computer peripherals.

Keep in mind that some components in your computer may only be able to be cleaned using a product designed for cleaning that component, if this is the case it will be mentioned in the cleaning tips.

- **Cloth** – A piece of cloth is the best tool to use when rubbing up a component. Although paper towels or tissues can be used on most hardware as well, we still recommend you to rub it with a piece of cloth.
- **Water or rubbing alcohol** – You may moisten a piece of cloth a bit with some water or rubbing alcohol and rub it on the computer. Unknown solvents may be harmful to the plastics parts.
- **Vacuum cleaner** – Absorb the dust, dirt, hair, cigarette particles, and other particles out of a computer can be one of the best methods of cleaning a computer. Over time these items can restrict the airflow in a computer and cause circuitry to corrode.
- **Cotton swabs** – Cotton swaps moistened with rubbing alcohol or water are excellent tools for wiping hard to reach areas in your keyboard, mouse, and other locations.
- **Foam swabs** – Whenever possible it is better to use lint free swabs such as foam swabs.

Note:

We strongly recommended that you should shut down the system before you start to clean any single components

Please follow the steps below.

1. Close all application programs.
2. Close operating software.
3. Turn off power switch
4. Remove all device
5. Pull out power cable

Scrap Computer Recycling

If the computer equipments need the maintenance or are beyond repair, we strongly recommended that you should inform us as soon as possible for the suitable solution. For the computers that are no longer useful or work well, please contact with worldwide distributors for recycling.

The worldwide distributors show on the following website:


https://www.onyx-healthcare.com/contact_en.php

Note:

Follow the national requirement to dispose unit

MD116E Battery LED identification

Default LED



	Charging	LED 1
Power on	Yes	On, Flashing
	No	On
Power OFF	Yes	On, Flashing
	No	Off
Suspend	Yes	On, Flashing
	No	On

Only AC-INNA

Battery Status	Capacity %	LED 1 Color	
Charging	0-1%	Cyan	
	1-20%	Orange-Red	
	21-95%	Yellow	
	96~100%	Green	
Discharging	<7%	Orange-Red ,Flashing	cannot Boot
	7-10%	Orange-Red	
	11-30%	Yellow	
	31-100%	Green	
	Cyan		



FCC Statement

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference, and
2. this device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the

following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.


Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

These requirements set a SAR limit of 1.6 W/kg averaged over one gram of tissue. The highest SAR value reported under this standard during product certification is 0.769 W/kg.





- The operation of this device is prohibited on oil platforms, cars, trains, boats, and aircraft, except that operation of this device is permitted in large aircraft while flying above 10,000 feet.
- Operation of transmitters in the 5.925-7.125 GHz band is prohibited for control of or communications with unmanned aircraft systems.



Documents / Resources

	<p>Onyx ONYX-MD116E 11.6 Inch LCD with LED Backlight [pdf] User Manual</p> <p>ONYX-MD116E 11.6 Inch LCD with LED Backlight, ONYX-MD116E, 11.6 Inch LCD with LED Backlight, LCD with LED Backlight, LED Backlight</p>
-------------------------------------------------------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

References

-  [Healthcare.com - 2023 Health Plans and Health Insurance Quote Search - HealthCare.com](#)
-  [Medical Computer|All Medical PC Manufacturer|ONYX](#)
-  [Contact | ONYX](#)
-  [Download | ONYX](#)
- [User Manual](#)

