




SCHWAIGER NET0010 Electricity Usage Monitor Instructions

[Home](#) » [Schwaiger](#) » SCHWAIGER NET0010 Electricity Usage Monitor Instructions 

Contents

- [1 SCHWAIGER NET0010 Electricity Usage Monitor](#)
- [2 Electricity Usage Monitor Display 180° rotatable](#)
 - [2.1 FEATURES \(NET0010\)](#)
- [3 TECHNICAL DATA](#)
- [4 Documents / Resources](#)
- [5 Related Posts](#)



SCHWAIGER NET0010 Electricity Usage Monitor



Electricity Usage Monitor Display 180° rotatable

The energy cost meter from SCHWAIGER® is designed for the connection to a standard household socket and serves as an inter-mediate socket to measure the power consumption of the connected device. The display, which

can be rotated by 180°, makes it easy to read off the costs, power, voltage and consumption in kilowatt hours. The device helps to detect high power consumption, which is caused, for example, by standby mode or old household appliances.



FEATURES (NET0010)

- For measuring and calculating the current energy consumption as well as the electricity costs of a connected electrical appliance
- With a large, 180° rotatable display for good readability of the measurement data
- Automatic data storage in the event of a power failure
- Display of current voltage in V, power consumption in W, energy consumption in kWh and energy costs in ff
- Easy operation and handling• For measuring and calculating the current energy consumption as well as the electricity costs of a connected electrical appliance
- With a large, 180° rotatable display for good readability of the measurement data
- Automatic data storage in the event of a power failure
- Display of current voltage in V, power consumption in W, energy consumption in kWh and energy costs in ff
- Easy operation and handling
- for plugging into a standard household 230 V power outlet
- Scope of delivery: energy cost meter, instruction manual, warranty card

TECHNICAL DATA

Connections

- Connections 1x Schake plug (type F) 1x Schake socket (type F)
- Power supply 230 V AC , 50 Hz
- Output current 16 A
- Output power 3680 W (max.)
- Range of voltage 150 – 276 V AC
- measuring
- Range of power measuring 0.3 – 3,680 W
- Display accuracy Voltage: +/- 1% / Power: +/- 2%
- Overvoltage category CAT II
- Point of use indoor use
- Protection class IP20
- Display 4-digits

- Display grove 2"
- Operating temperature $+5^{\circ} - +40^{\circ} \text{ }^{\circ}\text{C}$
- Color white
- Weight (set) 120 g
- Dimensions (width) 58 mm
- Dimensions (height) 109 mm
- Dimensions (depth) 84 mm
- Packaging carton

Tel. +49 (09101) 702-0

www.schwaiger.de

Errors, variations and changes concerning technical data and illustrations are subject to change. Our General Terms and Conditions for the Supply of Goods and Services apply.

Documents / Resources



NET0010 Electricity Usage Monitor, NET0010, Electricity Usage Monitor, Usage Monitor, Monitor