



# StarTech.com DKT31CHDVCM USB-C 10 Gbps Single Monitor Mini Docking Station User Guide

[Home](#) » [StarTech.com](#) » StarTech.com DKT31CHDVCM USB-C 10 Gbps Single Monitor Mini Docking Station User Guide 

## Contents

- 1 [StarTech.com DKT31CHDVCM USB-C 10 Gbps Single Monitor Mini Docking Station](#)
- 2 [Product Diagram \(DKT31CHDVCM\)](#)
- 3 [Powering the Docking Station](#)
- 4 [Connecting a Display to the Docking Station](#)
- 5 [Connecting Peripherals to the Docking Station](#)
  - 5.1 [Product Resolution](#)
  - 5.2 [Product Dimensions](#)
- 6 [FCC Compliance Statement](#)
  - 6.1 [Industry Canada Statement](#)
- 7 [Warranty Information](#)
  - 7.1 [Limitation of Liability](#)
  - 7.2 [Safety Measures](#)
- 8 [Documents / Resources](#)
  - 8.1 [References](#)
- 9 [Related Posts](#)



**StarTech.com DKT31CHDVCM USB-C 10 Gbps Single Monitor Mini Docking Station**



USB-C™ 10Gbps Single Monitor Mini Docking Station with HDMI, DP, or VGA | PD | 24cm Wrap Around Cable

### Product Diagram (DKT31CHDVCM)



Component		Function
1	RJ45 Port	<ul style="list-style-type: none"> <li>Connect the <b>Docking Station</b> to a <b>Network Device</b>.</li> </ul>
2	USB-A Port x 2	<ul style="list-style-type: none"> <li>Connect a <b>USB Peripheral Device</b> to the <b>Docking Station</b>.</li> <li>Fast-charge devices that comply with USB Battery Charging specification Revision 1.2.</li> <li>Supports up to 5V at 1.5A, 7.5W charging.</li> </ul>
3	USB-C Port	<ul style="list-style-type: none"> <li>Connect a <b>USB Peripheral Device</b> to the <b>Docking Station</b>.</li> <li>Supports up to 5V at 1.5A, 7.5W charging.</li> <li>PD Pass Through.</li> </ul>
4	USB-C Connector	<ul style="list-style-type: none"> <li>Connect the <b>Docking Station</b> to a <b>Host Laptop</b>.</li> </ul>
5	DisplayPort Port	<ul style="list-style-type: none"> <li>Connect a <b>Display Device</b> to the <b>Docking Station</b>.  <b>Note:</b> The connected <b>Host Laptop</b> must be enabled with DP ALT Mode.</li> </ul>
6	HDMI Port	<ul style="list-style-type: none"> <li>Connect a <b>Display Device</b> to the <b>Docking Station</b>.  <b>Note:</b> The connected <b>Host Laptop</b> must be enabled with DP ALT Mode.</li> </ul>
7	VGA Port	<ul style="list-style-type: none"> <li>Connect a <b>Display Device</b> to the <b>Docking Station</b>.  <b>Note:</b> The connected <b>Host Laptop</b> must be enabled with DP ALT Mode.</li> </ul>

## Requirements

For the latest product information, technical specifications, manuals, and Declarations of Conformance, please visit:

[www.startech.com/DKT31CHDVCM](http://www.startech.com/DKT31CHDVCM)

## **Host**

- Laptop with USB-C or Thunderbolt 3 port and with DP ALT Mode enabled x 1

## **Display**

- VGA, HDMI, or DisplayPort compatible x 1

## **Cables (depends on configuration)**

- VGA Cable x 1
- HDMI Cable x 1
- DisplayPort Cable x 1
- CAT5e/6 Cable x 1

## **Powering the Docking Station**

1. Unravel the Wrap Around Cable from the Docking Station Housing, by holding onto the USB-C Connector and gently pulling the cable outward, away from the Docking Station Housing.
2. Connect the USB-C Connector to a USB-C or Thunderbolt 3 Port on the Host Laptop.

## **Connecting a Display to the Docking Station**

When more than one Display is connected to the Docking Station, the first Display that was connected will be the active Display until the Display is disconnected from the Docking Station. The priority when you have three monitors connected to the Docking Station is as follows: DisplayPort -> HDMI -> VGA.

### **DisplayPort**

- Connect a DisplayPort Cable (sold separately) to the DisplayPort Port on the Docking Station and to a DisplayPort Port on a Display Device.

### **HDMI**

- Connect a HDMI Cable (sold separately) to the HDMI Port on the Docking Station and to an HDMI Port on a Display Device.

### **VGA**

- Connect a VGA Cable (sold separately) to the VGA Port on the Docking Station and to a VGA Port on a Display Device.

## **Connecting Peripherals to the Docking Station**

### **RJ45**

- Connect a CAT5e/6 Cable (sold separately) to the RJ45 Port on the Docking Station and the other end to an RJ45 port on a Network Device.

## USB-A

- Connect a USB Peripheral's Connector to the USB-A Port on the Docking Station.

## USB-C

- Connect a USB Peripheral's Connector to the USB-C Port on the Docking Station.

## Product Resolution

Resolution	Frequency	Single Screen Extended
Full HD (1920×1080, 1920×1200)	60 Hz	Yes
2K (2560×1440, 2560×1600)	60 Hz	Yes
UHD (3840×2160)	30 Hz	Yes
4K (4096×2160)	24 Hz	Yes
UHD (3840×2160)	60 Hz	Yes*

\* Only supported when host port supports DP 1.4

## Product Dimensions

Unit of Measure	Dimension
Product Diameter	90 mm
Product Height	32.5 mm

## FCC Compliance Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference, and
2. this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by StarTech.com could void the user's authority to operate the equipment.

### **Industry Canada Statement**

This Class B digital apparatus complies with Canadian ICES-003.

Use of Trademarks, Registered Trademarks, and other Protected Names and Symbols

This manual may make reference to trademarks, registered trademarks, and other protected names and/or symbols of third-party companies not related in any way to StarTech.com. Where they occur these references are for illustrative purposes only and do not represent an endorsement of a product or service by StarTech.com, or an endorsement of the product(s) to which this manual applies by the third-party company in question.

[StarTech.com](http://StarTech.com) hereby acknowledges that all trademarks, registered trademarks, service marks, and other protected names and/or symbols contained in this manual and related documents are the property of their respective holders.

### **Warranty Information**

This product is backed by a three-year warranty.

For further information on product warranty terms and conditions, please refer to [www.startech.com/warranty](http://www.startech.com/warranty).

### **Limitation of Liability**

In no event shall the liability of StarTech.com Ltd. and StarTech.com USA LLP (or their officers, directors, employees or agents) for any damages (whether direct or indirect, special, punitive, incidental, consequential, or otherwise), loss of profits, loss of business, or any pecuniary loss, arising out of or related to the use of the product exceed the actual price paid for the product. Some states do not allow the exclusion or limitation of incidental or consequential damages. If such laws apply, the limitations or exclusions contained in this statement may not apply to you.

### **Safety Measures**

- Cables (including power and charging cables) should be placed and routed to avoid creating electric, tripping or safety hazards.

[StarTech.com](http://StarTech.com) Ltd.  
45 Artisans Crescent  
London, Ontario  
N5V 5E9  
Canada

[StarTech.com](http://StarTech.com) LLP  
4490 South Hamilton Road  
Groveport, Ohio 43125  
U.S.A.


[StarTech.com](http://StarTech.com) Ltd.  
Unit B, Pinnacle 15  
Gowerton Road

Brackmills,  
Northampton  
NN4 7BW  
United Kingdom

[StarTech.com](http://StarTech.com) Ltd.  
Siriusdreef 17-27  
2132 WT Hoofddorp  
The Netherlands

- FR: [startech.com/fr](http://startech.com/fr)
- DE: [startech.com/de](http://startech.com/de)
- ES: [startech.com/es](http://startech.com/es)
- NL: [startech.com/nl](http://startech.com/nl)
- IT: [startech.com/it](http://startech.com/it)
- JP: [startech.com/jp](http://startech.com/jp)

## Documents / Resources

	<a href="#">StarTech.com DKT31CHDVCM USB-C 10 Gbps Single Monitor Mini Docking Station</a> [pdf] User Guide DKT31CHDVCM USB-C 10 Gbps Single Monitor Mini Docking Station, DKT31CHDVCM, DKT31CHDVCM USB-C 10 Gbps Single Monitor Mini Docking Station, USB-C 10 Gbps Single Monitor, Single Monitor, Single Monitor Mini Docking Station, Mini Docking Station, Docking Station
--	---

## References

- [StarTech.com | IT Pro's Trusted Source for Connectivity Accessories](#)
- [Unsere Produkte dienen IT- und A/V-Profis zum Verbinden, Konvertieren, Erweitern, Splitten und Switchen | Deutschland](#)
- [StarTech.com diseña y fabrica una variada gama de componentes para ordenadores, cables, conmutadores KVM, racks para... | España](#)
- [StarTech.com conçoit et fabrique une vaste sélection de pièces d'ordinateur, de câbles, de commutateur KVM, de racks... | France](#)
- [Pezzi per computer, cavi, switch KVM, server rack e soluzioni per reti | Italia](#)
- [IT & A / V](#)
- [StarTech.com ontwerpt en produceert een enorme selectie computeronderdelen, kabels, KVM-switches, serverracks en... | Nederland](#)
- [USB C Multiport Adapter - HDMI/DP/VGA - USB-C Multiport Adapters | StarTech.com](#)
- [StarTech.com Support](#)
- [StarTech.com Warranty Policy](#)